

PP_azul

```
1|      10|      20|      30|      40|      50|      60|      70|      80|      90|      100|      110|
1  (* ===== *)
2  (* SECCIÓN: PP_azul *)
3  (* Gestion del pick and place para piezas azules *)
4  (* ===== *)
5
6  IF IN_Vision_Sensor_3_Bool_0 and IN_Vision_Sensor_3_Bool_1 THEN
7      OUT_Emitter5_Emit:= TRUE;
8  END_IF;
9
10 IF OUT_Emitter5_Emit THEN
11     SET (OUT => OUT_BeltConveyor_4_7);
12 END_IF;
13
14 F_TRIG_5 (CLK := IN_Diffuse_Sensor_15);
15
16 IF F_TRIG_5.Q THEN
17     RESET (OUT =>OUT_BeltConveyor_4_7);
18     SET (OUT => OUT_Two_Axis_Pick_Place_2_Z);
19     OUT_Emitter5_Emit:= FALSE;
20 END_IF;
21
22 R_TRIG_27 (CLK := IN_TwoAxis_PickPlace_2_Detected);
23
24 IF R_TRIG_27.Q THEN
25     SET ( OUT => OUT_Two_Axis_Pick_Place_2_Grab);
26
27 END_IF;
28
29 R_TRIG_24 (CLK := OUT_Two_Axis_Pick_Place_2_Grab);
30
31
32 IF R_TRIG_24.Q THEN
33     RESET( OUT => OUT_Two_Axis_Pick_Place_2_Z);
34 END_IF;
35
36 F_TRIG_6 (CLK := IN_TwoAxis_PickPlace_2_Moving_Z );
37
38 IF F_TRIG_6.Q then
39     SET( OUT_Two_Axis_Pick_Place_2_X );
40 END_IF;
41
42 F_TRIG_9 (CLK := IN_Diffuse_Sensor_13);
43
44
45 IF OUT_TWO_AXIS_PICK_PLACE_2_X and IN_Right_Positioner_4_Clamped THEN
46     SET ( OUT_Two_Axis_Pick_Place_2_Z );
47 END_IF;
48
49 F_TRIG_10 (CLK := IN_TwoAxis_PickPlace_2_Moving_Z);
50
51
52 IF OUT_Two_Axis_Pick_Place_2_Z and OUT_Two_Axis_Pick_Place_2_X and F_TRIG_10.Q THEN
53     RESET (OUT_Two_Axis_Pick_Place_2_Grab);
54     RESET( OUT => OUT_Two_Axis_Pick_Place_2_Z);
55 END_IF;
56
57 IF F_TRIG_9.Q THEN
58     SET ( OUT_Right_Positioner_4_Clamp);
59 END_IF;
60
61 F_TRIG_20 (CLK := IN_TwoAxis_PickPlace_2_Moving_Z);
62
63 IF F_TRIG_20.Q and OUT_Right_Positioner_4_Clamp THEN
64     RESET( OUT => OUT_Two_Axis_Pick_Place_2_X);
65 END_IF;
66
67 F_TRIG_21 (CLK := IN_TwoAxis_PickPlace_2_Moving_X);
68
69 IF F_TRIG_21.Q AND OUT_Right_Positioner_4_Clamp THEN
70     RESET ( OUT_Right_Positioner_4_Clamp);
71     SET (OUT_Right_Positioner_4_Raise);
72 END_IF;
73
74 F_TRIG_22 (CLK := IN_Diffuse_Sensor_14);
75
76 IF F_TRIG_22.Q THEN
77     RESET(OUT=>OUT_Right_Positioner_4_Raise);
78     RESET(OUT=>OUT_Right_Positioner_4_Clamp);
79 END_IF;
```