

Intermountain West Mesh

Advert, Loop Detection, and Delay Settings

Adverts

We recommend an advert interval of **47 hours**, so adverts happen as little as possible while maintaining discovery, yet won't occur at the same time every day.

Loop Detection

On all repeaters that allow it, send the command
set loop.detect moderate via CLI.

With loop.detect = moderate:

1-byte path: rejects the packet if its own ID appears 2 times

2-byte & 3-byte path: rejects the packet if its own ID appears 1 time

Delays

txdelay controls the random wait before retransmitting flood packets; a higher value gives nearby nodes more time to transmit first, reducing collisions. **direct.txdelay** does the same for direct packets but is usually lower for faster delivery, while **rxdelay** prioritizes stronger copies and can discard weaker duplicates.

These commands can be sent via CLI, or set upon flashing a repeater:

For nodes with 20+ neighbors:

```
set txdelay 2
set direct.txdelay 2
set rxdelay 3
```

For nodes with 10-19 neighbors:

```
set txdelay 1.5
set direct.txdelay 1
set rxdelay 3
```

For nodes with 5-9 neighbors:

```
set txdelay 0.8
set direct.txdelay 0.4
set rxdelay 3
```

For nodes with 1-4 neighbors:

```
set txdelay 0.3
set direct.txdelay 0.1
set rxdelay 3
```

For mobile repeaters (i.e. vehicle nodes):

```
set txdelay 2
set direct.txdelay 2
set rxdelay 3
```