SmartSlydr REST API

Version 0.4

SmartSlydr REST API allows SmartSlydr users to integrate and operate the device from third party Smart Home platforms. User will onboard the device using LycheeThings mobile application. Once device is onboarded and calibrated with mobile application user can integrate the APIs with other Smart Home platforms to operate.

Authentication:

API to authenticate user. This API will authenticate the user and response the access token. Other APIs can be called with provided token. Access token has validity of 30 minutes.

URL **:** https://34yl6ald82.execute-api.us-east-2.amazonaws.com/prod/auth

Method **:** POST

Input Parameter (Body)

```
{
    "username" : "<userID>",
    "password" : "<Passoword>"
}
```

Response :

```
{
    "statusCode": 200,
    "access_token": "…................. qsZ_402i3OykfnRcR8C3fSeXtd7zi9DSQ",
    "token_type": "Bearer",
    "refresh_token": "…................. M.I7e97OMWmVityuSk27FecQ"
}
```

Refresh Token:

Auth API is used to authenticate the user which will generate an access_token. This access token has validity for 30 minutes. User can refresh access_token using refresh token API.

URL : https://34yl6ald82.execute-api.us-east-2.amazonaws.com/prod/token

Method : POST

Input Parameters:

```
{
    "refresh_token" : "…….. WHASsCzwKlrpD185nX51OFIaQ.nz0CL6HnQw8LZUbcwvnPZw"
}
```

Response:

```
{
    "statusCode": 200,
    "access_token": "…….. 7Sh71HYhnK3NvC4bjAyL916idcCGOiQHXlWSzA",
    "token_type": "Bearer"
}
```

Device List:

User can call device list API to get the list of devices and common information of device using this API.

URL : https://34yl6ald82.execute-api.us-east-2.amazonaws.com/prod/devices

Header : **<key> : <value>**
Authorization : <access token>

Method : GET

Input Parameters :

Response :

```
{
    "statusCode": 200,
    "room_lists": [
        {
            "room_name": "Family Room",
            "device_list": [
                {
                    "device_id": "010000F8",
                    "devicename": "010000F8",
                    "petpass": [
                        {
                            "slot": "1",
                            "name": "Charlie"
                        },
                        {
                            "slot": "2",
                            "name": "Button"
```

```
                    }
                ],
                "room_name": "Family Room",
                "room_id": "context0.5086073427380156",
                "wlansignal": -55,
                "temperature": 40,
                "humidity": 50,
                "position": 0,
                "error": "000",
                "status": "device is online"
            },
            {
                "device_id": "01000006",
                "devicename": "01000006",
                "petpass": [
                    {
                        "slot": "1",
                        "name": "Rocky"
                    }
                ],
                "room_name": "Family Room",
                "room_id": "context0.5086073427380156",
                "wlansignal": -74,
                "temperature": 24,
                "humidity": 50,
                "position": 0,
                "error": "000",
                "status": "device is online"
            }
        ]
    },
]
}
```


Get Status :

User can fetch the device status and other information using get status API. User can pass following commands :

a) Position
b) Petpass
c) sound
d) wlansignal

e) temperature
f) humidity
g) wlanmac

URL : https://34yl6ald82.execute-api.us-east-2.amazonaws.com/prod/operation/get

Header : **<key> : <value>**
Authorization : <access token>

Method : POST

Input Parameters :

```
{
    "commands" : [
            {
                "device_id" : "01000003",
                "command" : "humidity"          //Can be replaced by other parameters
            }
    ]
}
```

Response :

```
{
    "statusCode": 200,
    "response": [
        {
            "humidity": 54,
            "device_id": "01000003",
            "status": "success"
        }
    ]
}
```

Set Command :

User can use set command API to operate the device or configure certain device options. User can device following commands with set command API:

a) position (Value 0-100)

b) petpass (Value 0/1)
c) Stop command using “position” key with Value 200

URL : https://34yl6ald82.execute-api.us-east-2.amazonaws.com/prod/operation

Header : <key> : <value>
Authorization : <access token>

Method : POST

Input Parameters :

```
{
    "setcommands" : [
        {
            "device_id" : "01000003",
            "commands": [
                {
                    "key": "position",
                    "value": 12
                }

            ]
        }
    ]
}
```

Response :

```
{
    "statusCode": 200,
    "response": [
        {
            "status": "success",
            "device_id": "01000003"
        }
    ]
}
```

Stop Command Example :

Input Parameters :

```
{
    "setcommands" : [
        {
            "device_id" : "01000003",
            "commands": [
                {
                    "key": "position",
                    "value": 200
                }

            ]
        }
    ]
}
```