Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	IO Performance	E144 *(2)*
1A	VREFB1N0	IO			DIFFIO_RX_L1n	DIFFOUT_L1n	Low_Speed	4
1A	VREFB1N0	IO			DIFFIO_RX_L2n	DIFFOUT_L2n	Low_Speed	3
1A	VREFB1N0	IO			DIFFIO_RX_L1p	DIFFOUT_L1p	Low_Speed	6
1A	VREFB1N0	IO			DIFFIO_RX_L2p	DIFFOUT_L2p	Low_Speed	5
1A	VREFB1N0	IO			DIFFIO_RX_L3n	DIFFOUT_L3n	Low_Speed	8
1A	VREFB1N0	IO			DIFFIO_RX_L4n	DIFFOUT_L4n	Low_Speed	7
1A	VREFB1N0	IO			DIFFIO_RX_L3p	DIFFOUT_L3p	Low_Speed	10
1A	VREFB1N0	IO			DIFFIO_RX_L4p	DIFFOUT_L4p	Low_Speed	9
1B	VREFB1N0	IO		JTAGEN				13
1B	VREFB1N0	IO		TMS	DIFFIO_RX_L7n	DIFFOUT_L7n	Low_Speed	15
1B	VREFB1N0	IO	VREFB1N0					14
1B	VREFB1N0	IO		TCK	DIFFIO_RX_L7p	DIFFOUT_L7p	Low_Speed	16
1B	VREFB1N0	IO		TDI	DIFFIO_RX_L8n	DIFFOUT_L8n	Low_Speed	17
1B	VREFB1N0	IO		TDO	DIFFIO_RX_L8p	DIFFOUT_L8p	Low_Speed	18
1B	VREFB1N0	IO			DIFFIO_RX_L10n	DIFFOUT_L10n	Low_Speed	19
1B	VREFB1N0	IO			DIFFIO_RX_L10p	DIFFOUT_L10p	Low_Speed	21
1B	VREFB1N0	IO			DIFFIO_RX_L12n	DIFFOUT_L12n	Low_Speed	23
1B	VREFB1N0	IO			DIFFIO_RX_L12p	DIFFOUT_L12p	Low_Speed	24
2	VREFB2N0	IO	CLK0n		DIFFIO_RX_L14n	DIFFOUT_L14n	High_Speed	25
2	VREFB2N0	IO	CLK0p		DIFFIO_RX_L14p	DIFFOUT_L14p	High_Speed	26
2	VREFB2N0	IO	CLK1n		DIFFIO_RX_L16n	DIFFOUT_L16n	High_Speed	27
2	VREFB2N0	IO	CLK1p		DIFFIO_RX_L16p	DIFFOUT_L16p	High_Speed	28
2	VREFB2N0	IO	VREFB2N0					31
2	VREFB2N0	IO	PLL_L_CLKOUTn		DIFFIO_RX_L19n	DIFFOUT_L19n	High_Speed	32
2	VREFB2N0	IO	PLL_L_CLKOUTp		DIFFIO_RX_L19p	DIFFOUT_L19p	High_Speed	33
3	VREFB3N0	IO			DIFFIO_TX_RX_B1n	DIFFOUT_B1n	High_Speed	40
3	VREFB3N0	IO			DIFFIO_RX_B2n	DIFFOUT_B2n	High_Speed	39
3	VREFB3N0	IO			DIFFIO_TX_RX_B1p	DIFFOUT_B1p	High_Speed	42
3	VREFB3N0	IO			DIFFIO_RX_B2p	DIFFOUT_B2p	High_Speed	41
3	VREFB3N0	IO			DIFFIO_TX_RX_B3n	DIFFOUT_B3n	High_Speed	44
3	VREFB3N0	IO			DIFFIO_TX_RX_B3p	DIFFOUT_B3p	High_Speed	46
3	VREFB3N0	IO			DIFFIO_TX_RX_B5n	DIFFOUT_B5n	High_Speed	48
3	VREFB3N0	IO			DIFFIO_RX_B6n	DIFFOUT_B6n	High_Speed	47
3	VREFB3N0	IO			DIFFIO_TX_RX_B5p	DIFFOUT_B5p	High_Speed	50
3	VREFB3N0	IO			DIFFIO_RX_B6p	DIFFOUT_B6p	High_Speed	49
3	VREFB3N0	IO			DIFFIO_TX_RX_B7n	DIFFOUT_B7n	High_Speed	52
3	VREFB3N0	IO			DIFFIO_RX_B8n	DIFFOUT_B8n	High_Speed	51
3	VREFB3N0	IO			DIFFIO_TX_RX_B7p	DIFFOUT_B7p	High_Speed	54
3	VREFB3N0	IO			DIFFIO_RX_B8p	DIFFOUT_B8p	High_Speed	53
3	VREFB3N0	IO	VREFB3N0					55
3	VREFB3N0	IO			DIFFIO_TX_RX_B12n	DIFFOUT_B12n	High_Speed	59
3	VREFB3N0	IO			DIFFIO_RX_B13n	DIFFOUT_B13n	High_Speed	60
3	VREFB3N0	IO			DIFFIO_TX_RX_B12p	DIFFOUT_B12p	High_Speed	61
3	VREFB3N0	IO			DIFFIO_RX_B13p	DIFFOUT_B13p	High_Speed	62
3	VREFB3N0	IO			DIFFIO_TX_RX_B14n	DIFFOUT_B14n	High_Speed	63
3	VREFB3N0	IO			DIFFIO_TX_RX_B14p	DIFFOUT_B14p	High_Speed	65
3	VREFB3N0	IO			DIFFIO_TX_RX_B16n	DIFFOUT_B16n	High_Speed	67
3	VREFB3N0	IO			DIFFIO_RX_B17n	DIFFOUT_B17n	High_Speed	68
3	VREFB3N0	IO			DIFFIO_TX_RX_B16p	DIFFOUT_B16p	High_Speed	69
3	VREFB3N0	IO			DIFFIO_RX_B17p	DIFFOUT_B17p	High_Speed	70
5	VREFB5N0	IO			DIFFIO_RX_R1p	DIFFOUT_R1p	High_Speed	75
5	VREFB5N0	IO			DIFFIO_RX_R2p	DIFFOUT_R2p	High_Speed	74
5	VREFB5N0	IO			DIFFIO_RX_R1n	DIFFOUT_R1n	High_Speed	78
5	VREFB5N0	IO			DIFFIO_RX_R2n	DIFFOUT_R2n	High_Speed	76
5	VREFB5N0	IO			DIFFIO_RX_R3p	DIFFOUT_R3p	High_Speed	79
5	VREFB5N0	IO						77
5	VREFB5N0	IO			DIFFIO_RX_R3n	DIFFOUT_R3n	High_Speed	81
5	VREFB5N0	IO	VREFB5N0					80
5	VREFB5N0	IO			DIFFIO_RX_R6p	DIFFOUT_R6p	High_Speed	85
5	VREFB5N0	IO			DIFFIO_RX_R7p	DIFFOUT_R7p	High_Speed	84
5	VREFB5N0	IO			DIFFIO_RX_R6n	DIFFOUT_R6n	High_Speed	87
5	VREFB5N0	IO			DIFFIO_RX_R7n	DIFFOUT_R7n	High_Speed	86
6	VREFB6N0	IO	CLK2p		DIFFIO_RX_R10p	DIFFOUT_R10p	High_Speed	88
6	VREFB6N0	IO	CLK2n		DIFFIO_RX_R10n	DIFFOUT_R10n	High_Speed	89
6	VREFB6N0	IO	CLK3p		DIFFIO_RX_R12p	DIFFOUT_R12p	High_Speed	90
6	VREFB6N0	IO	CLK3n		DIFFIO_RX_R12n	DIFFOUT_R12n	High_Speed	91
6	VREFB6N0	IO	DPCLK3		DIFFIO_RX_R16p	DIFFOUT_R16p	High_Speed	94
6	VREFB6N0	IO	VREFB6N0					92
6	VREFB6N0	IO	DPCLK2		DIFFIO_RX_R16n	DIFFOUT_R16n	High_Speed	95
6	VREFB6N0	IO			DIFFIO_RX_R17p	DIFFOUT_R17p	High_Speed	97
6	VREFB6N0	IO			DIFFIO_RX_R18p	DIFFOUT_R18p	High_Speed	98
6	VREFB6N0	IO			DIFFIO_RX_R17n	DIFFOUT_R17n	High_Speed	99
6	VREFB6N0	IO			DIFFIO_RX_R18n	DIFFOUT_R18n	High_Speed	100
6	VREFB6N0	IO			DIFFIO_RX_R21p	DIFFOUT_R21p	High_Speed	101
6	VREFB6N0	IO			DIFFIO_RX_R21n	DIFFOUT_R21n	High_Speed	103
6	VREFB6N0	IO			DIFFIO_RX_R23p	DIFFOUT_R23p	High_Speed	105
6	VREFB6N0	IO			DIFFIO_RX_R23n	DIFFOUT_R23n	High_Speed	106
8	VREFB8N0	IO			DIFFIO_RX_T3p	DIFFOUT_T3p	Low_Speed	112
8	VREFB8N0	IO		DEV_CLRn	DIFFIO_RX_T3n	DIFFOUT_T3n	Low_Speed	113
8	VREFB8N0	IO		DEV_OE	DIFFIO_RX_T5p	DIFFOUT_T5p	Low_Speed	115
8	VREFB8N0	IO			DIFFIO_RX_T5n	DIFFOUT_T5n	Low_Speed	117
8	VREFB8N0	IO	VREFB8N0					114
8	VREFB8N0	IO		CONFIG_SEL				120
8	VREFB8N0	IO						116
8	VREFB8N0	Input_only		nCONFIG				122
8	VREFB8N0	IO			DIFFIO_RX_T7p	DIFFOUT_T7p	Low_Speed	124
8	VREFB8N0	IO			DIFFIO_RX_T8p	DIFFOUT_T8p	Low_Speed	123
8	VREFB8N0	IO			DIFFIO_RX_T7n	DIFFOUT_T7n	Low_Speed	126
8	VREFB8N0	IO			DIFFIO_RX_T8n	DIFFOUT_T8n	Low_Speed	125

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	IO Performance	E144 *(2)*
8	VREFB8N0	IO			DIFFIO_RX_T9p	DIFFOUT_T9p	Low_Speed	128
8	VREFB8N0	IO			DIFFIO_RX_T10p	DIFFOUT_T10p	Low_Speed	127
8	VREFB8N0	IO		CRC_ERROR	DIFFIO_RX_T9n	DIFFOUT_T9n	Low_Speed	130
8	VREFB8N0	IO			DIFFIO_RX_T10n	DIFFOUT_T10n	Low_Speed	129
8	VREFB8N0	IO		nSTATUS	DIFFIO_RX_T11p	DIFFOUT_T11p	Low_Speed	131
8	VREFB8N0	IO			DIFFIO_RX_T12p	DIFFOUT_T12p	Low_Speed	134
8	VREFB8N0	IO		CONF_DONE	DIFFIO_RX_T11n	DIFFOUT_T11n	Low_Speed	135
8	VREFB8N0	IO			DIFFIO_RX_T12n	DIFFOUT_T12n	Low_Speed	137
8	VREFB8N0	IO			DIFFIO_RX_T13p	DIFFOUT_T13p	Low_Speed	138
8	VREFB8N0	IO			DIFFIO_RX_T14p	DIFFOUT_T14p	Low_Speed	139
8	VREFB8N0	IO			DIFFIO_RX_T13n	DIFFOUT_T13n	Low_Speed	140
8	VREFB8N0	IO			DIFFIO_RX_T14n	DIFFOUT_T14n	Low_Speed	141
		GND						96
		GND						83
		GND						66
		GND						57
		GND						45
		GND						38
		GND						30
		GND						20
		GND						143
		GND						133
		GND						119
		GND						110
		GND						11
		GND						104
		VCCIO1						22
		VCCIO1						12
		VCCIO2						29
		VCCIO3						64
		VCCIO3						56
		VCCIO3						43
		VCCIO5						82
		VCCIO6						93
		VCCIO6						102
		VCCIO8						136
		VCCIO8						121
		VCCIO8						111
		VCCA1						35
		VCCA2						34
		VCCA3						107
		VCCA4						2
		VCCA5						71
		VCC_ONE						73
		VCC_ONE						72
		VCC_ONE						58
		VCC_ONE						37
		VCC_ONE						36
		VCC_ONE						144
		VCC_ONE						142
		VCC_ONE						132
		VCC_ONE						118
		VCC_ONE						109
		VCC_ONE						108
		VCC_ONE						1

Notes:

(1) For more information about pin definition and pin connection guidelines, refer to the
Intel MAX 10 FPGA Device Family Pin Connection Guidelines.

(2) The E144-pin package has an exposed ground pad at the bottom of the package. The exposed ground pad is used for electrical connectivity and not for thermal purposes. You must connect the exposed ground pad to the ground plane of the PCB.

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	IO Performance	M153
1A	VREFB1N0	IO			DIFFIO_RX_L1n	DIFFOUT_L1n	Low_Speed	D2
1A	VREFB1N0	IO			DIFFIO_RX_L2n	DIFFOUT_L2n	Low_Speed	C1
1A	VREFB1N0	IO			DIFFIO_RX_L1p	DIFFOUT_L1p	Low_Speed	C2
1A	VREFB1N0	IO			DIFFIO_RX_L2p	DIFFOUT_L2p	Low_Speed	B1
1A	VREFB1N0	IO			DIFFIO_RX_L3n	DIFFOUT_L3n	Low_Speed	F5
1A	VREFB1N0	IO			DIFFIO_RX_L4n	DIFFOUT_L4n	Low_Speed	E1
1A	VREFB1N0	IO			DIFFIO_RX_L3p	DIFFOUT_L3p	Low_Speed	G5
1A	VREFB1N0	IO			DIFFIO_RX_L4p	DIFFOUT_L4p	Low_Speed	E2
1B	VREFB1N0	IO		JTAGEN				G7
1B	VREFB1N0	IO		TMS	DIFFIO_RX_L7n	DIFFOUT_L7n	Low_Speed	G1
1B	VREFB1N0	IO	VREFB1N0					G2
1B	VREFB1N0	IO		TCK	DIFFIO_RX_L7p	DIFFOUT_L7p	Low_Speed	J1
1B	VREFB1N0	IO		TDI	DIFFIO_RX_L8n	DIFFOUT_L8n	Low_Speed	H5
1B	VREFB1N0	IO		TDO	DIFFIO_RX_L8p	DIFFOUT_L8p	Low_Speed	H4
1B	VREFB1N0	IO			DIFFIO_RX_L10n	DIFFOUT_L10n	Low_Speed	H3
1B	VREFB1N0	IO			DIFFIO_RX_L10p	DIFFOUT_L10p	Low_Speed	J2
1B	VREFB1N0	IO			DIFFIO_RX_L12n	DIFFOUT_L12n	Low_Speed	L1
1B	VREFB1N0	IO			DIFFIO_RX_L12p	DIFFOUT_L12p	Low_Speed	K2
2	VREFB2N0	IO	CLK0n		DIFFIO_RX_L14n	DIFFOUT_L14n	High_Speed	J4
2	VREFB2N0	IO	CLK0p		DIFFIO_RX_L14p	DIFFOUT_L14p	High_Speed	J5
2	VREFB2N0	IO	CLK1n		DIFFIO_RX_L16n	DIFFOUT_L16n	High_Speed	K5
2	VREFB2N0	IO	CLK1p		DIFFIO_RX_L16p	DIFFOUT_L16p	High_Speed	K4
2	VREFB2N0	IO	DPCLK0		DIFFIO_RX_L18n	DIFFOUT_L18n	High_Speed	L5
2	VREFB2N0	IO	VREFB2N0					P1
2	VREFB2N0	IO	DPCLK1		DIFFIO_RX_L18p	DIFFOUT_L18p	High_Speed	L4
2	VREFB2N0	IO						R2
2	VREFB2N0	IO	PLL_L_CLKOUTn		DIFFIO_RX_L19n	DIFFOUT_L19n	High_Speed	N1
2	VREFB2N0	IO	PLL_L_CLKOUTp		DIFFIO_RX_L19p	DIFFOUT_L19p	High_Speed	P2
3	VREFB3N0	IO			DIFFIO_TX_RX_B1n	DIFFOUT_B1n	High_Speed	M4
3	VREFB3N0	IO			DIFFIO_RX_B2n	DIFFOUT_B2n	High_Speed	P3
3	VREFB3N0	IO			DIFFIO_TX_RX_B1p	DIFFOUT_B1p	High_Speed	M5
3	VREFB3N0	IO			DIFFIO_RX_B2p	DIFFOUT_B2p	High_Speed	R3
3	VREFB3N0	IO			DIFFIO_TX_RX_B3n	DIFFOUT_B3n	High_Speed	L6
3	VREFB3N0	IO			DIFFIO_RX_B4n	DIFFOUT_B4n	High_Speed	P4
3	VREFB3N0	IO			DIFFIO_TX_RX_B3p	DIFFOUT_B3p	High_Speed	L7
3	VREFB3N0	IO			DIFFIO_RX_B4p	DIFFOUT_B4p	High_Speed	R5
3	VREFB3N0	IO			DIFFIO_TX_RX_B5n	DIFFOUT_B5n	High_Speed	P6
3	VREFB3N0	IO			DIFFIO_RX_B6n	DIFFOUT_B6n	High_Speed	R7
3	VREFB3N0	IO			DIFFIO_TX_RX_B5p	DIFFOUT_B5p	High_Speed	P7
3	VREFB3N0	IO			DIFFIO_RX_B6p	DIFFOUT_B6p	High_Speed	P8
3	VREFB3N0	IO			DIFFIO_TX_RX_B7n	DIFFOUT_B7n	High_Speed	L8
3	VREFB3N0	IO			DIFFIO_RX_B8n	DIFFOUT_B8n	High_Speed	P9
3	VREFB3N0	IO			DIFFIO_TX_RX_B7p	DIFFOUT_B7p	High_Speed	M7
3	VREFB3N0	IO			DIFFIO_RX_B8p	DIFFOUT_B8p	High_Speed	R9
3	VREFB3N0	IO			DIFFIO_TX_RX_B9n	DIFFOUT_B9n	High_Speed	M8
3	VREFB3N0	IO	VREFB3N0					R11
3	VREFB3N0	IO			DIFFIO_TX_RX_B9p	DIFFOUT_B9p	High_Speed	N8
3	VREFB3N0	IO						P12
3	VREFB3N0	IO			DIFFIO_TX_RX_B10n	DIFFOUT_B10n	High_Speed	R14
3	VREFB3N0	IO			DIFFIO_TX_RX_B10p	DIFFOUT_B10p	High_Speed	P15
3	VREFB3N0	IO			DIFFIO_TX_RX_B12n	DIFFOUT_B12n	High_Speed	L9
3	VREFB3N0	IO			DIFFIO_TX_RX_B12p	DIFFOUT_B12p	High_Speed	M9
3	VREFB3N0	IO			DIFFIO_TX_RX_B14n	DIFFOUT_B14n	High_Speed	L10
3	VREFB3N0	IO			DIFFIO_TX_RX_B14p	DIFFOUT_B14p	High_Speed	M11
3	VREFB3N0	IO			DIFFIO_TX_RX_B16n	DIFFOUT_B16n	High_Speed	P14
3	VREFB3N0	IO			DIFFIO_TX_RX_B16p	DIFFOUT_B16p	High_Speed	R13
5	VREFB5N0	IO			DIFFIO_RX_R1p	DIFFOUT_R1p	High_Speed	M12
5	VREFB5N0	IO			DIFFIO_RX_R2p	DIFFOUT_R2p	High_Speed	N15
5	VREFB5N0	IO			DIFFIO_RX_R1n	DIFFOUT_R1n	High_Speed	L11
5	VREFB5N0	IO			DIFFIO_RX_R2n	DIFFOUT_R2n	High_Speed	N14
5	VREFB5N0	IO			DIFFIO_RX_R3p	DIFFOUT_R3p	High_Speed	K11
5	VREFB5N0	IO						M14
5	VREFB5N0	IO			DIFFIO_RX_R3n	DIFFOUT_R3n	High_Speed	K12
5	VREFB5N0	IO	VREFB5N0					L15
5	VREFB5N0	IO			DIFFIO_RX_R6p	DIFFOUT_R6p	High_Speed	J9
5	VREFB5N0	IO			DIFFIO_RX_R7p	DIFFOUT_R7p	High_Speed	K14
5	VREFB5N0	IO			DIFFIO_RX_R6n	DIFFOUT_R6n	High_Speed	J11
5	VREFB5N0	IO			DIFFIO_RX_R7n	DIFFOUT_R7n	High_Speed	J14
6	VREFB6N0	IO	CLK2p		DIFFIO_RX_R10p	DIFFOUT_R10p	High_Speed	J12
6	VREFB6N0	IO	CLK2n		DIFFIO_RX_R10n	DIFFOUT_R10n	High_Speed	H11
6	VREFB6N0	IO	CLK3p		DIFFIO_RX_R12p	DIFFOUT_R12p	High_Speed	H12
6	VREFB6N0	IO	CLK3n		DIFFIO_RX_R12n	DIFFOUT_R12n	High_Speed	H13
6	VREFB6N0	IO			DIFFIO_RX_R14p	DIFFOUT_R14p	High_Speed	J15
6	VREFB6N0	IO			DIFFIO_RX_R14n	DIFFOUT_R14n	High_Speed	G15
6	VREFB6N0	IO	DPCLK3		DIFFIO_RX_R16p	DIFFOUT_R16p	High_Speed	G11
6	VREFB6N0	IO	VREFB6N0					E15
6	VREFB6N0	IO	DPCLK2		DIFFIO_RX_R16n	DIFFOUT_R16n	High_Speed	G12
6	VREFB6N0	IO						E14
6	VREFB6N0	IO			DIFFIO_RX_R17p	DIFFOUT_R17p	High_Speed	F11
6	VREFB6N0	IO			DIFFIO_RX_R18p	DIFFOUT_R18p	High_Speed	C15
6	VREFB6N0	IO			DIFFIO_RX_R17n	DIFFOUT_R17n	High_Speed	F12
6	VREFB6N0	IO			DIFFIO_RX_R18n	DIFFOUT_R18n	High_Speed	C14
6	VREFB6N0	IO			DIFFIO_RX_R23p	DIFFOUT_R23p	High_Speed	E11
6	VREFB6N0	IO			DIFFIO_RX_R23n	DIFFOUT_R23n	High_Speed	D12
8	VREFB8N0	IO			DIFFIO_RX_T1p	DIFFOUT_T1p	Low_Speed	D11
8	VREFB8N0	IO			DIFFIO_RX_T2p	DIFFOUT_T2p	Low_Speed	B15
8	VREFB8N0	IO			DIFFIO_RX_T1n	DIFFOUT_T1n	Low_Speed	D10
8	VREFB8N0	IO			DIFFIO_RX_T2n	DIFFOUT_T2n	Low_Speed	B14
8	VREFB8N0	IO			DIFFIO_RX_T3p	DIFFOUT_T3p	Low_Speed	C8

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	IO Performance	M153
8	VREFB8N0	IO			DIFFIO_RX_T4p	DIFFOUT_T4p	Low_Speed	B13
8	VREFB8N0	IO		DEV_CLRn	DIFFIO_RX_T3n	DIFFOUT_T3n	Low_Speed	B8
8	VREFB8N0	IO			DIFFIO_RX_T4n	DIFFOUT_T4n	Low_Speed	A14
8	VREFB8N0	IO		DEV_OE	DIFFIO_RX_T5p	DIFFOUT_T5p	Low_Speed	E10
8	VREFB8N0	IO			DIFFIO_RX_T5n	DIFFOUT_T5n	Low_Speed	E9
8	VREFB8N0	IO	VREFB8N0					A13
8	VREFB8N0	IO		CONFIG_SEL				D8
8	VREFB8N0	IO			DIFFIO_RX_T6p	DIFFOUT_T6p	Low_Speed	B12
8	VREFB8N0	Input_only		nCONFIG				E8
8	VREFB8N0	IO			DIFFIO_RX_T6n	DIFFOUT_T6n	Low_Speed	B11
8	VREFB8N0	IO			DIFFIO_RX_T7p	DIFFOUT_T7p	Low_Speed	B7
8	VREFB8N0	IO			DIFFIO_RX_T8p	DIFFOUT_T8p	Low_Speed	A9
8	VREFB8N0	IO			DIFFIO_RX_T7n	DIFFOUT_T7n	Low_Speed	B6
8	VREFB8N0	IO			DIFFIO_RX_T8n	DIFFOUT_T8n	Low_Speed	A11
8	VREFB8N0	IO			DIFFIO_RX_T9p	DIFFOUT_T9p	Low_Speed	D7
8	VREFB8N0	IO			DIFFIO_RX_T10p	DIFFOUT_T10p	Low_Speed	A7
8	VREFB8N0	IO		CRC_ERROR	DIFFIO_RX_T9n	DIFFOUT_T9n	Low_Speed	E7
8	VREFB8N0	IO			DIFFIO_RX_T10n	DIFFOUT_T10n	Low_Speed	A5
8	VREFB8N0	IO		nSTATUS	DIFFIO_RX_T11p	DIFFOUT_T11p	Low_Speed	D6
8	VREFB8N0	IO						B4
8	VREFB8N0	IO		CONF_DONE	DIFFIO_RX_T11n	DIFFOUT_T11n	Low_Speed	E6
8	VREFB8N0	IO			DIFFIO_RX_T13p	DIFFOUT_T13p	Low_Speed	A2
8	VREFB8N0	IO			DIFFIO_RX_T13n	DIFFOUT_T13n	Low_Speed	A3
		GND						R15
		GND						R1
		GND						M6
		GND						M2
		GND						M10
		GND						L12
		GND						J7
		GND						H8
		GND						H14
		GND						G9
		GND						G4
		GND						E5
		GND						E12
		GND						D9
		GND						D5
		GND						B2
		GND						A15
		GND						A1
		VCCIO1						F2
		VCCIO1						H2
		VCCIO2						L2
		VCCIO3						P5
		VCCIO3						P11
		VCCIO3						P10
		VCCIO5						L14
		VCCIO6						G14
		VCCIO6						F14
		VCCIO8						B9
		VCCIO8						B5
		VCCIO8						B10
		NC						F4
		NC						E4
		NC						D4
		VCCA1						N2
		VCCA2						D14
		VCCA3						B3
		VCCA4						P13
		VCC_ONE						J8
		VCC_ONE						H9
		VCC_ONE						H7
		VCC_ONE						G8

Note:
(1) For more information about pin definition and pin connection guidelines, refer to the
Intel MAX 10 FPGA Device Family Pin Connection Guidelines.

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	IO Performance	U169
1A	VREFB1N0	IO			DIFFIO_RX_L1n	DIFFOUT_L1n	Low Speed	D1
1A	VREFB1N0	IO			DIFFIO_RX_L2n	DIFFOUT_L2n	Low Speed	C1
1A	VREFB1N0	IO			DIFFIO_RX_L1p	DIFFOUT_L1p	Low Speed	C2
1A	VREFB1N0	IO			DIFFIO_RX_L2p	DIFFOUT_L2p	Low Speed	B1
1A	VREFB1N0	IO			DIFFIO_RX_L3n	DIFFOUT_L3n	Low Speed	E3
1A	VREFB1N0	IO			DIFFIO_RX_L4n	DIFFOUT_L4n	Low Speed	F1
1A	VREFB1N0	IO			DIFFIO_RX_L3p	DIFFOUT_L3p	Low Speed	E4
1A	VREFB1N0	IO			DIFFIO_RX_L4p	DIFFOUT_L4p	Low Speed	E1
1B	VREFB1N0	IO		JTAGEN				E5
1B	VREFB1N0	IO		TMS	DIFFIO_RX_L7n	DIFFOUT_L7n	Low Speed	G1
1B	VREFB1N0	IO	VREFB1N0					H1
1B	VREFB1N0	IO		TCK	DIFFIO_RX_L7p	DIFFOUT_L7p	Low Speed	G2
1B	VREFB1N0	IO		TDI	DIFFIO_RX_L8n	DIFFOUT_L8n	Low Speed	F5
1B	VREFB1N0	IO		TDO	DIFFIO_RX_L8p	DIFFOUT_L8p	Low Speed	F6
1B	VREFB1N0	IO			DIFFIO_RX_L10n	DIFFOUT_L10n	Low Speed	F4
1B	VREFB1N0	IO			DIFFIO_RX_L10p	DIFFOUT_L10p	Low Speed	G4
1B	VREFB1N0	IO			DIFFIO_RX_L12n	DIFFOUT_L12n	Low Speed	H2
1B	VREFB1N0	IO			DIFFIO_RX_L12p	DIFFOUT_L12p	Low Speed	H3
2	VREFB2N0	IO	CLK0n		DIFFIO_RX_L14n	DIFFOUT_L14n	High Speed	G5
2	VREFB2N0	IO			DIFFIO_RX_L15n	DIFFOUT_L15n	High Speed	J1
2	VREFB2N0	IO	CLK0p		DIFFIO_RX_L14p	DIFFOUT_L14p	High Speed	H6
2	VREFB2N0	IO			DIFFIO_RX_L15p	DIFFOUT_L15p	High Speed	J2
2	VREFB2N0	IO	CLK1n		DIFFIO_RX_L16n	DIFFOUT_L16n	High Speed	H5
2	VREFB2N0	IO			DIFFIO_RX_L17n	DIFFOUT_L17n	High Speed	M1
2	VREFB2N0	IO	CLK1p		DIFFIO_RX_L16p	DIFFOUT_L16p	High Speed	H4
2	VREFB2N0	IO			DIFFIO_RX_L17p	DIFFOUT_L17p	High Speed	M2
2	VREFB2N0	IO	DPCLK0		DIFFIO_RX_L18n	DIFFOUT_L18n	High Speed	N2
2	VREFB2N0	IO	VREFB2N0					L1
2	VREFB2N0	IO	DPCLK1		DIFFIO_RX_L18p	DIFFOUT_L18p	High Speed	N3
2	VREFB2N0	IO						L2
2	VREFB2N0	IO	PLL_L_CLKOUTn		DIFFIO_RX_L19n	DIFFOUT_L19n	High Speed	M3
2	VREFB2N0	IO			DIFFIO_RX_L20n	DIFFOUT_L20n	High Speed	K1
2	VREFB2N0	IO	PLL_L_CLKOUTp		DIFFIO_RX_L19p	DIFFOUT_L19p	High Speed	L3
2	VREFB2N0	IO			DIFFIO_RX_L20p	DIFFOUT_L20p	High Speed	K2
3	VREFB3N0	IO			DIFFIO_TX_RX_B1n	DIFFOUT_B1n	High Speed	L5
3	VREFB3N0	IO			DIFFIO_RX_B2n	DIFFOUT_B2n	High Speed	M4
3	VREFB3N0	IO			DIFFIO_TX_RX_B1p	DIFFOUT_B1p	High Speed	L4
3	VREFB3N0	IO			DIFFIO_RX_B2p	DIFFOUT_B2p	High Speed	M5
3	VREFB3N0	IO			DIFFIO_TX_RX_B3n	DIFFOUT_B3n	High Speed	K5
3	VREFB3N0	IO			DIFFIO_RX_B4n	DIFFOUT_B4n	High Speed	N4
3	VREFB3N0	IO			DIFFIO_TX_RX_B3p	DIFFOUT_B3p	High Speed	J5
3	VREFB3N0	IO			DIFFIO_RX_B4p	DIFFOUT_B4p	High Speed	N5
3	VREFB3N0	IO			DIFFIO_TX_RX_B5n	DIFFOUT_B5n	High Speed	N6
3	VREFB3N0	IO			DIFFIO_RX_B6n	DIFFOUT_B6n	High Speed	N7
3	VREFB3N0	IO			DIFFIO_TX_RX_B5p	DIFFOUT_B5p	High Speed	M7
3	VREFB3N0	IO			DIFFIO_RX_B6p	DIFFOUT_B6p	High Speed	N8
3	VREFB3N0	IO			DIFFIO_TX_RX_B7n	DIFFOUT_B7n	High Speed	J6
3	VREFB3N0	IO			DIFFIO_RX_B8n	DIFFOUT_B8n	High Speed	M8
3	VREFB3N0	IO			DIFFIO_TX_RX_B7p	DIFFOUT_B7p	High Speed	K6
3	VREFB3N0	IO			DIFFIO_RX_B8p	DIFFOUT_B8p	High Speed	M9
3	VREFB3N0	IO			DIFFIO_TX_RX_B9n	DIFFOUT_B9n	High Speed	J7
3	VREFB3N0	IO	VREFB3N0					N11
3	VREFB3N0	IO			DIFFIO_TX_RX_B9p	DIFFOUT_B9p	High Speed	K7
3	VREFB3N0	IO						N12
3	VREFB3N0	IO			DIFFIO_TX_RX_B10n	DIFFOUT_B10n	High Speed	M13
3	VREFB3N0	IO			DIFFIO_RX_B11n	DIFFOUT_B11n	High Speed	N10
3	VREFB3N0	IO			DIFFIO_TX_RX_B10p	DIFFOUT_B10p	High Speed	M12
3	VREFB3N0	IO			DIFFIO_RX_B11p	DIFFOUT_B11p	High Speed	N9
3	VREFB3N0	IO			DIFFIO_TX_RX_B12n	DIFFOUT_B12n	High Speed	M11
3	VREFB3N0	IO			DIFFIO_TX_RX_B12p	DIFFOUT_B12p	High Speed	L11
3	VREFB3N0	IO			DIFFIO_TX_RX_B14n	DIFFOUT_B14n	High Speed	J8
3	VREFB3N0	IO			DIFFIO_TX_RX_B14p	DIFFOUT_B14p	High Speed	K8
3	VREFB3N0	IO			DIFFIO_TX_RX_B16n	DIFFOUT_B16n	High Speed	M10
3	VREFB3N0	IO			DIFFIO_TX_RX_B16p	DIFFOUT_B16p	High Speed	L10
5	VREFB5N0	IO			DIFFIO_RX_R1p	DIFFOUT_R1p	High Speed	K10
5	VREFB5N0	IO			DIFFIO_RX_R2p	DIFFOUT_R2p	High Speed	K11
5	VREFB5N0	IO			DIFFIO_RX_R1n	DIFFOUT_R1n	High Speed	J10
5	VREFB5N0	IO			DIFFIO_RX_R2n	DIFFOUT_R2n	High Speed	L12
5	VREFB5N0	IO			DIFFIO_RX_R3p	DIFFOUT_R3p	High Speed	K12
5	VREFB5N0	IO						L13
5	VREFB5N0	IO			DIFFIO_RX_R3n	DIFFOUT_R3n	High Speed	J12
5	VREFB5N0	IO	VREFB5N0					K13
5	VREFB5N0	IO			DIFFIO_RX_R4p	DIFFOUT_R4p	High Speed	J9
5	VREFB5N0	IO			DIFFIO_RX_R5p	DIFFOUT_R5p	High Speed	J13
5	VREFB5N0	IO			DIFFIO_RX_R4n	DIFFOUT_R4n	High Speed	H10
5	VREFB5N0	IO			DIFFIO_RX_R5n	DIFFOUT_R5n	High Speed	H13
5	VREFB5N0	IO			DIFFIO_RX_R6p	DIFFOUT_R6p	High Speed	H9
5	VREFB5N0	IO			DIFFIO_RX_R7p	DIFFOUT_R7p	High Speed	G13
5	VREFB5N0	IO			DIFFIO_RX_R6n	DIFFOUT_R6n	High Speed	H8
5	VREFB5N0	IO			DIFFIO_RX_R7n	DIFFOUT_R7n	High Speed	G12
6	VREFB6N0	IO	CLK2p		DIFFIO_RX_R10p	DIFFOUT_R10p	High Speed	G9
6	VREFB6N0	IO	CLK2n		DIFFIO_RX_R10n	DIFFOUT_R10n	High Speed	G10
6	VREFB6N0	IO	CLK3p		DIFFIO_RX_R12p	DIFFOUT_R12p	High Speed	F13
6	VREFB6N0	IO	CLK3n		DIFFIO_RX_R12n	DIFFOUT_R12n	High Speed	E13
6	VREFB6N0	IO			DIFFIO_RX_R14p	DIFFOUT_R14p	High Speed	F12
6	VREFB6N0	IO			DIFFIO_RX_R14n	DIFFOUT_R14n	High Speed	E12
6	VREFB6N0	IO	DPCLK3		DIFFIO_RX_R16p	DIFFOUT_R16p	High Speed	F9
6	VREFB6N0	IO	VREFB6N0					D13
6	VREFB6N0	IO	DPCLK2		DIFFIO_RX_R16n	DIFFOUT_R16n	High Speed	F10
6	VREFB6N0	IO						C13
6	VREFB6N0	IO			DIFFIO_RX_R17p	DIFFOUT_R17p	High Speed	F8

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	IO Performance	U169
6	VREFB6N0	IO			DIFFIO_RX_R18p	DIFFOUT_R18p	High Speed	B12
6	VREFB6N0	IO			DIFFIO_RX_R17n	DIFFOUT_R17n	High Speed	E9
6	VREFB6N0	IO			DIFFIO_RX_R18n	DIFFOUT_R18n	High Speed	B11
6	VREFB6N0	IO			DIFFIO_RX_R19p	DIFFOUT_R19p	High Speed	C12
6	VREFB6N0	IO			DIFFIO_RX_R20p	DIFFOUT_R20p	High Speed	B13
6	VREFB6N0	IO			DIFFIO_RX_R19n	DIFFOUT_R19n	High Speed	C11
6	VREFB6N0	IO			DIFFIO_RX_R20n	DIFFOUT_R20n	High Speed	A12
6	VREFB6N0	IO			DIFFIO_RX_R21p	DIFFOUT_R21p	High Speed	E10
6	VREFB6N0	IO			DIFFIO_RX_R21n	DIFFOUT_R21n	High Speed	D9
6	VREFB6N0	IO			DIFFIO_RX_R23p	DIFFOUT_R23p	High Speed	D12
6	VREFB6N0	IO			DIFFIO_RX_R23n	DIFFOUT_R23n	High Speed	D11
8	VREFB8N0	IO			DIFFIO_RX_T1p	DIFFOUT_T1p	Low Speed	C10
8	VREFB8N0	IO			DIFFIO_RX_T2p	DIFFOUT_T2p	Low Speed	A8
8	VREFB8N0	IO			DIFFIO_RX_T1n	DIFFOUT_T1n	Low Speed	C9
8	VREFB8N0	IO			DIFFIO_RX_T2n	DIFFOUT_T2n	Low Speed	A9
8	VREFB8N0	IO			DIFFIO_RX_T3p	DIFFOUT_T3p	Low Speed	B10
8	VREFB8N0	IO			DIFFIO_RX_T4p	DIFFOUT_T4p	Low Speed	A10
8	VREFB8N0	IO		DEV_CLRn	DIFFIO_RX_T3n	DIFFOUT_T3n	Low Speed	B9
8	VREFB8N0	IO			DIFFIO_RX_T4n	DIFFOUT_T4n	Low Speed	A11
8	VREFB8N0	IO		DEV_OE	DIFFIO_RX_T5p	DIFFOUT_T5p	Low Speed	D8
8	VREFB8N0	IO			DIFFIO_RX_T5n	DIFFOUT_T5n	Low Speed	E8
8	VREFB8N0	IO	VREFB8N0					B7
8	VREFB8N0	IO		CONFIG_SEL				D7
8	VREFB8N0	IO			DIFFIO_RX_T6p	DIFFOUT_T6p	Low Speed	A7
8	VREFB8N0	Input_only		nCONFIG				E7
8	VREFB8N0	IO			DIFFIO_RX_T6n	DIFFOUT_T6n	Low Speed	A6
8	VREFB8N0	IO			DIFFIO_RX_T7p	DIFFOUT_T7p	Low Speed	B6
8	VREFB8N0	IO			DIFFIO_RX_T8p	DIFFOUT_T8p	Low Speed	A4
8	VREFB8N0	IO			DIFFIO_RX_T7n	DIFFOUT_T7n	Low Speed	B5
8	VREFB8N0	IO			DIFFIO_RX_T8n	DIFFOUT_T8n	Low Speed	A3
8	VREFB8N0	IO			DIFFIO_RX_T9p	DIFFOUT_T9p	Low Speed	E6
8	VREFB8N0	IO			DIFFIO_RX_T10p	DIFFOUT_T10p	Low Speed	B3
8	VREFB8N0	IO		CRC_ERROR	DIFFIO_RX_T9n	DIFFOUT_T9n	Low Speed	D6
8	VREFB8N0	IO			DIFFIO_RX_T10n	DIFFOUT_T10n	Low Speed	B4
8	VREFB8N0	IO		nSTATUS	DIFFIO_RX_T11p	DIFFOUT_T11p	Low Speed	C4
8	VREFB8N0	IO						A5
8	VREFB8N0	IO		CONF_DONE	DIFFIO_RX_T11n	DIFFOUT_T11n	Low Speed	C5
8	VREFB8N0	IO			DIFFIO_RX_T13p	DIFFOUT_T13p	Low Speed	A2
8	VREFB8N0	IO			DIFFIO_RX_T13n	DIFFOUT_T13n	Low Speed	B2
		GND						N13
		GND						N1
		GND						M6
		GND						L9
		GND						J4
		GND						H12
		GND						G7
		GND						F3
		GND						E11
		GND						D5
		GND						C3
		GND						B8
		GND						A13
		GND						A1
		VCCIO1						F2
		VCCIO1						G3
		VCCIO2						K3
		VCCIO2						J3
		VCCIO3						L8
		VCCIO3						L7
		VCCIO3						L6
		VCCIO5						J11
		VCCIO5						H11
		VCCIO6						G11
		VCCIO6						F11
		VCCIO8						C8
		VCCIO8						C7
		VCCIO8						C6
		NC						E2
		NC						D3
		NC						D2
		VCCA1						K4
		VCCA2						D10
		VCCA3						D4
		VCCA4						K9
		VCC_ONE						H7
		VCC_ONE						G8
		VCC_ONE						G6
		VCC_ONE						F7

Note:
(1) For more information about pin definition and pin connection guidelines, refer to the
Intel MAX 10 FPGA Device Family Pin Connection Guidelines.

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	IO Performance	U324
1A	VREFB1N0	IO			DIFFIO_RX_L1n	DIFFOUT_L1n	Low_Speed	D4
1A	VREFB1N0	IO			DIFFIO_RX_L2n	DIFFOUT_L2n	Low_Speed	C2
1A	VREFB1N0	IO			DIFFIO_RX_L1p	DIFFOUT_L1p	Low_Speed	E4
1A	VREFB1N0	IO			DIFFIO_RX_L2p	DIFFOUT_L2p	Low_Speed	D2
1A	VREFB1N0	IO			DIFFIO_RX_L3n	DIFFOUT_L3n	Low_Speed	G6
1A	VREFB1N0	IO			DIFFIO_RX_L4n	DIFFOUT_L4n	Low_Speed	B1
1A	VREFB1N0	IO			DIFFIO_RX_L3p	DIFFOUT_L3p	Low_Speed	H6
1A	VREFB1N0	IO			DIFFIO_RX_L4p	DIFFOUT_L4p	Low_Speed	C1
1A	VREFB1N0	IO			DIFFIO_RX_L5n	DIFFOUT_L5n	Low_Speed	F5
1A	VREFB1N0	IO			DIFFIO_RX_L6n	DIFFOUT_L6n	Low_Speed	D1
1A	VREFB1N0	IO			DIFFIO_RX_L5p	DIFFOUT_L5p	Low_Speed	E5
1A	VREFB1N0	IO			DIFFIO_RX_L6p	DIFFOUT_L6p	Low_Speed	E1
1A	VREFB1N0	IO			DIFFIO_RX_L7n	DIFFOUT_L7n	Low_Speed	G3
1A	VREFB1N0	IO			DIFFIO_RX_L8n	DIFFOUT_L8n	Low_Speed	F1
1A	VREFB1N0	IO			DIFFIO_RX_L7p	DIFFOUT_L7p	Low_Speed	F2
1A	VREFB1N0	IO			DIFFIO_RX_L8p	DIFFOUT_L8p	Low_Speed	G1
1B	VREFB1N0	IO			DIFFIO_RX_L9n	DIFFOUT_L9n	Low_Speed	G7
1B	VREFB1N0	IO			DIFFIO_RX_L10n	DIFFOUT_L10n	Low_Speed	H2
1B	VREFB1N0	IO		JTAGEN	DIFFIO_RX_L9p	DIFFOUT_L9p	Low_Speed	H7
1B	VREFB1N0	IO			DIFFIO_RX_L10p	DIFFOUT_L10p	Low_Speed	H1
1B	VREFB1N0	IO		TMS	DIFFIO_RX_L11n	DIFFOUT_L11n	Low_Speed	J7
1B	VREFB1N0	IO	VREFB1N0				Low_Speed	J3
1B	VREFB1N0	IO		TCK	DIFFIO_RX_L11p	DIFFOUT_L11p	Low_Speed	J8
1B	VREFB1N0	IO					Low_Speed	J4
1B	VREFB1N0	IO		TDI	DIFFIO_RX_L12n	DIFFOUT_L12n	Low_Speed	H3
1B	VREFB1N0	IO			DIFFIO_RX_L13n	DIFFOUT_L13n	Low_Speed	J2
1B	VREFB1N0	IO		TDO	DIFFIO_RX_L12p	DIFFOUT_L12p	Low_Speed	H4
1B	VREFB1N0	IO			DIFFIO_RX_L13p	DIFFOUT_L13p	Low_Speed	J1
1B	VREFB1N0	IO			DIFFIO_RX_L14n	DIFFOUT_L14n	Low_Speed	J6
1B	VREFB1N0	IO			DIFFIO_RX_L15n	DIFFOUT_L15n	Low_Speed	K2
1B	VREFB1N0	IO			DIFFIO_RX_L14p	DIFFOUT_L14p	Low_Speed	K7
1B	VREFB1N0	IO			DIFFIO_RX_L15p	DIFFOUT_L15p	Low_Speed	K1
1B	VREFB1N0	IO			DIFFIO_RX_L16n	DIFFOUT_L16n	Low_Speed	K4
1B	VREFB1N0	IO			DIFFIO_RX_L17n	DIFFOUT_L17n	Low_Speed	L1
1B	VREFB1N0	IO			DIFFIO_RX_L16p	DIFFOUT_L16p	Low_Speed	K3
1B	VREFB1N0	IO			DIFFIO_RX_L17p	DIFFOUT_L17p	Low_Speed	L2
2	VREFB2N0	IO	CLK0n		DIFFIO_RX_L18n	DIFFOUT_L18n	High_Speed	L3
2	VREFB2N0	IO			DIFFIO_RX_L19n	DIFFOUT_L19n	High_Speed	M1
2	VREFB2N0	IO	CLK0p		DIFFIO_RX_L18p	DIFFOUT_L18p	High_Speed	M3
2	VREFB2N0	IO			DIFFIO_RX_L19p	DIFFOUT_L19p	High_Speed	M2
2	VREFB2N0	IO	CLK1n		DIFFIO_RX_L20n	DIFFOUT_L20n	High_Speed	K8
2	VREFB2N0	IO			DIFFIO_RX_L21n	DIFFOUT_L21n	High_Speed	N1
2	VREFB2N0	IO	CLK1p		DIFFIO_RX_L20p	DIFFOUT_L20p	High_Speed	L8
2	VREFB2N0	IO			DIFFIO_RX_L21p	DIFFOUT_L21p	High_Speed	P1
2	VREFB2N0	IO	DPCLK0		DIFFIO_RX_L22n	DIFFOUT_L22n	High_Speed	M4
2	VREFB2N0	IO	VREFB2N0				High_Speed	R1
2	VREFB2N0	IO	DPCLK1		DIFFIO_RX_L22p	DIFFOUT_L22p	High_Speed	N3
2	VREFB2N0	IO					High_Speed	R2
2	VREFB2N0	IO			DIFFIO_RX_L23n	DIFFOUT_L23n	High_Speed	R3
2	VREFB2N0	IO			DIFFIO_RX_L24n	DIFFOUT_L24n	High_Speed	P2
2	VREFB2N0	IO			DIFFIO_RX_L23p	DIFFOUT_L23p	High_Speed	T3
2	VREFB2N0	IO			DIFFIO_RX_L24p	DIFFOUT_L24p	High_Speed	P3
2	VREFB2N0	IO			DIFFIO_RX_L25n	DIFFOUT_L25n	High_Speed	L7
2	VREFB2N0	IO			DIFFIO_RX_L26n	DIFFOUT_L26n	High_Speed	T1
2	VREFB2N0	IO			DIFFIO_RX_L25p	DIFFOUT_L25p	High_Speed	M7
2	VREFB2N0	IO			DIFFIO_RX_L26p	DIFFOUT_L26p	High_Speed	T2
2	VREFB2N0	IO	PLL_L_CLKOUTn		DIFFIO_RX_L27n	DIFFOUT_L27n	High_Speed	N4
2	VREFB2N0	IO			DIFFIO_RX_L28n	DIFFOUT_L28n	High_Speed	U1
2	VREFB2N0	IO	PLL_L_CLKOUTp		DIFFIO_RX_L27p	DIFFOUT_L27p	High_Speed	P4
2	VREFB2N0	IO			DIFFIO_RX_L28p	DIFFOUT_L28p	High_Speed	U2
3	VREFB3N0	IO			DIFFIO_TX_RX_B1n	DIFFOUT_B1n	High_Speed	R4
3	VREFB3N0	IO			DIFFIO_RX_B2n	DIFFOUT_B2n	High_Speed	U3
3	VREFB3N0	IO			DIFFIO_TX_RX_B1p	DIFFOUT_B1p	High_Speed	T4
3	VREFB3N0	IO			DIFFIO_RX_B2p	DIFFOUT_B2p	High_Speed	V2
3	VREFB3N0	IO			DIFFIO_TX_RX_B3n	DIFFOUT_B3n	High_Speed	P6
3	VREFB3N0	IO			DIFFIO_RX_B4n	DIFFOUT_B4n	High_Speed	V3
3	VREFB3N0	IO			DIFFIO_TX_RX_B3p	DIFFOUT_B3p	High_Speed	P5
3	VREFB3N0	IO			DIFFIO_RX_B4p	DIFFOUT_B4p	High_Speed	V4
3	VREFB3N0	IO			DIFFIO_TX_RX_B5n	DIFFOUT_B5n	High_Speed	R5
3	VREFB3N0	IO			DIFFIO_RX_B6n	DIFFOUT_B6n	High_Speed	U5
3	VREFB3N0	IO			DIFFIO_TX_RX_B5p	DIFFOUT_B5p	High_Speed	R6
3	VREFB3N0	IO			DIFFIO_RX_B6p	DIFFOUT_B6p	High_Speed	V5
3	VREFB3N0	IO			DIFFIO_TX_RX_B7n	DIFFOUT_B7n	High_Speed	T5
3	VREFB3N0	IO			DIFFIO_RX_B8n	DIFFOUT_B8n	High_Speed	T7
3	VREFB3N0	IO			DIFFIO_TX_RX_B7p	DIFFOUT_B7p	High_Speed	T6
3	VREFB3N0	IO			DIFFIO_RX_B8p	DIFFOUT_B8p	High_Speed	T8
3	VREFB3N0	IO			DIFFIO_TX_RX_B9n	DIFFOUT_B9n	High_Speed	N7
3	VREFB3N0	IO	VREFB3N0				High_Speed	U6
3	VREFB3N0	IO			DIFFIO_TX_RX_B9p	DIFFOUT_B9p	High_Speed	N8
3	VREFB3N0	IO					High_Speed	V6
3	VREFB3N0	IO			DIFFIO_TX_RX_B10n	DIFFOUT_B10n	High_Speed	R8
3	VREFB3N0	IO			DIFFIO_RX_B11n	DIFFOUT_B11n	High_Speed	U7
3	VREFB3N0	IO			DIFFIO_TX_RX_B10p	DIFFOUT_B10p	High_Speed	R9
3	VREFB3N0	IO			DIFFIO_RX_B11p	DIFFOUT_B11p	High_Speed	V7
3	VREFB3N0	IO			DIFFIO_TX_RX_B12n	DIFFOUT_B12n	High_Speed	V9
3	VREFB3N0	IO			DIFFIO_RX_B13n	DIFFOUT_B13n	High_Speed	U8
3	VREFB3N0	IO			DIFFIO_TX_RX_B12p	DIFFOUT_B12p	High_Speed	U9
3	VREFB3N0	IO			DIFFIO_RX_B13p	DIFFOUT_B13p	High_Speed	V8
3	VREFB3N0	IO			DIFFIO_TX_RX_B14n	DIFFOUT_B14n	High_Speed	M8

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	IO Performance	U324
3	VREFB3N0	IO			DIFFIO_RX_B15n	DIFFOUT_B15n	High_Speed	V10
3	VREFB3N0	IO			DIFFIO_TX_RX_B14p	DIFFOUT_B14p	High_Speed	M9
3	VREFB3N0	IO			DIFFIO_RX_B15p	DIFFOUT_B15p	High_Speed	V11
3	VREFB3N0	IO			DIFFIO_TX_RX_B16n	DIFFOUT_B16n	High_Speed	T9
3	VREFB3N0	IO			DIFFIO_RX_B17n	DIFFOUT_B17n	High_Speed	V12
3	VREFB3N0	IO			DIFFIO_TX_RX_B16p	DIFFOUT_B16p	High_Speed	T10
3	VREFB3N0	IO			DIFFIO_RX_B17p	DIFFOUT_B17p	High_Speed	U11
4	VREFB4N0	IO			DIFFIO_TX_RX_B18n	DIFFOUT_B18n	High_Speed	P10
4	VREFB4N0	IO			DIFFIO_RX_B19n	DIFFOUT_B19n	High_Speed	U12
4	VREFB4N0	IO			DIFFIO_TX_RX_B18p	DIFFOUT_B18p	High_Speed	N11
4	VREFB4N0	IO			DIFFIO_RX_B19p	DIFFOUT_B19p	High_Speed	U13
4	VREFB4N0	IO			DIFFIO_TX_RX_B20n	DIFFOUT_B20n	High_Speed	M10
4	VREFB4N0	IO	VREFB4N0				High_Speed	T11
4	VREFB4N0	IO			DIFFIO_TX_RX_B20p	DIFFOUT_B20p	High_Speed	L10
4	VREFB4N0	IO					High_Speed	T12
4	VREFB4N0	IO			DIFFIO_TX_RX_B21n	DIFFOUT_B21n	High_Speed	R10
4	VREFB4N0	IO			DIFFIO_RX_B22n	DIFFOUT_B22n	High_Speed	V13
4	VREFB4N0	IO			DIFFIO_TX_RX_B21p	DIFFOUT_B21p	High_Speed	R11
4	VREFB4N0	IO			DIFFIO_RX_B22p	DIFFOUT_B22p	High_Speed	V14
4	VREFB4N0	IO			DIFFIO_TX_RX_B23n	DIFFOUT_B23n	High_Speed	R12
4	VREFB4N0	IO			DIFFIO_RX_B24n	DIFFOUT_B24n	High_Speed	T13
4	VREFB4N0	IO			DIFFIO_TX_RX_B23p	DIFFOUT_B23p	High_Speed	R13
4	VREFB4N0	IO			DIFFIO_RX_B24p	DIFFOUT_B24p	High_Speed	T14
4	VREFB4N0	IO			DIFFIO_TX_RX_B25n	DIFFOUT_B25n	High_Speed	R14
4	VREFB4N0	IO			DIFFIO_RX_B26n	DIFFOUT_B26n	High_Speed	V15
4	VREFB4N0	IO			DIFFIO_TX_RX_B25p	DIFFOUT_B25p	High_Speed	T15
4	VREFB4N0	IO			DIFFIO_RX_B26p	DIFFOUT_B26p	High_Speed	U15
4	VREFB4N0	IO			DIFFIO_TX_RX_B27n	DIFFOUT_B27n	High_Speed	U16
4	VREFB4N0	IO			DIFFIO_RX_B28n	DIFFOUT_B28n	High_Speed	V16
4	VREFB4N0	IO			DIFFIO_TX_RX_B27p	DIFFOUT_B27p	High_Speed	U17
4	VREFB4N0	IO			DIFFIO_RX_B28p	DIFFOUT_B28p	High_Speed	V17
5	VREFB5N0	IO			DIFFIO_RX_R1p	DIFFOUT_R1p	High_Speed	N14
5	VREFB5N0	IO			DIFFIO_RX_R2p	DIFFOUT_R2p	High_Speed	T16
5	VREFB5N0	IO			DIFFIO_RX_R1n	DIFFOUT_R1n	High_Speed	P14
5	VREFB5N0	IO			DIFFIO_RX_R2n	DIFFOUT_R2n	High_Speed	R16
5	VREFB5N0	IO			DIFFIO_RX_R3p	DIFFOUT_R3p	High_Speed	M12
5	VREFB5N0	IO			DIFFIO_RX_R4p	DIFFOUT_R4p	High_Speed	U18
5	VREFB5N0	IO			DIFFIO_RX_R3n	DIFFOUT_R3n	High_Speed	M11
5	VREFB5N0	IO			DIFFIO_RX_R4n	DIFFOUT_R4n	High_Speed	T18
5	VREFB5N0	IO			DIFFIO_RX_R5p	DIFFOUT_R5p	High_Speed	N15
5	VREFB5N0	IO			DIFFIO_RX_R6p	DIFFOUT_R6p	High_Speed	N16
5	VREFB5N0	IO			DIFFIO_RX_R5n	DIFFOUT_R5n	High_Speed	M15
5	VREFB5N0	IO			DIFFIO_RX_R6n	DIFFOUT_R6n	High_Speed	M16
5	VREFB5N0	IO			DIFFIO_RX_R7p	DIFFOUT_R7p	High_Speed	R15
5	VREFB5N0	IO					High_Speed	P16
5	VREFB5N0	IO			DIFFIO_RX_R7n	DIFFOUT_R7n	High_Speed	P15
5	VREFB5N0	IO	VREFB5N0				High_Speed	P17
5	VREFB5N0	IO			DIFFIO_RX_R8p	DIFFOUT_R8p	High_Speed	L12
5	VREFB5N0	IO			DIFFIO_RX_R9p	DIFFOUT_R9p	High_Speed	T17
5	VREFB5N0	IO			DIFFIO_RX_R8n	DIFFOUT_R8n	High_Speed	L11
5	VREFB5N0	IO			DIFFIO_RX_R9n	DIFFOUT_R9n	High_Speed	R17
5	VREFB5N0	IO			DIFFIO_RX_R10p	DIFFOUT_R10p	High_Speed	L15
5	VREFB5N0	IO			DIFFIO_RX_R11p	DIFFOUT_R11p	High_Speed	L16
5	VREFB5N0	IO			DIFFIO_RX_R10n	DIFFOUT_R10n	High_Speed	K15
5	VREFB5N0	IO			DIFFIO_RX_R11n	DIFFOUT_R11n	High_Speed	K16
5	VREFB5N0	IO			DIFFIO_RX_R12p	DIFFOUT_R12p	High_Speed	R18
5	VREFB5N0	IO			DIFFIO_RX_R13p	DIFFOUT_R13p	High_Speed	N18
5	VREFB5N0	IO			DIFFIO_RX_R12n	DIFFOUT_R12n	High_Speed	P18
5	VREFB5N0	IO			DIFFIO_RX_R13n	DIFFOUT_R13n	High_Speed	M18
6	VREFB6N0	IO	CLK2p		DIFFIO_RX_R14p	DIFFOUT_R14p	High_Speed	K12
6	VREFB6N0	IO			DIFFIO_RX_R15p	DIFFOUT_R15p	High_Speed	M17
6	VREFB6N0	IO	CLK2n		DIFFIO_RX_R14n	DIFFOUT_R14n	High_Speed	K11
6	VREFB6N0	IO			DIFFIO_RX_R15n	DIFFOUT_R15n	High_Speed	L18
6	VREFB6N0	IO	CLK3p		DIFFIO_RX_R16p	DIFFOUT_R16p	High_Speed	L17
6	VREFB6N0	IO			DIFFIO_RX_R17p	DIFFOUT_R17p	High_Speed	K18
6	VREFB6N0	IO	CLK3n		DIFFIO_RX_R16n	DIFFOUT_R16n	High_Speed	K17
6	VREFB6N0	IO			DIFFIO_RX_R17n	DIFFOUT_R17n	High_Speed	J18
6	VREFB6N0	IO			DIFFIO_RX_R18p	DIFFOUT_R18p	High_Speed	H18
6	VREFB6N0	IO			DIFFIO_RX_R19p	DIFFOUT_R19p	High_Speed	H17
6	VREFB6N0	IO			DIFFIO_RX_R18n	DIFFOUT_R18n	High_Speed	G18
6	VREFB6N0	IO			DIFFIO_RX_R19n	DIFFOUT_R19n	High_Speed	G17
6	VREFB6N0	IO			DIFFIO_RX_R20p	DIFFOUT_R20p	High_Speed	J11
6	VREFB6N0	IO			DIFFIO_RX_R20n	DIFFOUT_R20n	High_Speed	J12
6	VREFB6N0	IO			DIFFIO_RX_R22p	DIFFOUT_R22p	High_Speed	J15
6	VREFB6N0	IO			DIFFIO_RX_R23p	DIFFOUT_R23p	High_Speed	J16
6	VREFB6N0	IO			DIFFIO_RX_R22n	DIFFOUT_R22n	High_Speed	H15
6	VREFB6N0	IO			DIFFIO_RX_R23n	DIFFOUT_R23n	High_Speed	H16
6	VREFB6N0	IO	DPCLK3		DIFFIO_RX_R26p	DIFFOUT_R26p	High_Speed	H11
6	VREFB6N0	IO	VREFB6N0				High_Speed	F18
6	VREFB6N0	IO	DPCLK2		DIFFIO_RX_R26n	DIFFOUT_R26n	High_Speed	H12
6	VREFB6N0	IO					High_Speed	E18
6	VREFB6N0	IO			DIFFIO_RX_R27p	DIFFOUT_R27p	High_Speed	F15
6	VREFB6N0	IO			DIFFIO_RX_R28p	DIFFOUT_R28p	High_Speed	G16
6	VREFB6N0	IO			DIFFIO_RX_R27n	DIFFOUT_R27n	High_Speed	G15
6	VREFB6N0	IO			DIFFIO_RX_R28n	DIFFOUT_R28n	High_Speed	F16
6	VREFB6N0	IO			DIFFIO_RX_R29p	DIFFOUT_R29p	High_Speed	E16
6	VREFB6N0	IO			DIFFIO_RX_R30p	DIFFOUT_R30p	High_Speed	D18
6	VREFB6N0	IO			DIFFIO_RX_R29n	DIFFOUT_R29n	High_Speed	D16
6	VREFB6N0	IO			DIFFIO_RX_R30n	DIFFOUT_R30n	High_Speed	E17

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	IO Performance	U324
6	VREFB6N0	IO			DIFFIO_RX_R31p	DIFFOUT_R31p	High_Speed	G11
6	VREFB6N0	IO			DIFFIO_RX_R32p	DIFFOUT_R32p	High_Speed	C18
6	VREFB6N0	IO			DIFFIO_RX_R31n	DIFFOUT_R31n	High_Speed	G12
6	VREFB6N0	IO			DIFFIO_RX_R32n	DIFFOUT_R32n	High_Speed	B18
6	VREFB6N0	IO			DIFFIO_RX_R33p	DIFFOUT_R33p	High_Speed	E15
6	VREFB6N0	IO			DIFFIO_RX_R34p	DIFFOUT_R34p	High_Speed	D17
6	VREFB6N0	IO			DIFFIO_RX_R33n	DIFFOUT_R33n	High_Speed	D15
6	VREFB6N0	IO			DIFFIO_RX_R34n	DIFFOUT_R34n	High_Speed	C17
7	VREFB7N0	IO			DIFFIO_RX_T1p	DIFFOUT_T1p	High_Speed	E14
7	VREFB7N0	IO			DIFFIO_RX_T2p	DIFFOUT_T2p	High_Speed	B17
7	VREFB7N0	IO			DIFFIO_RX_T1n	DIFFOUT_T1n	High_Speed	D14
7	VREFB7N0	IO			DIFFIO_RX_T2n	DIFFOUT_T2n	High_Speed	B16
7	VREFB7N0	IO			DIFFIO_RX_T3p	DIFFOUT_T3p	High_Speed	D12
7	VREFB7N0	IO					High_Speed	A17
7	VREFB7N0	IO			DIFFIO_RX_T3n	DIFFOUT_T3n	High_Speed	D13
7	VREFB7N0	IO	VREFB7N0				High_Speed	A16
7	VREFB7N0	IO			DIFFIO_RX_T4p	DIFFOUT_T4p	High_Speed	C16
7	VREFB7N0	IO			DIFFIO_RX_T5p	DIFFOUT_T5p	High_Speed	A15
7	VREFB7N0	IO			DIFFIO_RX_T4n	DIFFOUT_T4n	High_Speed	C15
7	VREFB7N0	IO			DIFFIO_RX_T5n	DIFFOUT_T5n	High_Speed	A14
7	VREFB7N0	IO			DIFFIO_RX_T6p	DIFFOUT_T6p	High_Speed	C14
7	VREFB7N0	IO			DIFFIO_RX_T7p	DIFFOUT_T7p	High_Speed	B14
7	VREFB7N0	IO			DIFFIO_RX_T6n	DIFFOUT_T6n	High_Speed	C13
7	VREFB7N0	IO			DIFFIO_RX_T7n	DIFFOUT_T7n	High_Speed	B13
7	VREFB7N0	IO			DIFFIO_RX_T8p	DIFFOUT_T8p	High_Speed	F11
7	VREFB7N0	IO			DIFFIO_RX_T9p	DIFFOUT_T9p	High_Speed	C12
7	VREFB7N0	IO			DIFFIO_RX_T8n	DIFFOUT_T8n	High_Speed	F12
7	VREFB7N0	IO			DIFFIO_RX_T9n	DIFFOUT_T9n	High_Speed	B12
7	VREFB7N0	IO			DIFFIO_RX_T10p	DIFFOUT_T10p	High_Speed	C11
7	VREFB7N0	IO			DIFFIO_RX_T11p	DIFFOUT_T11p	High_Speed	A13
7	VREFB7N0	IO			DIFFIO_RX_T10n	DIFFOUT_T10n	High_Speed	B11
7	VREFB7N0	IO			DIFFIO_RX_T11n	DIFFOUT_T11n	High_Speed	A12
8	VREFB8N0	IO			DIFFIO_RX_T12p	DIFFOUT_T12p	Low_Speed	D10
8	VREFB8N0	IO			DIFFIO_RX_T13p	DIFFOUT_T13p	Low_Speed	A11
8	VREFB8N0	IO			DIFFIO_RX_T12n	DIFFOUT_T12n	Low_Speed	D9
8	VREFB8N0	IO			DIFFIO_RX_T13n	DIFFOUT_T13n	Low_Speed	A10
8	VREFB8N0	IO			DIFFIO_RX_T14p	DIFFOUT_T14p	Low_Speed	F10
8	VREFB8N0	IO			DIFFIO_RX_T15p	DIFFOUT_T15p	Low_Speed	A9
8	VREFB8N0	IO			DIFFIO_RX_T14n	DIFFOUT_T14n	Low_Speed	G10
8	VREFB8N0	IO			DIFFIO_RX_T15n	DIFFOUT_T15n	Low_Speed	A8
8	VREFB8N0	IO			DIFFIO_RX_T16p	DIFFOUT_T16p	Low_Speed	B9
8	VREFB8N0	IO			DIFFIO_RX_T17p	DIFFOUT_T17p	Low_Speed	C10
8	VREFB8N0	IO		DEV_CLRn	DIFFIO_RX_T16n	DIFFOUT_T16n	Low_Speed	B8
8	VREFB8N0	IO			DIFFIO_RX_T17n	DIFFOUT_T17n	Low_Speed	C9
8	VREFB8N0	IO		DEV_OE	DIFFIO_RX_T18p	DIFFOUT_T18p	Low_Speed	D8
8	VREFB8N0	IO					Low_Speed	A7
8	VREFB8N0	IO			DIFFIO_RX_T18n	DIFFOUT_T18n	Low_Speed	D7
8	VREFB8N0	IO	VREFB8N0				Low_Speed	B7
8	VREFB8N0	IO		CONFIG_SEL			Low_Speed	G9
8	VREFB8N0	IO			DIFFIO_RX_T19p	DIFFOUT_T19p	Low_Speed	A6
8	VREFB8N0	Input_only		nCONFIG			Low_Speed	H9
8	VREFB8N0	IO			DIFFIO_RX_T19n	DIFFOUT_T19n	Low_Speed	A5
8	VREFB8N0	IO			DIFFIO_RX_T20p	DIFFOUT_T20p	Low_Speed	C6
8	VREFB8N0	IO			DIFFIO_RX_T21p	DIFFOUT_T21p	Low_Speed	C8
8	VREFB8N0	IO			DIFFIO_RX_T20n	DIFFOUT_T20n	Low_Speed	B5
8	VREFB8N0	IO			DIFFIO_RX_T21n	DIFFOUT_T21n	Low_Speed	C7
8	VREFB8N0	IO			DIFFIO_RX_T22p	DIFFOUT_T22p	Low_Speed	C5
8	VREFB8N0	IO			DIFFIO_RX_T23p	DIFFOUT_T23p	Low_Speed	A4
8	VREFB8N0	IO		CRC_ERROR	DIFFIO_RX_T22n	DIFFOUT_T22n	Low_Speed	C4
8	VREFB8N0	IO			DIFFIO_RX_T23n	DIFFOUT_T23n	Low_Speed	B4
8	VREFB8N0	IO		nSTATUS	DIFFIO_RX_T24p	DIFFOUT_T24p	Low_Speed	G8
8	VREFB8N0	IO			DIFFIO_RX_T25p	DIFFOUT_T25p	Low_Speed	A3
8	VREFB8N0	IO		CONF_DONE	DIFFIO_RX_T24n	DIFFOUT_T24n	Low_Speed	H8
8	VREFB8N0	IO			DIFFIO_RX_T25n	DIFFOUT_T25n	Low_Speed	B3
8	VREFB8N0	IO			DIFFIO_RX_T26p	DIFFOUT_T26p	Low_Speed	D6
8	VREFB8N0	IO			DIFFIO_RX_T27p	DIFFOUT_T27p	Low_Speed	A2
8	VREFB8N0	IO			DIFFIO_RX_T26n	DIFFOUT_T26n	Low_Speed	D5
8	VREFB8N0	IO			DIFFIO_RX_T27n	DIFFOUT_T27n	Low_Speed	B2
		GND						E2
		GND						E3
		GND						V18
		GND						V1
		GND						U4
		GND						U14
		GND						U10
		GND						R7
		GND						N5
		GND						N2
		GND						N17
		GND						N12
		GND						N10
		GND						M14
		GND						L4
		GND						K9
		GND						K6
		GND						K13
		GND						J17
		GND						J10
		GND						H14

Bank Number	VREF	Pin Name/Function	Optional Function(s)	Configuration Function	Dedicated Tx/Rx Channel	Emulated LVDS Output Channel	IO Performance	U324
		GND						G4
		GND						G2
		GND						F8
		GND						F17
		GND						E6
		GND						E13
		GND						E10
		GND						D3
		GND						B6
		GND						B15
		GND						B10
		GND						A18
		GND						A1
		VCCIO1A						H5
		VCCIO1A						G5
		VCCIO1B						K5
		VCCIO1B						J5
		VCCIO2						M5
		VCCIO2						L6
		VCCIO2						L5
		VCCIO3						P9
		VCCIO3						P8
		VCCIO3						P7
		VCCIO3						N9
		VCCIO4						P12
		VCCIO4						P11
		VCCIO5						M13
		VCCIO5						L14
		VCCIO5						L13
		VCCIO5						K14
		VCCIO6						J14
		VCCIO6						J13
		VCCIO6						H13
		VCCIO6						G14
		VCCIO6						G13
		VCCIO7						E12
		VCCIO7						E11
		VCCIO7						D11
		VCCIO8						F9
		VCCIO8						E9
		VCCIO8						E8
		VCCIO8						E7
		NC						N13
		NC						F7
		VCCA1						M6
		VCCA2						F14
		VCCA3						F3
		VCCA3						F6
		VCCA3						F4
		VCCA4						P13
		VCC_ONE						L9
		VCC_ONE						K10
		VCC_ONE						J9
		VCC_ONE						H10
		VCC_ONE						N6
		VCC_ONE						F13
		VCC_ONE						C3

Note:
(1) For more information about pin definition and pin connection guidelines, refer to the
Intel MAX 10 FPGA Device Family Pin Connection Guidelines.

Date	Version	Changes Made
December 2014	2014.12.15	Initial release.
May 2015	2015.05.08	Added note (2) to Pin List E144.
December 2016	2016.12.23	Removed I/O performance for single-ended pins.
February 2017	2017.02.21	Rebranded as Intel.
December 2017	2017.12.15	Added Pin List U324.