Main notebook

Deepak Mallubhotla

2017-11-25, Last update 2017-11-25

1 Drude model σ and ϵ

The assumptions of the Drude model are simple: we have interaction-free electrons that occasionally undergo some scattering process during a time dt with probability $\frac{dt}{\tau}$, where τ is some phenomenological parameter. This scattering will randomise electron momentum.

Our ultimate goal will be to find the conductivity σ and the dielectric constant ϵ in the Drude model, with Drude relaxation time τ, electron density n and electron mass m. We'll find

$$\sigma_{\mathrm{DC}} = \frac{ne^2\tau}{m} \tag{1}$$

$$\sigma_{\mathrm{AC}} = \frac{ne^2\tau}{m}\frac{1}{1-i\omega\tau} \qquad \text{For SI and Gaussian} \tag{2}$$

$$\epsilon_r = 1 + i\frac{4\pi\sigma}{\omega} \qquad \text{Gaussian} \tag{3a}$$

$$\epsilon_r = 1 + i\frac{\sigma}{\omega\epsilon_0} \qquad \text{SI} \tag{3b}$$

Our dielectric constant can be rewritten to plug in for σ, giving us

$$\epsilon = 1 + i\frac{4\pi\sigma}{\omega} \tag{4}$$

$$= 1 + i\frac{4\pi\sigma_{\mathrm{DC}}}{\omega}\frac{1}{1-i\omega\tau} \tag{5}$$

$$= 1 + i\frac{4\pi\sigma_{\mathrm{DC}}}{\omega}\frac{1}{1-i\omega\tau}\frac{1+i\omega\tau}{1+i\omega\tau} \tag{6}$$

$$= 1 + i\frac{4\pi\sigma_{\mathrm{DC}}}{\omega}\frac{1+i\omega\tau}{1+\omega^2\tau^2} \tag{7}$$

$$= \left(1 - \frac{4\pi\sigma_{\mathrm{DC}}\omega\tau}{\omega\left(1+\omega^2\tau^2\right)}\right) + i\left(\frac{4\pi\sigma_{\mathrm{DC}}}{\omega\left(1+\omega^2\tau^2\right)}\right) \tag{8}$$

$$= \left(1 - \frac{4\pi\sigma_{\mathrm{DC}}\tau}{1+\omega^2\tau^2}\right) + i\left(\frac{4\pi\sigma_{\mathrm{DC}}}{\omega\left(1+\omega^2\tau^2\right)}\right) \tag{9}$$

This lets us write down the explicit real and imaginary of the Drude dielectric function.

1.1 Limiting forms of the Drude model

We can look at the large and small ω limits for the Drude dielectric function.

1.2 Derivations for Drude model

1.2.1 Conductivity

We can start unit-system independently, with the expression $\langle \mathbf{j} \rangle = \sigma \mathbf{E}$. We can also relate our current to our average electron velocity: $\mathbf{j} = ne\mathbf{v}$. Imagine at time $t = 0$ our electron undergoes a Drude collision, and emerges with $\mathbf{v}_{t=0} = \mathbf{v_0}$. After a time t, the electron will accelerate with acceleration $-\frac{e\mathbf{E}}{m}$ (which fortunately remains unit independent). Because it will only accelerate for a time τ on average before a collision, it will end up with velocity $\mathbf{v} = -\frac{e\mathbf{E}}{m}\tau + \mathbf{v_0}$. The average velocity, and current, will be

$$\langle \mathbf{v} \rangle = -\frac{e\mathbf{E}}{m}\tau + \langle \mathbf{v_0} \rangle \tag{10}$$

$$= -\frac{e\mathbf{E}}{m}\tau \tag{11}$$

$$\frac{\mathbf{j}}{ne} = -\frac{e\mathbf{E}}{m}\tau \tag{12}$$

$$\mathbf{j} = -\frac{ne^2\tau}{m}\mathbf{E}. \tag{13}$$

This of course gives us, unit-independently, our DC conductivity $\sigma_{\text{DC}} = \frac{ne^2\tau}{m}$