

1 Explicit parts of Lindhard function

We want to find the explicit real and imaginary parts of the Lindhard function. To begin with, we can start with the case where $\nu \rightarrow 0$, which means long relaxation times.

We have our Lindhard form

$$\epsilon_l = 1 + \frac{3\omega_p^2}{k^2 v_F^2} \frac{(\omega + i\nu) f_l((\omega + i\nu)/kv_F)}{\omega + i\nu f_l((\omega + i\nu)/kv_F)}, \quad (1)$$

where

$$f_l(x) = 1 - \frac{x}{2} \ln \frac{x+1}{x-1}. \quad (2)$$

1.1 Pines result

From Pines, we have the forms

$$\begin{aligned} \text{Re}[\epsilon_l] = 1 + \frac{k_{TF}^2}{k^2} & \left(\frac{1}{2} + \frac{k_F}{4k} \left[\left(1 - \frac{\left(\omega - \frac{\hbar k^2}{2m} \right)^2}{k^2 v_F^2} \right) \ln \left[\frac{\omega - kv_F - \frac{\hbar k^2}{2m}}{\omega + kv_F - \frac{\hbar k^2}{2m}} \right] \right. \right. \\ & \left. \left. + \left(1 - \frac{\left(\omega + \frac{\hbar k^2}{2m} \right)^2}{k^2 v_F^2} \right) \ln \left[\frac{\omega + kv_F + \frac{\hbar k^2}{2m}}{\omega - kv_F + \frac{\hbar k^2}{2m}} \right] \right] \right) \end{aligned} \quad (3)$$

$$\text{Im}[\epsilon_l] = \begin{cases} \frac{\pi}{2} \frac{\omega}{kv_F} \frac{k_{TF}^2}{k^2}, & \omega \leq kv_F - \frac{\hbar k^2}{2m} \\ \frac{\pi}{4} \frac{k_F}{k} \left(1 - \frac{\left(\omega - \frac{\hbar k^2}{2m} \right)^2}{k^2 v_F^2} \right) \frac{k_{TF}^2}{k^2}, & kv_F - \frac{\hbar k^2}{2m} \leq \omega \leq kv_F + \frac{\hbar k^2}{2m} \\ 0, & \omega \geq kv_F + \frac{\hbar k^2}{2m} \end{cases} \quad (4)$$

1.2 Long relaxation time forms of the logs

In order to analyse the $\nu \rightarrow 0$ limit, we can start by looking at what happens to the logarithms in the Lindhard function:

$$\ln \frac{\omega + i\nu + kv_F}{\omega + i\nu - kv_F} \quad (5)$$

The first thing to note is that the numerator will always have a very small, positive argument, while the denominator will have a small argument which may be positive or negative. As Lindhard mentions, these logarithms should all have imaginary parts between $\pm i\pi$. This effectively means we can treat each logarithm as giving the principal value, which give us a result that looks like

$$\ln \frac{\sqrt{(\omega + kv_F)^2 + \nu^2}}{\sqrt{(\omega - kv_F)^2 + \nu^2}} + i(\theta_+ - \theta_-), \quad (6)$$

where θ_+ and θ_- are the arguments of the numerator and denominator. For small ν , θ_+ is proportional to ν , as it'll be determined by an arcsine. However, the denominator may be negative, which would contribute a factor of $\theta_- = +i\pi$ (with a plus sign because ν would be just above the real line).

$$\ln \frac{\omega + i\nu + kv_F}{\omega + i\nu - kv_F} = \ln \frac{\sqrt{(\omega + kv_F)^2 + \nu^2}}{\sqrt{(\omega - kv_F)^2 + \nu^2}} + i(\theta_+ - \theta_-) \quad (7)$$

$$= \ln \frac{\sqrt{(\omega + kv_F)^2}}{\sqrt{(\omega - kv_F)^2}} - \sigma i\pi \quad (8)$$

$$= \ln \left| \frac{\omega + kv_F}{\omega - kv_F} \right| - \sigma i\pi, \quad (9)$$

where $\sigma = 1$ if $\omega < kv_F$, and 0 otherwise.

1.3 Taking long scattering time limit

To make our constants line up with the Pines form, we'll use the definition $k_{TF}^2 = \frac{3\omega_p^2}{v_F^2}$, giving us

$$\epsilon_l = 1 + \frac{k_{TF}^2}{k^2} \frac{(\omega + i\nu) f_l((\omega + i\nu)/kv_f)}{\omega + i\nu f_l((\omega + i\nu)/kv_f)}, \quad (10)$$

We can't simply set $\nu = 0$, as we need to respect the relation

$$\frac{1}{x + i\delta} = \frac{1}{x} - i\pi\delta(x) \quad (11)$$

$$\epsilon_l = 1 + \frac{k_{TF}^2}{k^2} \frac{(\omega + i\nu) \left(1 - \frac{\omega + i\nu}{2kv_F} \left(\ln \left| \frac{\omega + kv_F}{\omega - kv_F} \right| - \sigma i\pi \right) \right)}{\omega + i\nu \left(1 - \frac{\omega + i\nu}{2kv_F} \left(\ln \left| \frac{\omega + kv_F}{\omega - kv_F} \right| - \sigma i\pi \right) \right)}. \quad (12)$$

We can eliminate all the terms proportional to ν in the numerator, as they will disappear as we take our limit:

$$\epsilon_l = 1 + \frac{k_{TF}^2}{k^2} \frac{(\omega + i\nu) \left(1 - \frac{\omega + i\nu}{2kv_F} \left(\ln \left| \frac{\omega + kv_F}{\omega - kv_F} \right| - \sigma i\pi\right)\right)}{\omega + i\nu \left(1 - \frac{\omega + i\nu}{2kv_F} \left(\ln \left| \frac{\omega + kv_F}{\omega - kv_F} \right| - \sigma i\pi\right)\right)} \quad (13)$$

$$\epsilon_l = 1 + \frac{k_{TF}^2}{k^2} \frac{\omega \left(1 - \frac{\omega}{2kv_F} \left(\ln \left| \frac{\omega + kv_F}{\omega - kv_F} \right| - \sigma i\pi\right)\right)}{\omega + i\nu \left(1 - \frac{\omega + i\nu}{2kv_F} \left(\ln \left| \frac{\omega + kv_F}{\omega - kv_F} \right| - \sigma i\pi\right)\right)} \quad (14)$$

$$\epsilon_l = 1 + \frac{k_{TF}^2}{k^2} \frac{\omega}{2kv_F} \frac{2kv_F - \omega \ln \left| \frac{\omega + kv_F}{\omega - kv_F} \right| + i\omega\pi\sigma}{\omega + i\nu \left(1 - \frac{\omega + i\nu}{2kv_F} \left(\ln \left| \frac{\omega + kv_F}{\omega - kv_F} \right| - \sigma i\pi\right)\right)} \quad (15)$$

We can now look at just the denominator:

$$= \omega + i\nu \left(1 - \frac{\omega + i\nu}{2kv_F} \left(\ln \left| \frac{\omega + kv_F}{\omega - kv_F} \right| - \sigma i\pi\right)\right) \quad (16)$$

$$= \omega + i\nu - i\nu \frac{\omega + i\nu}{2kv_F} \left(\ln \left| \frac{\omega + kv_F}{\omega - kv_F} \right| - \sigma i\pi\right) \quad (17)$$

$$= \omega + i\nu + \frac{\nu^2 - i\nu\omega}{2kv_F} \left(\ln \left| \frac{\omega + kv_F}{\omega - kv_F} \right| - \sigma i\pi\right) \quad (18)$$

$$= \omega + \frac{\nu^2}{2kv_F} L - \frac{\nu\omega\pi\sigma}{2kv_F} + i\nu - i \frac{\nu\omega}{2kv_F} L - i \frac{\nu^2\sigma\pi}{2kv_F}, \quad (19)$$

where $L = \ln \left| \frac{\omega + kv_F}{\omega - kv_F} \right|$. We can notice here that all the imaginary terms are proportional to ν . We can ignore the ν^2 term, as it will go to zero faster than the other terms. We can see that we essentially have two regimes: if $\omega < 2kv_F$, this will have a positive imaginary part, and if $\omega > 2kv_F$, the imaginary part will be negative.

We can also notice that the only real part that will survive the limiting process is simply ω (which is of course clear from the original form of the denominator anyway). This lets us essentially write the denominator as

$$\omega + i\nu\zeta C, \quad (20)$$

where I'm defining ζ as 1 if $\omega < 2kv_F$, and -1 otherwise. We also can note that C is an irrelevant positive constant; when we take the long scattering time limit, all that matters is that the imaginary part is proportional to ν .

Plugging this back into (15) gives us

$$\epsilon_l = 1 + \frac{k_{TF}^2}{k^2} \frac{\omega}{2kv_F} \frac{2kv_F - \omega \ln \left| \frac{\omega + kv_F}{\omega - kv_F} \right| + i\omega\pi\sigma}{\omega + i\nu \left(1 - \frac{\omega + i\nu}{2kv_F} \left(\ln \left| \frac{\omega + kv_F}{\omega - kv_F} \right| - \sigma i\pi \right) \right)} \quad (21)$$

$$\epsilon_l = 1 + \frac{k_{TF}^2}{k^2} \frac{\omega}{2kv_F} \frac{2kv_F - \omega \ln \left| \frac{\omega + kv_F}{\omega - kv_F} \right| + i\omega\pi\sigma}{\omega + i\nu\zeta C} \quad (22)$$

$$= 1 + \frac{k_{TF}^2}{k^2} \frac{\omega}{2kv_F} \left(2kv_F - \omega \ln \left| \frac{\omega + kv_F}{\omega - kv_F} \right| + i\omega\pi\sigma \right) \left(\frac{1}{\omega} - i\pi\zeta\delta(\omega) \right) \quad (23)$$

$$= 1 + \frac{k_{TF}^2}{k^2} \frac{\omega}{2kv_F} \left(\frac{2kv_F}{\omega} - L + i\pi\sigma - i\pi\zeta 2kv_F\delta(\omega) + (iL\zeta + \sigma\zeta) \pi\omega\delta(\omega) \right) \quad (24)$$

We can eliminate the terms proportional to $\omega\delta(\omega)$:

$$\epsilon_l = 1 + \frac{k_{TF}^2}{k^2} \frac{\omega}{2kv_F} \left(\frac{2kv_F}{\omega} - L + i\pi\sigma - i\pi\zeta 2kv_F\delta(\omega) \right) \quad (25)$$

$$= 1 + \frac{k_{TF}^2}{k^2} \left(1 - \frac{\omega}{2kv_F} L + \frac{\omega}{2kv_F} i\pi\sigma - i\pi\zeta\omega\delta(\omega) \right) \quad (26)$$

$$= 1 + \frac{k_{TF}^2}{k^2} \left(1 - \frac{\omega}{2kv_F} L + \frac{\omega}{2kv_F} i\pi\sigma \right) \quad (27)$$