DA Timer Help

Oct 24, 2026 · @dom



DA Timer by DW · © 2026 DW

What DA Timer does

DA Timer is a show timer for a broadcast Director's Assistant. It runs two clocks: a **segment** clock for the current item and a **program** clock for the whole show. It tells you whether you're over or under on each segment and in total.

It can also back-time to a hard out, keep a log of notes, mark times you can export to Excel, and put the clocks on a second screen for the presenter or floor. It runs on Windows and Mac, and can be driven from a Stream Deck.

The main screen

The top card is the segment clock and the bottom card is the program clock. Each card's coloured bar on the left goes green when that clock is running.

Button	What it does
ALL START / ALL STOP	Starts or stops both clocks together
START / STOP (on a card)	Starts or stops just that clock
NEXT (segment card)	Ends the current segment, records its time in the running order, and starts the next one from zero
RESET (program card)	Clears both clocks and the segment times, ready for a new show (asks first; Undo brings it back)
PRESET	Types in a time, e.g. if you started late; works while the clock is running

Under each clock, the goal and “left” or “over” readout turns amber in the last 15 seconds of a segment and red once it's over. The toolbar along the bottom opens everything else.

Features

Each of these is in the toolbar, and you can switch off any you don't need in **Settings**.

Feature	What it's for
Running order	Lists each segment with its goal, actual time, +/− and start-by time
Goals & hard out	Set a goal for each segment (or paste them from Excel) and a hard out: an off-air time or a total program length
Back-timing	With a hard out set, a band shows time to out, projected length and how much to cut or spare
Log	Type a note (the time is stamped when you start typing) or press Mark; each entry records the time of day and program time. **Export to Excel** saves it
Clock	Shows the time of day in the header
Dual screen / Output screen	Puts a clean full-screen clock display on a second screen for the presenter or floor
Show	Saves each show's name, logos, titles and colours, so you can switch between shows
Stream Deck	Plug a Stream Deck in and DA Timer drives it directly. Or use the Elgato plugin
Time source	Uses the computer clock, network time (NTP) or LTC timecode from an audio input
Undo	Undoes the last action, including an accidental reset, without losing time on the clocks

If DA Timer closes unexpectedly mid-show, it offers to restore the clocks and log when you reopen it.

Keyboard shortcuts

Single-key shortcuts don't fire while you're typing a note, and can be switched off in Settings.

Key (Windows)	Key (Mac)	Does
Space	Space	Start / stop both clocks
N	N	Next segment
D	D	Output screen on / off
L	L	Running order on / off
T	T	Time-of-day clock on / off
G	G	Goals & hard out
F2	F2 (fn+F2)	Type a log note
Ctrl+M	Cmd+M	Log a mark
Ctrl+Z	Cmd+Z	Undo
Ctrl+,	Cmd+,	Settings
F11 / Esc	fn+F11 / Esc	Full screen on / off

First launch on a Mac

macOS blocks DA Timer the first time because it isn't signed with a paid Apple developer certificate. Allow it once per Mac, and again after each new version. You'll need the Mac's login password or Touch ID.

1. Drag **DA Timer.app** into **Applications**, then double-click it. When the "Not Opened" warning appears, click **Done** (not Move to Trash).
2. Open **System Settings** → **Privacy & Security**.
3. Scroll down to **Security**. Next to **"DA Timer" was blocked to protect your Mac**, click **Open Anyway**.
4. In the next warning, click **Open Anyway** again.
5. Enter your password or use Touch ID. DA Timer opens, and opens normally from then on.

If **Open Anyway** isn't there, double-click DA Timer again, then go back to Privacy & Security. The button only appears for a while after a blocked attempt.