

SAMBP Model-Based Bus Differential Protection: Extending the Inverse-Estimation Framework to 87B

Technical Report IITM/EE/PhD/AVE/TR-04/2026

Indian Institute of Technology Madras
Department of Electrical Engineering

Arjun Eluvathingal April 2026

Abstract

This report extends the SAMBP (Signal-Adapted Model-Based Protection) framework to bus differential (87B) protection. A three-parameter zone model $\theta_B = [I_{diff}, \varphi, \varepsilon_{CT}]$ is proposed, where the CT mismatch/saturation factor ε_{CT} is used to derive an internal-fault indicator $f_{int} = \text{clip}(1 - \varepsilon_{CT}/\varepsilon_{thresh}, 0, 1)$ that is both identifiable and monotone. The column-normalised condition number satisfies $\kappa_n \leq 6.3$ across all scenarios, the lowest of any SAMBP function to date. A two-pass Levenberg-Marquardt estimator and a Stage-2 model-veto gate are implemented and validated on six canonical events. Five of six events are correctly classified with zero assertion failures; CT open-circuit is documented as an irreducible limitation requiring a high-impedance bus differential scheme.

Contents

1	Introduction	2
2	Bus Differential Relay — Mathematical Foundation	3
2.1	Operating and Restraint Quantities	3
2.2	Dual-Slope Percentage-Differential Characteristic	3
2.3	CT Saturation Model	3
3	SAMBP Zone Model for 87B	3
3.1	Three-Parameter Model	3
3.2	Analytical Jacobian	4
3.3	Internal-Fault Indicator	4
4	Estimation and Gate	4
4.1	Two-Pass Levenberg-Marquardt	4
4.2	Stage-2 Model-Veto Gate	5
5	Results	5
5.1	Parameter Bounds	5
5.2	Study Results	5
5.3	Condition Number Comparison (Updated)	6
6	Discussion	7
6.1	Structural Simplicity of 87B	7
6.2	Comparison with High-Impedance Bus Differential	7
6.3	Stage-2 Veto Generalisation	7

7	Future Work	7
8	Conclusions	8
A	Proof of Proposition 3.1	8
B	Software	9

List of Figures

1	87B operating plane. External fault + CT saturation (orange triangle) falls deep in the trip region but is restrained by the Stage-2 model-veto gate ($f_{int} = 0.00$, $\kappa_n = 2.7$). Internal faults (red star, grey cross) lie above the trip boundary.	6
2	Four-feeder 87B bus differential protection zone. Source feeder F_0 and three load feeders F_1 – F_3 ; CT outputs wired to the 87B/SAMBP relay.	6

List of Tables

1	87B zone model parameter bounds and physical interpretation.	5
2	87B batch study results. All 6 events processed, 0 assertion failures.	5
3	Column-normalised condition numbers — all SAMBP functions.	7
4	Stage-2 model-veto gate: primary target across SAMBP differential functions.	7

1 Introduction

Bus differential (87B) protection is the primary protection for high-voltage and extra-high-voltage bus sections in transmission and sub-transmission networks [1, 2]. Its operating principle is identical to transformer differential (87T): the algebraic sum of all feeder currents must be zero when no fault exists within the zone.

Motivation for SAMBP extension

The SAMBP framework has been applied to synchronous-generator overcurrent (TR-01/TR-02/2026) and to transformer and line differential protection (TR-03/2026). Bus differential presents a structurally simpler problem than 87T or 87L:

- **No vector-group correction** (all feeders at the same bus voltage level; no Yd11 matrix required).
- **No charging-current compensation** (unlike 87L).
- **No harmonic blocking** (no inrush or over-excitation for a bus section; second/fifth harmonic terms are absent).
- **CT mismatch** is the dominant source of spurious differential.

These properties lead to a three-parameter zone model that achieves $\kappa_n \approx 4$ –6, the best-conditioned model in the SAMBP suite.

2 Bus Differential Relay — Mathematical Foundation

2.1 Operating and Restraint Quantities

For a bus section with N feeders, all currents referred to the bus voltage base and expressed in per-unit of the bus rated current I_{bus} :

$$I_{op}(t) = \left| \sum_{k=1}^N i_k(t) \right|, \quad I_{rst}(t) = \frac{1}{2} \sum_{k=1}^N |i_k(t)| \quad (1)$$

Currents are signed positive when flowing *into* the bus. For an ideal external fault all currents cancel ($I_{op} \approx 0$); for an internal bus fault the fault current has no return path through any feeder CT ($I_{op} \approx I_{fault}$).

2.2 Dual-Slope Percentage-Differential Characteristic

The 87B trip criterion follows the same dual-slope form as 87T (see TR-03/2026, §2.1):

$$I_{op} > I_{op}^{threshold}(I_{rst}) = \begin{cases} \max(I_{op}^{min}, SLP_1 I_{rst}) & I_{rst} \leq I_{rst}^{(k)} \\ \max(I_{op}^{min}, SLP_1 I_{rst}^{(k)} + SLP_2(I_{rst} - I_{rst}^{(k)})) & I_{rst} > I_{rst}^{(k)} \end{cases} \quad (2)$$

Default parameters: $I_{op}^{min} = 0.20$, $SLP_1 = 0.25$, $SLP_2 = 0.50$, $I_{rst}^{(k)} = 1.0$ pu. An unrestrained high-set at 8.0 pu bypasses the characteristic for severe close-in faults.

2.3 CT Saturation Model

CT saturation above the knee current I_{knee} is modelled as soft clipping:

$$i_{CT}(t) = \begin{cases} i_{true}(t) & |i_{true}| \leq I_{knee} \\ I_{knee} \operatorname{sgn}(i_{true}) + \alpha(i_{true} - I_{knee} \operatorname{sgn}(i_{true})) & |i_{true}| > I_{knee} \end{cases} \quad (3)$$

with compression ratio $\alpha = 0.15$ (soft saturation, 85 % compression above knee). The knee is set at $I_{knee} = 0.6 I_{fault}$, ensuring definite saturation during an external fault.

3 SAMBP Zone Model for 87B

3.1 Three-Parameter Model

The differential current during an external fault with CT saturation has the characteristic form of a saturated sinusoid. For a soft knee model, the dominant distortion is an odd-harmonic series whose lowest term is a square-wave component. Truncating to the fundamental and the square-wave:

$$i_{diff}(t; \theta_B) = I_{diff} \sin(\omega t + \varphi) + \epsilon_{CT} I_{diff} \operatorname{sgn}(\sin(\omega t)) \quad (4)$$

The three-parameter vector is:

$$\theta_B = \begin{bmatrix} I_{diff} \\ \varphi \\ \epsilon_{CT} \end{bmatrix} \in [0, 10] \times [-\pi, \pi] \times [0, 0.5] \quad (5)$$

Remark 3.1. *The 87B model is a proper subset of the 87T model (TR-03/2026, Eq. 11): it retains only the fundamental and the CT-saturation term, dropping the second-harmonic (k_2) and fifth-harmonic (k_5) components which are absent for a busbar (no inrush or over-excitation source in the zone).*

3.2 Analytical Jacobian

The Jacobian $J \in \mathbb{R}^{N \times 3}$ has columns:

$$\frac{\partial i_{diff}}{\partial I_{diff}} = \sin(\omega t + \varphi) + \varepsilon_{CT} \operatorname{sgn}(\sin \omega t) \quad (6)$$

$$\frac{\partial i_{diff}}{\partial \varphi} = I_{diff} \cos(\omega t + \varphi) \quad (7)$$

$$\frac{\partial i_{diff}}{\partial \varepsilon_{CT}} = I_{diff} \operatorname{sgn}(\sin \omega t) \quad (8)$$

Proposition 3.1 (Identifiability of the 87B model). *The three basis functions $\{\sin(\omega t + \varphi), \cos(\omega t + \varphi), \operatorname{sgn}(\sin \omega t)\}$ are linearly independent for any $\varphi \in (-\pi, \pi)$ and $T \geq 1/f$, giving $\operatorname{rank}(J) = 3$ and $\kappa_n < \infty$.*

Proof. $\sin(\omega t + \varphi)$ and $\cos(\omega t + \varphi)$ are orthogonal for $T = 1/f$. The square-wave $\operatorname{sgn}(\sin \omega t)$ has Fourier series $\frac{4}{\pi} \sum_{n \text{ odd}} \frac{\sin(n\omega t)}{n}$, which contains only odd harmonics $n \geq 1$. Its projection onto the fundamental subspace $\operatorname{span}\{\sin \omega t, \cos \omega t\}$ is $\frac{4}{\pi} \sin \omega t$, which is not zero but also not equal to any rotation of $\sin(\omega t + \varphi)$ for $\varepsilon_{CT} \neq 0$. The residual $\operatorname{sgn}(\sin \omega t) - \frac{4}{\pi} \sin \omega t - 0 \cdot \cos \omega t$ contains harmonics $n = 3, 5, \dots$ that are orthogonal to the fundamental. Hence $\operatorname{sgn}(\sin \omega t) \notin \operatorname{span}\{\sin(\omega t + \varphi), \cos(\omega t + \varphi)\}$ and all three columns of J are linearly independent. $\square$

3.3 Internal-Fault Indicator

Following the SAMBP philosophy (no fitted indicator, derivation from absence of blocking signatures):

$$f_{int} = \operatorname{clip}\left(1 - \frac{\varepsilon_{CT}}{\varepsilon_{thresh}}, 0, 1\right) \quad (9)$$

with $\varepsilon_{thresh} = 0.10$. When $\varepsilon_{CT} \approx 0$ (clean sinusoidal differential, no CT distortion) $f_{int} = 1$: the differential is consistent with an internal fault. When $\varepsilon_{CT} \geq \varepsilon_{thresh}$, $f_{int} = 0$: the distortion pattern is consistent with CT saturation, not a genuine internal fault.

4 Estimation and Gate

4.1 Two-Pass Levenberg-Marquardt

Pass 1 fits all three parameters on the full window. Pass 2 refines only ε_{CT} on the last 2 cycles (tail window) with I_{diff} and φ fixed from Pass 1. The tail emphasises the steady-state saturation distortion after the initial transient.

4.2 Stage-2 Model-Veto Gate

Identical in structure to the 87T and 87L Stage-2 gates (TR-03/2026, §5): when $\kappa_n < 30$ and $f_{int} < 0.60$, the conventional trip is suppressed. For 87B this primarily targets the external fault + CT saturation scenario.

The CT open-circuit case ($\varepsilon_{CT} \approx 0$, $f_{int} \approx 1$) is *not* blocked by the veto because the model correctly identifies the pure-fundamental differential as consistent with an internal fault. This is an irreducible limitation of percentage-differential protection: a pure fundamental differential cannot be distinguished from an internal fault without additional information (e.g. directional comparison or high-impedance scheme).

5 Results

5.1 Parameter Bounds

Table 1: 87B zone model parameter bounds and physical interpretation.

Parameter	Symbol	Lower	Upper	Physical meaning
Diff. fundamental	I_{diff}	0.0	10.0	Peak differential [pu bus rated]
Phase	φ	$-\pi$	π	Phasor angle [rad]
CT distortion	ε_{CT}	0.0	0.5	Square-wave fraction

5.2 Study Results

Table 2 shows the relay decision for all six canonical events. Five of six events are correctly classified; CT open-circuit is logged as a known limitation.

Table 2: 87B batch study results. All 6 events processed, 0 assertion failures.

Event	Conv.	Final	Source	κ_n	f_{int}	ε_{CT}
Normal load	✗	✗	no_trip	4.4	1.00	0.000
External fault	✗	✗	no_trip	4.3	1.00	0.000
External+CT sat.	✓	✗	model_veto	2.7	0.00	0.265
Internal A-G	✓	✓	conventional	4.3	1.00	0.000
Internal 3-phase	✓	✓	conventional	4.3	1.00	0.000
CT open-circuit *	✓	✓	model	4.4	1.00	0.000

✓=trip, ✗=no trip. *CT open-circuit is a documented limitation (see Remark 5.1).

Remark 5.1 (CT open-circuit limitation). *When a CT fails open-circuit, the relay sees an apparent differential equal to the load current of the failed feeder. The zone model estimates $\varepsilon_{CT} \approx 0$ (the waveform is a clean sinusoid, not a saturated one) and $f_{int} \approx 1.0$. The Stage-2 veto does not fire and the conventional trip passes through, causing a spurious trip.*




Figure 1: 87B operating plane. External fault + CT saturation (orange triangle) falls deep in the trip region but is restrained by the Stage-2 model-veto gate ($f_{int} = 0.00$, $\kappa_n = 2.7$). Internal faults (red star, grey cross) lie above the trip boundary.




Figure 2: Four-feeder 87B bus differential protection zone. Source feeder F_0 and three load feeders F_1 – F_3 ; CT outputs wired to the 87B/SAMBP relay.

This is the same root cause as the 87T normal-load sensitivity issue resolved in TR-03/2026: f_{int} cannot distinguish between a clean internal-fault differential and a clean CT-failure differential. A high-impedance bus differential scheme provides immunity by monitoring CT secondary voltages, but this is outside the scope of the current SAMBP implementation.

5.3 Condition Number Comparison (Updated)

Table 3 collects κ_n values across all four SAMBP protection functions. The 87B model achieves the lowest condition number owing to its reduced parametrisation (3 parameters vs. 4–6 for other functions).

Table 3: Column-normalised condition numbers — all SAMBP functions.

Function	Model	p	Typical κ_n	Threshold
OC (sync generator)	Reduced 6-param	6	5–20	50
87T (transformer)	5-param harmonic	5	4–7	30
87L (line diff.)	4-param sine+DC	4	2–3	30
87B (bus diff.)	3-param CT model	3	2–6	30

6 Discussion

6.1 Structural Simplicity of 87B

The 87B zone model is the simplest in the SAMBP suite. Its three parameters are all identifiable, and the f_{int} derivation reduces to a single ratio $\epsilon_{CT}/\epsilon_{thresh}$. This simplicity has two consequences:

1. **Lower computational cost.** The Jacobian is $N \times 3$ rather than $N \times 5$ or $N \times 6$, reducing Pass 1 cost by 60 % relative to 87T.
2. **Less discrimination power.** The model cannot distinguish a pure-sinusoidal differential (internal fault) from a CT open-circuit failure, because both produce $\epsilon_{CT} \approx 0$.

6.2 Comparison with High-Impedance Bus Differential

High-impedance (hi-Z) bus differential schemes are immune to CT open-circuit because they monitor the voltage across the relay rather than the differential current. The SAMBP 87B is a low-impedance differential scheme: it uses summed CT currents and is therefore subject to the same CT open-circuit vulnerability as conventional low-impedance 87B relays.

6.3 Stage-2 Veto Generalisation

Table 4 summarises how the Stage-2 model-veto gate is applied across all three differential protection functions. The same mechanism ($\kappa_n < 30$ AND $f_{int} < f_{int,thresh}$) resolves the principal security challenge of each function.

Table 4: Stage-2 model-veto gate: primary target across SAMBP differential functions.

Function	Primary veto target	Discriminant
87T	External fault + CT saturation	f_{int} via k_2, k_5, ϵ_{CT}
87L	Skew-induced spurious differential	f_{int} via I_{fund} / I_{DC} ratio
87B	External fault + CT saturation	f_{int} via ϵ_{CT} only

7 Future Work

1. **High-impedance 87B supplement.** Add a CT secondary voltage monitor to the SAMBP gate to detect CT open-circuit without relying on the differential current alone.

2. **Multi-bus-section coordination.** Extend to double-busbar arrangements with bus-coupler CT, requiring a selector logic layer analogous to the OC coordination in TR-02/2026.
3. **System integration study.** Demonstrate all four SAMBP functions (OC, 87T, 87L, 87B) operating in coordination on a test network, resolving zone overlaps and CT sharing conflicts.
4. **IEC 61850 GOOSE integration.** Replace hard-wired CT secondary cables with GOOSE messages from IEC 61869-9 Merging Units, adding latency-aware synchronisation to the 87B differential calculation.

8 Conclusions

This report has demonstrated that the SAMBP inverse-estimation framework transfers directly to 87B bus differential protection with minimal adaptation. The three-parameter zone model $\theta_B = [I_{diff}, \varphi, \varepsilon_{CT}]$:

1. Achieves $\kappa_n \leq 6.3$ (best-conditioned SAMBP model to date).
2. Identifies CT saturation via ε_{CT} and derives f_{int} without fitting a collinear indicator.
3. Correctly restrains external fault + CT saturation via the Stage-2 model-veto gate ($f_{int} = 0.00$, $\kappa_n = 2.7$).
4. Trips correctly on single-phase and three-phase internal bus faults.

The SAMBP differential protection suite now spans three functions — 87T, 87L, and 87B — all sharing the same five-layer architecture: conventional baseline, reduced-parameter zone model, two-pass LM estimator, Stage-2 confidence gate, and function-specific fallback.

References

- [1] J. L. Blackburn and T. J. Domin, *Protective Relaying: Principles and Applications*. CRC Press, 3rd ed., 2006.
- [2] “IEC 60255-187-3: Functional requirements for differential protection based on phase comparison for busbars,” 2021.

A Proof of Proposition 3.1

See §3 above. The key step is that $\text{sgn}(\sin \omega t)$ is not in the span of $\{\sin(\omega t + \varphi), \cos(\omega t + \varphi)\}$ because its Fourier expansion has non-zero coefficients at odd harmonics $n \geq 3$. These are orthogonal to the fundamental subspace over $T = 1/f$, ensuring the three-column Jacobian is full-rank.

B Software

All code for this study is located at:

`/root/phd_thesis/sambp/sambp_bus_diff/`

Key modules:

- `models/bus_diff_baseline.py` — conventional 87B relay
- `models/bus_event_library.py` — 6 synthetic events
- `models/bus_reduced_zone_model.py` — 3-parameter model
- `inverse_estimation/bus_inverse_estimator.py` — two-pass LM
- `adaptation/bus_confidence_gate.py` — Stage-2 gate
- `run_bus_diff_study.py` — batch study runner