

Physics-Constrained Adaptive Slope for Differential Protection: A Projected-Gradient Law with Lyapunov Stability Guarantees

Arun V. Eluvathingal, *Student Member, IEEE*, and R. K. Prasad, *Member, IEEE*

Abstract—Percentage-restrain differential protection relies on a slope parameter k that defines the trip/restrain boundary in the $(I_{\text{bias}}, I_{\text{diff}})$ plane. Fixed-slope settings, tuned offline for a nominal generation mix, lose discrimination when inverter-based resources (IBRs) alter fault-current magnitude and phase on a cycle-by-cycle timescale. This paper casts slope adaptation as an online parameter estimation problem in which $k(t)$ is governed by a projected-gradient update law and constrained to a time-varying feasible set $\mathcal{K}(\kappa_n) = [k_{\min}(\kappa_n), k_{\max}]$ derived from the physics of the IBR fleet through the Levenberg–Marquardt (LM) condition number κ_n . We prove, via a quadratic Lyapunov function, that the closed-loop tracking error $\tilde{k} = k - k^*$ is ultimately bounded with a known ultimate bound ε_∞ , and that the constraint projection does not enlarge the bound relative to unconstrained gradient descent. A corollary establishes that the SAMBPS Stage-2 veto gate ($\kappa_n < 30$) is necessary and sufficient for the feasible set to be non-empty and for the ultimate bound to be finite. Simulation on a 33 kV feeder with mixed IBR penetration (17–62%) shows RMSE in slope tracking of 0.014 pu over a 200–400 ms window, compared to 0.096–0.115 pu for fixed-slope alternatives.

Index Terms—adaptive control, differential protection, Lyapunov stability, projected gradient, inverter-based resources, parameter estimation, condition number, model-based protection

I. INTRODUCTION

The percentage-restrain differential relay is the primary protection function for transformers, generators, motors, and bus bars in power systems [1], [2]. Its operating characteristic is defined by the condition:

$$I_{\text{diff}} > k \cdot I_{\text{bias}}, \quad (1)$$

where $I_{\text{diff}} = |I_1 + I_2|$ is the differential current, $I_{\text{bias}} = (|I_1| + |I_2|)/2$ is the bias current, and $k \in (0, 1)$ is the slope. For conventional synchronous generators, k is set offline based on maximum through-fault current and CT error margins, producing a fixed value of 0.20–0.60 [3].

The proliferation of IBRs introduces two complicating phenomena. First, the fault-current magnitude is bounded by the IBR current limiter to 1.0–1.5 pu, compared to 5–10 pu for synchronous machines; this compresses the $(I_{\text{bias}}, I_{\text{diff}})$

operating points toward the slope line, reducing discrimination margin. Second, the effective slope of the impedance characteristic varies with the IBR current ratio k_{ibr} (fraction of bus current supplied by IBRs), which changes on a minute-to-hour timescale with dispatch and weather [4], [5].

A fixed slope cannot simultaneously guarantee:

- *Sensitivity* (trip all internal faults) when k_{ibr} is large and differential current is small;
- *Selectivity* (restrain all external faults) when k_{ibr} is small and through-fault currents are large.

Numerical illustrations in Section II quantify the sensitivity–selectivity tension.

A. Contributions

This paper makes the following contributions to adaptive control theory and power system protection:

- 1) **Formal problem statement (C1a):** We cast slope adaptation as a continuous-time online parameter estimation problem with a time-varying unknown $k^*(t)$ and a physics-derived constraint set $\mathcal{K}(\kappa_n(t))$ (Definition 1).
- 2) **Projected-gradient adaptive law (C1b):** We propose a gradient descent update with projection onto $\mathcal{K}$ (Algorithm 1), and show it is implementable in real-time at 100 ms cycle rates on embedded DSPs.
- 3) **Lyapunov stability theorem (C1c):** Theorem 1 proves ultimate boundedness of the tracking error with explicit bound $\varepsilon_\infty = (\dot{k}_{\max}^* + k_{\min\max})/\alpha$, where α is the adaptation rate and $k_{\max}^*$ bounds the drift rate of the optimal slope.
- 4) **Constraint necessity proof (C1d):** Corollary 1 shows that $\mathcal{K}(\kappa_n)$ is non-empty if and only if $\kappa_n < 30$, directly linking the control-theoretic result to the SAMBPS veto gate.
- 5) **Numerical validation (C1e):** On a 33 kV mixed-IBR feeder, the adaptive law achieves $7\times$ lower slope RMSE than the best fixed-slope alternative in 200–400 ms windows.

B. Related work

Adaptive relaying was surveyed in [6]; the specific problem of adaptive differential protection appears in [7], [8], but neither work addresses IBR fleet dynamics or provides closed-loop

The authors are with the Department of Electrical Engineering, Indian Institute of Technology Madras, Chennai 600036, India (e-mail: arun.eluvathingal@iitm.ac.in). Manuscript received April 14, 2026.

This work is part of the SAMBP project (Self-Adaptive Model-Based Protection) at IIT Madras. The adaptive slope law constitutes Contribution C1 of the SAMBPS unified architecture.

stability proofs. Parameter adaptation for relays using model reference adaptive systems (MRAS) was proposed in [9], but convergence was shown only for LTI systems. The present work extends MRAS-style adaptation to the nonlinear, time-varying IBR fault regime with a verifiable stability guarantee.

II. PROBLEM FORMULATION

A. Linear Regression Model for the Slope

At each protection cycle $t_k = k \cdot T_s$ ($T_s = 100$ ms), the relay measurement provides a scalar observation:

$$y_k = \phi_k k^* + \eta_k, \quad (2)$$

where $y_k = I_{\text{diff}}(t_k)$ is the differential current, $\phi_k = I_{\text{bias}}(t_k)$ is the regressor (bias current), $k^* \in \mathbb{R}$ is the true optimal slope, and η_k is bounded measurement noise, $|\eta_k| \leq \bar{\eta}$.

The optimal slope $k^*(t)$ is a slowly time-varying unknown satisfying $|\dot{k}^*(t)| \leq \dot{k}_{\text{max}}^*$ almost everywhere. The goal is to estimate $k(t) \approx k^*(t)$ using only (y_k, ϕ_k) while respecting the constraint $k(t) \in \mathcal{K}(t)$.

Assumption 1 (Regressor excitation). *There exist $T_0 > 0$ and $\mu > 0$ such that $\sum_{k=0}^{N_0-1} \phi_k^2 \geq \mu$ with $N_0 = T_0/T_s$ during any fault event. (Persistent excitation is guaranteed by the fault-current injection.)*

B. Physics-Derived Feasible Set

Definition 1 (Physics-feasible slope set). *Let $\kappa_n(t)$ be the Levenberg–Marquardt condition number of the SAMBPS LI inverse estimator, and let $\hat{k}_{\text{ibr}}(t)$ be the estimated IBR current ratio. Define:*

$$k_{\min}(\kappa_n) = k_0 + \Delta k \cdot \sigma(\beta(\kappa_n - \kappa^*)), \quad (3)$$

$$k_{\max} = 0.80, \quad (4)$$

$$\mathcal{K}(\kappa_n) = [k_{\min}(\kappa_n), k_{\max}], \quad (5)$$

where $k_0 = 0.20$, $\Delta k = 0.42$, $\beta > 0$, and σ is the logistic sigmoid.

The sigmoid form in (3) encodes the physical intuition that a well-conditioned estimator ($\kappa_n \ll \kappa^* = 30$) supports a tighter lower bound (higher sensitivity), while a poorly-conditioned one ($\kappa_n \rightarrow 30^-$) requires a larger margin against CT saturation and model error.

Fig. 1 shows the resulting trip/restrain regions for the adaptive slope envelope alongside the two fixed baselines. The fixed $k = 0.30$ setting misclassifies IBR-heavy external faults (high I_{bias} , low I_{diff}), while $k = 0.60$ misses internal faults near the slope line.

III. ADAPTIVE LAW DESIGN

A. Projected-Gradient Update

Definition 2 (Euclidean projection). *For a closed convex set $\mathcal{K} = [a, b]$, the projection of $z \in \mathbb{R}$ is $\Pi_{\mathcal{K}}(z) = \min(b, \max(a, z))$.*

Define the tracking error $\tilde{k} = k - k^*$. The cost function for the gradient step is the instantaneous squared residual:

$$J_k = \frac{1}{2} (y_k - \phi_k k)^2 = \frac{1}{2} e_k^2, \quad (6)$$




Fig. 1. Percentage-restrain characteristic. Fixed slopes $k = 0.30$ (gray dashed) and $k = 0.60$ (gray solid) bracket the operating point cloud. The adaptive envelope (blue) tightly bounds the physics-feasible trip region, eliminating missed trips (red dots above $k = 0.60$) while maintaining selectivity for external faults (green squares).

Algorithm 1 Physics-Constrained Projected-Gradient Adaptive Law

Inputs: (y_k, ϕ_k) per cycle; κ_n from LM estimator; adaptation gain $\gamma > 0$; initial slope k_0 .

Output: updated slope k_{j+1} for next cycle.

- 1) Compute prediction error: $e_k = y_k - \phi_k k_j$.
- 2) Compute unconstrained gradient step: $k^{\text{raw}} = k_j + \gamma \phi_k e_k$.
- 3) Update feasible set from LM: $\mathcal{K}_j = [k_{\min}(\kappa_n(t_k)), k_{\max}]$.
- 4) Project: $k_{j+1} = \Pi_{\mathcal{K}_j}(k^{\text{raw}})$.
- 5) Output k_{j+1} to trip comparator (1).




Fig. 2. Physics-constrained adaptive slope control loop. Terminal measurements (V_t, I_t, ω) feed the SAMBPS LM estimator (green), which produces $\hat{k}_{\text{ibr}}$ and κ_n . These determine the constraint set $\mathcal{K}(\kappa_n)$ used by the projection block (orange) to bound the gradient update (blue). The trip comparator uses the current $k(t)$ against the relay measurement.

where $e_k = y_k - \phi_k k$ is the prediction error.

In continuous time, Algorithm 1 corresponds to:

$$\dot{k}(t) = \Pi_{\mathcal{K}(t)} \{ \gamma \phi(t) (y(t) - \phi(t) k(t)) \}, \quad (7)$$

with the understanding that projection is evaluated with respect to $\mathcal{K}(\kappa_n(t))$ at the current time.

Fig. 2 illustrates the closed-loop structure.

IV. STABILITY ANALYSIS

A. Lyapunov Function

Consider the quadratic candidate:

$$V(t) = \frac{\tilde{k}(t)^2}{2\gamma}, \quad (8)$$

where $\tilde{k} = k - k^*$. Differentiating along trajectories of (7):

$$\begin{aligned} \dot{V} &= \frac{\dot{\tilde{k}}}{\gamma} \tilde{k} - \frac{\tilde{k}}{\gamma} \dot{k}^* \\ &= \frac{\tilde{k}}{\gamma} \Pi_{\mathcal{K}}\{\gamma\phi(y - \phi k)\} - \frac{\tilde{k}}{\gamma} \dot{k}^*. \end{aligned} \quad (9)$$

Lemma 1 (Projection inequality). *For any $z \in \mathbb{R}$ and $\xi \in \mathcal{K}$:*

$$(\Pi_{\mathcal{K}}(z) - \xi)(z - \xi) \geq |\Pi_{\mathcal{K}}(z) - \xi|^2. \quad (10)$$

Proof. Standard result for projection onto a closed convex set; see [10]. $\square$

Applying Lemma 1 with $z = \gamma\phi(y - \phi k)$ and $\xi = 0$ (since $0 \in \mathcal{K}$ under assumption $k_0 \leq 0 \leq k_{\max}$, relaxed below), and expanding $y - \phi k = \phi\tilde{k} + \eta$:

$$\begin{aligned} \dot{V} &\leq -\phi^2 \tilde{k}^2 + |\phi| \bar{\eta} |\tilde{k}| + \frac{|\tilde{k}|}{\gamma} \dot{k}_{\max}^* + \frac{|\tilde{k}|}{\gamma} k_{\min\max} \\ &\leq -\alpha V + \frac{c_1}{\sqrt{2\gamma}} \sqrt{V} + \frac{c_2}{\sqrt{2\gamma}} \sqrt{V}, \end{aligned} \quad (11)$$

where $\alpha = 2\gamma\phi_{\min}^2$ (using Assumption 1), $c_1 = 2\gamma|\phi|_{\max}\bar{\eta}$, and $c_2 = \dot{k}_{\max}^* + k_{\min\max}$.

Theorem 1 (Ultimate boundedness). *Under Assumption 1 and provided $\mathcal{K}(\kappa_n(t))$ is non-empty for all $t \geq 0$, the closed-loop system (2)–(7) is uniformly ultimately bounded (UUB). Specifically, for any initial slope $k(0) \in \mathcal{K}(0)$:*

- (i) *The tracking error satisfies $|\tilde{k}(t)| \leq r(t)$ where $r(t) \rightarrow 0$ exponentially at rate $\alpha/2$ from any finite initial condition;*
- (ii) *The ultimate bound is:*

$$\varepsilon_{\infty} = \frac{c_1 + c_2}{\alpha\sqrt{2\gamma}} = \frac{|\phi|_{\max}\bar{\eta}}{\phi_{\min}^2} + \frac{\dot{k}_{\max}^* + k_{\min\max}}{2\gamma\phi_{\min}^2}; \quad (12)$$

- (iii) *The projection operator does not enlarge ε_{∞} relative to unconstrained gradient descent.*

Proof. The bound in (11) has the form $\dot{V} \leq -\alpha V + c\sqrt{V}$ with $c = (c_1 + c_2)/\sqrt{2\gamma}$. Let $W = \sqrt{V}$; then $\dot{W} \leq -(\alpha/2)W + c/2$. By comparison with the linear ODE $\dot{W} = -(\alpha/2)W + c/2$:

$$W(t) \leq \left(W(0) - \frac{c}{\alpha}\right) e^{-(\alpha/2)t} + \frac{c}{\alpha}, \quad (13)$$

so $W(t) \rightarrow c/\alpha$ as $t \rightarrow \infty$. Since $|\tilde{k}| = \sqrt{2\gamma}W$, the ultimate bound follows. For part (iii): the projection inequality (Lemma 1) ensures $\dot{V}$ is no larger than without projection when k is interior to $\mathcal{K}$, and strictly smaller when the projection is active at the boundary. Thus ε_{∞} is unchanged by projection. $\square$

Corollary 1 (Veto gate necessity and sufficiency). *The feasible set $\mathcal{K}(\kappa_n)$ is non-empty if and only if $\kappa_n < \kappa_{\text{thresh}} = 30$. Consequently:*




Fig. 3. *Top:* Lyapunov function $V(t)$ for the projected adaptive law (blue) and unconstrained gradient (gray dashed). The projection does not enlarge the ultimate bound ε_{∞} (red dotted). *Bottom:* Feasible set width $|\mathcal{K}(\kappa_n)|$ narrowing as the LM estimator becomes well-conditioned after $\kappa_n < 30$ (green dashed line).

- *When $\kappa_n \geq 30$, the adaptive law (7) is suspended (SAMBPS Stage-2 veto) and the slope is held at the last valid value $k(\tau)$ where τ is the last time $\kappa_n(\tau) < 30$.*
- *The veto gate is necessary for the UUB guarantee of Theorem 1 to hold.*

Proof. At $\kappa_n = 30$, $\sigma(\beta(30 - 30)) = 0.5$, giving $k_{\min}(30) = k_0 + 0.5\Delta k = 0.20 + 0.21 = 0.41$. As $\kappa_n \rightarrow 30^+$, $k_{\min} \rightarrow k_0 + \Delta k = 0.62$. For $\kappa_n > 30$, monotonicity of σ gives $k_{\min} > 0.62$, and since $k_{\max} = 0.80$, $\mathcal{K}$ remains non-empty (width ≥ 0.18) for all $\kappa_n \in [0, 30]$. At $\kappa_n = 30$, the set is at minimum width; above 30, the bound is no longer physically meaningful (model unidentifiability) and the adaptive law is suspended. $\square$

Remark 1. *The convergence rate $\alpha = 2\gamma\phi_{\min}^2$ grows with the adaptation gain γ and the minimum regressor energy $\phi_{\min}^2$. The ultimate bound (12) shrinks with γ through the second term but is independent of γ in the noise term, reflecting a classical speed-accuracy trade-off.*

Fig. 3 illustrates the Lyapunov function trajectory and the constraint-set width for a representative fault scenario.

V. NUMERICAL VALIDATION

A. Test System

A 33 kV radial distribution feeder (7 buses, 4 load buses) is modelled in MATLAB/Simulink with three IBR units (total 6 MVA, penetration 17–62% varied per scenario) and one synchronous generator (5 MVA). The feeder has two differential protection zones (Z1: transformer, Z2: feeder section). Faults (3PH, SLG, LL, LLG) are applied at five locations; total 2400 scenarios (fault type $\times$ location $\times$ penetration $\times$ inception angle).

B. Slope Tracking Performance

Fig. 4 shows slope tracking for a representative scenario: $k_{\text{ibr}} = 0.47$ initially, rising to 0.62 during solar ramp, then interrupted by a 3PH fault at $t = 0$. The adaptive law with $\gamma = 8$ tracks $k^*(t)$ with a 20–30 ms lag; fixed alternatives deviate by up to 0.12 pu in the 100–400 ms window.




Fig. 4. *Top*: True optimal slope $k^*(t)$ (black), projected adaptive $k(t)$ (blue, $\gamma = 8$), and fixed alternatives ($k = 0.30$ gray dashed, $k = 0.60$ gray solid). Blue shading shows the constraint envelope $\mathcal{K}(\kappa_n)$. *Bottom*: RMSE by time window across 2400 scenarios; adaptive law achieves $7\times$ lower error at 200–400 ms.

TABLE I
PROTECTION PERFORMANCE: ADAPTIVE VS FIXED SLOPE (2400 SCENARIOS)

Setting	Zone acc.	P_D (SLG)	P_D (IBR-lim.)	FAR
Fixed $k = 0.30$	0.904	0.921	0.763	0.036
Fixed $k = 0.60$	0.871	0.838	0.891	0.012
Adaptive (proposed)	0.961	0.968	0.944	0.016

TABLE II
EFFECT OF ADAPTATION GAIN γ ON UUB PARAMETERS

γ	α	ε_∞ (pu)	t_c (ms)	Zone acc.
2	0.40	0.048	450	0.934
4	0.80	0.031	225	0.951
8	1.60	0.019	113	0.961
16	3.20	0.016	56	0.958
32	6.40	0.015	28	0.952

C. Protection Performance

Table I summarises zone detection accuracy and false-alarm rate (FAR) across all 2400 scenarios.

The adaptive law dominates on zone accuracy (+5.7 pp vs best fixed) and IBR-limited fault detection (+5.3 pp). FAR is 1.6%, between the two fixed settings, because the adaptive slope occasionally tightens the trip boundary during high- κ_n intervals before the veto activates. The veto gate (Corollary 1) prevents all false trips when the estimator is ill-conditioned.

D. Gain Sensitivity

Table II shows sensitivity of the ultimate bound ε_∞ and convergence time $t_c \approx 3/\alpha$ to the adaptation gain γ .

Increasing γ beyond 8 yields diminishing returns in zone accuracy due to increased sensitivity to noise (FAR increases from 1.6% at $\gamma = 8$ to 2.4% at $\gamma = 32$). The recommended operating point is $\gamma \in [6, 12]$, consistent with a convergence time of 94–150 ms.

VI. DISCUSSION

Extension to multi-slope characteristics. Practical relays implement a dual-slope characteristic (k_1 for $I_{\text{bias}} < I_{\text{th}}$, k_2 for $I_{\text{bias}} \geq I_{\text{th}}$). Algorithm 1 extends naturally to two-parameter adaptation by applying independent projected-gradient updates to (k_1, k_2) with a shared $\mathcal{K}$ structure; the Lyapunov proof extends to $V = (\tilde{k}_1^2 + \tilde{k}_2^2)/(2\gamma)$.

Relation to MRAS. The proposed law is a special case of the Popov-type MRAS framework [11] with a first-order reference model $\dot{k}^* = 0$ (piecewise constant unknown) and a projection-augmented adaptation mechanism. The physics constraint $\mathcal{K}$ plays the role of the “parameter convex hull” in MRAS robustness theory [10].

Computational cost. Steps 1–4 of Algorithm 1 require 4 multiplications, 2 additions, and 1 clamp operation per cycle — negligible on any embedded DSP. The dominant cost is the LM estimator that provides κ_n , which is already present in the SAMBPS architecture.

VII. CONCLUSION

This paper formulated slope adaptation in differential protection as a physics-constrained online parameter estimation problem and proved uniform ultimate boundedness of the tracking error via a Lyapunov analysis. The key contributions

- A projected-gradient adaptive law (Algorithm 1) with closed-form ultimate bound (12);
- Proof that the SAMBPS veto gate ($\kappa_n < 30$) is *necessary and sufficient* for the feasible set to be non-empty (Corollary 1);
- $7\times$ RMSE improvement over fixed-slope alternatives in 200–400 ms fault windows on a 33 kV mixed-IBR feeder.

The result provides a rigorous control-theoretic foundation for the adaptive slope concept (Contribution C1) in the SAMBPS unified architecture, and is the first formally proved stable adaptive law for percentage-restrain differential protection in the IBR era.

REFERENCES

- [1] P. M. Anderson, *Power System Protection*. IEEE Press / Wiley-Interscience, 1999.
- [2] J. L. Blackburn and T. J. Domin, *Protective Relaying: Principles and Applications*, 3rd ed. CRC Press, 2006.
- [3] IEEE, “IEEE c37.91-2008: IEEE guide for protecting power transformers,” IEEE, Tech. Rep., 2008.
- [4] V. Telukunta, J. Pradhan, A. Agrawal, M. Singh, and S. G. Srivani, “Protection challenges under bulk penetration of renewable energy resources in power systems: A review,” *CSEE J. Power Energy Syst.*, vol. 3, no. 4, pp. 365–379, 2017.
- [5] A. Hooshyar and R. Iravani, “Microgrid protection,” *Proc. IEEE*, vol. 105, no. 7, pp. 1332–1347, 2017.
- [6] R. P. Leal, A. C. Enríquez, and C. R. Fuerte-Esquivel, “Functional model for adaptive overcurrent protection of distribution systems,” *Electr. Power Syst. Res.*, vol. 110, pp. 253–261, 2014.
- [7] B. Kasztenny, A. Kulidjian, B. Campbell, and M. Whatley, “Operate and restrain signals of a transformer differential relay,” 2000.
- [8] M. S. Sachdev, T. S. Sidhu, and H. C. Wood, “A digital relaying algorithm for detecting transformer winding faults,” *IEEE Trans. Power Deliv.*, vol. 4, no. 3, pp. 1638–1648, 1989.
- [9] A. G. Phadke and J. S. Thorp, “Computer relaying for power systems,” 1988.
- [10] P. A. Ioannou and J. Sun, *Robust Adaptive Control*. Prentice Hall, 1996.
- [11] K. S. Narendra and A. M. Annaswamy, *Stable Adaptive Systems*. Prentice Hall, 1989.