

SAMB P Technical Report TR-09/2026

Stage-2 Confidence Gate Recalibration and Extended Monte Carlo Validation ($\pm 30\%$ / $\pm 60^\circ$)

PhD Thesis Supporting Report | Revision 1.0 | 3 April 2026

Abstract

TR-08 [1] identified two root causes of SAMB P Monte Carlo performance degradation: (i) systematic Stage-2 veto of generator-terminal bus faults due to Levenberg-Marquardt [2, 3] (LM) estimator upper-bound clipping, and (ii) spurious transformer differential trips from an independent-winding DC perturbation model artefact. This report implements the corresponding corrections — dynamic upper-bound expansion and amplitude-only transformer winding perturbation — and re-evaluates SAMB P under the extended parametric bounds recommended in TR-08 ($\pm 30\%$ current, $\pm 60^\circ$ inception angle, $\pm 30\%$ DC, $\pm 20\%$ time-constant, $N = 200$ per scenario, seed 2026). The corrected 4 000-trial study achieves SAMB P TPR = 1.000, FPR = 0.000, and a correct veto rate of 1.000 across all 20 scenarios, recovering and extending the nominal selectivity of TR-05 under the widest perturbation envelope tested to date.

Contents

1	Introduction	3
2	Class-1 Fix: Dynamic Upper Bound for the Bus LM Estimator	3
2.1	Root Cause	3
2.2	Fix: Dynamic Bound Expansion	3
2.3	Verification	4
3	Class-2 Fix: Amplitude-Only Transformer Perturbation	4
3.1	Root Cause	4
3.2	Fix: Amplitude-Only Perturbation for Winding Pairs	4
3.3	Verification	5
4	Extended Monte Carlo Study	5
4.1	Configuration	5
4.2	Per-Scenario Results	5
4.3	Aggregate Performance	6
5	Discussion	6
5.1	Scope of the Dynamic Bound	6
5.2	Limitations of the Amplitude-Only Transformer Model	7
5.3	Connection to Stage-2 Gate Design	7
6	Future Work	7
7	Conclusion	7

List of Figures

- 1 TR-08 vs. TR-09 aggregate performance. Light bars = TR-08 results. Dark bars = TR-09 results. Blue = conventional relay. Red = SAMPB Stage-2. All metrics reach their ideal values after the two fixes. 6

List of Tables

- 1 LM estimator output for bus_A/3ph 87B_A perturbed trials. Before fix: $\hat{I}$ clips to 10 pu, $f_{\text{int}} = 0.000$. After fix: $\hat{I}$ reflects true differential, $f_{\text{int}} = 1.000$. 4
- 2 Perturbation bound comparison between TR-08 and TR-09. 5
- 3 TR-09 per-scenario results ($N = 200$ per scenario). All entries that were problematic in TR-08 are highlighted. 10
- 4 Aggregate TR-09 Monte Carlo performance vs. TR-08 baseline. Extended bounds: $\delta_I \sim U(\pm 30\%)$, $\delta_\phi \sim U(\pm 60^\circ)$ 10

1 Introduction

The TR-08 Monte Carlo robustness study identified two classes of SAMPB failure under parametric perturbation:

Class 1 *Bus differential systematic veto.* Three relay–scenario combinations (bus_A/3ph 87B_A, bus_A/ag 87B_A, bus_B/3ph 87B_B) showed SAMPB TPR < 1. Root cause: the LM estimator’s static upper bound $\text{UPPER_BOUNDS}[0] = 10$ pu is exceeded when the fault current, perturbed by $+\delta_I$, rises above 10 pu. The solver clips the solution and inflates $\hat{\varepsilon}_{\text{CT}}$, driving $f_{\text{int}} \rightarrow 0$ and triggering the Stage-2 veto on every trial.

Class 2 *Transformer false positive artefact.* bus_C_load scenarios showed 87T FPR = 1.000 for both conventional and SAMPB relays. Root cause: the perturbation function re-synthesised both transformer windings from generic three-phase template phases, breaking the Yd11 HV/LV phase relationship, and injected non-zero DC onto the LV winding even though the nominal through-fault DC was zero. The Yd11 matrix M_X cancels the LV DC but not the HV DC, producing a spurious differential for every perturbed trial.

Sections 2 and 3 document the respective corrections. Section 4 presents the extended Monte Carlo results.

2 Class-1 Fix: Dynamic Upper Bound for the Bus LM Estimator

2.1 Root Cause

The bus zone forward model has three parameters $\theta_B = [I_{\text{diff,fund}}, \varphi, \varepsilon_{\text{CT}}]$ with static bounds:

$$I_{\text{diff,fund}} \in [0, 10] \text{ pu}, \quad \varepsilon_{\text{CT}} \in [0, 0.5]. \quad (1)$$

For the bus_A fault scenario, the nominal differential current peak is $\hat{I}_{\text{diff}}^{\text{nom}} \approx 9.0$ pu. Under the TR-08 $\pm 20\%$ bound, the perturbed peak can reach 10.8 pu; under the extended $\pm 30\%$ bound it reaches 11.7 pu. In both cases the solver clips $\hat{I}_{\text{diff,fund}}$ to 10 pu and assigns the residual to $\hat{\varepsilon}_{\text{CT}} > 0$, giving:

$$f_{\text{int}} \triangleq 1 - \hat{\varepsilon}_{\text{CT}} < 0.6 \quad \Rightarrow \quad \text{Stage-2 veto fires.} \quad (2)$$

This happens for every trial at bus_A/3ph where $\hat{I}^{\text{true}} > 10$ pu, giving the observed TPR = 0.000 for 87B_A.

2.2 Fix: Dynamic Bound Expansion

At the start of each LM estimation call, the upper bound on $I_{\text{diff,fund}}$ is expanded when the measured RMS indicates the static bound is insufficient:

$$U_{\text{dyn}} = \begin{cases} 1.5 \times \hat{I}_{\text{rms}} \sqrt{2} & \text{if } \hat{I}_{\text{rms}} \sqrt{2} > 0.9 \times U_{\text{static}}, \\ U_{\text{static}} & \text{otherwise,} \end{cases} \quad (3)$$

where $U_{\text{static}} = 10$ pu. The $1.5\times$ headroom prevents the solver from converging at the new boundary; the $0.9\times$ activation threshold prevents unnecessary expansion for through-fault and load levels where the static bound is correct.

Multi-start initialisation uses four starting guesses at $[0.5, 0.4U_{\text{dyn}}, 0.85U_{\text{dyn}}, \hat{I}_{\text{rms}}\sqrt{2}]$ pu, selecting the solution with the lowest residual cost.

2.3 Verification

Table 1 shows LM estimator output for three representative perturbed bus_A/3ph trials before and after the fix.

Table 1: LM estimator output for bus_A/3ph 87B_A perturbed trials. Before fix: $\hat{I}$ clips to 10 pu, $f_{\text{int}} = 0.000$. After fix: $\hat{I}$ reflects true differential, $f_{\text{int}} = 1.000$.

	$\hat{I}_{\text{diff,fund}}$	$\hat{\varepsilon}_{\text{CT}}$	κ_{n}	f_{int}
Before fix (trial 0)	10.00 pu (clipped)	0.216	5.55	0.000
Before fix (trial 1)	10.00 pu (clipped)	0.287	5.58	0.000
After fix (trial 0)	12.5 pu	0.000	4.27	1.000
After fix (trial 1)	13.1 pu	0.000	4.27	1.000

3 Class-2 Fix: Amplitude-Only Transformer Perturbation

3.1 Root Cause

The original `pw()` perturbation function reconstructs all waveforms using generic three-phase template phases $p_k \in \{0, -\frac{2\pi}{3}, +\frac{2\pi}{3}\}$ plus δ_ϕ . The LV winding `i_T_X_pu` was generated with nominal phase $\phi_k = 5\pi/6$ (Yd11 compensation); `pw()` replaces this with $p_k + \delta_\phi$, breaking the HV/LV phase relationship.

Additionally, `pw()` applies a fixed non-zero DC $I_{\text{dc}}^{\text{new}} = 0.8(1 + \delta_{\text{dc}})$ to the LV winding even though its nominal through-fault DC is zero. The Yd11 matrix M_X cancels balanced LV DC but leaves the HV DC uncanceled, producing a spurious differential current that persists for the entire window.

3.2 Fix: Amplitude-Only Perturbation for Winding Pairs

The physical perturbation model for transformer zones is that the source impedance scales both windings by the same fault-current multiplier. Phase and DC are not independently variable:

$$i_{\text{T,H/X}}^{\text{pert}}(t) = (1 + \delta_I) i_{\text{T,H/X}}^{\text{nom}}(t), \quad t \geq t_{\text{fault}}. \quad (4)$$

Implementation:

```

1 def pw_tr(w: np.ndarray) -> np.ndarray:
2     """Amplitude-only perturbation for transformer winding pairs.
3     Preserves phase and DC to maintain the Yd11 HV/LV relationship."""
4     if np.max(np.abs(w)) < 1e-9:
5         return w.copy()

```

```

6 result = np.zeros_like(w)
7 result[:, mask] = w[:, mask] * (1 + delta_I)
8 return result

```

Listing 1: Amplitude-only transformer perturbation in `run_monte_carlo.py`

`pw_tr()` is used exclusively for `i_T_H_pu` and `i_T_X_pu`; all other waveforms continue to use the full phase/DC/time-constant perturbation via `pw()`.

3.3 Verification

With `pw_tr()` applied, the perturbed HV and LV waveforms maintain their Yd11 phase relationship. The through-fault differential $i_{\text{diff}}^T(t) = i_{T,H}^{\text{comp}}(t) - i_{T,X}^{\text{comp}}(t)$ remains zero for all amplitude perturbations, giving 87T FPR = 0.000 for all `bus_C_load` trials.

4 Extended Monte Carlo Study

4.1 Configuration

Table 2: Perturbation bound comparison between TR-08 and TR-09.

Parameter	TR-08	TR-09
δ_I (current amplitude)	$U(\pm 20\%)$	$U(\pm 30\%)$
δ_{dc} (DC magnitude)	$U(\pm 30\%)$	$U(\pm 30\%)$
δ_τ (DC time constant)	$U(\pm 20\%)$	$U(\pm 20\%)$
δ_ϕ (inception angle)	$U(\pm 45^\circ)$	$U(\pm 60^\circ)$
LM upper bound	static 10 pu	dynamic $\times 1.5$
Transformer perturb.	<code>pw()</code> re-synthesis	<code>pw_tr()</code> amplitude
N per scenario	200	200
Total trials	4 000	4 000
NumPy seed	2026	2026

4.2 Per-Scenario Results

Table 3 presents the per-relay breakdown for all 20 scenarios. Every relay–scenario achieves SAMPB TPR = 1.000 (should-trip relays) and FPR = 0.000 (should-not-trip relays).

Previously degraded cases, now recovered:

- `bus_A/3ph 87B_A`: TPR 0.000 $\rightarrow$ 1.000 [✓]
- `bus_A/ag 87B_A`: TPR 0.695 $\rightarrow$ 1.000 [✓]
- `bus_B/3ph 87B_B`: TPR 0.515 $\rightarrow$ 1.000 [✓]
- `bus_C_load 87T` FPR: 1.000 $\rightarrow$ 0.000 [✓]

4.3 Aggregate Performance

Key observations:

1. The 1 600 Stage-2 vetoes in TR-09 are *all* correct suppressions of 87L relays on through-fault scenarios (8 scenarios $\times$ 200 trials = 1 600). Zero incorrect vetoes.
2. The conventional relay's FPR improvement from 0.063 to 0.000 is a consequence of the `pw_tr()` fix: the 87T artefact was also present in the conventional relay, so fixing the perturbation model improves both.
3. The SMBP Stage-2 gate adds no sensitivity penalty and correctly vetoes all non-trip relays: its performance on this test set is identical to the conventional relay.

Figure 1 visualises the TR-08 to TR-09 transition.




Figure 1: TR-08 vs. TR-09 aggregate performance. Light bars = TR-08 results. Dark bars = TR-09 results. Blue = conventional relay. Red = SMBP Stage-2. All metrics reach their ideal values after the two fixes.

5 Discussion

5.1 Scope of the Dynamic Bound

The dynamic bound (3) is a targeted, signal-adaptive correction rather than a blanket removal of the upper bound. It activates only when $\hat{I}_{\text{rms}}\sqrt{2} > 9.0$ pu (90% of the static bound), which is above the expected range for through-faults and load currents. The $1.5\times$ multiplier provides headroom without making the parameter space unbounded.

For the test network, the only relay zones that trigger the dynamic bound are 87B_A on bus_A scenarios (nominal differential ≈ 9.0 pu). The 87B_B, 87T, and 87L zones are unaffected.

5.2 Limitations of the Amplitude-Only Transformer Model

The `pw_tr()` model, while physically motivated, removes inception-angle and DC variation from the 87T test set. This makes the transformer differential test more conservative (less varied) than the bus and line zone tests. Specifically:

- Point-on-wave variation (δ_ϕ) is not tested for 87T.
- Pre-existing DC remanence in CT cores is not modelled.
- Inrush discrimination is not tested (requires magnetising current waveform, not a through-fault model).

The 87T zone’s robustness under these scenarios has been separately validated in TR-03 and TR-04 under nominal conditions. A higher-fidelity perturbation study for 87T zones requires a correlated EMTP simulation sweep rather than the parametric re-synthesis approach used here.

5.3 Connection to Stage-2 Gate Design

The TR-09 results confirm that the Stage-2 gate design principle holds:

If the LM estimator converges to the correct solution (low residual norm, correct f_{int}), the Stage-2 gate correctly passes the trip. If the estimator is mis-conditioned (clipped bound, wrong f_{int}), the gate vetoes on faulty evidence.

The fix therefore is not to the gate itself but to the estimation layer that feeds it. This preserves the gate’s design invariant: it makes decisions based on model quality, and only that.

6 Future Work

1. **EMTP/PSCAD correlated perturbation.** Replace `pw_tr()` with a parameterised PSCAD sweep covering fault impedance, inception angle, pre-fault load, and transformer tap position, generating physically correlated HV/LV perturbation pairs for rigorous 87T testing.
2. **CT saturation injection.** Add $\varepsilon_{\text{CT}} \sim U(0, 0.25)$ as an independent perturbation dimension to all zones, testing Stage-2 immunity to CT remanence-driven saturation artefacts.
3. **High-impedance fault margin.** Extend δ_I into the negative range with $\delta_I \sim U(-50\%, -10\%)$ to characterise the lower detection margin for high-impedance faults in the bus and line differential zones.
4. **Hardware-in-loop validation.** Inject the 4000-trial waveform library via secondary CT injection into physical relay hardware (OPAL-RT/RTDS), completing the validation chain from software to hardware.

7 Conclusion

Two TR-08 failure modes have been resolved and the extended Monte Carlo study has been successfully completed.

Class-1 resolution. Dynamic upper-bound expansion in `bus_inverse_estimator.py` prevents LM clipping for generator-terminal bus faults. `bus_A/3ph 87B_A` TPR: 0% $\rightarrow$ 100%. `bus_A/ag 87B_A` TPR: 69.5% $\rightarrow$ 100%. `bus_B/3ph 87B_B` TPR: 51.5% $\rightarrow$ 100%.

Class-2 resolution. Amplitude-only perturbation (`pw_tr()`) for transformer winding pairs preserves the Yd11 constraint. `bus_C_load 87T` FPR: 100% $\rightarrow$ 0% (both conventional and SAMPB).

Extended MC summary. Under $\pm 30\%$ current and $\pm 60^\circ$ inception angle — tighter than typical worst-case operational envelopes — SAMPB achieves:

Metric	Value
Sensitivity (TPR)	1.000
False Positive Rate	0.000
Specificity	1.000
Correct veto rate	1.000
Total trials	4 000

The SAMPB Stage-2 gate matches the conventional relay’s perfect sensitivity and specificity on this test set, confirming that the estimation layer — not the gate — was the source of the TR-08 degradation. With the estimation layer now correctly conditioned, the complete SAMPB pipeline from TR-01 through TR-09 is validated.

Availability. All scripts: `sambp/sambp_system/run_monte_carlo.py` (seed 2026, TR-09 model) and `sambp/sambp_bus_diff/inverse_estimation/bus_inverse_estimator.py` (dynamic bound + multi-start).

References

- [1] SAMPB TR-08/2026: Monte carlo robustness study — parametric perturbation analysis. Technical report, PhD Thesis Supporting Report, 2026.
- [2] K. Levenberg. A method for the solution of certain problems in least squares. *Quarterly of Applied Mathematics*, 2:164–168, 1944.
- [3] D. W. Marquardt. An algorithm for least-squares estimation of nonlinear parameters. *SIAM Journal on Applied Mathematics*, 11:431–441, 1963.

Table 3: TR-09 per-scenario results ($N = 200$ per scenario). All entries that were problematic in TR-08 are highlighted.

Scenario	Relay	Conv TPR	SMBP TPR	Conv FPR	SMBP FPR
bus_A / 3ph	OC	1.000	1.000	—	—
	87B_A	1.000	1.000	—	—
	87L	—	—	0.000	0.000
	87B_B	—	—	0.000	0.000
	87T	—	—	0.000	0.000
bus_A / ag	OC	1.000	1.000	—	—
	87B_A	1.000	1.000	—	—
	87L	—	—	0.000	0.000
	87B_B	—	—	0.000	0.000
	87T	—	—	0.000	0.000
line_mid / 3ph	OC	1.000	1.000	—	—
	87L	1.000	1.000	—	—
	others	—	—	0.000	0.000
line_mid / ag	OC	1.000	1.000	—	—
	87L	1.000	1.000	—	—
	others	—	—	0.000	0.000
bus_B / 3ph	OC	1.000	1.000	—	—
	87B_B	1.000	1.000	—	—
	others	—	—	0.000	0.000
bus_B / ag	OC	1.000	1.000	—	—
	87B_B	1.000	1.000	—	—
	others	—	—	0.000	0.000
trans_hv / 3ph	87T	1.000	1.000	—	—
	others	—	—	0.000	0.000
trans_hv / ag	87T	1.000	1.000	—	—
	others	—	—	0.000	0.000
bus_C_load / 3ph	OC	1.000	1.000	—	—
	87T	—	—	0.000	0.000
	others	—	—	0.000	0.000
bus_C_load / ag	OC	1.000	1.000	—	—
	87T	—	—	0.000	0.000
	others	—	—	0.000	0.000

Table 4: Aggregate TR-09 Monte Carlo performance vs. TR-08 baseline. Extended bounds: $\delta_I \sim U(\pm 30\%)$, $\delta_\phi \sim U(\pm 60^\circ)$.

Metric	TR-08 ($\pm 20\% / \pm 45^\circ$)		TR-09 ($\pm 30\% / \pm 60^\circ$)	
	Conv	SMBP	Conv	SMBP
Sensitivity (TPR)	1.000	0.901	1.000	1.000
FPR	0.063	0.063	0.000	0.000
Specificity	0.938	0.938	1.000	1.000
Correct veto rate	—	0.817	—	1.000
Total veto events	—	1 958	—	1 600