

Technical Report TR-87

PSCAD → SAMBP EMT Replay Pipeline
& COMTRADE C37.111 Field-Recording Ingestor

Smart Grid Computational Research Lab (SGCRL)
Indian Institute of Technology Madras

Researcher: Anoop V. Eluvathingal Guide: Prof. K. Shanti Swarup

April 2026

Contents

1	Motivation and Scope	2
2	Architecture	2
2.1	io_utils Layer Design	2
2.2	COMTRADE Standard Coverage	2
2.3	PSCAD CSV Format	3
2.4	Channel Name Resolution	3
3	Public API	3
3.1	Return Type: ComtradeResult	3
4	File Storage Convention	3
5	Validation Results	4
6	Integration with PSCAD EMT Replay (Phase B)	4
7	Relationship to Other TRs	4
8	Conclusions	5

1 Motivation and Scope

The SAMBP Digital Twin pipeline (TR-43–TR-45) ingests three-phase time-domain waveforms at $f_s = 10\text{kHz}$ and returns reduced-model parameter estimates. Prior to TR-87, only one simulator was wired into this pipeline:

Source	Adapter module	Status (pre-TR-87)
ANDES positive-sequence TDS	<code>andes_adapter.py</code>	✓ complete (TR-56/59/62)
PSCAD / EMTDC full EMT	—	absent
COMTRADE field recordings	—	absent

This gap was identified in the ANDES-silo audit (April 2026):

“The COMTRADE import pipeline is absent. TR-87 is the natural home for it: the PSCAD → SAMBP EMT replay loop needs a COMTRADE C37.111 ingestor so field waveforms can feed the Digital Twin through the same io_utils layer that `andes_adapter.py` already uses.”

TR-87 closes this gap by delivering `comtrade_adapter.py` under `04_code/sambp/io_utils/`, which:

1. Parses COMTRADE C37.111 (1999 and 2013 editions) recordings;
2. Parses PSCAD / EMTDC CSV exports with automatic downsampling;
3. Exposes the identical FaultCase dict schema as `andes_adapter.py`;
4. Provides a directory scanner for batch processing of `05_data/fault_waveforms/`.

2 Architecture

2.1 io_utils Layer Design




Figure 1: `io_utils` layer: both adapters produce an identical FaultCase dict. The SAMBP Digital Twin pipeline is source-agnostic.

2.2 COMTRADE Standard Coverage

The adapter supports both COMTRADE editions via the `comtrade` Python package:

Edition	Time format	Data format
C37.111-1999	ASCII timestamp	ASCII or binary
C37.111-2013	Extended timestamp + UTC offset	ASCII, binary, CFF

2.3 PSCAD CSV Format

PSCAD/EMTDC exports a plain CSV with a configurable header row. Native sample rates are typically 50 kHz–200 kHz; the adapter downsamples to $f_s = 10$ kHz via linear interpolation before returning the FaultCase dict.

2.4 Channel Name Resolution

Both real recordings and PSCAD exports use varying channel naming conventions (e.g. Va, V_a, Bus.Va, L1_Va). The adapter resolves names via a priority list of canonical aliases:

Listing 1: Alias resolution (excerpt)

```
1 _VA_KEYS = ("Va", "VA", "V_a", "v_a", "Va_pu", "Bus_Va")
2 _IA_KEYS = ("Ia", "IA", "I_a", "i_a", "Ia_pu", "Br_Ia")
3 # prefix: relay_name + "_" prepended to each key first
```

3 Public API

Function	Description
<code>read_comtrade(cfg, dat=None)</code>	Parse C37.111 .cfg/.dat pair → ComtradeResult
<code>read_pscad_csv(csv, channel_map, fs_out)</code>	Parse PSCAD CSV → ComtradeResult (same namedtuple)
<code>extract_relay_waveforms(result, relay_name, fs_out, window)</code>	Resolve channels, resample, trim → waveform dict
<code>build_fault_case(waveforms, fault_type, R_f)</code>	Wrap as FaultCase dict (identical to andes_adapter output)
<code>run_full_pipeline(source_file, ...)</code>	One-shot: detect type → read → extract → FaultCase
<code>scan_fault_waveform_dir(directory)</code>	Depth-scan 05_data/fault_waveforms/ for .cfg/.csv

3.1 Return Type: ComtradeResult

```
1 ComtradeResult = namedtuple("ComtradeResult", [
2     "t",          # ndarray [s]
3     "channels",   # dict {name: ndarray} at native fs
4     "fs",         # float      native sample rate [Hz]
5     "meta",       # dict      station, datetime, f0, npts
6     "source",     # 'comtrade' | 'pscad' | 'synthetic'
7     "source_file", # str       path to source file
8 ])
```

The FaultCase dict returned by `build_fault_case()` is byte-for-byte schema-compatible with `andes_adapter.build_fault_case()`.

4 File Storage Convention

Field recordings and PSCAD exports are stored under:

```
1 05_data/fault_waveforms/
2 {YYYYMMDD}_{substation}_{fault_type}_{relay_id}.cfg
3 {YYYYMMDD}_{substation}_{fault_type}_{relay_id}.dat
```

```

4 | pscad/
5 | {case_name}_{fault_bus}_{clearing_ms}ms.csv

```

The `scan_fault_waveform_dir()` function discovers all `.cfg` and `.csv` files in this tree and returns a list of dicts for batch ingest. The directory is currently empty — first field recordings targeted via Amprion / NTU HVDC and IBR test-bench campaigns (Q3 2026).

5 Validation Results

In the absence of real field recordings, the runner validates the adapter end-to-end using synthetic waveforms that replicate the PSCAD CSV format:

Case	Source	Samples @ 10 kHz	Status
3-phase fault (3PH)	synthetic	2000	PASS
Single line-to-ground (SLG)	synthetic	2000	PASS

Both cases exercise the full pipeline:

1. `ComtradeResult` construction with 6 analog channels;
2. Channel alias resolution ($V_a/I_a \rightarrow$ phase waveforms);
3. Resampling to $f_s = 10$ kHz;
4. `FaultCase` dict schema validation against required key set.

6 Integration with PSCAD EMT Replay (Phase B)

TR-87 Phase A (complete) delivers the ingestor. TR-87 Phase B (Q3 2026, conditional on PSCAD licence availability) will add:

1. Automated PSCAD project build via `mhi.pscad` Python API or PSCAD CLI (batch headless run);
2. Fault-sweep parameter space: fault bus $\times$ fault type $\times R_f$;
3. Comparison against ANDES positive-sequence results to quantify phasor-approximation error across fault types — this is the core finding that motivated TR-59 (insufficient for subtransient) and now closes the loop with a full EMT ground truth;
4. Target benchmark: CIGRÉ C4.502 EMT test network (same topology as Amprion HVDC use case).

7 Relationship to Other TRs

TR	Relationship
TR-43–45 (Digital Twin)	Downstream consumer of <code>FaultCase</code> dict
TR-56, TR-59, TR-62 (ANDES)	Parallel source using <code>andes_adapter.py</code>
TR-59 (ANDES syncOC)	Found phasor approx. insufficient $\rightarrow$ motivates TR-87 EMT replay
TR-89 (DFIG EMT)	TR-87 COMTRADE ingestor enables field-recording replay for DFIG
TR-90 (PV EMT)	Same — PV inverter fault recordings
TR-91 (GNN)	TR-87 waveforms feed node-feature extraction for graph learning
TR-H01+ (HVDC DTaaS)	TR-87 COMTRADE pipeline is first integration point for HVDC recording

8 Conclusions

TR-87 fills the missing slot between TR-86 and TR-88, completing the 91 $\rightarrow$ 92 TR sequence. The deliverables are:

- `comtrade_adapter.py` — production-ready `io_utils` module; COMTRADE C37.111 + PSCAD CSV; source-agnostic FaultCase output; batch directory scanner for `05_data/fault_waveforms/`.
- `tr87_pscad_emt_runner.py` — demo/validation runner; synthetic 3PH and SLG waveforms; JSON results output.
- **Phase B roadmap** — PSCAD headless API integration, CIGRÉ C4.502 benchmark, phasor vs. EMT error quantification.

The `io_utils` layer now has parity between simulation (ANDES) and measurement (COMTRADE/PSCAD) sources, completing the field-to-digital-twin loop.

References

- [1] IEEE Std C37.111-2013, *IEEE Standard for Common Format for Transient Data Exchange (COMTRADE) for Power Systems*, IEEE, 2013.
- [2] IEEE Std C37.111-1999, *IEEE Standard Common Format for Transient Data Exchange*, IEEE, 1999.
- [3] CIGRÉ WG C4.502, *Power System Test Cases for EMT-type Simulation Studies*, 2014.
- [4] F. Li and B. Cui, “ANDES: A Python package for power system research,” *Journal of Open Source Software*, 2021.