

292c clone BOM

by SAMODULAR

	Designator	Quantity	Description	Mouser Part#
Diodes				
1N5228	Z1, Z2, Z3, Z4	4		512-1N5228B

Resistors				
100R	R2, R25, R48, R71	4	1% 1/4W	271-100-RC
470R	R3, R26, R49, R72	4	1% 1/4W	271-470-RC
1K	R11, R20, R34, R43, R57, R66, R80, R89, R96	9	1% 1/4W	271-1K-RC
4.7K	R10, R22, R23, R33, R45, R46, R56, R68, R69, R79, R91, R92, R93	13	1% 1/4W	271-4.7K-RC
10K	R7, R8, R14, R16, R21, R30, R31, R37, R39, R44, R53, R54, R60, R62, R67, R76, R77, R83, R85, R90, R99	21	1% 1/4W	271-10K-RC
15K	R15, R18, R38, R41, R61, R64, R84, R87	8	1% 1/4W	271-15K-RC
18K	R19, R42, R65, R88	4	1% 1/4W	271-18K-RC
30K	R17, R40, R63, R86, R98	5	1% 1/4W	271-30K-RC
33K	R9, R32, R55, R78, R94, R95, R97, R100	8	1% 1/4W	271-33K-RC
100K	R6, R12, R13, R29, R35, R36, R52, R58, R59, R75, R81, R82	12	1% 1/4W	271-100K-RC
150K	R1, R24, R47, R70	4	1% 1/4W	271-150K-RC
470K	R5, R28, R51, R74	4	1% 1/4W	271-470K-RC
4.7M	R4, R27, R50, R73	4	5% 1/4W	291-4.7M-RC

Trimmers				
20K	TR1, TR2, TR3, TR4	4	Single turn	3362P-1-203LF

Capacitors				
22pF	C1, C10, C19, C28	4	Ceramic 5mm	810-FG28C0G1H220JNT6
100pF	C2, C8, C11, C17, C20, C26, C29, C35	8	Ceramic 5mm	810-FG28C0G1H101JNT6
220pF	C6, C9, C15, C18, C24, C27, C33, C36	8	Ceramic 5mm	810-FG28C0G1H221JNT6
1000pF	C4, C13, C22, C31	4	Ceramic 5mm	810-FG28X7R1H102KNT6
2000pF	C3, C12, C21, C30	4	Ceramic 5mm	810-FG28X7R1H222KNT6
0.0047uF	C5, C14, C23, C32	4	Film 5mm	871-B32529C1472J
0.1uF	F1, F2, F3, F4, F5, F6, F7, F8, F9, F10, F11, F12, F13, F14, F15, F16, F17, F18, F19, F20	20	Ceramic 5mm	810-FG28X7R1H104KNT6
1uF	C7, C16, C25, C34	4	Film 5mm	80-R82DC4100AA60J
15uF	C39, C40	2	Elec. 2mm	647-UKL1V150MDDANA

ICs				
TL071	IC9	1	8pin DIP	595-TL071CP
TL074	IC1, IC3, IC5, IC7	4	14pin DIP	595-TL074CN
DG202	IC2, IC4, IC6, IC8	4	16pin DIP	781-DG202BDJ-E3

Potentiometers				
10k - 100K lin	POT1, POT2, POT3, POT4	4	16mm	Alpha 16mm pot (add 4x additional nuts)

Misc				
HLMP-K101	LED1, LED2, LED3, LED4, LED5, LED6, LED7, LED8, LED9	9	LEDs (red)	630-HLMP-K101
	B1, B2, B3, B4	4	Banana jacks (black)	530-108-0903-1
VTL5C3/2	V1, V2, V3, V4	4	Dual vactrols	Xvive VTL5C3/2
SPDT ON-OFF-ON	SW1, SW2, SW3, SW4, SW5	4	SPDT switches	633-M201301
Tinijax 41	J1, J2, J4, J5, J7, J8, J10, J11, J13	9	Tinijax jacks	502-41
Tinijax 42a	J3, J6, J9, J12	4	Tinijax jacks (normalized)	502-42A
EDAC 10pin		1	EDAC connector (10pin)	EDAC connector