

Research Proposal - Complexity Costs of Fault-Tolerance Circuits.

Michael Ben-Or David Ponomarevsky

January 7, 2026

Abstract

We aim to study the overhead costs of fault-tolerant circuits in terms of both depth and width expansions. This means we ask what the optimal cost factor is, in each of the parameters alone, that one can hope to achieve, and also raise the question about the trade-off relation between the two. We ask these questions from both classical and quantum perspectives. The following proposal states the problems and subproblems that might shed light on the answer.

1 Introduction.

The Quantum Computation model is widely believed to be superior to classical models, offering asymptotic speedup in tasks such as factoring [Sho97], searching [Gro96], simulating, and more relative to the best-known classical solutions. Yet even though there is almost complete agreement about the superiority of the ideal quantum model, there is still a debate over whether it is possible to implement complex computation in the real world, where the qubits and gates are subject to faults. Similarly, the feasibility of realizing classical computation has also been an open question. In fact the question about the feasibility of computation under noise is almost as ancient as the computer science field itself, initialized by Von Neumann [Neu56] at the time that classical computation putted in debuts. Time been pass and the followed works had pointed that not even a polynomial computation in the presence of noise is still reasonable but one can implement a fault tolerance version at a most constant times cost at the circuits depth [Pip85]. Or in asymptotic sense, classical computation in the presence of noise is as exactly hard as computation in ideal environment.

Recently, the feasibility question has been raised again, this time regarding quantum circuits, and while an intensive work has been done, and also succeed to prove that polynomial quantum computation can be made fault tolerance, [AB99],[Got14] and even with an only constant overhead at the original circuit width [Gro19], polylogarithmic depth [TKY24], and logarithmic depth [NP24]. Yet the minimal required depth overhead is still not well understood. That raises our first open problem:

Open-Problem 1. Is there a fault-tolerance scheme that maps circuits to noise-tolerant versions with a depth that is at most a constant times more? If not, what is the lower bound for depth overhead?

We stress that in all the mentioned constructions, the original constant-depth gates are mapped to logical presentations whose underlying implementation has asymptotically growing depth. This is in contrast to Pippenger [Pip85], where the logical gates are $O(1)$ -depth circuits.

Such an expansion prevents any construction that merely shifts presentations without interfering with the logical computation path of the original circuits from reaching a constant depth overhead. Previous works have made way to bypass this obstacle; notably, [Ngu24] and [Li+25] present good error correction codes with transversal **CCZ** gates, and the series of works by Bombin [BM06], [Bom10], [Bom15] yield the 2D-color and 3D-color codes, which can be embedded on low-dimensional lattices (2D and 3D) and offer transversal gate implementation, where the first offers the whole Clifford group and the second the **T** gate. However, no code with a non-trivial distance and $O(1)$ -depth implementation for a complete universal gate set is known what raises our following open problem:

Open-Problem 2. Is there an error correction code with non-trivial distance for which a full universal gate set over the logical qubits can be realized at constant depth?

Since error correction codes with trivial distance might have a constant depth realization of a universal gate set (take, for example, the code where any codeword consists of a single physical qubit that encodes the logical state, adjacent to garbage), it is also interesting to ask whether there is a turning point:

Open-Problem 3. If the answer to Open-Problem 2 is yes, what is the minimum distance for which there exists a code with that distance, and the code provides a universal gate set realization at constant depth?

Similarly, one can also ask whether the code dimension plays a role in the feasibility of realizing logical gates. Recent work provides a first result regarding the width-depth tradeoff. Specifically, they show that for classical codes with distance d , for any logical qubit i , there exists a logical qubit $j \neq i$ such that the code offers the $\mathbf{CX}_{i,j}$ logical gate at most at l -depth. Then, it must hold that $k = O\left(\frac{n}{d^{2-l}}\right)$. They also mention that their proof does not imply an analogous tradeoff relation for quantum codes. This brings us to ask if the result can be generalized to the implementation of general gates and to quantum error correction codes.

Open-Problem 4. Whether there is a relation between the depth of a logical gate of an error correction code and the dimension and depth of that code. Is that relation identical for both classical and quantum codes? If not, how does the trade-off behave in each case?

Zooming out from the operations over code blocks raises the question in the context of fault-tolerant circuits. In classical settings, lower bounds on the overall circuit size were established. A series of works [Gal91], [RS91], showed that fault-tolerant circuits that compute Boolean functions that are s -sensitive, meaning that a change in one of s bits in the input leads to a different output, must exhibit at least $\Omega(s \log s)$ size. In particular, a fault-tolerant circuit that computes the n -bit **Xor** function must have $\Omega(n \log n)$ size.

Furthermore, [Rom06] exhibits a trade-off in a model in which the given input is already encoded. In that model, they provide a fault-tolerant circuit with a width overhead of the circuit being $\Theta\left(\frac{\log n}{\log \log n}\right)$, while the depth overhead is $\Theta(\log \log n)$. So, it's attempting to ask if for any w and d such that $w \cdot d = \log(n)$, a fault-tolerant circuit with w and d width and depth overhead can be realized:

Open-Problem 5. Consider a circuit over n classical (quantum) bits. What are the domains of depth d and width w for which the circuit can be fault-tolerant at the cost of w and d width and depth overheads? How does the answer change if we assume encoded input?

The questions above address the fault tolerance of general circuits, but focusing on shallow circuits also attracts special interest, particularly for near-term applications. Since today's quantum machines struggle to maintain quantum states for extended periods, researchers were motivated to define **NISQ**, which stands for Noisy Intermediate-Scale Quantum, referring to the current era of quantum computing characterized by quantum processors with a limited number of qubits and susceptibility to errors due to noise. Nevertheless, there are certain known problem candidates for demonstrating quantum advantage, such as factoring [Sho97] and Instantaneous Quantum Polynomial-time [BMS17], [Pal+24], which have been proven to be solvable by sampling from logarithmic-depth quantum circuits. We emphasize that in [Pal+24] they showed a realization that uses constant quantum depth circuits with the intermediation of a polynomial classical circuit in the middle. From a technical perspective, that means that to implement the protocol, one has to protect the quantum state for the time that the classical routine lasts. Hence, it is interesting to ask what both quantum and classical low-resource fault-tolerant realizations can be designed for those particular problems.

Open-Problem 6. Does sampling from **IQP** have a fault-tolerant realization using $\log n$ depth circuits, namely an $O(1)$ -depth overhead? Or at least, is it possible to postpone all the classical computation until after the qubits are measured? Are there any other candidates for demonstrating quantum advantage that can be realized using shallow circuits?

Another application that uses logarithmic depth is encoding. It was shown in [MN98] that stabilizer codes can be prepared at logarithmic depth, and not only that, but the preparation circuit is composed of only Hadamard and controlled-Pauli gates. In other words, the family of encoder circuits is much less rich than general circuits, and therefore, it is interesting to

ask about the synthesis of encoded codewords. By synthesis, we mean generating the encoded codeword itself and not a logical representation of it (not a concatenation with another code).

Open-Problem 7. Do encoders have a fault-tolerant realization with an $O(1)$ -depth overhead?

In addition to NISQ, another common characterization for limited quantum computation is computation without reset gates — namely, the gates which initialize qubits to the zero state $|0\rangle$. It was proved that in this model, when restricted to polynomial space, any computation that lasts longer than logarithmic depth results in noise [Aha+96]. Having a constant depth-overhead fault tolerance scheme would imply the feasibility of log depth computation in that model.

Open-Problem 8. Assuming there are $\Theta(\log(n))$ -depth circuits that can be fault-tolerized at the cost of $O(1)$ -depth overhead, could those constructions be generalized to hold in the non-reset gates regime?

Last but not least, we would like to connect fault-tolerance results to complexity theory in a broad manner. Historically, new inventions of error correction codes have stimulated advances in PCP theory and vice versa. For instance, the left-right Cayley complex [Din+22], [LZ22], [PK21] was used recently in [BMV24] to design a routing net that is robust to collapses, which in turn was used to construct a proof-checking scheme in a manner similar to the Polishchuk-Spielman approach [PS94]. Another recent result showed that having an $O(1)$ -depth overhead fault tolerance protocol implies that quantum PCP with logarithmic soundness could be achieved [ABN24]. Thus, we suggest the following vague question:

Open-Problem 9. Whether fault-tolerant construction can help to design a verification scheme? Does an analog to the robustness routing protocol exist for verifying quantum computations? What else can be borrowed from the fault-tolerant world for the use of quantum PCP?

This work addresses the above. We ask whether a magnitude depth overhead is an unavoidable price that one has to pay, if a Constant Depth Fault Tolerance Construction (CDFT) exists, and if so, how to construct it. In particular, whether an ideal $\mathbf{QNC}_1$, the class of problems that can be decided by logarithmic depth quantum circuits, can be computed in noisy- $\mathbf{QNC}_1$ circuits.

The proposal is organized as follows. Section 2 presents the notations, formal definitions, and states the open problems that will be studied through the research. Then, Section 3 describes strategies to prove CDFT. In particular, it lists primitives that can be used to achieve it and discusses how far we are from obtaining them. Having said that, Section 4 presents the first cues against the possibility of CDFT and provides the entry points to prove the impossibility claim. Finally, Section 5 discusses the applications and implications of either the correctness of CDFT or the impossibility of CDFT, from both theoretical and practical views.

2 Notations.

We use the standard notations commonly used in the literature. When not otherwise mentioned, we consider quantum states over qubits, each lying in a two-dimensional Hilbert space $\mathcal{H}_2$, and denote by $\mathcal{H}_{2^n}$ the Hilbert space of an n -qubit system. Pure quantum states and their dual presentations are denoted by $|\psi\rangle, \langle\psi|$, and in the matrix representation, we use $|\psi\rangle\langle\psi|$ to denote its density matrix. We will use ρ to denote a mixed state, whose density matrix is a trace one PSD matrix. We use $\mathcal{N} : L(\mathcal{H}) \rightarrow L(\mathcal{H})$ to denote a p -local stochastic noise channel, namely a channel in which for any subset S of the (qu)bits, the probability that all the qubits in S absorb noise is less than $p^{|S|}$. We recall that for a constant-depth circuit, when the fanout/in of its subgates is bounded, one can map the running of the circuits subjected to p -local stochastic noise to a running when the states are subjected only to p' -local stochastic noise before entering the circuit, and then the rest of the computation is done in an ideal environment [Got14], where p' is a function of p and constants. If the gate is also a measure, for example as a decoder, then the mapping induces also q -local stochastic noise on the measurements.

We think about computation subjected to noise as the running of a circuit, in which at any time, qubits might be 'flipped', or formally, with some constant probability, they are replaced with the fully mixed state. Since our computation might create correlations between the errors, we will assume nothing about the behavior of the errors except that big errors are unlikely. By doing that, the induction step doesn't have to guarantee the errors being uncorrelated.




Figure 1: Circuit subjected to noise.

We use Definition 2.1 to describe the running of a circuit subjected to noise. Section 2 illustrates a noisy circuit. In the figure, the channel $\mathcal{N}$ acts on each qubit separately, yet this is not the case, and we impose it in that way only to make a clear distinction between the original gates and the noise channels.

Definition 2.1. *p*-Noisy Circuit. Given a circuit C (regardless of the model), its *p*-noisy version $\tilde{C}$ is the circuit obtained by alternately taking layers from C and then passing each (qu)bit through a *p*-local stochastic channel.

Generally speaking, we say that a decision problem is solvable by a uniform family of circuits $\mathcal{C}$ if there is a polynomial $\text{poly} : \mathbb{R} \rightarrow \mathbb{R}$, such that for any large enough $n \in \mathbb{N}$, there exist $a, b \in (0, 1)$ at a distance of at least $b - a > 1/\text{poly}(n)$ and a polynomial Turing machine M such that for any given instance x with encoding length $|x| = n$, the running of M on x outputs $C_x \in \mathcal{C}$ that, when running over the zero word 0^* , induces on the first (qu)bit at least b probability to be at 1 if x is in the language and at most a to be at 1 otherwise. If a decision problem is solvable by a *p*-noisy version of $C \in \mathcal{C}$, we say that the problem is solvable by noisy- $\mathcal{C}$. We abuse the notation, and for complexity class Q , we define noisy- Q to be all the decision problems solvable by the noisy version of the circuit family that solves the problems in Q . For example, noisy-BQP is the class of all the decision problems solvable by noisy polynomial quantum circuits.

The first class we are interested in is Nick's Class, **NC** characterizing the boolean circuits at logarithmic depth. This class was proven by Pippenger to be equal to its noisy version, namely noisy-NC = NC [Pip85]. Formally defined as follows:

Definition 2.2 (NC - Nick's Class). NC_i is the class of decision problems solvable by a uniform family of Boolean circuits, with polynomial size, depth $O(\log^i(n))$, and fan-in 2.

Second, the analog class of **NC** is **QNC**, which characterizes logarithmic depth quantum circuits. In **QNC**, the circuits are also allowed to have any single qubit gate. While in the classical case the number of functions from $\{0, 1\}^2 \rightarrow \{0, 1\}$ is finite, in the quantum case we have an infinite number of single gates. That motivated us to define **QNC_G** - the circuits when the gate set is restricted to some finite, constant size group G . We emphasize that in **BQP** there is no point in restricting to such a family since any gate can be polynomially approximated at polylogarithmic depth, so in that case, the restriction does not change computational power and one can assume to be able to apply any single qubit gate. However, when considering shallow circuits at logarithmic depth, such assumptions don't hold anymore.

Definition 2.3 (QNC). The class of decision problems solvable by polynomial size, polylogarithmic-depth, and finite fan out/in quantum circuits with bounded probability of error. Similarly to NC_i , QNC_i is the class where the circuits have $\log^i(n)$ depth.

Definition 2.4 ($\mathbf{QNC}_G$). For a fixing finite fan in/out gateset G , the class with deciding circuits at polynomial size, composed only for gates in G and at depth at most polylogarithmic. And in similar to $\mathbf{QNC}_i$, $\mathbf{QNC}_{G,i}$ is the restriction to circuits with depth at most $\log^i(n)$.

Another setting which we find interesting is the equipping of classes with an unbounded fanout CNOT gate, a gate which acts as $|x\rangle \prod_i |y_i\rangle \rightarrow |x\rangle \prod_i |x \oplus y_i\rangle$. There are two main reasons we find those class worth considering. First, the unbounded fanout CNOT can be decomposed by chaining only two-qubit CNOTs, since for any CSS code, a CNOT can be implemented in a fault-tolerant manner almost for free. Second, there are candidates at $\mathbf{QNC}_{0,f}$ for proving quantum advantage [BMS17], [Pal+24].

Definition 2.5 ($\mathbf{QNC}_{0,f}$). Similarly to $\mathbf{QNC}_0$, the class of decision problems solvable by constant depth and bounded fan out/in quantum circuits equipped additionally with a 'quantum fanout' gate is available, which CNOTs a qubit into arbitrarily many target qubits in a single step.

Finally, the last setting we consider is the restriction of the classes when there is no access to fresh qubits, or equivalently, no reset gates are allowed. In this setting, any step of computation accumulates entropy, and an exponential trade-off relation between entropy and depth was proved.

Definition 2.6 ($\mathbf{QNC}_1$ without reset gates.). The class of decision problems solvable by polynomial size, logarithmic-depth, and finite fan out/in quantum circuits with bounded probability of error, without reset gates.

Those definitions lead us to ask our first open problem:

Open-Problem 10 (The Main Open Problem.).

$$\text{Does } \mathbf{QNC}_1 = \text{noisy-}\mathbf{QNC}_1?$$

Our second main problem investigates whether it matters which universal gateset is used for the simulation, or whether the answer to the previous question is affirmative when our computation is restricted to a finite gateset G' , given that the source was also restricted to using local computation in a finite set. That is, we ask:

Open-Problem 11 (Constant Depth Overhead on G' Restricted Machine.). Does there exist a finite universal set G' such that for any finite two-qubit gateset G it holds that:

$$\mathbf{QNC}_{G,1} = \text{noisy-}\mathbf{QNC}_{G',1}?$$

In this context, we mention the work of [Kim25], which shows that using a catalyst state¹, no bounded fan-out computation can simulate any single qubit gate with a constant T depth. Namely, in our words, they prove that there exists a finite gate set G' such that:

$$\mathbf{QNC}_{f,1} = \mathbf{QNC}_{f,G',1} \text{ using catalyst state.}$$

We hope that our work will also lead to an understanding of the importance, or the non-importance, of the basic components being used.

3 Strategies to get CDFT.

Here we summarize and present the main gadgets that were invented in past fault tolerance constructions [AB99], [Got14], and [Gro19]. These gadgets will allow us to simplify the model we work with, presenting an almost proof for CDFT, and focusing our question about complexity into a question about the existence of particular quantum error correction codes. The main gadgets are fault-tolerant State Preparation (SP) and Memory error correction codes (ME). The first presents how, while using the original fault tolerance construction based on concatenation [AB99], one can initialize any quantum state subjected to local stochastic noise at no additional cost to the fault tolerance construction scheme being used. Since encoding is a Clifford operation, and any m -bit Clifford can be implemented in $O(\log m)$ time, then when $m = \Theta(\log^\alpha n)$ the

¹In the catalytic computation model, one has access to a complicated resource state $|\phi\rangle$, yet he has to return/keep it at the end of the running.

fault-tolerant version of the 'encoder' has $O(\log n)$ depth. So using SP, one can initialize m -length blocks encoded in any error correction code at noisy- $\mathbf{QNC}_1$.

The second gadget is Memory, a particular type of code which allows restraining the error rate by exhibiting a constant depth procedure that, when promising that the error rate is below a threshold, suppresses the error by at least a constant factor. Using memory, we will be able to promise with high probability that the error rate is lower than some fraction.

3.1 State Preparation.




Figure 2: Preparing a quantum states via the concatenation fault tolerance.

The following definition extends the idea of solving decision problems with computation subjected to noise to preparing quantum states with fault tolerance when subjected to noise.

Definition 3.1 (State Preparation.). Let $\mathcal{C}$ be a set of circuits. We say that $S : \mathcal{C} \rightarrow p\text{-noisy circuits}$ is an $[\alpha, (p \rightarrow q)]$ -State-Preparation scheme for $\mathcal{C}$ if for any $C \in \mathcal{C}$, we have that $S(C) = \tilde{C}$ such that:

1. $\text{Depth}(\tilde{C}) \leq \alpha \text{Depth}(C)$.
2. $\text{Width}(\tilde{C}) \leq \alpha \text{Width}(C)$.
3. The state prepared by $\tilde{C}$, namely $\tilde{C}|0\rangle$ is the state prepared by C when subjected to q -local stochastic noise.

Based on the fault-tolerance construction in [AB99], one can obtain a $[\text{polylog}(n), (p \rightarrow q)]$ -SP, where n is the number of the source's circuit qubits, which will next be used as a block length of a desired code. Here we present an informal description of it and refer to [Gro19] for more details.

Figure 2 illustrates the preparation scheme. Denote by E the encoder of the desired code to prepare, and by E_{con}^{-1} the decoder of the single-level concatenation code. First, we apply a fault-tolerant version of the encoder E , using the k -level concatenated code; that stage is represented as $\Phi^k(E)$. Then we decode the concatenated code from top to bottom; namely, in the j th stage, we apply $\Phi^{j-1}(E_{\text{con}}^{-1})$.

Since the probability of a logic error at the k -level concatenation code is bounded by $(cp)^{2^{k-1}}$, we have by the union bound that the probability that the i th bit, in the target state, will absorb an error at the end is bounded by:

$$(cp)^{2^{k-1}} + (cp)^{2^{k-2}} + \dots (cp)^{2^{k-3}} + \dots + cp \leq c_2 p$$

So we prepared the state subjected to local noise (depolarizing noise) at rate $q = c_2 p$. The depth of the circuit is at most two times the depth of $\Phi^k(E)$ so α equals the overhead of the fault tolerance scheme namely $\alpha = \text{polylog}(n)$.

As mentioned before, that gadget allows us to assume the initialization of encoded codewords at block length $|B|$ such that $|B| \cdot \text{polylog}(|B|) = O(\log n)$ while remaining in $\mathbf{QNC}_1$, and to focus on finding suitable codes that enable computation with constant depth overhead.

3.2 Memory.

Informally, a memory code is a code that stores a logical state for a long time while keeping the noise below a certain amount. We define it formally by saying that the code is equipped with a constant depth decoder that reduces an error affecting at most a β portion of the qubits into an error affecting at most a γ portion of the qubits.

Definition 3.2 (Ideal (β, γ) -Memory). We say that a (quantum) error correction code C is an Ideal (β, γ) -Memory code if there is a constant depth procedure $\mathbf{D}$ such that for any I of size $|I| \geq (1 - \beta)n$ and a mixed states σ and ρ such σ distributed over the C 's codewords $\sigma \in C$ and $\mathbf{Tr}_I(\rho) = \mathbf{Tr}_I(\sigma)$, we have that there is subset of qubits J at size at least $(1 - \gamma)n$:

$$\mathbf{Tr}_J \mathbf{D}(\rho) = \mathbf{Tr}_J(\sigma)$$

We would like to extend the memory gadgets to work with high probability, which motivates us to define the following:

Definition 3.3 ($(\mathcal{P}_1, \mathcal{P}_2)$ - thermal couple.). Let $\mathcal{P}_1, \mathcal{P}_2$ be sets of density matrices induced over the n -qubit Hilbert space, and let $\mathcal{N}$ be a p -stochastic local noise channel for some constant $p \in (0, 1)$. We say that the couple $(\mathcal{P}_1, \mathcal{P}_2)$ is a thermal couple if for any $\rho \in \mathcal{P}_2$, we have $\mathcal{N}(\rho) \in \mathcal{P}_1$ with high probability.

Definition 3.4 ($(\mathcal{P}_1, \mathcal{P}_2)$ -Memory). Consider a $(\mathcal{P}_1, \mathcal{P}_2)$ - thermal couple, We say that C is a $(\mathcal{P}_1, \mathcal{P}_2)$ -Memory if there is a constant depth procedure $\mathbf{D}$, such that for any $\rho \in \mathcal{P}_1$ we have $\mathbf{D}(\rho) \in \mathcal{P}_2$, with high probability.

For example, consider a code C with a Δ -regular Tanner graph. Let $\mathcal{P}_1$ be all the noisy states derived from codewords in C such that the syndrome graph induced by them can be decomposed into disjoint $\Delta/2$ -connected components $A_1, A_2, \dots, A_l$, each of size at most $|A_i| < \beta\sqrt{n}$, and the $\Delta/2$ -distance between any two of them A_i, A_j , namely the number of edges needed to add to merge them into one single $\Delta/2$ -connected component, is at least $\theta \min(|A_i|, |A_j|)$. We call such decomposition characterization $(\beta\sqrt{n}, \theta)$ error decomposition.

Now let $\mathcal{P}_2$ be all the deviations from C , such that the syndrome graph induced by them can be decomposed into $(\gamma\sqrt{n}, \frac{\beta}{\gamma}\theta)$ error decomposition. The couple $(\mathcal{P}_1, \mathcal{P}_2)$ is thermal couple, And combining the quantum expander code and the parallel small set-flip decoder [Gro19] they defines a $(\mathcal{P}_1, \mathcal{P}_2)$ -memory.

3.3 Gate Teleportation.

Gate teleportation is a method to 'encode' operations by quantum states. At a high level, given a precomputed state, it allows one to apply an operation (gate) using (probably) simpler gates. The precomputed states are called **Magic States**.

3.3.1 Leading Example: T -Teleportation.

Recall that the Clifford² + T is a universal quantum gate set. The Clifford group alone is considered, from the computer science point of view, a simple/weak computational class since it can be classically simulated³. Yet, we will see that given access to the magic $|T\rangle = T|+\rangle$, one can simulate the T gate using only Clifford gates and measurements.

²Generated by H, S and CX

³And conjectured to be strictly weaker than $\mathbf{P}$




Figure 3: Usage of Ideal (β, γ) -Memory to obtain fault tolerance computation.

In Figure 4, we have the T -teleportation gadget. The state progresses up to the measurement as follows:

$$\begin{aligned}
 \left(\sum_x \alpha_x |x\rangle \right) \otimes \frac{1}{\sqrt{2}} (|0\rangle + e^{i\frac{\pi}{4}} |1\rangle) &\xrightarrow{\text{CX}} \sum_{x,y} \frac{1}{\sqrt{2}} \alpha_x |x\rangle |x \oplus y\rangle e^{i\frac{\pi}{4}y} \\
 &\mapsto \begin{cases} \sum_x \alpha_x |x\rangle e^{i\frac{\pi}{4}x} = T|\psi\rangle & \text{measured 0} \\ \sum_x \alpha_x |x\rangle e^{i\frac{\pi}{4}\bar{x}} & \text{measured 1} \end{cases} \\
 &\xrightarrow{\text{CS}} \begin{cases} T|\psi\rangle \\ \sum_x \alpha_x |x\rangle e^{i(\frac{\pi}{4}\bar{x} + \frac{\pi}{2}x)} = \sum_x \alpha_x |x\rangle e^{i\frac{\pi}{4}} e^{i(\frac{\pi}{4}\bar{x} + \frac{\pi}{4}x)} \end{cases} \\
 &= \begin{cases} T|\psi\rangle \\ e^{i\frac{\pi}{4}} \sum_x \alpha_x |x\rangle e^{i\frac{\pi}{4}} = e^{i\frac{\pi}{4}} T|\psi\rangle \end{cases}
 \end{aligned}$$

Similarly, any two-qubit gate U can be encoded using a proper magic state, and the gate teleportation will be composed by entangling using CNOT, then measurement, and eventually, upon the measurement result P , applying a correction $UPU^\dagger$. We refer to [Got14] and [Gro19] for further reading.

Open-Problem 12. Does there exist a Memory code for which one can implement gate teleportation to a universal gate set in a local manner?



Figure 4: Simulating the T -gate, using the $|T\rangle$ magic state.

3.4 An almost $\text{QNC}_1 = \text{noisy-QNC}_1$.

We provide beneath without a formal proof a fault construction that gives an almost CDFT.

1. We start by initializing many encoded magic states and encoded zeros via the state preparation scheme. Since the block is of length $\log^\alpha(n)$, the depth required for that stage is $\log \log(n)$.
2. In each even step, we apply $\mathbf{D}$ to keep the error rate low. It fails with probability at most $\Theta(\frac{1}{n^k})$, so by the union bound the probability that $\mathbf{D}$ had at least a single failure is bounded by $\Theta(\frac{1}{n^{k'}})$.
3. We compute the gates over the odd iterations. Each gate is replaced by two applications of gate teleportation, exploiting the magic states. Each application of Clifford, in the second and the first level of the Clifford hierarchy, is followed by $\log(\log(n))$ depth computation for deciding which operation should be applied next.

So overall, the depth overhead we get is $\log \log n$, where the bottleneck is the time required to decide on the final gate to apply given the measurement results in the gate-teleportation gadget. That raises the question of whether there exist memory codes for which one can perform the correction search in $O(1)$ depth. [Gu+24]

4 Cues against CDFT.

So far, we discussed what might give CDFT. In this section, we briefly review results concerning the hardness of implementing logical operators fault-tolerantly at constant depth. We first present a property of stabilizer codes called disjointness [JKY18] [BK21], which quantifies how the structure of the code is far from being just a union of disjoint subsystems. In [JKY18], they proved a relation between the disjointness value and the complexities of the logical operators that can be computed either transversally or by shallow depth circuits.

Then, we present a connection between the ability to compute Toffoli transversely and computing homomorphically [NS17]. The connection was shown to hold for a relatively wide family of codes, yet it is not generally correct for all codes. In particular, it doesn't hold for the Shor code.

4.1 The disjointness of stabilizer codes.

Definition 4.1. Let P be a logical Pauli in a stabilizer code C . Denote by $\Delta_c(P)$ the c -disjointness of P , which is defined to be the size of the maximal subset of P -representations such that each qubit touches at most c of them, divided by c .

The c -disjointness of C is defined to be the minimum of c -disjointness, where the minimization is taken over all the logical Paulis of C . [JKY18] proves the following: let $d_\uparrow$ and $d_\downarrow$ be the maximal and minimal weights of a codeword in C . Then all the logical operators in C are in the

$$1 + \lceil \log_\Delta \frac{d_\uparrow}{d_\downarrow} \rceil \text{ 'th Clifford hierarchy}$$

Hence, we interest code with a finite disjointness.

1. **Disjointness of classical repetition code.** = 1

The X_1 generator is $X^{\otimes n}$, the Z_1 generator representations are $\{Z^i \otimes I^{\otimes n/i} : i \in [n]\}$ and for Y_1 are $\{Y^i \otimes X^{\otimes n/i} : i \in [n]\}$. Thus, $\Delta_c(X_1) = \frac{1}{c}$ for any c and $\Delta_c = \frac{1}{c} \Rightarrow \Delta = 1$.

2. **Disjointness of 2D Toric code.** $\geq \frac{\sqrt{n}}{2}$.

First, notice that any two representations of Y_1 intersect in at least two qubits (four orbits, two horizontally and two vertically). Thus, $\Delta_1(Y_1) = 1$. In addition, since one can take disjoint columns as X_1 representations and disjoint rows as Z_1 representations, we have that $\Delta_1(X_1) = \Delta_1(Z_1)$ is at least $\sqrt{n}$. Similarly, we get the same for Y_2, X_2, Z_2 , and therefore, $\Delta_1 = \min \Delta_1 = 1$.

Yet, for Δ_2 , we have from the same arguments as presented previously that $\Delta_2(X_1) = \Delta_2(Z_1) \geq \frac{1}{2}\sqrt{n}$. And also $\Delta_2(Y_1) \geq \frac{1}{2}\sqrt{n}$.

Open-Problem 13. Does there exist a memory code that has asymptotically approaches $\rightarrow 1$ disjointness?

4.2 Fault Tolerance and Homomorphic Computation.

While the disjointness property is a property of a code and therefore can be thought of as a computational restriction, one can also ask if there are informational obstacles. In [NS17], the authors succeeded in linking a transversal Toffoli to extremely low overhead homomorphic computation, what in turn contradicts a known information theoretic bounds.

Definition 4.2. A quantum code is an r -fold quantum code, if its codewords can be written as product over r subsystems:

$$|i\rangle_L = \otimes_j^r |\psi_{i,j}\rangle$$

When we think of the states in each subsystem as codewords of subcodes, note that any code is at least a 1-fold code. If each of the subcodes has distance 1, then we call the code a maximally redundant code. An example of a maximally redundant code is the Shor code.

Figure 5 outlines the encoding in the suggested homomorphic scheme. The input is encoded via the r -fold code (in the figure $r = 1$), and then we think of the qubits as arranged in a matrix, each row is matched to a logical qubit, and the i th row consists of all of the i th physical qubits of each logical qubit. Then, any i th row of qubits, except the last one, is transplanted in the place of a random column of an $n \times n$ -qubit mixed state. Those qubits are sent to the prover. (For $r > 1$, we spare a qubit from each subsystem.)

Observe that any transversal gate in the original code can be implemented by transversal application over each of the $n \times n$ separation bulk. So having transversal Toffoli enables the prover to simulate any classical computation while keeping the mixed structure.

It was shown in [NS17] that any binary code which is not a maximally redundant code cannot offer transversal logical Toffoli; otherwise, it implies the existence of a relatively low-resource consuming homomorphic protocol which violates Nayak's bound [Nay99].

Open-Problem 14. Does computing Toffoli at shallow depth, similar to the transversal case, imply homomorphic computation at a cost contradicting Nayak's bound? And in a more general context, when Information Theory imposes restrictions on the depth overhead of fault tolerance?

5 Summery and Applications.

Up to this point, we have tried to gets hints about whether it is likely to have a CDFT. Now we're prompted to ask: Suppose that we have an answer about the hardness of computing in the presence of noise compared to computing in an ideal environment, what can be learned beyond the context of fault tolerance? We divide our discussion into the YES scenario, in which we have CDFT, and the NO scenario, in which we don't.

5.1 The NO Scenario.

Since we know that classical computation in the presence of noise can be computed at constant overhead in depth and in particular $\text{Noise-NC}_1 = \text{NC}_1$, it's tempting to conclude that this scenario implies $\text{NC}_1 \neq \text{QNC}_1$. Yet, taking a second look points out that such a move is not so direct, and that is because of two main reasons. First, the impossibility of CDFT doesn't contradict by itself a scenario where QNC_1 is degenerated, for example, if $\text{QNC}_1 = \text{QNC}_0$. Then one can close QNC_1 to noise by mapping circuits to their constant depth equivalence first




Figure 5: Skecth of the encryption scheme, taken form [NS17]

and then applying a fault tolerance scheme; the final circuit would be a fault-tolerant circuit at logarithmic depth. Second, when saying that we know how to compute classily in the presence of noise, we mean in the presence of classical noise.

Open-Problem 15. Whether and when, separation between noise classes implies separation between their ideal origins, In particular, on what conditions:

$$\mathbf{QNC}_1 \neq \text{Noisy-}\mathbf{QNC}_1 \Rightarrow \mathbf{QNC}_1 \neq \mathbf{NC}_1$$

5.2 The YES Scenario.

Having a CDFT is the first stage in realizing a quantum advantage when restricted to limited (quantum) computational power. Especially, it's required to enable computation in logarithmic depth in the setting where reset gates are not allowed. This is due to the fact that there is a trade-off between the memory of the system and the entropy accumulated, which grows exponentially with the depth [AB99]. We finish the proposal by presenting a question of engineering. We would like to have an end-to-end realization of computation that might demonstrate quantum advantage in the limited setting without reset gates.

Open-Problem 16. Quantum Advantage Without Reset Gates. Does there exist problems believed to be hard classically but easy quantumly, which can be computed fault-tolerantly, without the use of reset gates? In particular, Is it possible to factor big integers or sampling from IQP without reset gates? What is the computational power of an ideally polynomial machine with an access to noisy- $\mathbf{QNC}_1$ machines without reset gates?

References

- [Neu56] J. von Neumann. “Probabilistic Logics and the Synthesis of Reliable Organisms From Unreliable Components”. In: *Automata Studies*. Ed. by C. E. Shannon and J. McCarthy. Princeton: Princeton University Press, 1956, pp. 43–98. ISBN: 9781400882618. DOI: [doi : 10.1515/9781400882618-003](https://doi.org/10.1515/9781400882618-003). URL: <https://doi.org/10.1515/9781400882618-003>.

- [Pip85] Nicholas Pippenger. “On networks of noisy gates”. In: *26th Annual Symposium on Foundations of Computer Science (sfcs 1985)*. 1985, pp. 30–38. DOI: [10.1109/SFCS.1985.41](https://doi.org/10.1109/SFCS.1985.41).
- [Gal91] A. Gal. “Lower bounds for the complexity of reliable Boolean circuits with noisy gates”. In: *[1991] Proceedings 32nd Annual Symposium of Foundations of Computer Science*. 1991, pp. 594–601. DOI: [10.1109/SFCS.1991.185424](https://doi.org/10.1109/SFCS.1991.185424).
- [RS91] R. Reischuk and B. Schmeltz. “Reliable computation with noisy circuits and decision trees-a general $n \log n$ lower bound”. In: *[1991] Proceedings 32nd Annual Symposium of Foundations of Computer Science*. 1991, pp. 602–611. DOI: [10.1109/SFCS.1991.185425](https://doi.org/10.1109/SFCS.1991.185425).
- [PS94] Alexander Polishchuk and Daniel A. Spielman. “Nearly-linear size holographic proofs”. In: *Proceedings of the Twenty-Sixth Annual ACM Symposium on Theory of Computing*. STOC ’94. Montreal, Quebec, Canada: Association for Computing Machinery, 1994, pp. 194–203. ISBN: 0897916638. DOI: [10.1145/195058.195132](https://doi.org/10.1145/195058.195132). URL: <https://doi.org/10.1145/195058.195132>.
- [Aha+96] D. Aharonov et al. *Limitations of Noisy Reversible Computation*. 1996. arXiv: [quant-ph/9611028](https://arxiv.org/abs/quant-ph/9611028) [quant-ph]. URL: <https://arxiv.org/abs/quant-ph/9611028>.
- [Gro96] Lov K. Grover. *A fast quantum mechanical algorithm for database search*. 1996. arXiv: [quant-ph/9605043](https://arxiv.org/abs/quant-ph/9605043) [quant-ph].
- [Sho97] Peter W. Shor. “Polynomial-Time Algorithms for Prime Factorization and Discrete Logarithms on a Quantum Computer”. In: *SIAM Journal on Computing* 26.5 (Oct. 1997), pp. 1484–1509. DOI: [10.1137/s0097539795293172](https://doi.org/10.1137/s0097539795293172). URL: <https://doi.org/10.1137/s0097539795293172>.
- [MN98] Cristopher Moore and Martin Nilsson. *Parallel Quantum Computation and Quantum Codes*. 1998. arXiv: [quant-ph/9808027](https://arxiv.org/abs/quant-ph/9808027) [quant-ph].
- [AB99] Dorit Aharonov and Michael Ben-Or. *Fault-Tolerant Quantum Computation With Constant Error Rate*. 1999. arXiv: [quant-ph/9906129](https://arxiv.org/abs/quant-ph/9906129) [quant-ph].
- [Nay99] Ashwin Nayak. *Optimal lower bounds for quantum automata and random access codes*. 1999. arXiv: [quant-ph/9904093](https://arxiv.org/abs/quant-ph/9904093) [quant-ph]. URL: <https://arxiv.org/abs/quant-ph/9904093>.
- [BM06] H. Bombin and M. A. Martin-Delgado. “Topological Quantum Distillation”. In: *Phys. Rev. Lett.* 97 (18 Oct. 2006), p. 180501. DOI: [10.1103/PhysRevLett.97.180501](https://doi.org/10.1103/PhysRevLett.97.180501). URL: <https://link.aps.org/doi/10.1103/PhysRevLett.97.180501>.
- [Rom06] Andrei Romashchenko. “Reliable computations based on locally decodable codes”. In: *Proceedings of the 23rd Annual Conference on Theoretical Aspects of Computer Science*. STACS’06. Marseille, France: Springer-Verlag, 2006, pp. 537–548. ISBN: 3540323015. DOI: [10.1007/11672142_44](https://doi.org/10.1007/11672142_44). URL: https://doi.org/10.1007/11672142_44.
- [Bom10] H. Bombin. “Topological subsystem codes”. In: *Phys. Rev. A* 81 (3 Mar. 2010), p. 032301. DOI: [10.1103/PhysRevA.81.032301](https://doi.org/10.1103/PhysRevA.81.032301). URL: <https://link.aps.org/doi/10.1103/PhysRevA.81.032301>.
- [Got14] Daniel Gottesman. *Fault-Tolerant Quantum Computation with Constant Overhead*. 2014. arXiv: [1310.2984](https://arxiv.org/abs/1310.2984) [quant-ph].
- [Bom15] Héctor Bombín. “Gauge color codes: optimal transversal gates and gauge fixing in topological stabilizer codes”. In: *New Journal of Physics* 17.8 (Aug. 2015), p. 083002. DOI: [10.1088/1367-2630/17/8/083002](https://doi.org/10.1088/1367-2630/17/8/083002). URL: <https://doi.org/10.1088/1367-2630/17/8/083002>.

- [BMS17] Michael J. Bremner, Ashley Montanaro, and Dan J. Shepherd. “Achieving quantum supremacy with sparse and noisy commuting quantum computations”. In: *Quantum* 1 (Apr. 2017), p. 8. ISSN: 2521-327X. DOI: [10.22331/q-2017-04-25-8](https://doi.org/10.22331/q-2017-04-25-8). URL: <https://doi.org/10.22331/q-2017-04-25-8>.
- [NS17] Michael Newman and Yaoyun Shi. *Limitations on Transversal Computation through Quantum Homomorphic Encryption*. 2017. arXiv: [1704.07798](https://arxiv.org/abs/1704.07798) [quant-ph]. URL: <https://arxiv.org/abs/1704.07798>.
- [JKY18] Tomas Jochym-O’Connor, Aleksander Kubica, and Theodore J. Yoder. “Disjointness of Stabilizer Codes and Limitations on Fault-Tolerant Logical Gates”. In: *Physical Review X* 8.2 (May 2018). ISSN: 2160-3308. DOI: [10.1103/PhysRevX.8.021047](https://doi.org/10.1103/PhysRevX.8.021047). URL: <http://dx.doi.org/10.1103/PhysRevX.8.021047>.
- [Gro19] Antoine Grospellier. “Constant time decoding of quantum expander codes and application to fault-tolerant quantum computation”. Theses. Sorbonne Université, Nov. 2019. URL: <https://theses.hal.science/tel-03364419>.
- [BK21] John Bostanci and Aleksander Kubica. *Finding the disjointness of stabilizer codes is NP-complete*. 2021. arXiv: [2108.04738](https://arxiv.org/abs/2108.04738) [quant-ph]. URL: <https://arxiv.org/abs/2108.04738>.
- [PK21] Pavel Panteleev and Gleb Kalachev. *Asymptotically Good Quantum and Locally Testable Classical LDPC Codes*. 2021. DOI: [10.48550/ARXIV.2111.03654](https://arxiv.org/abs/2111.03654). URL: <https://arxiv.org/abs/2111.03654>.
- [Din+22] Irit Dinur et al. *Good Locally Testable Codes*. 2022. DOI: [10.48550/ARXIV.2207.11929](https://arxiv.org/abs/2207.11929). URL: <https://arxiv.org/abs/2207.11929>.
- [LZ22] Anthony Leverrier and Gilles Zémor. *Quantum Tanner codes*. 2022. arXiv: [2202.13641](https://arxiv.org/abs/2202.13641) [quant-ph].
- [ABN24] Anurag Anshu, Nikolas P. Breuckmann, and Quynh T. Nguyen. “Circuit-to-Hamiltonian from Tensor Networks and Fault Tolerance”. In: *Proceedings of the 56th Annual ACM Symposium on Theory of Computing*. STOC ’24. ACM, June 2024, pp. 585–595. DOI: [10.1145/3618260.3649690](https://doi.org/10.1145/3618260.3649690). URL: <http://dx.doi.org/10.1145/3618260.3649690>.
- [BMV24] Mitali Bafna, Dor Minzer, and Nikhil Vyas. *Quasi-Linear Size PCPs with Small Soundness from HDX*. 2024. arXiv: [2407.12762](https://arxiv.org/abs/2407.12762) [cs.CC]. URL: <https://arxiv.org/abs/2407.12762>.
- [Gu+24] Shouzen Gu et al. “Single-Shot Decoding of Good Quantum LDPC Codes”. In: *Communications in Mathematical Physics* 405.3 (Mar. 2024). ISSN: 1432-0916. DOI: [10.1007/s00220-024-04951-6](https://doi.org/10.1007/s00220-024-04951-6). URL: <http://dx.doi.org/10.1007/s00220-024-04951-6>.
- [Ngu24] Quynh T. Nguyen. *Good binary quantum codes with transversal CCZ gate*. 2024. arXiv: [2408.10140](https://arxiv.org/abs/2408.10140) [quant-ph]. URL: <https://arxiv.org/abs/2408.10140>.
- [NP24] Quynh T. Nguyen and Christopher A. Pattison. “Quantum Fault Tolerance with Constant-Space and Logarithmic-Time Overheads”. In: *Proceedings of the 57th Annual ACM Symposium on Theory of Computing* (2024). URL: <https://api.semanticscholar.org/CorpusID:273850180>.
- [Pal+24] Louis Paletta et al. “Robust sparse IQP sampling in constant depth”. In: *Quantum* 8 (May 2024), p. 1337. ISSN: 2521-327X. DOI: [10.22331/q-2024-05-06-1337](https://doi.org/10.22331/q-2024-05-06-1337). URL: <https://doi.org/10.22331/q-2024-05-06-1337>.

- [TKY24] Shiro Tamiya, Masato Koashi, and Hayata Yamasaki. *Polylog-time- and constant-space-overhead fault-tolerant quantum computation with quantum low-density parity-check codes*. 2024. arXiv: [2411.03683](https://arxiv.org/abs/2411.03683) [quant-ph]. URL: <https://arxiv.org/abs/2411.03683>.
- [Kim25] Isaac H. Kim. *Catalytic z -rotations in constant T -depth*. 2025. arXiv: [2506.15147](https://arxiv.org/abs/2506.15147) [quant-ph]. URL: <https://arxiv.org/abs/2506.15147>.
- [Li+25] Yiming Li et al. *Poincaré Duality and Multiplicative Structures on Quantum Codes*. 2025. arXiv: [2512.21922](https://arxiv.org/abs/2512.21922) [quant-ph]. URL: <https://arxiv.org/abs/2512.21922>.