

Quantum Fault Tolerance Meets Toom's Contours

Michael Ben-Or David Ponarovsky

April 19, 2026

1 Computation Model

Informally, a quantum circuit is a placement of a collection of quantum gates, taken from a finite set, in different space-time locations. Each space-time location, associated with a gate, encodes the time of the application and the qubits in the support of the gate. Formally

Separate between an element gate $g \in \mathcal{G}$ and a gate, which also has a space-time location.

Definition 1.1 (Quantum Circuit). A space-time location l is a tuple that encodes in its first coordinate time, and in its second coordinate a subset of integers referring to a support of (q)bits. For a collection of quantum gates $\mathcal{G} = \{g: L(\mathcal{H}_2^{\otimes \Delta}) \rightarrow L(\mathcal{H}_2^{\otimes \Delta})\}$, and integers $w, d \in \mathbb{N}$ a quantum circuit C , with depth d and width w , is a collection of tuples $\{u_i = (g_i, l_i)\}$, where u_i are the gates of C and each u_i is composed of a gate $g_i \in \mathcal{G}$ and a space-time location $l_i \in \mathbb{Z}_d \times \mathbb{Z}_w^\Delta$. The gates of C have to satisfy the constraint that for every two gates with the same time coordinate, there cannot be a non-empty intersection in their space coordinate, namely for $u_i = (g_i, l_i), u_j = (g_j, l_j) \in C$, the equality $l_{i,1} = l_{j,1}$ implies $l_{i,2} \cap l_{j,2} = \emptyset$. We define the t -cut of C to be $C|_t := \{u_i = (g_i, l_i): u_i \in C \text{ and } l_{i,1} = t\}$.

To define the running of a quantum circuit C on a given (mixed) quantum state, we will need to have the notion of the acyclic directed graph associated with C .

Definition 1.2 (Associated Computation DAG). Let $C = \{u_i\}$ be a quantum circuit with depth d and width w . We define the associated computation DAG of C , denoted by π_C , to be the acyclic directed graph $\pi_C = (\mathcal{U}, E)$ as follows:

1. The vertex set $\mathcal{U}$ is the gate set of C , namely $\mathcal{U} = \{u_i\}$.
2. For $u_i = (g_i, l_i), u_j = (g_j, l_j)$, There is an edge $\{u_i, u_j\} \in E$ if and only if:

$$j \in \arg \min_j \{l_{j,1} : l_{j,1} > l_{i,1} \text{ and } l_{j,2} \cap l_{i,2} \neq \emptyset\}$$

Note that there might be multiple indices that get the minimum, so the out degree might be greater than one.

In addition, suppose that $J = \{j_1, j_2, \dots, j_k\} \subset [|C|]$ is an order of the indices of the gates in C according to the topological order induced by π_C . Then, we say that J is an order of indices that agrees with π_C and define the series of circuit $C_J = \{C_{J,i}\}$ as follows:

1. The first element: $C_{J,1} = \{u_{j_1}\}$
2. Then, $C_{J,i+1} = C_{J,i} \cup \{u_{j_i}\}$. We name $C_{J,i}$ the partial computation circuit until step i .

Definition 1.3. Let ρ be a density matrix over w qubits, and let $C = \{u_i\}$ be a quantum circuit with depth d and width w . For any density matrix σ , quantum gate $g \in \mathcal{G}$, and location l , the application of the gate-location tuple (g, l) on σ , denoted by $(g, l) \circ \sigma$, is the application of g on σ where wires are ordered such that the first qubit in the input to g is $l_{2,1}$, the second is $l_{2,2}$, and so on. The result of the application of C on ρ , denoted by $C \circ \rho$, is given by iterative applications of the gates $\{u_i\}$ on ρ , according to a topological order induced by π_C .

We say that $\rho_1, \rho_2, \dots, \rho_k$ is a computation prefix if $\rho_1 = \rho$ and $\rho_{i+1} = u'_i \circ \rho_i$, where $\{u'_i\}$ is a prefix of a topological ordering of $\{u_i\}$. If $\{u'_i\}$ contains all the gates in $\{u_i\}$, then we call $\rho_1, \rho_2, \dots, \rho_k$ a running.

Definition 1.4 (C Subjected to $\mathcal{E}$). Let $C = \{u_i\}$ be a quantum circuit with depth d and width w . For a set of fault locations $\mathcal{E} \subset [d] \times [w]$, we define the quantum circuit C subjected to $\mathcal{E}$, denoted by $C[\mathcal{E}] = \{u'_i\}$, to be the quantum circuit that is the result of the following map:

$$u_i = (g_i, (l_{i,1}, l_{i,2})) \mapsto \begin{cases} (g_i, (2l_{i,1}, l_{i,2})) & u_i \in C \\ (g_i, (2l_{i,1}-1, l_{i,2})) & u_i \in \mathcal{E} \end{cases}$$

We will denote the associated computation DAG of C affected by $\mathcal{E}$ as $\pi[C, \mathcal{E}]$.

Definition 1.5 (Faults Propagation to a Step τ). For a quantum circuit $C = \{u_i\}$, with depth d , an order $J = \{j_1, j_2, \dots, j_k\} \subset [|C|]$ that agrees with π_C , and gate u_i in C , a propagation of a gate $u_i \in C$ to step τ is the quantum operator $X: L(\mathcal{H}_2^w) \rightarrow L(\mathcal{H}_2^w)$ obtained by the follow process:

1. First, check if i precedes τ in J . If not, then return $X = I$. Otherwise, denote $j_l = i$, and look for an operator X_1 such that $u_{j_l} u_{j_{l+1}} = u_{j_{l+1}} X_1$.
2. Then, for $k \leq \tau - l$, look for an operator $X_k: L(\mathcal{H}_2^w) \rightarrow L(\mathcal{H}_2^w)$, such that $X_{k-1} u_{j_{l+1}} = u_{j_{l+1}} X_k$.
3. At the final stage of the process, namely where $k = \tau - l$, we define $X := X_k$ to be the propagation of u_j to step τ .

For a quantum circuit C , a set of faults $\mathcal{E} = \{e_i\}$, an order $J \subset [|C[\mathcal{E}]]$ that agrees with $\pi_{C[\mathcal{E}]}$, and a step $\tau \in J$, denote by $X_{e_i}^\tau$ the propagation of $e_i \in \mathcal{E}$ in $C[\mathcal{E}]$ to step τ . Let $j'_1, j'_2, \dots, j'_l$ be the indices of the faults in $\mathcal{E}$ such that their corresponding

positions in J precede τ , ordered according to the reverse topological order induced by $\pi_{\mathcal{E}}$. The propagated error to step τ is defined by

$$X^\tau := \prod_i X_{e_{j'_i}^\tau}$$

Definition 1.6 (Deviation). For a quantum circuit C , a set of faults $\mathcal{E}$, and step τ , let X^τ be the propagated error at step τ . We define the deviation of $C[\mathcal{E}]$ from C at step τ by the set of indices on which X^τ acts non-trivially.

Definition 1.7. Using the same notations as in Definition 1.6, for a set of unitary operators $\mathcal{S} = \{s: \mathcal{H}_2^w \rightarrow \mathcal{H}_2^w\}$, we define the propagated error up to stabilizers in $\mathcal{S}$ as $X^\tau[S] := \min_{s \in \mathcal{S}} \{w(sX)\}$. Then, we define the deviation of $C[\mathcal{E}]$ from C at step τ up to stabilizers in $\mathcal{S}$ to be the subset of coordinates on which $X^\tau[S]$ acts non-trivially.

Definition 1.8 (Generalized Tanner Graph). For registers a and b , their generalized Tanner graph is their 'union' $\mathcal{T}_a \cup \mathcal{T}_b$. This allows us to define the Tanner graph of a quantum circuit C , at step τ , by stacking together Tanner graphs. This also allows us to define the Tanner graph if a register. [rewrite. add definition for a register \$R\$ of quantum circuit \$C\$.](#)

Definition 1.9 (Clustered Deviation). For a quantum circuit C , a register R of C , and a set of faults $\mathcal{E}$, let $\mathcal{T}_R$ be the Tanner graph of R , and let $\mathcal{D}_\tau$ be the deviation of $C[\mathcal{E}]$ from C on R at step τ . Denote by $\mathcal{T}_R|_{\mathcal{D}_\tau}$ the subgraph of $\mathcal{T}_R$ induced by the restriction of the left vertices (bits) to the indices in $\mathcal{D}_\tau$. Let us abuse and extend the connection notion to Tanner graphs by defining that two left vertices are connected if and only if they share a right neighbor. We define the deviation clusters at step τ to be the connected components of $\mathcal{T}_R|_{\mathcal{D}_\tau}$. The size of each deviation cluster is the number of right vertices it contains.

Claim 1.10. Let C be a quantum circuit composed of gates with bounded fan degree $\Delta \in \mathbb{N}$. In addition, let R be a quantum register encoded by a quantum error correction code $\mathcal{C}$ with Tanner graph $\mathcal{T}$ that has left and right degrees Δ_1 and Δ_2 . Fix a set of faults $\mathcal{E}$, and an order J that agrees with $\pi_{C[\mathcal{E}]}$. For any τ , denote by $Y_1^{(\tau)}, Y_2^{(\tau)}, \dots, Y_l^{(\tau)}$ the deviation clusters at step $\tau \in J$. Assume that at step $\tau_1 \in J$ there is a deviation cluster $Y_i^{(\tau_1)}$ of size $|Y_i^{(\tau_1)}|$. Then there is a deviation cluster at step $\tau_1 - 1$, let's denote it by Z , such $Z \cap Y_i^{(\tau_1)} \neq \emptyset$ and Z is of size at least:

$$|Z| \geq \frac{1}{\Delta \Delta_1 \Delta_2} |Y_i^{(\tau_1)}|$$

Furthermore there is a deviation cluster at step $\tau_1 - 1$, let's denote it by Z' , such $Z' \cap Y_i^{(\tau_1)} \neq \emptyset$, and Z' is of size at most:

$$|Z'| \leq \Delta \Delta_1 \Delta_2 |Y_i^{(\tau_1)}|$$

[Add:](#) that when it isn't mentioned, we assume that the error at time t can be decomposed into a product $\Rightarrow$ at each step, a fault is supported on at most one (q)bit.

Proof. Denote by $u = (g, l)$ the gate at step τ . If u acts trivially on the (q)bits in $Y_i^{(\tau_1)}$ then they also belong to deviation on register R at step $\tau_1 - 1$. Since they are connected in $\mathcal{T}$ they form a deviation cluster on register R at step $\tau_1 - 1$ and we got the desired. Thus it is left to handle the case in which u acts non-trivially on (q)bits in $Y_i^{(\tau_1)}$. Since u acts on at most Δ qubits, and each qubit has at most $\Delta_1(\Delta_2 - 1)$ neighbors at $\mathcal{T}$ it follows that u acts non trivially on at most

$$\Delta + \Delta\Delta_1(\Delta_2 - 1) \leq \Delta\Delta_1\Delta_2$$

deviation clusters at step $\tau_1 - 1$. Let l be integer no greater than $\Delta\Delta_1\Delta_2$ and let $Y_1, Y_2, \dots, Y_l$ be the deviation cluster, on register R , at step $\tau_1 - 1$, on which u acts non trivially, since $Y_i^{(\tau_1)} \subset \bigcup_j Y_j$. We have that:

$$\begin{aligned} |Y_i^{(\tau_1)}| &\leq \sum_j |Y_j| \leq \Delta\Delta_1\Delta_2 \max_j |Y_j| \\ \Rightarrow \max_j |Y_j| &\geq \frac{1}{\Delta\Delta_1\Delta_2} |Y_i^{(\tau_1)}| \end{aligned} \tag{1}$$

Complete the second inequality. Should consider to erase what have already written about it. To get the second inequality, we use the fact that u is a unitary gate, in particular, u is reversible. Let $C_{J, \tau_1} = u_1, \dots, u_{\tau_1}$ be the partial computation circuit until step τ_1 . Observe that $C_{J, \tau_1 - 1}$ is obtained by stacking $u_{\tau_1}^\dagger$ as a final stage to C_{J, τ_1} , denoted by $u_{\tau_1}^\dagger \circ C_{J, \tau_1}$. Thus, the deviation from C_{J, τ_1} at step $\tau_1 - 1$ equals the deviation from $u_{\tau_1}^\dagger \circ C_{J, \tau_1}$ at step $\tau_1 + 1$. By eq. (1), $\square$

Corollary 1.11. Let $\alpha = 1/(\Delta\Delta_1\Delta_2)$. Assume that at the initial step j_1 there is no deviation cluster of size more than αd , and that at a step $\tau_1 \in J$ there is a deviation cluster $Y_i^{(\tau_1)}$ of size $|Y_i^{(\tau_1)}| > d$. Then there is a step $\tau_o < \tau_1, \tau_o \in J$ for which there is a deviation cluster Z at step τ_o , such that the size of Z is in the range $(\alpha d, d)$.

Proof. $\square$

Claim 1.12. Let A be the event in which, until time t , there is a time t' such that there is a deviation cluster of size greater than d . For any τ , let B_τ be the event that step τ is the first step to has a deviation cluster of size in the range $(\alpha d, d)$. Then:

$$\mathbf{Pr}[A] \leq 2wd \max_{\tau \in [2wd]} \mathbf{Pr}[B_\tau]$$

Proof.

$$\mathbf{Pr}[A] \leq \mathbf{Pr}\left[\bigcup_{\tau} B_\tau\right] \leq 2wd \max_{\tau \in [2wd]} \mathbf{Pr}[B_\tau]$$

$\square$