

D126, D1218, D1224, D1238, D1240 Batteries



The 12 volt Sealed Lead-Acid Batteries are maintenance-free standby and auxiliary power supplies that provide long service life and dependability. The D126 (pictured above) fits in any of the currently offered company product enclosures and connects to the 2 color-coded battery leads supplied with the panel or module. A D122 Dual Battery Harness may connect two D126 batteries in parallel to double the amp hour output. The D1218 can be used with all compatible control panels. The D1218, D1224, D1238 are larger than the D126 and must be mounted in a suitable enclosure to accommodate their size. The D1218, D1224, and D1238 have 2 bolt-fastened terminals and include hardware for attaching battery leads or spade connectors.

■ System Overview

These batteries are for use only with charging circuits calibrated for lead-acid batteries. They are suitable for supplying backup power for fire, security, and access control systems during AC power failures.

■ Features

- 12 VDC sealed lead-acid
- Fully rechargeable
- Maintenance-free
- For use with current company-supported control/communicators
- For use as secondary power for accessory modules
- Long service life

■ Certifications and Approvals

UL Standards (D126 only)	UL294, Access Control System Units UL1076, Proprietary Burglar Alarm Units and Systems
cUL Standards	Signal Appliances, Miscellaneous, Certified for Canada
Approvals	(D126 only): • FM • BSA • DSI CSFM (D126 and D1218): CSFM

■ Planning

Refer to the appropriate control panel installation manual for information on calculating the standby battery requirements for the system. Total continuous and intermittent current requirements must not exceed the amp hour capacity of the batteries.

The D126 battery installs inside the D8103, D8109, D8109, and D8109G control panel enclosures and connects to the panel through the color-coded D122 Dual Battery harness consisting of 2 leads. The D1218, D1224, D1238, D1240 are larger batteries and install in separate approved enclosures. Some enclosures do not support 2 batteries. Refer to the appropriate control/communicator operation and installation manual.

■ Technical Specifications

Battery Capacity	
D126:	12 V, 7 Ah
D1218:	12 V, 18 Ah
D1224:	12 V, 24 Ah
D1238:	12 V, 38 Ah
D1240:	12 V, 4 Ah
Battery Dimensions (LxW)	
D126:	6 in. x 3 in. (15 cm x 8 cm)
D1218:	7 in. x 3 in. (18 cm x 8 cm)
D1224:	7 in. x 5 in. (18 cm x 13 cm)
D1238:	8 in. x 7 in. (20 cm x 18 cm)
D1240:	4 in. x 3.5 in (10 cm x 8.9 cm)
Battery Dimensions (Height with Terminals)	
D126:	4 in. (10 cm)
D1218:	7 in. (18 cm)
D1224:	7 in. (18 cm)
D1238:	7 in. (18 cm)
D1240:	2.7 in. (68.6 mm)
Battery Weight	
D126:	5.5 lb. (2.5 kg)
D1218:	14 lb. (6 kg)
D1224:	19 lb. (9 kg)
D1238:	29 lb. (13 kg)
D1240:	3 lb. (1.7 kg)

■ Hardware Options

For additional information on the Material Safety Data Sheets on these products, please visit the company website.

D113 Battery Lead Supv Module

Supervises wiring connections for two 12 V batteries that are connected to the same set of charging terminals.



D122 Dual Battery Harness

Color-coded wire harness with circuit breaker to protect charging circuit when connecting more than one 12 volt battery to a control/communicator.



D122L Dual Battery Harness with Long Leads

Color-coded wire harness with circuit breaker to protect charging circuit when connecting more than one 12 volt battery to a control/communicator. Provides 35 in. (89 cm) leads to allow extra 12 volt batteries to be installed in an adjacent enclosure.



D8132 Battery Charger Module

Charges up to two 12 VDC, 7 Ah or two 12 VDC, 18 Ah batteries such as the D126 or D1218 (not included) and increases battery standby time.

