

Rechargeable Lithium-Ion Batteries

Procedures for **charging** and **querying** the Teledyne Webb Research (TWR) rechargeable lithium-ion smart battery packs used in Slocum G3 gliders.

Source

Organized from the TWR guide *"Rechargeable Lithium Ion Batteries: Procedures for Charging and Querying"* (Rev. 2022-09-06). This is a condensed reference – defer to the official Teledyne documentation for your specific glider.

Hardware Overview

The rechargeable packs are **smart batteries**: each communicates over a set of channels, addressed as \$R, 0 through \$R, 3 .

Pack	Channel(s)	Location
Aft pack	\$R, 0 (Channel 0) and \$R, 1 (Channel 1)	Aft section
Pitch pack	\$R, 2 (Channel 2)	Forward section
Extended energy bay pack	\$R, 3 (Channel 3)	Energy bay (if installed)

Channel assignment is not always consistent

A pitch or extended energy-bay pack registers as **Channel 2 (\$R, 2)** or **Channel 3 (\$R, 3)** depending on the cable it is connected to. If no extended energy bay is installed, Channel 2 or Channel 3 will simply not respond.