

Power connector (2 x 11-pin)*Usage: Optional*

A			Dir	B			Dir
1	IN+	I	Power positive input	2	IN+	I	Power positive input
3	IN+	I	Power positive input	4	IN+	I	Power positive input
5	IN+	I	Power positive input	6	OUT+	O	Power positive output
7	OUT+	O	Power positive output	8	OUT+	O	Power positive output
9	OUT+	O	Power positive output	10	OUT+	O	Power positive output
11	OUT-	O	Power negative output	12	OUT-	O	Power negative output
13	OUT-	O	Power negative output	14	OUT-	O	Power negative output
15	IN-	I	Power negative input	16	IN-	I	Power negative input
17	IN-	I	Power negative input	18	IN-	I	Power negative input
19	SENSE-	I	Sense negative input	20	SENSE+	I	Sense negative input

Used on slots #1, #2 and #4 only

Examples of backplane connector models: PH2-20-UA, Examples of backplane connector models: PH2-20-UA, 77313-124-22LF, ZL202-20G, 10129381-922002BLF, ZL202-20G

Signal connector*Usage: Mandatory*

A			Dir	Description	B			Dir	Description
1	PE	I		Protective Earth	1	+12V	I		DC power
2	+12V	I		DC power	2	+12V	I		DC power
3	+12V	I		DC power	3	GND			
4	GND				4	+3V3	I		DC power
5	+5V	I		DC power	5	+3V3	I		DC power
6	+5V	I		DC power	6	+VAUX	I		Backup DC power
7	GND				7	GND			
8	SHUTDOWN	I		Shutdown/Low-power (active low)	8	RESETn	I		Module reset (active low)
9	SMBUS_ALERT	O		Shared SMBus alert (active low)	9	NFAULT	I/O OD		Fault (open drain)
10	SCL/SMBCLK	I		Shared I ² C/SMBus Clock	10	SDA/SMBDAT	I/O		Shared I ² C/SMBus Data
11	GND				11	GND			
12	GND				12	GND			
13	RSVD1			Reserved / Ethernet TXRX_A-	13	OE_SYNC/TIN	I		Trigger in
14	RSVD2			Reserved / Ethernet TXRX_A+	14	TOUT	O**		Trigger out
15	RSVD3			Reserved / Ethernet TXRX_B-	15	AC_FREQ	I		AC Mains frequency
16	RSVD4			Reserved / Ethernet TXRX_B+	16	REFCLK+	I		SE or CLK+ 10MHz reference
17	RSVD5			Reserved / Ethernet TXRX_C-	17	REFCLK-	I		CLK- 10 MHz reference
18	RSVD6			Reserved / Ethernet TXRX_C+	18	UART_RX*	O		Shared UART RX
19	RSVD7			Reserved / Ethernet TXRX_D-	19	UART_TX*	I		Shared UART TX
20	RSVD8			Reserved / Ethernet TXRX_D+	20	BOOTn	I		Module bootloader select
21	SCLK	I		Shared SPI CLK	21	GND			
22	MOSI	I		Shared MOSI	22	PCIe_CLK+	I		PCIe clock
23	MISO	O		Shared MISO	23	PCIe_CLK-	I		PCIe clock
24	IRQn	O		Module IRQ	24	GND			
25	CSAn	I		Module Chip select A	25	PCIe_RX-	I		PCIe RX
26	CSBn	I		Module Chip select B	26	PCIe_RX+	I		PCIe RX
27	HSD+	I/O		USB 2.0	27	PCIe_TX-	O		PCIe TX
28	HSD-	I/O		USB 2.0	28	PCIe_TX+	O		PCIe TX
29	SSTX+	O		USB 3.0 Tx	29	PCIe_CLKREQ	I		PCIe clock request
30	SSTX-	O		USB 3.0 Tx	30	PCIe_WAKE	I		PCIe wake
31	SSRX+	I		USB 3.0 Rx	31	GND			
32	SSRX-	I		USB 3.0 Rx	32	ETH_SYNC	O		IEEE 1588 sync

*) Connect module UART_RX to master MCU UART_TX and module UART_TX to master MCU UART_RX

Examples of backplane connector models (gold plating of 0.25 um or thicker, not „flash“): 10018783-10101TLF, 10018783-11101TLF

**) Tri-state, only one module can drive this output at any time