

SCHNEIDER - DOL

No.	Daya Motor Telemecanique	Contactur Telemecanique	Thermal Overload Telemecanique	Motor Circuit Breaker Telemecanique	Cable (NYY)	Ampere Motor 3 Phase (280V)
1.	0,06 KW	LC1 K09 10 M7 (Utama)	LR 2 K03 01 (0,11-0,16A)	GV2-M02 (0,16-0,25A)	1x(4x1,5 mm2)	0.12
2.	0,09 KW	LC1 K09 10 M7 (Utama)	LR 2 K03 03 (0,23-0,36A)	GV2-M03 (0,25-40A)	1x(4x1,5 mm2)	0.18
3.	0,12 KW	LC1 K09 10 M7 (Utama)	LR 2 K03 04 (0,36-0,54A)	GV2-M04 (0,4-0,63A)	1x(4x1,5 mm2)	0.24
4.	0,25 KW	LC1 K09 10 M7 (Utama)	LR 2 K03 06 (0,80-1,20A)	GV2-M05 (0,63-1,0A)	1x(4x1,5 mm2)	0.5
5.	0,37 KW	LC1 K09 10 M7 (Utama)	LR 2 K03 06 (0,80-1,20A)	GV2-M06 (1,0-1,6A)	1x(4x1,5 mm2)	1.03
6.	0,55 KW	LC1 K09 10 M7 (Utama)	LR 2 K03 07 (1,20-1,80A)	GV2-M07 (1,6-2,5A)	1x(4x1,5 mm2)	1.6
7.	0,75 KW	LC1 K09 10 M7 (Utama)	LR 2 K03 08 (1,80-2,60A)	GV2-M07 (1,6-2,5A)	1x(4x1,5 mm2)	2
8.	1,1 KW	LC1 K09 10 M7 (Utama)	LR 2 K03 08 (1,80-2,60A)	GV2-M08 (2,50-4,0A)	1x(4x1,5 mm2)	2.6
9.	1,5 KW	LC1 K09 10 M7 (Utama)	LR 2 K03 10 (2,60-3,70A)	GV2-M08 (2,50-4,0A)	1x(4x1,5 mm2)	3.5
10.	2,2 KW	LC1 K09 10 M7 (Utama)	LR 2 K03 12 (3,70-5,50A)	GV2-M10 (4,0-6,0A)	1x(4x1,5 mm2)	5
11.	3 KW	LC1 K09 10 M7 (Utama)	LR 2 K03 14 (5,50-8,00A)	GV2-M14 (6,0-10,0A)	1x(4x1,5 mm2)	6.6
12.	3,7 KW	LC1 K09 10 M7 (Utama)	LR 2 K03 14 (5,50-8,00A)	GV2-M14 (6,0-10,0A)	1x(4x1,5 mm2)	7.7
13.	4 KW	LC1 K09 10 M7 (Utama)	LR 2 K03 14 (5,50-8,00A)	GV2-M14 (6,0-10,0A)	1x(4x2,5 mm2)	8.5
14.	5,5 KW	LC1 D09 10 M7 (Utama)	LR 2 D13 16 (10,0-16,50A)	GV2-M16 (9,0-14,0A)	1x(4x2,5 mm2)	11.5
15.	7,5 KW	LC1 D18 10 M7 (Utama)	LR 2 D13 21 (12,0-16,50A)	GV2-M20 (13,0-18,0A)	1x(4x4 mm2)	15.5
16.	9 KW	LC1 D18 10 M7 (Utama)	LR 2 D13 22 (17,0-25,0A)	GV2-M21 (17,0-23,0A)	1x(4x6 mm2)	18.5
17.	11 KW	LC1 D25 10 M7 (Utama)	LR 2 D13 22 (17,0-25,0A)	GV2-M22 (20,0-25,0A)	1x(4x10 mm2)	n
18.	15 KW	LC1 D32 10 M7 (Utama)	LR 2 D23 53 (23,0-32,0A)	GV2-M32 (24,0-32,0A)	1x(4x16 mm2)	30
19.	18,5 KW	LC1 D40 11 M7 (Utama)	LR 2 D33 53 (37,0-50,0A)	GV2-M32 (24,0-32,0A)	1x(4x16 mm2)	37
20.	22 KW	LC1 D40 11 M7 (Utama)	LR 2 D33 57 (37,0-50,0A)	GV2-M40 (25,0-40,0A)	1x(4x25 mm2)	44
21.	30 KW	LC1 D50 11 M7 (Utama)	LR 2 D33 61 (48,0-65,0A)	GV2-M63 (40,0-63,0A)	1x(4x35 mm2)	60
22.	37 KW	LC1 D65 10 M7 (Utama)	LR 2 D33 63 (63,0-80,0A)	GV2-M80 (63,0-80,0A)	1x(4x50 mm2)	72