

2- FortiGate LAN Configuration

Overview

This guide demonstrates how to configure a LAN interface on a FortiGate firewall, including IP addressing, administrative access, DHCP services, and DNS settings.

Lab Environment

Firewall: FortiGate VM64

LAN Interface: port2

LAN IP Address: 172.16.0.1/24

DHCP Range: 172.16.0.30 - 172.16.0.254

Related Video: <https://www.youtube.com/watch?v=wXaH2nbRWN8>

Step 1 - Navigate to Interfaces

Navigate to Network > Interfaces and edit the LAN interface (port2).

Step 2 - Configure the LAN Interface

Alias: LAN

Role: LAN

Addressing Mode: Manual

IP Address: 172.16.0.1/24

Step 3 - Configure Administrative Access

Enable HTTPS, SSH, and PING.

Step 4 - Configure LLDP

Enable Receive LLDP and Transmit LLDP to allow neighboring devices to discover each other.

Step 5 - Enable DHCP Server

DHCP Range: 172.16.0.30 - 172.16.0.254

Gateway: Same as Interface IP

DNS: Same as System DNS

Lease Time: 604800 seconds

Verification

Verify that client devices receive an IP address, gateway, and DNS settings from FortiGate.

Result

The LAN interface is configured successfully and provides Layer 3 gateway functionality, administrative access, DHCP services, and DNS assignment.

The screenshot shows the 'Edit Interface' configuration page for a LAN interface in the Emre-IT-Portfolio. The left sidebar contains a navigation menu with categories like Network, Diagnostics, Policy & Objects, Security Profiles, VPN, User & Authentication, System, Security Fabric, and Log & Report. The 'Network' category is expanded, showing options like Interfaces, DNS, IPAM, SD-WAN, Static Routes, Policy Routes, RIP, OSPF, BGP, Routing Objects, and Multicast. The 'Interfaces' option is selected. The main configuration area is titled 'Edit Interface' and contains the following fields and sections:

- Name:** LAN (port2)
- Alias:** LAN
- Type:** Physical Interface
- VRF ID:** 0
- Role:** LAN
- Addressing mode:** Manual (selected), IPAM, DHCP, PPPoE
- IP/Netmask:** 172.16.0.1/255.255.255.0
- Create address object matching subnet:** ☒
- Name:** port2 address
- Destination:** 172.16.0.0/24
- Secondary IP address:** ☐
- Administrative Access:**
 - IPv4:**
 - ☒ HTTPS
 - ☐ SSH
 - ☐ RADIUS Accounting
 - ☒ PING
 - ☐ SNMP
 - ☐ Security Fabric Connection
 - ☐ FMG-Access
 - ☐ FTM
 - ☐ Speed Test
- Receive LLDP:** Use VDOM Setting ☒ Enable ☐ Disable
- Transmit LLDP:** Use VDOM Setting ☒ Enable ☐ Disable

The screenshot shows the 'Edit Interface' configuration page for a LAN interface in the Emre-IT-Portfolio, specifically the DHCP Server configuration section. The left sidebar is the same as the previous screenshot. The main configuration area is titled 'Edit Interface' and contains the following fields and sections:

- DHCP Server:**
 - DHCP status:** ☒ Enabled ☐ Disabled
 - Address range:** 172.16.0.30-172.16.0.254
 - Netmask:** 255.255.255.0
 - Default gateway:** Same as Interface IP (selected), Specify
 - DNS server:** Same as System DNS (selected), Same as Interface IP, Specify
 - Lease time:** 604800 second(s)
- Advanced:**
 - Network:**
 - Device detection:** ☒
 - Security mode:** ☐
 - Traffic Shaping:**
 - Outbound shaping profile:** ☐
 - Outbound bandwidth:** ☐
 - Miscellaneous:**
 - Comments:** 0/255
 - Status:** ☒ Enabled ☐ Disabled