

FÓRMULAS GENERALES

Relaciones trigonométricas

$\cos(\alpha \pm \beta) = \cos(\alpha) \cdot \cos(\beta) \mp \sin(\alpha) \cdot \sin(\beta)$
$\sin(\alpha \pm \beta) = \sin(\alpha) \cdot \cos(\beta) \pm \cos(\alpha) \cdot \sin(\beta)$
$\sin(\alpha) \cdot \sin(\beta) = \frac{1}{2} \cdot [\cos(\alpha - \beta) - \cos(\alpha + \beta)]$
$\cos(\alpha) \cdot \cos(\beta) = \frac{1}{2} \cdot [\cos(\alpha - \beta) + \cos(\alpha + \beta)]$
$\sin(\alpha) \cdot \cos(\beta) = \frac{1}{2} \cdot [\sin(\alpha - \beta) + \sin(\alpha + \beta)]$
$\cos(2\alpha) = \cos^2(\alpha) - \sin^2(\alpha)$
$\sin(2\alpha) = 2 \cdot \sin(\alpha) \cdot \cos(\alpha)$
$\sin^2(\alpha) = \frac{1}{2} \cdot (1 - \cos(2\alpha))$
$\cos^2(\alpha) = \frac{1}{2} \cdot (1 + \cos(2\alpha))$

Función de densidad de probabilidad normal	$f(x) = \frac{1}{\sigma\sqrt{2\pi}} e^{-\frac{(x-\mu)^2}{2\sigma^2}}$
--	---

Pares básicos de la Transformada de Fourier

$\mathbf{x(t)}$	$\mathbf{X(\omega)}$
$e^{j\omega_0 t}$	$2\pi\delta(\omega - \omega_0)$
$\cos(\omega_0 t)$	$\pi [\delta(\omega - \omega_0) + \delta(\omega + \omega_0)]$
$\sin(\omega_0 t)$	$\frac{\pi}{j} [\delta(\omega - \omega_0) - \delta(\omega + \omega_0)]$
1	$2\pi\delta(\omega)$
$\Pi\left(\frac{t}{2T_1}\right) = \begin{cases} 1 & t < T_1 \\ 0 & t > T_1 \end{cases}$	$2T_1 \operatorname{sinc}\left(\frac{\omega T_1}{\pi}\right) = \frac{2\sin(\omega T_1)}{\omega}$
$\frac{W}{\pi} \operatorname{sinc}\left(\frac{Wt}{\pi}\right) = \frac{\sin(Wt)}{\pi t}$	$X(\omega) = \begin{cases} 1 & \omega < W \\ 0 & \omega > W \end{cases}$
$\delta(t)$	1
$\delta(t - t_0)$	$e^{-j\omega t_0}$

Propiedades de la Transformada de Fourier

Señal	Transformada de Fourier
$x(t)$	$X(\omega)$
$y(t)$	$Y(\omega)$
$ax(t) + by(t)$	$aX(\omega) + bY(\omega)$
$x(t - t_0)$	$e^{-j\omega t_0} X(\omega)$
$e^{j\omega_0 t} x(t)$	$X(\omega - \omega_0)$
$x(at)$	$\frac{1}{ a } X\left(\frac{\omega}{a}\right)$
$x(t) * y(t)$	$X(\omega) \cdot Y(\omega)$
$x(t) \cdot y(t)$	$\frac{1}{2\pi} X(\omega) * Y(\omega)$

COMUNICACIONES ANALÓGICAS

Modulaciones lineales

	Modulación AM	Modulación DBL	Modulación FM
Señal	$A_p \cdot [1 + mx_n(t)] \cdot \cos(\omega_p t)$	$A_p \cdot x(t) \cdot \cos(\omega_p t)$	$A_p \cdot \cos\left(\omega_p t + \omega_d \int^t x(\lambda) d\lambda\right)$
Potencia media	$\frac{A_p^2}{2} + \frac{m^2 A_p^2}{2} S_{xn} = P_p + 2P_{BL}$	$\frac{A_p^2}{2} S_x = 2P_{BL}$	$\frac{A_p^2}{2}$
Potencia de cresta	$\frac{1}{2} A_p^2 (1 + m)^2$	$\frac{1}{2} [A_p \cdot x(t) _{max}]^2$	$\frac{A_p^2}{2}$
Ancho de banda	$B_T = 2 \cdot W_x$		$B_T \approx 2(D + a)W_x$ $a = \begin{cases} 2 & 2 \leq D \leq 10 \\ 1 & c.c. \end{cases}$ $D = \frac{\omega_d x(t) _{max}}{W_x}$

Ruido en modulaciones analógicas

SNR en banda base	$\gamma = \frac{P_R}{N_0 W_x}$
SNR en predetección	$\left(\frac{S}{N}\right)_R = \frac{W_x}{B_T} \cdot \gamma$
Modulación AM	$\left(\frac{S}{N}\right)_D = \frac{m^2 S_{xn}}{1 + m^2 S_{xn}} \cdot \gamma$
Modulación DBL	$\left(\frac{S}{N}\right)_D = \gamma$
Modulación FM	$\left(\frac{S}{N}\right)_D = 3D^2 S_{xn} \gamma$
Modulación FM deénfasis ($B_{de} \ll W_x$)	$\left(\frac{S}{N}\right)_D = \frac{\omega_d^2}{B_{de}^2} S_x \gamma$

COMUNICACIONES DIGITALES

Modulaciones digitales

Sistema M-ario unidimensional		$P_e = \frac{2(M-1)}{M} Q\left(\frac{d}{\sqrt{2N_0}}\right)$
Cota de la unión		$P_e \leq \frac{1}{M} \sum_{i=1}^M \sum_{\substack{k=1 \\ k \neq i}}^M Q\left(\frac{d_{ik}}{\sqrt{2N_0}}\right)$
Cota de la unión simplificada		$P_e \leq (M-1) \cdot Q\left(\frac{d_{min}}{\sqrt{2N_0}}\right)$
PSK	$M = 2$	$P_e = Q\left(\sqrt{\frac{2E_b}{N_0}}\right)$
	$M \geq 4$	$P_e = 2 \cdot Q\left(\sqrt{\frac{2E_s}{N_0}} \sin\left(\frac{\pi}{M}\right)\right)$
DPSK	$M = 2$	$P_e = \frac{1}{2} e^{-\frac{E_b}{N_0}}$
FSK coherente	$M = 2$	$P_e = Q\left(\sqrt{\frac{E_b}{N_0}}\right)$
	$M \geq 4$	$P_e \leq (M-1) \cdot Q\left(\sqrt{\frac{E_s}{N_0}}\right)$
FSK no coherente	$M = 2$	$P_e = \frac{1}{2} e^{-\frac{E_b}{2N_0}}$
QAM	$\log_2(M)$ par	$P_e \approx 4 \left(1 - \frac{1}{\sqrt{M}}\right) \cdot Q\left(\sqrt{\frac{3 \cdot E_s}{(M-1) \cdot N_0}}\right)$
MSK	$M=2$	$P_e = Q\left(\sqrt{\frac{2E_b}{N_0}}\right)$

	Codificación Gray (ASK, QAM, PSK)	FSK
Probabilidad de error de bit	$P_b = \frac{1}{\log_2(M)} P_e$	$P_b = \frac{2^{\log_2(M)-1}}{2^{\log_2(M)} - 1} P_e$

Filtro de coseno alzado, $0 \leq \alpha \leq 1$

$$H(\omega) = \begin{cases} 1 & |\omega| \leq \pi \frac{1-\alpha}{T} \\ \frac{1}{2} \left[1 + \cos\left(\frac{T}{2\alpha} \cdot \left(|\omega| - \pi \frac{1-\alpha}{T}\right)\right) \right] & \pi \frac{1-\alpha}{T} \leq |\omega| \leq \pi \frac{1+\alpha}{T} \\ 0 & c.c. \end{cases}$$

Densidad espectral de potencia de la PAM (banda base)

$x(t) = \sum_{n=-\infty}^{\infty} a_n h(t - nT)$	$S_x(\omega) = \frac{1}{T} H(\omega) ^2 S_a(\omega)$
$S_a(\omega) = \sum_{m=-\infty}^{\infty} R_a[m] \cdot e^{-j\omega mT}$	$\sum_{m=-\infty}^{\infty} e^{-j\omega mT} = \frac{2\pi}{T} \sum_{m=-\infty}^{\infty} \delta(\omega - m \frac{2\pi}{T})$

Ancho de banda (Hz) de las modulaciones paso banda

	$h(t) = \begin{cases} \frac{1}{\sqrt{T}} & 0 \leq t < T \\ 0 & \text{c.c.} \end{cases}$	$h(t) = \frac{\sin\left(\frac{\pi}{T}t\right)}{\frac{\pi}{T}t}$
M-PSK y M-QAM	$\frac{2R_b}{\log_2(M)} = \frac{2}{T}$	$\frac{R_b}{\log_2(M)} = \frac{1}{T}$
M-FSK (coherente)	$\frac{(M+3)R_b}{2 \cdot \log_2(M)} = \frac{(M+3)}{2 \cdot T}$	$\frac{(M+1)R_b}{2 \cdot \log_2(M)} = \frac{(M+1)}{2 \cdot T}$
M-FSK (no coherente)	$\frac{(M+1)R_b}{\log_2(M)} = \frac{(M+1)}{T}$	$\frac{M \cdot R_b}{\log_2(M)} = \frac{M}{T}$

Tabla de valores de Q(x)

x	Q(x)	x	Q(x)	x	Q(x)	x	Q(x)
0,0	5,000000e-01	1,8	3,593032e-02	3,6	1,591086e-04	5,4	3,332043e-08
0,1	4,601722e-01	1,9	2,871656e-02	3,7	1,077997e-04	5,5	1,898956e-08
0,2	4,207403e-01	2,0	2,275013e-02	3,8	7,234806e-05	5,6	1,071760e-08
0,3	3,820886e-01	2,1	1,786442e-02	3,9	4,809633e-05	5,7	5,990378e-09
0,4	3,445783e-01	2,2	1,390345e-02	4,0	3,167124e-05	5,8	3,315742e-09
0,5	3,085375e-01	2,3	1,072411e-02	4,1	2,065752e-05	5,9	1,817507e-09
0,6	2,742531e-01	2,4	8,197534e-03	4,2	1,334576e-05	6,0	9,865876e-10
0,7	2,419637e-01	2,5	6,209665e-03	4,3	8,539898e-06	6,1	5,303426e-10
0,8	2,118554e-01	2,6	4,661189e-03	4,4	5,412542e-06	6,2	2,823161e-10
0,9	1,840601e-01	2,7	3,466973e-03	4,5	3,397673e-06	6,3	1,488226e-10
1,0	1,586553e-01	2,8	2,555131e-03	4,6	2,112456e-06	6,4	7,768843e-11
1,1	1,356661e-01	2,9	1,865812e-03	4,7	1,300809e-06	6,5	4,016001e-11
1,2	1,150697e-01	3,0	1,349898e-03	4,8	7,933274e-07	6,6	2,055790e-11
1,3	9,680049e-02	3,1	9,676035e-04	4,9	4,791830e-07	6,7	1,042099e-11
1,4	8,075666e-02	3,2	6,871378e-04	5,0	2,866516e-07	6,8	5,230951e-12
1,5	6,680720e-02	3,3	4,834242e-04	5,1	1,698268e-07	6,9	2,600125e-12
1,6	5,479929e-02	3,4	3,369291e-04	5,2	9,964437e-08	7,0	1,279813e-12
1,7	4,456546e-02	3,5	2,326291e-04	5,3	5,790128e-08		