



MECHATRONICS SYSTEM INTEGRATION (MCTA 3203)

SEMESTER 1 2025/2026

WEEK 9: COLOR DETECTION AND ANALYSIS

SECTION 2

GROUP 16

LECTURER: ZULKIFLI BIN ZAINAL ABIDIN & WAHJU SEDIONO

Date of Experiment: Monday, 8 December 2025

Date of Submission: Monday, 15 December 2025

NO.	GROUP MEMBERS	MATRIC NO
1.	MUHAMMAD HAIKAL ZULHILMI BIN FAIROF	2313025
2.	MUHAMMAD FAIZ IZWAN BIN NOR EFFENDI	2313509
3.	AINUL JAARIAH BINTI ALIUDIN	2312664

ABSTRACT

This experiment focuses on the design and evaluation of a color detection system using an Arduino microcontroller and a Pixy (Gravity Pixy) Camera. The objective of the experiment was to detect and analyze different colors accurately under various conditions and to assess the performance of an AI vision-based color detection approach. The Pixy camera was trained using its built-in color recognition feature to identify multiple colors, each assigned a unique color ID. An Arduino program was used to receive color detection data via serial communication and display the detected color information in real time. The system was tested using different colored objects under varying lighting conditions to evaluate detection accuracy, response time, and consistency. The results show that the Pixy camera provided reliable and consistent color detection, outperforming conventional color sensors in terms of robustness to lighting variations and ease of calibration.

TABLES OF CONTENTS

ABSTRACT.....	2
TABLES OF CONTENTS.....	3
1. INTRODUCTION.....	4
2. MATERIAL AND EQUIPMENT.....	5
3. EXPERIMENTAL SETUP.....	6
3.1 Part 1: Color Detection with Color Sensor.....	6
3.1.1 Materials Needed.....	6
3.1.2 Hardware Setup and Wiring (TCS3200 Sensor).....	6
3.1.3 Arduino Programming Details.....	7
3.1.4 Python Interface.....	8
3.2 Part 2: Object/Color Detection with Pixy v1 Camera.....	8
3.2.1 Materials Needed.....	8
3.2.2 Hardware Setup and Wiring (Pixy v1 Camera).....	8
3.2.3 Pixy Configuration (Pre-Calibration).....	9
3.2.4 Arduino Programming Details.....	9
4. METHODOLOGY.....	10
Hardware Setup.....	10
Software Development.....	10
Testing and Data Collection.....	10
5. DATA COLLECTION.....	11
5.1 Part 1: TCS3200 Color Sensor Data (Raw Frequency Readings).....	11
5.2 Part 2: Pixy v1 Smart Vision Sensor Data (Object Tracking).....	12
6. DATA ANALYSIS.....	14
6.1 Color Detection Accuracy.....	14
6.2 Performance Under Different Lighting Conditions.....	14
6.3 Response Time Analysis.....	14
6.4 Comparison with Conventional Color Sensors.....	14
7. RESULTS.....	16
8. DISCUSSIONS.....	18
9. CONCLUSION.....	19
10. RECOMMENDATION.....	20
REFERENCES.....	21
APPENDICES.....	22
<i>Appendix A.....</i>	<i>22</i>
<i>Appendix B.....</i>	<i>24</i>
<i>Appendix C.....</i>	<i>25</i>
ACKNOWLEDGEMENT.....	26
STUDENTS DECLARATION.....	26
<i>Certificate of Originality and Authenticity.....</i>	<i>27</i>

1. INTRODUCTION

This report details the implementation and comparative analysis of two distinct sensor technologies for automated object and color recognition within the context of the Mechatronics System Integration module (MCTA3203). The experiment's primary objective was to design and evaluate functional systems for detecting color or objects using an Arduino microcontroller. The experiment was executed in two phases: first, using a basic TCS3200 Color Sensor, where the sensor was interfaced with an Arduino to measure raw Red, Green, and Blue light frequencies, with the intent of transmitting this data via serial communication for later interpretation and color identification; and second, utilizing the capabilities of a Pixy v1 Smart Vision Sensor (CMUcam5), which involved integrating the camera with the Arduino via SPI to detect pre-taught object signatures and extract positional and size data (ID, X, Y, Width, Height) in real-time. Following hardware setup, programming, and necessary calibration for both the raw frequency sensor and the smart vision camera, various objects were tested. The central focus of this report is to analyze the collected data on detection accuracy and system performance under practical conditions (such as varying lighting and response times), and ultimately to determine the efficacy and limitations of each sensor approach.

2. MATERIAL AND EQUIPMENT

- **Arduino Uno** – serves as the main controller for processing camera data
- **Pixy Camera (Gravity Pixy / Pixy2)** – used for color recognition and object detection
- **USB cable** – for programming and powering the Arduino
- **Jumper wires** – for serial communication connections
- **Breadboard** (optional) – for circuit organization
- **Computer with Arduino IDE installed** – used to upload code and monitor outputs
- **Pixy Camera Arduino Library** – enables communication between Arduino and Pixy camera
- **Colored objects** (e.g., red, green, blue) – used as test samples

3. EXPERIMENTAL SETUP

3.1 Part 1: Color Detection with Color Sensor

This section details the setup for color detection using a dedicated color sensor.

3.1.1 Materials Needed

- Arduino board
- Color sensor (TCS3200)
- Jumper wires
- Breadboard
- Computer with Arduino IDE and Python installed
- USB cable for Arduino
- RGB LED (optional)

3.1.2 Hardware Setup and Wiring (TCS3200 Sensor)

The color sensor is connected to the Arduino using jumper wires according to the pin definitions in the provided sketch. The connections are as follows:

Sensor Pin	Arduino Pin (Defined in Sketch)	Function
S0	Digital Pin 4	Output frequency scaling selection
S1	Digital Pin 5	Output frequency scaling selection
S2	Digital Pin 6	Photodiode filter selection (low bit)

S3	Digital Pin 7	Photodiode filter selection (high bit)
OUT	Digital Pin 8 (sensorOut)	Frequency output signal
VCC	5V	Power supply
GND	GND	Ground




Figure 3.1.2.1 TCS3200 connection and wiring with Arduino

3.1.3 Arduino Programming Details

The provided Arduino sketch interfaces with the color sensor to read frequency data corresponding to Red, Green, and Blue light intensity (see *Appendix A*).

3.1.4 Python Interface

The next step in the experiment involves writing a **Python program** to communicate with the Arduino over the serial connection using the **pyserial** library. This program will receive the raw frequency data, interpret it, and determine the detected color (see *Appendix B*).

3.2 Part 2: Object/Color Detection with Pixy v1 Camera

This setup details the hardware configuration, wiring, and Arduino programming for the object detection experiment using the Pixy v1 Smart Vision Sensor as an alternative to the HuskyLens.

3.2.1 Materials Needed

- Arduino board (Uno or compatible)
- Pixy v1 Camera (CMUcam5)
- Connecting Cable (typically comes with Pixy)
- Jumper wires
- External power supply (if needed for high current draw)
- Computer with Arduino IDE
- Objects pre-taught to the Pixy for recognition (different colors/signatures)

3.2.2 Hardware Setup and Wiring (Pixy v1 Camera)

The Pixy v1 camera is typically interfaced with the Arduino via its **SPI (Serial Peripheral Interface)** port for high-speed communication.

Pixy v1 Pin	Arduino Uno Pin	Function
GND	GND	Ground connection
VCC	5V	Power supply

MISO	D12	SPI Data Out
MOSI	D11	SPI Data In
SCK	D13	SPI Clock
CS	D10	SPI Chip Select

Additionally, the provided code uses Digital Pin 7 for an indicator LED:

- **LED Pin:** Digital Pin 7

3.2.3 Pixy Configuration (Pre-Calibration)

Before running the Arduino code, the Pixy camera must be configured and taught to recognize the target objects/colors (signatures) using the PixyMon utility software on a computer:

1. **Color Signatures:** Use PixyMon to "teach" the Pixy camera the different colors or objects (called **Signatures**) you intend to detect.
2. **ID Assignment:** Each recognized color/object will be assigned a unique signature ID (1 through 7). The Arduino code reads this signature ID ([sig](#)).
3. **Default Action:** Ensure the camera is configured to detect and track these signatures.

3.2.4 Arduino Programming Details

The provided Arduino sketch interfaces with the Pixy v1 camera using the [Pixy.h](#) library (see *Appendix C*).

4. METHODOLOGY

The experiment was conducted to design and evaluate a color detection system using two different approaches: a conventional color sensor and a vision-based system using a Pixy Cam. The methodology consisted of hardware setup, software development, and performance testing.

Hardware Setup

An Arduino Uno was used as the main microcontroller. For the first approach, a color sensor was connected to the Arduino using a breadboard and jumper wires. The sensor was powered using the Arduino's 5V and GND pins, and its signal pins were connected according to the sensor datasheet.

For the second approach, a Pixy Cam (CMUcam5) was interfaced with the Arduino Uno using SPI communication. The Pixy Cam was powered directly from the Arduino and configured to detect predefined color signatures. The camera was mounted facing the target objects to ensure clear visibility and consistent detection.

Software Development

An Arduino program was developed to read RGB data from the color sensor, process the values, and transmit the data to a computer via serial communication. A Python program was used to receive and interpret the data for color classification and visualization.

For the Pixy Cam system, the Pixy library was installed in the Arduino IDE. The Pixy Cam was trained to recognize specific colors using the PixyMon software by creating unique color signatures. The Arduino code continuously read detected object signatures and their coordinates, allowing identification of different colored objects in real time.

Testing and Data Collection

Various colored objects were tested under different lighting conditions. The detected color, response time, and detection consistency were recorded for both systems. The performance of the color sensor and Pixy Cam was then compared based on accuracy, stability, and response speed.

5. DATA COLLECTION

The following quantitative data was collected during the two experimental phases: Part 1 using the TCS3200 Color Sensor, and Part 2 using the Pixy v1 Smart Vision Sensor. This data was essential for the analysis of system performance, stability, and accuracy.

5.1 Part 1: TCS3200 Color Sensor Data (Raw Frequency Readings)

Data was collected by reading the frequency output (raw R, G, B light intensity) for various target colors. The Arduino communicated this data serially for interpretation by the Python program.

Target Color	Lighting Condition	R (Red Frequency)	G (Green Frequency)	B (Blue Frequency)	Observed Color (Python Output)	Accuracy
Red Block	Standard Lab Light	148	185	225	Red	Correct
Red Block	Dimmed Light	195	240	280	Red	Correct
Red Block	Window Light	120	150	170	Green	Incorrect
Green Block	Standard Lab Light	210	155	250	Green	Correct

Blue Block	Standard Lab Light	240	235	150	Blue	Correct
White Paper	Standard Lab Light	105	100	110	White	Correct
White Paper	Bright Desk Lamp	70	65	75	Yellow	Incorrect

Observation: The TCS3200 system demonstrated that changes in ambient light significantly influenced the raw RGB readings, occasionally leading to incorrect color identification.

5.2 Part 2: Pixy v1 Smart Vision Sensor Data (Object Tracking)

The Pixy v1 camera was pre-trained to recognize specific color signatures (Sig). The Arduino continuously reads the object's ID, position (X, Y), and size (W, H) via SPI communication.

Target Object Color	Signature ID (Sig)	X Position (Center)	Y Position (Center)	Width (W)	Height (H)	Detection Consistency (%)	Response Time (ms)
Red Object	1	158	110	55	70	98%	20

Green Object	2	162	108	60	85	99%	18
Blue Object	3	155	112	75	50	98%	22
Red Object (Moving)	1	<i>Varies (e.g., 50 to 250)</i>	<i>Varies (e.g., 50 to 180)</i>	55	70	97%	21
Red Object (Dim Light)	1	160	110	55	70	95%	20

Observation: The Pixy Cam maintained a high detection consistency and provided stable object block data across trials, confirming its superior performance and robustness compared to the TCS3200.

6. DATA ANALYSIS

6.1 Color Detection Accuracy

The Pixy camera was calibrated using its built-in color recognition mode by teaching the camera three different colors. Each color was stored as a unique color signature. During testing, the camera successfully detected and classified the trained colors, outputting the corresponding color ID along with positional information.

The detection accuracy was high when the camera was calibrated under stable lighting conditions. The Pixy camera was able to differentiate between colors even when the object position changed, indicating reliable performance.

6.2 Performance Under Different Lighting Conditions

The system was tested under normal indoor lighting, brighter light, and dimmer conditions. Under consistent indoor lighting, the Pixy camera showed stable and repeatable results. However, under excessive brightness or shadows, minor misdetections occurred, particularly for colors with similar shades. Recalibration under consistent lighting significantly improved detection performance.

6.3 Response Time Analysis

The Pixy camera demonstrated fast response times, with color detection occurring almost instantaneously when an object entered the camera's field of view. The response time was suitable for real-time applications such as color-based sorting and robotic control.

6.4 Comparison with Conventional Color Sensors

Compared to traditional color sensors such as the TCS3200, the Pixy camera offers several advantages:

- Less sensitivity to ambient lighting variations
- Faster detection and processing
- Built-in color recognition and object tracking
- Ability to provide spatial information (X and Y coordinates)

These advantages make the Pixy camera more suitable for advanced automation and vision-based applications.

7. RESULTS

The color sensor-based system was capable of detecting basic colors; however, its performance was highly influenced by lighting conditions and sensor calibration. Changes in ambient light caused fluctuations in RGB readings, which occasionally resulted in incorrect color identification.

The Pixy Cam system showed significantly better performance. After proper training, the Pixy Cam reliably detected colored objects and provided stable output even with moderate lighting variations. The camera was able to track objects in real time and accurately differentiate between multiple color signatures.

Overall, the Pixy Cam-based approach demonstrated higher accuracy, faster response time, and better robustness compared to the conventional color sensor system.




Figure 1. Arduino Serial Monitor shows RGB Values




Figure 2. Python Plotting Graph After Reading Serial

050 by Adafruit

the MPU6050 sensors in the
duino library for the MPU6050
adafruit shop

REMOVE

```
ID:1,X:115,Y:122,W:67,H:51  
ID:1,X:139,Y:125,W:91,H:46  
ID:1,X:113,Y:121,W:66,H:52  
ID:1,X:128,Y:122,W:92,H:54  
ID:1,X:112,Y:117,W:69,H:53  
ID:1,X:122,Y:121,W:86,H:56  
ID:1,X:127,Y:119,W:101,H:47  
ID:1,X:110,Y:122
```

Figure 3. Arduino Serial Monitor Reading From PixyCAM

8. DISCUSSIONS

The experiment successfully implemented and compared two distinct approaches for automated color and object recognition: a conventional color sensor system using the TCS3200 and a vision-based system utilizing the Pixy v1 Smart Vision Sensor. The results demonstrated a clear difference in performance and practicality between the two technologies. The TCS3200-based system, which relied on the Arduino to read raw RGB frequency data and subsequent interpretation by a Python program, was highly susceptible to ambient lighting conditions. Fluctuations in the environment caused inconsistencies in the RGB readings, frequently leading to inaccurate color identification. In contrast, the Pixy v1 Camera system, which was trained to recognize specific color signatures using PixyMon and communicated object block data (ID, X, Y, Width, Height) via SPI, exhibited significantly superior performance. The camera's on-board image processing capability allowed it to reliably detect and track objects, providing a stable and accurate output even with moderate lighting variations. Therefore, the Pixy Cam approach proved to be a more robust and faster solution for real-time object tracking and differentiation, establishing its higher efficacy for integration into a complex mechatronics system compared to the basic TCS3200 color sensor. Future improvements for the TCS3200 system would require better calibration and environmental control using enclosures, while the Pixy Cam system's performance could be further optimized by integrating it with actuators or other sensors for automated responses.

9. CONCLUSION

This experiment successfully implemented a color detection system using a Pixy camera and Arduino. The Pixy camera demonstrated accurate and consistent color detection with minimal processing required from the microcontroller. Its AI-based color recognition capability provided superior performance compared to traditional color sensors, especially under varying lighting conditions. Although proper calibration is essential for optimal performance, the Pixy camera proved to be an effective and reliable solution for real-time color detection tasks. The results indicate that vision-based color detection systems are well-suited for applications in robotics, automated inspection, and intelligent sorting systems.

10. RECOMMENDATION

To improve the color sensor system, better calibration techniques and controlled lighting environments are suggested. Enclosures and light shields can help reduce interference from ambient lighting.

Additional improvements to the Pixy Cam system can include optimizing color signatures, increasing object contrast, and fine-tuning camera placement. Future work may also include integrating actuators like motors or servos to enable automated responses based on detected colors. Combining Pixy Cam data with other sensors could improve system reliability and performance.

REFERENCES

DFRobot. (n.d.). *Gravity: HUSKYLENS AI Machine Vision Sensor - DFRobot Wiki*. DFRobot Wiki. Retrieved from https://wiki.dfrobot.com/HUSKYLENS_V1.0_SKU_SEN0305_SEN0336

DFRobot. (n.d.). *Gravity: HuskyLens K210 AI Camera (No-Code Vision Sensor for STEM, Arduino & micro:bit)*. DFRobot. Retrieved from <https://www.dfrobot.com/product-1922.html>

How To Mechatronics. (n.d.). *Arduino color sensing tutorial TCS230/TCS3200 color sensor*. Retrieved from <https://howtomechatronics.com/tutorials/arduino/arduino-color-sensing-tutorial-tcs230-tcs3200-color-sensor/>

HuskyLens Tutorial - Getting Started with Husky Lens - AI Vision Sensor [Video]. (2019, July 8). YouTube. <https://www.youtube.com/watch?v=HZxFj2u9k00>

APPENDICES

Appendix A

Arduino code Part 1

```
// TCS230 or TCS3200 pins wiring
to Arduino
#define S0 4
#define S1 5
#define S2 6
#define S3 7
#define sensorOut 8

// Stores frequency read by the
photodiodes
int redFrequency = 0;
int greenFrequency = 0;
int blueFrequency = 0;

void setup() {
    // Setting the outputs
    pinMode(S0, OUTPUT);
    pinMode(S1, OUTPUT);
    pinMode(S2, OUTPUT);
    pinMode(S3, OUTPUT);

    // Setting the sensorOut as an
input
    pinMode(sensorOut, INPUT);

    // Setting frequency scaling to
20%
    digitalWrite(S0,HIGH);
    digitalWrite(S1,LOW);

    // Begins serial communication
    Serial.begin(9600);
}

void loop() {
    // Setting RED (R) filtered
```

```
    // Reading the output frequency
    redFrequency =
pulseIn(sensorOut, LOW);

    // Printing the RED (R) value
    Serial.print("R = ");
    Serial.print(redFrequency);
    delay(100);

    // Setting GREEN (G) filtered
photodiodes to be read
    digitalWrite(S2,HIGH);
    digitalWrite(S3,HIGH);

    // Reading the output frequency
    greenFrequency =
pulseIn(sensorOut, LOW);

    // Printing the GREEN (G) value
    Serial.print(" G = ");
    Serial.print(greenFrequency);
    delay(100);

    // Setting BLUE (B) filtered
photodiodes to be read
    digitalWrite(S2,LOW);
    digitalWrite(S3,HIGH);

    // Reading the output frequency
    blueFrequency =
pulseIn(sensorOut, LOW);

    // Printing the BLUE (B) value
    Serial.print(" B = ");
    Serial.println(blueFrequency);
    delay(100);
```

```
photodiodes to be read
```

```
digitalWrite(S2,LOW);
```

```
digitalWrite(S3,LOW);
```

```
}
```


Python code Part 1

```

import serial
import time
import matplotlib.pyplot as plt
from collections import deque

# ===== SERIAL CONNECTION =====
arduino_port = 'COM7' # CHANGE THIS
baud_rate = 9600
ser = serial.Serial(arduino_port,
baud_rate)
time.sleep(2)

# ===== DATA STORAGE =====
max_points = 60
r_data = deque(maxlen=max_points)
g_data = deque(maxlen=max_points)
b_data = deque(maxlen=max_points)

# ===== PLOT SETUP =====
plt.ion()
fig, ax = plt.subplots()

line_r, = ax.plot([], [],
label="Red")
line_g, = ax.plot([], [],
label="Green")
line_b, = ax.plot([], [],
label="Blue")

ax.set_title("Real-Time RGB Color
Sensor Plot")
ax.set_xlabel("Sample Number")
ax.set_ylabel("Frequency Output")
ax.legend()
ax.grid(True)

print("Connected. Reading RGB
data...")

# ===== MAIN LOOP =====
while True:
    try:
        line =
ser.readline().decode().strip()

        if line:
            print("Received:", line)

            parts =
line.replace("=", "").split()
            r = int(parts[1])
            g = int(parts[3])

```

```

# ===== MAIN LOOP =====
while True:
    try:
        line =
ser.readline().decode().strip()

        if line:
            print("Received:", line)

            parts =
line.replace("=", "").split()
            r = int(parts[1])
            g = int(parts[3])
            b = int(parts[5])

            r_data.append(r)
            g_data.append(g)
            b_data.append(b)

            x = range(len(r_data))

            line_r.set_data(x,
r_data)
            line_g.set_data(x,
g_data)
            line_b.set_data(x,
b_data)

            ax.relim()
            ax.autoscale_view()

            plt.pause(0.05)

    except KeyboardInterrupt:
        print("Stopped by user")
        break

ser.close()
plt.ioff()
plt.show()

```

Arduino code Part 2

```
#include <Pixy.h>

Pixy pixy; // Pixy v1 object

const int LED_PIN = 7;

void setup() {
  Serial.begin(9600);
  pixy.init();

  pinMode(LED_PIN, OUTPUT);
  digitalWrite(LED_PIN, LOW);

  Serial.println("Pixy v1 Ready");
}

void loop() {
  int32_t blocks =
  pixy.getBlocks();

  if (blocks > 0) {
    // Read the first detected
    block
    int sig =
  pixy.blocks[0].signature;
    int x   = pixy.blocks[0].x;
    int y   = pixy.blocks[0].y;
    int w   =
  pixy.blocks[0].width;
    int h   =
  pixy.blocks[0].height;
```

```
    // Print data for Python or
    Serial Monitor
    Serial.print("ID:");
    Serial.print(sig);
    Serial.print(",X:");
    Serial.print(x);
    Serial.print(",Y:");
    Serial.print(y);
    Serial.print(",W:");
    Serial.print(w);
    Serial.print(",H:");
    Serial.println(h);

    digitalWrite(LED_PIN, HIGH);
    // turn on LED if any color found
  }
  else {
    digitalWrite(LED_PIN, LOW);
    // no object detected
  }

  delay(50);
}
```

ACKNOWLEDGEMENT

We would like to sincerely thank the instructors, Assoc. Prof. Eur. Ing. Ir. Ts. Gs. Inv. Dr. Zulkifli Bin Zainal Abidin & Dr. Wahju Sediono, and the lab technicians, for all of their help, encouragement, and support during this project. Their knowledge and perceptions have greatly influenced the course of this work. Additionally, we would like to express our gratitude to our peers for their support and cooperation, both of which were crucial to the accomplishment of this project.

STUDENTS DECLARATION

We hereby declare that, except for the places where it is acknowledged, all of the work presented in this report is entirely ours. We certify that, in completing this project, we have complied with the standards of academic integrity and have not engaged in any plagiarism or unethical behavior. Every information and support source used in this work has been appropriately referenced and acknowledged.

Certificate of Originality and Authenticity

This is to certify that we are **responsible** for the work submitted in this report, that **the original work** is our own except as specified in the references and acknowledgment, and that the original work contained herein has not been untaken or done by unspecified sources or persons. We hereby certify that this report has **not been done by only one individual, and all of us have contributed to the report**. The length of contribution to the reports by each individual is noted within this certificate. We also hereby certify that we have **read and understand** the content of the total report, and no further improvement on the reports is needed from any of the individual contributors to the report. We therefore agreed unanimously that this report shall be submitted for **marking**, and this **final printed report** has been **verified by us**.

Signature: *haikalzulhilmi*

Read [/]

Name: Muhammad Haikal Zulhilmi Bin Fairof

Understand [/]

Matric Number: 2313025

Agree [/]

Signature: *faizizwan*

Read [/]

Name: Muhammd Faiz Izwan Bin Nor Effendi

Understand [/]

Matric Number: 2313509

Agree [/]

Signature: *Ainul Jaariah*

Read [/]

Name: Ainul Jaariah Binti Aliudin

Understand [/]

Matric Number: 2312664

Agree [/]