

WL Insulated Case Circuit Breaker

Ratings for UL489 Listed Breakers

WL frame ratings – frame size 1		800A			1200A			1600A			2000A		
Rating Class		S	H	L	S	H	L	S	H	L	S	H	L
Interrupting current frame Ics (kAIR RMS) 50/60 Hz	240VAC	65	85	100	65	85	100	65	85	100	65	85	100
	480VAC	65	85	100	65	85	100	85	85	100	65	85	100
	600VAC	65	65	65	65	65	65	65	65	65	65	65	65
Short-time current Icw (kA RMS)	0.4 sec.	65	65	65	65	65	65	65	65	65	65	65	65
Extended instantaneous protection rating (kA RMS)	480VAC	65	85	100	65	85	100	65	85	100	65	85	100
	600VAC	65	65	65	65	65	65	65	65	65	65	65	65
Close and latch rating (kA RMS)		65	65	65	65	65	65	65	65	65	65	65	65
Applicable rating plug range		200 - 800A			200 - 1200A			200 - 1600A			200 - 2000A		
Mechanical make-time (ms)		35			35			35			35		
Mechanical break-time (ms)		34			34			34			34		
Electric close make-time (ms)		50			50			50			50		
Electric trip/ UV break-time (ms)		40/73			40/73			40/73			40/73		
Electric trip and reclose interval (ms)		80			80			80			80		
Mechanical duty cycles (no maint.)		7500			7500			7500			7500		
Electrical duty cycles (no maint.)		7500			7500			7500			7500		
Draw-out breaker efficiency (Watts loss at In)		80			180			350			530		
Fixed-mount breaker efficiency (Watts loss at In)		60			120			160			270		
Ambient operating temperature (°C)		-25 to 40			-25 to 40			-25 to 40			-25 to 40		

WL frame ratings – frame size 2		800A			1200A			1600A			2000A			2500A		3000A	
Rating Class		S	L	C	S	L	C	S	L	C	S	L	C	L	C	L	C
Interrupting current frame Ics (kAIR RMS) 50/60 Hz	240VAC	65	100	150	65	100	150	65	100	150	65	100	150	100	150	100	150
	480VAC	65	100	150	65	100	150	65	100	150	65	100	150	100	150	100	150
	600VAC	65	85	100	65	85	100	65	85	100	65	85	100	85	100	85	100
Short-time current Icw (kA RMS)	0.4 sec.	65	85	100	65	85	100	65	85	100	65	85	100	85	100	85	100
Extended instantaneous protection rating (kA RMS)	480VAC	65	100	150	65	100	150	65	100	150	65	100	150	100	150	100	150
	600VAC	65	85	100	65	85	100	65	85	65	65	85	100	85	100	85	100
Close and latch rating (kA RMS)		65	85	100	65	85	100	65	85	100	65	85	100	85	100	85	100
Applicable rating plug range		200 - 800A			200 - 1200A			200 - 1600A			200 - 2000A			200 - 2500A		200 - 3000A	
Mechanical make-time (ms)		35			35			35			35			35		35	
Mechanical break-time (ms)		34			34			35			34			34		34	
Electric close make-time (ms)		50			50			50			50			50		50	
Electric trip/ UV break-time (ms)		40/73			40/73			40/73			40/73			40/73		40/73	
Electric trip and reclose interval (ms)		80			80			80			80			80		80	
Mechanical duty cycles (no maint.)		10,000 (5000 for Class C)			10,000 (5000 for Class C)			10,000 (5000 for Class C)			10,000 (5000 for Class C)			10,000 (5000 for Class C)		10,000 (5000 for Class C)	
Electrical duty cycles (no maint)		7500 (5000 for Class C)			7500 (5000 for Class C)			7500 (5000 for Class C)			4000			4000		4000	
Draw-out breaker efficiency (Watts loss at In)		85			150			320			500			680		1000	
Fixed-mount breaker efficiency (Watts loss at In)		40			80			120			230			320		480	
Ambient operating temperature (°C)		-25 to 40			-25 to 40			-25 to 40			-25 to 40			-25 to 40		-25 to 40	

Note: Frame Size 1 H-Class only for switches

WL Insulated Case Circuit Breaker

Ratings for UL489 Listed Breakers

WL frame ratings – Frame size 3		4000A		5000A	
Rating Class		L	C	L	C
Interrupting current frame lcs (kAIR RMS) 50/60 Hz	240VAC	100	150	100	150
	480VAC	100	150	100	150
	600VAC	85	100	85	100
Short-time current /cw (kA RMS)	0.4 sec.	85	100	85	100
Extended instantaneous protection rating (kA RMS)	480VAC	100	150	100	150
	600VAC	85	100	85	100
Close and latch rating (kA RMS)		85	100	85	100
Applicable rating plug range		800 - 4000A		800 - 5000A	
Mechanical make-time (ms)		35		35	
Mechanical break-time (ms)		34		34	
Electric close make-time (ms)		50		50	
Electric trip/ UV break-time (ms)		40/73		40/73	
Electric trip and reclose interval (ms)		80		80	
Mechanical duty cycles (no maint.)		5000		5000	
Electrical duty cycles (no maint.)		2000		2000	
Draw-out breaker efficiency (Watts loss at I _n)		1100		1100	
Fixed-mount breaker efficiency (Watts loss at I _n)		580		580	
Ambient operating temperature (°C)		-25 to 40		-25 to 40	

Ratings for UL489 Listed non-automatic switches

WL frame ratings		Frame size 1 800-2000A	Frame size 2 800 - 3000A	Frame size 3 4000/5000A
Rating Class		L	L	L
Breaking capacity with external relay (kA RMS) 50/60 Hz, instantaneous trip	240VAC	100	100	100
	480VAC	100	100	100
	600VAC	85	85	85
Short-time current /cw (kA RMS)	0.4 sec.	85	85	85

WL Insulated Case Circuit Breaker

UL 489 Listed Catalog Number

Interrupting rating, frame size, breaker type and frame rating

Note: Cradle must be ordered separately for drawout breaker types (see page 39)

Class	Interrupt rating (kA)		Frame Max ampere rating (A)1	Frame size			Breaker type		Breaker catalog number														
	240VAC 480VAC	600VAC		1	2	3	Fixed mount	Drawout	↑	↑	↑	↑	↑	↑	↑	↑	↑	↑	↑	↑	↑	↑	↑
S	65	65	800	X			X		S	1	F	3	0	8									
S	65	65	800		X		X		S	2	F	3	0	8									
S	65	65	800	X				X	S	1	D	3	0	8									
S	65	65	800		X			X	S	2	D	3	0	8									
S	65	65	1200	X			X		S	1	F	3	1	2									
S	65	65	1200		X		X		S	2	F	3	1	2									
S	65	65	1200	X				X	S	1	D	3	1	2									
S	65	65	1200		X			X	S	2	D	3	1	2									
S	65	65	1600	X			X		S	1	F	3	1	6									
S	65	65	1600		X		X		S	2	F	3	1	6									
S	65	65	1600	X				X	S	1	D	3	1	6									
S	65	65	1600		X			X	S	2	D	3	1	6									
S	65	65	2000	X			X		S	1	F	3	2	0									
S	65	65	2000		X		X		S	2	F	3	2	0									
S	65	65	2000	X				X	S	1	D	3	2	0									
S	65	65	2000		X			X	S	2	D	3	2	0									
L	100	65	800	X			X		L	1	F	3	0	8									
L	100	85	800		X		X		L	2	F	3	0	8									
L	100	65	800	X				X	L	1	D	3	0	8									
L	100	85	800		X			X	L	2	D	3	0	8									
L	100	65	1200	X			X		L	1	F	3	1	2									
L	100	85	1200		X		X		L	2	F	3	1	2									
L	100	65	1200	X				X	L	1	D	3	1	2									
L	100	85	1200		X			X	L	2	D	3	1	2									
L	100	65	1600	X			X		L	1	F	3	1	6									
L	100	85	1600		X		X		L	2	F	3	1	6									
L	100	65	1600	X				X	L	1	D	3	1	6									
L	100	85	1600		X			X	L	2	D	3	1	6									
L	100	65	2000	X			X		L	1	F	3	2	0									
L	100	85	2000		X		X		L	2	F	3	2	0									
L	100	65	2000	X				X	L	1	D	3	2	0									
L	100	85	2000		X			X	L	2	D	3	2	0									
L	100	85	2500		X		X		L	2	F	3	2	5									
L	100	85	2500		X			X	L	2	D	3	2	5									
L	100	85	3000		X		X		L	2	F	3	3	0									
L	100	85	3000		X			X	L	2	D	3	3	0									
L	100	85	4000			X	X		L	3	F	3	4	0									
L	100	85	4000			X		X	L	3	D	3	4	0									
L	100	85	5000			X	X		L	3	F	3	5	0									
L	100	85	5000			X		X	L	3	D	3	5	0									
C	150	100	800		X		X		C	2	F	3	0	8									
C	150	100	800		X			X	C	2	D	3	0	8									
C	150	100	1200		X		X		C	2	F	3	1	2									
C	150	100	1200		X			X	C	2	D	3	1	2									
C	150	100	1600		X		X		C	2	F	3	1	6									
C	150	100	1600		X			X	C	2	D	3	1	6									
C	150	100	2000		X		X		C	2	F	3	2	0									
C	150	100	2000		X			X	C	2	D	3	2	0									
C	150	100	2500		X		X		C	2	F	3	2	5									
C	150	100	2500		X			X	C	2	D	3	2	5									
C	150	100	3000		X		X		C	2	F	3	3	0									
C	150	100	3000		X			X	C	2	D	3	3	0									
C	150	100	4000			X	X		C	3	F	3	4	0									
C	150	100	4000			X		X	C	3	D	3	4	0									
C	150	100	5000			X	X		C	3	F	3	5	0									
C	150	100	5000			X		X	C	3	D	3	5	0									

WL Insulated Case Circuit Breaker

UL 489 Listed Catalog Number

Rating Plug

Breaker catalog number

Maximum continuous current rating	For use with frame size			Breaker catalog number														
	1	2	3	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15
200	X	X									A							
225	X	X									B							
250	X	X									C							
300	X	X									D							
315	X	X									E							
350	X	X									F							
400	X	X									G							
450	X	X									H							
500	X	X									J							
600	X	X									K							
630	X	X									L							
700	X	X									M							
800	X	X	X								N							
1000	X	X	X								P							
1200	X	X	X								Q							
1250	X	X	X								R							
1600	X	X	X								T							
2000	X	X	X								U							
2500		X	X								V							
3000		X	X								W							
3200			X								Y							
4000			X								Z							
5000			X								1							

Electronic trip unit (ETU)¹⁾

Trip unit models	Function			LCD display Alpha num.	Ground fault		EMC filter	
	L	S	I		Alarm	Trip		
ETU745	X	(X)	(X)					C
ETU745	X	(X)	(X)	X				D
ETU745	X	(X)	(X)		X			E
ETU745	X	(X)	(X)	X	X			F
ETU745	X	(X)	(X)		X	X		G
ETU745	X	(X)	(X)	X	X	X		H
ETU745	X	(X)	(X)				X	3
ETU745	X	(X)	(X)	X			X	4
ETU745	X	(X)	(X)		X		X	5
ETU745	X	(X)	(X)	X	X		X	6
ETU745	X	(X)	(X)		X	X	X	7
ETU745	X	(X)	(X)	X	X	X	X	8
ETU776	X	(X)	(X)					V
ETU776	X	(X)	(X)		X			W
ETU776	X	(X)	(X)		X	X		Y
ETU776	X	(X)	(X)				X	M
ETU776	X	(X)	(X)		X		X	Z
ETU776	X	(X)	(X)		X	X	X	1

(X) Indicates function can be disabled by user

1 Neutral protection "N" is available as standard.

WL Insulated Case Circuit Breaker

UL 489 Listed Catalog Number

Bell alarm, breaker ready-to-close, auxiliary contacts						Breaker catalog number														
Remote reset coil voltage		Form C contacts	Breaker ready-to-close 1b contact	Breaker open/close auxiliary switches		None	9	10	11	12	13	14	15							
AC	DC			2a + 2b	4a + 4b															
		X																		X
			X																	A
																				B
				X																C
					X															D
		X	X																	E
		X		X																F
		X			X															G
			X	X																H
			X		X															I
		X	X	X																J
		X	X		X															K
	24	X																		L
	48	X																		M
120	125	X																		N
240	250	X																		O
	24	X	X																	P
	48	X	X																	Q
120	125	X	X																	R
240	250	X	X																	S
	24	X		X																T
	48	X		X																U
120	125	X		X																V
240	250	X		X																W
	24	X			X															Y
	48	X			X															Z
120	125	X			X															1
240	250	X			X															2
	24	X	X	X																3
	48	X	X	X																4
120	125	X	X	X																5
240	250	X	X	X																6
	24	X	X		X															7
	48	X	X		X															8
120	125	X	X		X															9
240	250	X	X		X															0

Shunt trip

Operation voltage		Status contact	Continuous duty coil (electrical interlock)	None	X
AC	DC				
	24				A
	48				B
120	125				C
240	250				D
	24	X			E
	48	X			F
120	125	X			G
240	250	X			H
	24		X		J
	48		X		K
120	125		X		L
240	250		X		M
	24	X	X		N
	48	X	X		P
120	125	X	X		R
240	250	X	X		S

WL Insulated Case Circuit Breaker

UL 489 Listed Catalog Number

Undervoltage Release (with or without time delay) or 2nd Shunt Trip						Breaker catalog number														
Operation voltage		UVR without delay	UVR with delay	UVR status ¹ contact (1NO)	2nd shunt trip															
AC	DC					1	2	3	4	5	6	7	8	9	10	11	12	13	14	15
						None										X				
	24	X															A			
	48	X															B			
120	125	X															C			
240	250	X															D			
	48		X														E			
120	125		X														F			
240	250		X														G			
	24				X												H			
	48				X												J			
120	125				X												K			
240	250				X												L			
	24	X		X													M			
	48	X		X													N			
120	125	X		X													P			
240	250	X		X													Q			
	48		X	X													R			
120	250		X	X													S			
240	250		X	X													T			

Charging motor, motor switch, operations counter

Charging motor operation voltage		Motor cut-off switch	Operations counter															
AC	DC																	
				None													X	
	24																A	
	48																B	
120	125																C	
240	250																D	
	24	X															E	
	48	X															F	
120	125	X															G	
240	250	X															H	
	24		X														J	
	48		X														K	
120	125		X														L	
240	250		X														M	
	24	X	X														N	
	48	X	X														P	
120	125	X	X														Q	
240	250	X	X														R	

¹ Status contact is only available when Communications is not installed on breaker. Signal is sent via communications in lieu of status contact.

WL Insulated Case Circuit Breaker

UL 489 Listed Catalog Number

Close coil, power metering and communications

Close coil operation voltage		Power metering capable	Modbus	PROFIBUS	Modbus TCP/ / PROFINET	Breaker catalog number														
						1	2	3	4	5	6	7	8	9	10	11	12	13	14	15
AC	DC					None														
	24																		X	
	48																		A	
120	125																		B	
240	250																		C	
			X																D	
				X															G	
					X														H	
	24		X																E	
	24			X															N	
	48		X																P	
	48			X															S	
120	125		X																T	
120	125			X															W	
120	125				X														Y	
240	250		X																J	
240	250			X															2	
	24	X	X																3	
	48	X	X																Q	
120	125	X	X																U	
240	250	X	X																Z	
	24	X		X															4	
	24	X			X														R	
	48	X				X													6	
	48	X		X															V	
120	125	X			X														7	
120	125	X				X													1	
240	250	X			X														9	
240	250	X				X													5	
		X	X																O	
		X																	L	
		X		X															M	
		X																	F	
		X			X														K	
120	125	X																	8	

Breaker locks

Key lock breaker OPEN position (lock type – KIRK) ¹	Key lock breaker OPEN position (lock type – SUPERIOR) ¹	Padlock provisions for OPEN and CLOSE push buttons ²	Padlock provisions for charging handle ²	
			None	X
X				A
		X		C
	X		X	E
X		X		F
	X	X		G
X			X	J
	X		X	S
		X	X	U
X		X	X	V
	X	X	X	W
		X	X	Z

Miscellaneous options

Key lock breaker OPEN position (provision only) ²	Manual trip reset ETU (Automatic trip reset is standard)	
	None	N
X		B
	X	C
X	X	D

¹ Custom key locks are not available and must be supplied by others. Order key lock provision if custom if keyed alike locks are required.

² Locks provided by others.

WL Insulated Case Switch

UL 489 Listed Non-automatic Catalog Number

Breaking capacity, frame size, switch type and frame rating

Breaking capacity, frame size, switch type and frame rating									Switch catalog number															
Class	Breaking capacity (kA)		Frame	Frame size			Switch type		1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	
	240VAC 480VAC	600VAC	Max ampere rating (A)	1	2	3	Fixed mounted	drawout																
L	100	85	800	X			X		L	1	Y	3	0	8	S	S								
L	100	85	800	X				X	L	1	Z	3	0	8	S	S								
L	100	85	1200	X			X		L	1	Y	3	1	2	S	S								
L	100	85	1200	X				X	L	1	Z	3	1	2	S	S								
L	100	85	1600	X			X		L	1	Y	3	1	6	S	S								
L	100	85	1600	X				X	L	1	Z	3	1	6	S	S								
L	100	85	2000	X			X		L	1	Y	3	2	0	S	S								
L	100	85	2000	X				X	L	1	Z	3	2	0	S	S								
L	100	85	800		X		X		L	2	Y	3	0	8	S	S								
L	100	85	800		X			X	L	2	Z	3	0	8	S	S								
L	100	85	1600		X		X		L	2	Y	3	1	6	S	S								
L	100	85	1600		X			X	L	2	Z	3	1	6	S	S								
L	100	85	2000		X		X		L	2	Y	3	2	0	S	S								
L	100	85	2000		X			X	L	2	Z	3	2	0	S	S								
L	100	85	2500		X			X	L	2	Y	3	2	5	S	S								
L	100	85	2500		X			X	L	2	Z	3	2	5	S	S								
L	100	85	3000		X		X		L	2	Y	3	3	3	S	S								
L	100	85	3000		X		X		L	2	Z	3	3	0	S	S								
L	100	85	4000		X		X		L	3	Y	3	4	0	S	S								
L	100	85	4000			X		X	L	3	Z	3	4	0	S	S								
L	100	85	5000			X	X		L	3	Y	3	5	0	S	S								
L	100	85	5000			X		X	L	3	Z	3	5	0	S	S								

Ready-to-close and auxiliary contacts

Ready-to-close		Breaker open/close auxiliary switches	
1b contact		2a + 2b	4a + 4b
			None
X			
	X		
		X	
X	X		
X		X	

WL Insulated Case Switch

UL 489 Listed Non-automatic Catalog Number

Shunt trip					Switch catalog number															
					1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	
Operation voltage		Status contact ¹	Shunt trip	Continuous duty rated (electrical interlock)																
AC	DC				None												X			
	24		X												A					
	48		X												B					
120	125		X												C					
240	250		X												D					
	24	X	X												E					
	48	X	X												F					
120	125	X	X												G					
240	250	X	X												H					
	24			X											J					
	48			X											K					
120	125			X											L					
240	250			X											M					
	24	X		X											N					
	48	X		X											P					
120	125	X		X											R					
240	250	X		X											S					

Undervoltage release (with or without time delay) or 2nd shunt trip

Operation voltage		UVR without delay	UVR with delay	UVR status ¹ contact (1NO)	2nd shunt trip		
AC	DC						
					None		X
	24	X					A
	48	X					B
120	125	X					C
240	250	X					D
	48		X				E
120	125		X				F
240	250		X				G
	24				X		H
	48				X		J
120	125				X		K
240	250				X		L
	24	X		X			M
	48	X		X			N
120	125	X		X			P
240	250	X		X			Q
	48		X	X			R
120	250		X	X			S
240	250		X	X			T

¹ Status contact is only available when communication is not installed. Signal is sent via communications in lieu of status contact.

WL Insulated Case Switch

UL 489 Listed Non-automatic Catalog Number

Charging motor, motor switch and operation counter				Switch catalog number														
				1	2	3	4	5	6	7	8	9	10	11	12	13	14	15
Charging motor operation voltage		Motor cut-off switch	Operations counter															
AC	DC			None											X			
	24														A			
	48														B			
120	125														C			
240	250														D			
	24	X													E			
	48	X													F			
120	125	X													G			
240	250	X													H			
	24		X												J			
	48		X												K			
120	125		X												L			
240	250		X												M			
	24	X	X												N			
	48	X	X												P			
120	125	X	X												Q			
240	250	X	X												R			

Close coil, communications

Close coil operation voltage		Power metering capable	Modbus ¹	PROFIBUS ¹	Modbus TCP / PROFINET ¹											
AC	DC															
						None									X	
	24														A	
	48														B	
120	125														C	
240	250														D	
			X												G	
				X											H	
					X										E	
	24		X												N	
	24			X											P	
	48		X												S	
	48			X											T	
120	125		X												W	
120	125			X											Y	
120	125				X										J	
240	250		X												2	
240	250			X											3	
120	125	X													8	

¹ Requires 24VDC power supply. Power metering not available on non-automatic switches and BSS is included.

WL Insulated Case Switch

UL 489 Listed Non-automatic Catalog Number

Switch locks				Switch catalog number																
				1	2	3	4	5	6	7	8	9	10	11	12	13	14	15		
Key lock switch OPEN position (lock type – KIRK) ¹	Key lock switch OPEN position (lock type – SUPERIOR) ¹	Padlock provisions for OPEN and CLOSE push buttons ²	Padlock provisions for charging handle	None														X		
X																		A		
		X																C		
			X															E		
	X																	F		
X		X																G		
	X	X																J		
X			X															S		
	X		X															U		
		X	X															V		
X		X	X															W		
	X	X	X															Z		
Miscellaneous options																				
Key lock switch OPEN position (provision only) ²				None														N		
X																		B		

¹ Custom key locks are not available and must be supplied by others. Order Key Lock Provisions if custom keys or keyed alike locks are required.

² Padlock provided by others.

WL Insulated Case Circuit Breaker

UL 489 Listed Accessories

External breaker accessories

Description		Catalog number
Front mount connectors for fixed breakers		
FS1, 85kAIC at 480V max.	800A, 1200A	WLHF12CONUL
FS2, 100kAIC at 480V max.	1600A	WLL2F16CONUL
FS2, 100kAIC at 480V max.	2000A	WLL2F20CONUL
FS2, 100kAIC at 480V max.	3000A	WLL2F30CONUL
FS3, 100kAIC at 480V max.	4000A, 5000A	WLL3F50CONUL
Mechanical lug		
FS1, 65kAIC at 480V max	800A, 1200A	WLS2P12CONUL
FS2, 65kAIC at 480V max	1600A, 2000A	WLS2P20CONUL
Rear vertical connectors		
FS1, 100kAIC at 480V max	800A, 1200A, 1600A, 2000A	WLH1R12CONUL
FS2, 100kAIC at 480V max	800A, 1200A, 1600A	WLL2R16CONUL
FS2, 100kAIC at 480V max	2000A	WLL2R20CONUL
FS2, 1100kAIC at 480V max	2500A, 3000A	WLL2R30CONUL
FS2, 150kAIC at 480V max	800A, 1200A, 1600A, 2000A, 2500A, 3000A	WLC2R30CONUL
FS3, 150kAIC at 480V max	4000A, 5000A	WLC3R50CONUL
Single phase CTs for metering, 5A secondary		
Rating:	800:5	WLG800NMCT23
Rating:	1200:5	WLG1200NMCT23
Rating:	1600:5	WLG1600NMCT23
Rating:	2000:5	WLG2000NMCT23
Rating:	2500:5	WLG2500NMCT23
Rating:	3000:5	WLG3000NMCT23
Rating:	4000:5	WLG4000NMCT23
Rating:	5000:5	WLG5000NMCT23
Modified differential ground fault (MDGF) CTs		
Modified differential GF	(FS2 1200:1) Phase CT	WLGMDGFCT2
Modified differential GF	(FS3 1200:1) Phase CT	WLGMDGFCT3
Modified differential GF	(FS2 and FS3 1200:1) Neutral CT	WLGNMDFCT23
4-wire residual ground fault sensor		
Without copper bus adapters (pass-thru mount) - for 3" max bus bar		WLNCT2
Without copper bus adapters (pass-thru mount) - for 3 - 5" max bus bar		WLNCT3
With copper bus adapters for bus bar connection - for 3" max bus bar		WLNCT2CB
With copper bus adapters for bus bar connection - for 3 - 5" max bus bar		WLCNMDGCT23
Mechanical interlocks		
Fixed mounted breaker (FS1)		WLNTLKF1
Fixed mounted breaker (FS2 and FS3)		WLNTLKF23
Miscellaneous external accessories		
Crimp lugs for 10# AWG secondary wiring (package of 70)		WL10RL
Auxiliary contact on drawout breaker (knife block)		WLCNMD
24V DC trip unit and communications power supply, 2.5A SITOP power, Class 2		WLSITOP25
24V DC trip unit and communications power supply 3.8A SITOP power, Class 2		WLSITOP1
Optional metric inserts and bolts for breaker mains (4 each) M8x25 for FS1 and FS2		WLMETRC
Optional metric inserts and bolts for breaker mains (4 each) M10x25 for FS3		WLMETRC3
Secondary disconnect coding kit for UL 489 fixed mounted breaker		WLCODEKITUL
Pull apart terminal block with 1 meter leads for UL 489 fix mounted breakers		WLTERMBLKUL

WL Insulated Case Breaker Cradles

UL 489 Listed Catalog Number

Interrupting rating, frame size, and frame rating							Cradle catalog number																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																													
							G	2	3	4	5	6	7	8	9	10	11	12	13	14	15																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																															
Class	Interrupt rating (kA)		Frame	Frame size																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																
	240VAC 480VAC	600VAC	Max ampere rating (A)	1	2	3																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																														
S	65	65	800	X			S	1	3	0	8																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																									

¹ Terminal blocks (X5, X6, X8, X9) are installed as standard.

WL Insulated Case Breaker Cradles

UL 489 Listed Catalog Number

				Cradle catalog number															
				G	2	3	4	5	6	7	8	9	10	11	12	13	14	15	
Arc chute covers															↑	↑	↑	↑	↑
None														X					
Arc chute covers				(FS1 only)										C					
Arc chute covers				(FS2 only)										D					
Arc chute covers				(FS3 only – except Class C)										B					
Door locks and mechanical interlocks																			
1. Mechanical interlock with 2.0 meter Bowden cable																			
2. Locks cubicle door, when breaker is in connect position				(FS2 and FS3)															
3. Locks cubicle door, when breaker is in connect position				(FS1 only)															
4. Locks against racking breaker if the cubicle door is open				(FS2 and FS3)															
1	2	3	4																
																X			
X																M			
	X															A			
		X														B			
			X													C			
X	X															D			
X	X		X													E			
X		X														F			
X			X													G			
	X		X													H			
Mechanism Operated Contacts (MOC)																			
Breaker open/close auxiliary switches (4a & 4b) in the following positions:																			
None																	X		
Test and Connect position				(FS1 and FS2 only)												M			
Connect position				(FS1 and FS2 only)												N			
Test and Connect position				(FS3 only)												P			
Connect position				(FS3 only)												Q			
Connector and heater options																			
Standard rear connectors																	X		
Standard rear connectors and a cradle heater				(FS2 and FS3)													H		
Rotatable rear connector				(FS1 and FS2 2000A and below, S Class)													J		
Rotatable rear connectors and a cradle heater				(FS2 2000A and below, S Class)													K		
Future use																			
Placeholder (required)																			N

WL Insulated Case Breaker Cradles

UL 489 Listed Accessories

Cradle accessories		Catalog number
3-phase metering CTs, cradle mounted (3 windows per CT)		
FS1 and FS2	Rating – 800:5	WLG8005MCT2
	Rating – 1200:5	WLG12005MCT2
	Rating – 1600:5	WLG16005MCT2
FS2	Rating – 2500:5	WLG25005MCT2
	Rating – 3000:5	WLG30005MCT2
FS3	Rating – 4000:5	WLG40005MCT3
	Rating – 5000:5	WLG50005MCT3

WL Power Circuit Breaker

Ratings for UL 1066 Listed (ANSI C37) Breakers

WL frame ratings – Frame size 2		800A					1600A				
Rating Class		N	S	H	L	F	N	S	H	L	F
Interrupting current frame <i>Ics</i> (kAIC RMS) 50/60 Hz	254VAC	50	65	85	100	200	50	65	85	100	200
	508VAC	50	65	85	100	200	50	65	85	100	200
	600VAC	—	—	—	—	200	—	—	—	—	200
	635VAC	50	65	65	85	—	50	65	65	85	—
Short-time current <i>Icw</i> (kA RMS)	1 sec.	50	65	65	85	—	50	65	65	85	—
Close and latch rating (kA RMS)		50	65	65	85	—	50	65	65	85	—
Applicable rating plug range		200 - 800A					200 - 1600A				
Mechanical make-time (ms)		35					35				
Mechanical break-time (ms)		34					34				
Electric close make-time (ms)		50					50				
Electric trip/ UV break-time (ms)		40/73					40/73				
Electric trip and reclose interval (ms)		80					80				
Mechanical duty cycles (with maint.) ¹		15,000					15,000				
Electrical duty cycles (with maint.) ¹		15,000					15,000				
Draw-out breaker efficiency (Watts loss at rated <i>I_n</i>)		85					320				
Draw-out fused breaker efficiency (Watts loss at rated <i>I_n</i>)		Consult factory					Consult factory				
Ambient operating temperature (°C)		-25 to 40					-25 to 40				

WL frame ratings – Frame size 2		2000A				3200A		
Rating Class		S	H	L	F	S	H	L
Interrupting current frame <i>Ics</i> (kAIC RMS) 50/60 Hz	254VAC	65	85	100	200	65	85	100
	508VAC	65	85	100	200	65	85	100
	600VAC	—	—	—	200	—	—	—
	635VAC	65	65	85	—	65	65	85
Short-time current <i>Icw</i> (kA RMS)	1 sec.	65	65	85	—	65	65	85
Close and latch rating (kA RMS)		65	65	85	—	65	65	85
Applicable rating plug range		200 - 2000A				200 - 3200A		
Mechanical make-time (ms)		35				35		
Mechanical break-time (ms)		34				34		
Electric close make-time (ms)		50				50		
Electric trip/ UV break-time (ms)		40/73				40/73		
Electric trip and reclose interval (ms)		80				80		
Mechanical duty cycles (with maint.) ¹		15,000				15,000		
Electrical duty cycles (with maint.) ¹		15,000				15,000		
Draw-out breaker efficiency (Watts loss at rated <i>I_n</i>)		700				1650		
Draw-out fused breaker efficiency (Watts loss at rated <i>I_n</i>)		Consult factory				Consult factory		
Ambient operating temperature (°C)		-25 to 40				-25 to 40		

¹ Maintenance means: replacing main contacts and arc chutes (see operating instructions).
M-Class main contacts can be replaced by Siemens personnel only.

WL Power Circuit Breaker

Ratings for UL 1066 Listed (ANSI C37) Breakers

WL frame ratings – Frame size 3WL frame		3200A		4000A				5000A				6000A		
Rating Class		M	F	H	L	M	F	H	L	M	F	H	L	M
Interrupting current frame I_{cs}	254VAC	150	200	85	100	150	200	85	100	150	200	85	100	150
(kAIC RMS) 50/60 Hz	508VAC	150	200	85	100	150	200	85	100	150	200	85	100	150
	600VAC	—	200	—	—	—	200	—	—	—	200	—	—	—
	635VAC	85	—	85	85	85	—	85	85	85	—	85	85	85
Short-time current I_{cw} (kA RMS)	1 sec.	100 ²	—	85	100 ²	100 ²	—	85	100 ²	100 ²	—	85	100 ²	100 ²
Close and latch rating (kA RMS)		100 ²	—	85	100 ²	100 ²	—	85	100 ²	100 ²	—	85	100 ²	100 ²
Applicable rating plug range		800 - 3200A		800 - 4000A				800 - 5000 A				800 - 6000 A		
Mechanical make-time (ms)		35		35				35				35		
Mechanical break-time (ms)		34		34				24				24		
Electric close make-time (ms)		50		50				50				50		
Electric trip/ UV break-time (ms)		40/73		40/73				40/73				40/73		
Electric trip and reclose interval (ms)		80		80				80				80		
Mechanical duty cycles (with maint.) ¹		10,000		10,000				10,000				10,000		
Electrical duty cycles (with maint.) ¹		10,000		10,000				10,000				10,000		
Draw-out breaker efficiency (Watts loss at rated I_n)		700		1100				1650				2375		
Draw-out fused breaker efficiency (Watts loss at rated I_n)		Consult factory		Consult factory				Consult factory				N/A		
Ambient operating temperature (°C)		-25 to 40		-25 to 40				-25 to 40				-25 to 40		

Ratings for UL 1066 Listed Non-automatic Switches

WL frame ratings		Frame size 2 800A - 3200A ⁴		Frame size 3 3200A - 6000A ⁴	
Rating Class		L	F ³	L	F ³
Breaking capacity with external relay (kA RMS)	254VAC	100	200	100	200
50/60 Hz, instantaneous trip	508VAC	100	200	100	200
	635VAC	85	200	85	200
Short-time current I_{cw} (kA RMS)	1 sec.	65	N/A	100	N/A

¹ Maintenance means: replacing main contacts and arc chutes (see operating instructions).

M-Class main contacts can be replaced by Siemens personnel only. Do not apply switch or breaker rated at 635VAC to a system with fault current > 85kA RMS.

² Short-time withstand current (I_{cw}) at 635 VAC is kAIC RMS.

³ Max. 600 VAC.

⁴ 3200A frame rating is only available in L-Class in Frame Size 2. 3200A frame rating is not available in L-Class in Frame Size 3.

WL Power Circuit Breaker

UL 1066 Listed Catalog Number

Interrupting rating, frame size, breaker type and frame rating (3-Pole Circuit Breakers)

Note: Cradle must be ordered separately (see page 54)

							Breaker catalog number															
Note: Cradle must be ordered separately (see page 54)							1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	
Class	Interrupt rating (kA)		Frame	Frame size		Fuse (A)	↑	↑	↑	↑	↑	↑										
	254VAC 508VAC	635VAC	Max ampere rating (A)	2	3																	
N	50	50	800	X			N	2	A	3	0	8										
N	50	50	1600	X			N	2	A	3	1	6										
S	65	65	800	X			S	2	A	3	0	8										
S	65	65	1600	X			S	2	A	3	1	6										
S	65	65	2000	X			S	2	A	3	2	0										
S	65	65	3200	X			S	2	A	3	3	2										
H	85	65	800	X			H	2	A	3	0	8										
H	85	65	1600	X			H	2	A	3	1	6										
H	85	65	2000	X			H	2	A	3	2	0										
H	85	65	3200	X			H	2	A	3	3	2										
H	85	85	4000		X		H	3	A	3	4	0										
H	85	85	5000		X		H	3	A	3	5	0										
H	85	85	6000		X		H	3	A	3	6	0										
L	100	85	800	X			L	2	A	3	0	8										
L	100	85	1600	X			L	2	A	3	1	6										
L	100	85	2000	X			L	2	A	3	2	0										
L	100	85	3200	X			L	2	A	3	3	2										
L	100	85	4000		X		L	3	A	3	4	0										
L	100	85	5000		X		L	3	A	3	5	0										
L	100	85	6000		X		L	3	A	3	6	0										
M	150	85	3200		X		M	3	A	3	3	2										
M	150	85	4000		X		M	3	A	3	4	0										
M	150	85	5000		X		M	3	A	3	5	0										
M	150	85	6000		X		M	3	A	3	6	0										
F	200	200	800	X		400	F	2	A	3	0	A										
F	200	200	800	X		600	F	2	A	3	0	B										
F	200	200	800	X		800	F	2	A	3	0	C										
F	200	200	800	X		900	F	2	A	3	0	D										
F	200	200	800	X		1000	F	2	A	3	0	E										
F	200	200	800	X		1200	F	2	A	3	0	F										
F	200	200	800	X		1600	F	2	A	3	0	G										
F	200	200	800	X		2000	F	2	A	3	0	H										
F	200	200	800	X		2500	F	2	A	3	0	J										
F	200	200	800	X		3000	F	2	A	3	0	K										
F	200	200	1600	X		400	F	2	A	3	1	A										
F	200	200	1600	X		600	F	2	A	3	1	B										
F	200	200	1600	X		800	F	2	A	3	1	C										
F	200	200	1600	X		900	F	2	A	3	1	D										
F	200	200	1600	X		1000	F	2	A	3	1	E										
F	200	200	1600	X		1200	F	2	A	3	1	F										
F	200	200	1600	X		1600	F	2	A	3	1	G										
F	200	200	1600	X		2000	F	2	A	3	1	H										
F	200	200	1600	X		2500	F	2	A	3	1	J										
F	200	200	1600	X		3000	F	2	A	3	1	K										
F	200	200	2000	X		400	F	2	A	3	2	A										
F	200	200	2000	X		600	F	2	A	3	2	B										
F	200	200	2000	X		800	F	2	A	3	2	C										
F	200	200	2000	X		900	F	2	A	3	2	D										
F	200	200	2000	X		1000	F	2	A	3	2	E										
F	200	200	2000	X		1200	F	2	A	3	2	F										
F	200	200	2000	X		1600	F	2	A	3	2	G										
F	200	200	2000	X		2000	F	2	A	3	2	H										
F	200	200	2000	X		2500	F	2	A	3	2	J										
F	200	200	2000	X		3000	F	2	A	3	2	K										
F	200	200	3200		X	6000	F	3	A	3	3	2										
F	200	200	4000		X	6000	F	3	A	3	4	0										
F	200	200	5000		X	6000	F	3	A	3	5	0										

WL Power Circuit Breaker

UL 1066 Listed Catalog Number

Interrupting rating, frame size, breaker type and frame rating (4-Pole Circuit Breakers)

Note: Cradle must be ordered separately (see page 54)

4-Pole Circuit Breakers)									Breaker catalog number															
Note: Cradle must be ordered separately (see page 54)									1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	
Class	Interrupt rating (kA)		Frame	Frame size		Fixed	Drawout	Neutral CT	↑	↑	↑	↑	↑	↑										
	254VAC 508VAC	635VAC	Max. ampere rating (A)	2	3																			
S	65	65	800	X			X	X	S	2	A	4	0	8										
S	65	65	800	X		X			S	2	H	4	0	8										
S	65	65	800	X			X		S	2	G	4	0	8										
S	65	65	800	X		X		X	S	2	K	4	0	8										
S	65	65	1600	X			X	X	S	2	A	4	1	6										
S	65	65	1600	X		X			S	2	H	4	1	6										
S	65	65	1600	X			X		S	2	G	4	1	6										
S	65	65	1600	X		X		X	S	2	K	4	1	6										
S	65	65	2000	X			X	X	S	2	A	4	2	0										
S	65	65	2000	X		X			S	2	H	4	2	0										
S	65	65	2000	X			X		S	2	G	4	2	0										
S	65	65	2000	X		X		X	S	2	K	4	2	0										
S	65	65	3200	X			X	X	S	2	A	4	3	2										
S	65	65	3200	X		X			S	2	H	4	3	2										
S	65	65	3200	X			X		S	2	G	4	3	2										
S	65	65	3200	X		X		X	S	2	K	4	3	2										
H	85	65	800	X			X	X	H	2	A	4	0	8										
H	85	65	800	X		X			H	2	H	4	0	8										
H	85	65	800	X			X		H	2	G	4	0	8										
H	85	65	800	X		X		X	H	2	K	4	0	8										
H	85	65	1600	X			X	X	H	2	A	4	1	6										
H	85	65	1600	X		X			H	2	H	4	1	6										
H	85	65	1600	X			X		H	2	G	4	1	6										
H	85	65	1600	X		X		X	H	2	K	4	1	6										
H	85	65	2000	X			X	X	H	2	A	4	2	0										
H	85	65	2000	X		X			H	2	H	4	2	0										
H	85	65	2000	X			X		H	2	G	4	2	0										
H	85	65	2000	X		X		X	H	2	K	4	2	0										
H	85	65	3200	X			X	X	H	2	A	4	3	2										
H	85	65	3200	X		X			H	2	H	4	3	2										
H	85	65	3200	X			X		H	2	G	4	3	2										
H	85	65	3200	X		X		X	H	2	K	4	3	2										
L	100	85	800	X			X	X	L	2	A	4	0	8										
L	100	85	800	X		X			L	2	H	4	0	8										
L	100	85	800	X			X		L	2	G	4	0	8										
L	100	85	800	X		X		X	L	2	K	4	0	8										
L	100	85	1600	X			X	X	L	2	A	4	1	6										
L	100	85	1600	X		X			L	2	H	4	1	6										
L	100	85	1600	X			X		L	2	G	4	1	6										
L	100	85	1600	X		X		X	L	2	K	4	1	6										
L	100	85	2000	X			X	X	L	2	A	4	2	0										
L	100	85	2000	X		X			L	2	H	4	2	0										
L	100	85	2000	X			X		L	2	G	4	2	0										
L	100	85	2000	X		X		X	L	2	K	4	2	0										
L	100	85	3200	X			X	X	L	2	A	4	3	2										
L	100	85	3200 ¹	X		X			L	2	H	4	3	2										
L	100	85	3200	X			X		L	2	G	4	3	2										
L	100	85	3200 ¹	X		X		X	L	2	K	4	3	2										
L	100	85	4000		X		X	X	L	3	A	4	4	0										
L	100	85	4000 ¹		X	X			L	3	H	4	4	0										
L	100	85	4000		X		X		L	3	G	4	4	0										
L	100	85	4000 ¹		X	X		X	L	3	K	4	4	0										
L	100	85	5000		X		X	X	L	3	A	4	5	0										
L	100	85	5000 ¹		X	X			L	3	H	4	5	0										
L	100	85	5000		X		X		L	3	G	4	5	0										
L	100	85	5000 ¹		X	X		X	L	3	K	4	5	0										
L	100	85	6000		X		X	X	L	3	A	4	6	0										
L	100	85	6000		X		X		L	3	G	4	6	0										

¹ FS2 3200A, FS3 4000A/5000A fixed mount breakers have vertical rear connectors included as standard.

WL Power Circuit Breaker

UL 1066 Listed Catalog Number

Rating plug			Breaker catalog number														
Maximum continuous current rating (A)	Frame size 2	Frame size 3	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15
200	X									A							
225	X									B							
250	X									C							
300	X									D							
315	X									E							
350	X									F							
400	X									G							
450	X									H							
500	X									J							
600	X									K							
630	X									L							
700	X									M							
800	X	X								N							
1000	X	X								P							
1200	X	X								Q							
1250	X	X								R							
1600	X	X								T							
2000	X	X								U							
2500	X	X								V							
3000	X	X								W							
3200	X	X								Y							
4000		X								Z							
5000		X								1							
6000		X								2							

Electronic trip units (ETU)

Trip unit models	Protective function			LCD display alpha num.	Ground fault		EMC filter	
	L	S	I		Alarm	Trip		
ETU745	X	(X)	(X)					C
ETU745	X	(X)	(X)	X				D
ETU745	X	(X)	(X)		X			E
ETU745	X	(X)	(X)	X	X			F
ETU745	X	(X)	(X)		X	X		G
ETU745	X	(X)	(X)	X	X	X		H
ETU745	X	(X)	(X)				X	3
ETU745	X	(X)	(X)	X			X	4
ETU745	X	(X)	(X)		X		X	5
ETU745	X	(X)	(X)	X	X		X	6
ETU745	X	(X)	(X)		X	X	X	7
ETU745	X	(X)	(X)	X	X	X	X	8
ETU776	X	(X)	(X)					V
ETU776	X	(X)	(X)		X			W
ETU776	X	(X)	(X)		X	X		Y
ETU776	X	(X)	(X)				X	M
ETU776	X	(X)	(X)		X		X	Z
ETU776	X	(X)	(X)		X	X	X	1

() Function can be disabled by user.

WL Power Circuit Breaker

UL 1066 Listed Catalog Number

Bell alarm, breaker ready-to-close, auxiliary contacts						Breaker catalog number														
Remote reset coil voltage		Form C contacts	Breaker ready-to-close 1b contact	Breaker open/close auxiliary switches																
AC	DC			2a + 2b	4a + 4b															
						None														X
		X																		A
			X																	B
				X																C
					X															D
		X	X																	E
		X		X																F
		X			X															G
			X	X																H
			X		X															I
		X	X	X																J
		X	X		X															K
	24	X																		L
	48	X																		M
120	125	X																		N
240	250	X																		O
	24	X	X																	P
	48	X	X																	Q
120	125	X	X																	R
240	250	X	X																	S
	24	X		X																T
	48	X		X																U
120	125	X		X																V
240	250	X		X																W
	24	X			X															Y
	48	X			X															Z
120	125	X			X															1
240	250	X			X															2
	24	X	X	X																3
	48	X	X	X																4
120	125	X	X	X																5
240	250	X	X	X																6
	24	X	X		X															7
	48	X	X		X															8
120	125	X	X		X															9
240	250	X	X		X															0

Shunt trip

Control voltage		Status contact	Continuous duty coil (electrical interlock)																	
AC	DC																			
				None																X
	24																			A
	48																			B
120	125																			C
240	250																			D
	24	X																		E
	48	X																		F
120	125	X																		G
240	250	X																		H
	24		X																	J
	48		X																	K
120	125		X																	L
240	250		X																	M
	24	X	X																	N
	48	X	X																	P
120	125	X	X																	R
240	250	X	X																	S

WL Power Circuit Breaker

UL 1066 Listed Catalog Number

Undervoltage release (with or without time delay) or 2nd shunt trip						Breaker catalog number														
Control voltage		UVR without delay	UVR with delay	UVR status contact ¹	2nd shunt trip															
AC	DC					1	2	3	4	5	6	7	8	9	10	11	12	13	14	15
					None											X				
	24	X															A			
	48	X															B			
120	125	X															C			
240	250	X															D			
	48		X														E			
120	125		X														F			
240	250		X														G			
	24				X												H			
	48				X												J			
120	125				X												K			
240	250				X												L			
	24	X		X													M			
	48	X		X													N			
120	125	X		X													P			
240	250	X		X													Q			
	48		X	X													R			
	125		X	X													S			
120	250		X	X													T			

Charging motor, motor switch, operations counter

Charging motor operation voltage		Motor cut-off switch	Operations counter																	
AC	DC			1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17
	24																			
	48																			
120	125																			
240	250																			
	24	X																		
	48	X																		
120	125	X																		
240	250	X																		
	24		X																	
	48		X																	
120	125		X																	
240	250		X																	
	24	X	X																	
	48	X	X																	
120	125	X	X																	
240	250	X	X																	

¹ Status contact is only available when communication is not installed on breaker. Signal is sent via communication in lieu of status contact.

WL Power Circuit Breaker

UL 1066 Listed Catalog Number

Close coil, power metering and communications

Close coil operation voltage		Power metering capable	Modbus 2	PROFIBUS 2 PROFINET	Modbus TCP/ PROFINET	Breaker catalog number														
						1	2	3	4	5	6	7	8	9	10	11	12	13	14	15
AC	DC					None													X	
		24																	A	
	48																		B	
120	125																		C	
240	250																		D	
			X																G	
				X															H	
					X														E	
	24		X																N	
	24			X															P	
	48		X																S	
	48			X															T	
120	125		X																W	
120	125			X															Y	
120	125				X														J	
240	250		X																2	
240	250			X															3	
	24	X	X																Q	
	48	X	X																U	
120	125	X	X																Z	
120	250	X	X																4	
	24	X		X															R	
	24	X			X														6	
	48	X		X															V	
	48	X			X														7	
120	125	X		X															1	
120	125	X			X														9	
240	250	X		X															5	
240	250	X			X														0	
		X		X															L	
		X		X															M	
		X																	F	
		X			X														K	
120	125	X																	8	

Breaker locks

Key lock breaker OPEN position (lock type – KIRK) 3	Key lock breaker OPEN position (lock type – SUPERIOR) 3	Padlock provisions for OPEN and CLOSE pushbuttons 4	Padlock provisions for charging handle 4																	
				None															X	
X																			A	
		X																	C	
	X			X															E	
X		X																	F	
	X	X																	G	
X																			J	
	X																		S	
																			U	
		X																	V	
X		X																	W	
	X	X																	Z	

Miscellaneous options 5

Key lock breaker OPEN position (provision only) 4	Manual trip reset ETU (Automatic trip reset is standard)																			
		None																	N	
X																			B	
			X																C	
X			X																D	

1 Requires External PTs for voltage input and 24VDC power supply.

2 Includes BSS device and requires 24VDC power supply.

3 Custom key locks are not available and must be supplied by others.

Order key lock provision if custom if keyed alike locks are required.

4 Locks provided by others.

5 If a breaker lock is chosen for Digit 14, a provision need not be ordered in Digit 15.

WL Power Circuit Breaker

UL 1066 Listed Non-automatic Catalog Number

Breaking capacity, frame size, switch type and frame rating (3-Pole Non-Automatic Circuit Breakers)

Breaking capacity, frame size, switch type and frame rating							Switch catalog number															
(3-Pole Non-Automatic Circuit Breakers)							1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	
Class	Breaking capacity (kA)		Frame	Frame size			↑	↑	↑	↑	↑	↑	↑	↑								
	240VAC		Max ampere			Fuse																
	480VAC	600VAC	rating (A)	2	3	(A)																
L	100	85	800	X			L	2	S	3	0	8	S	S								
L	100	85	1600	X			L	2	S	3	1	6	S	S								
L	100	85	2000	X			L	2	S	3	2	0	S	S								
L	100	85	3200	X			L	2	S	3	2	2	S	S								
L	100	85	4000		X		L	3	S	3	4	0	S	S								
L	100	85	5000		X		L	3	S	3	5	0	S	S								
F	200	200	800	X		1000	F	2	S	3	0	E	S	S								
F	200	200	800	X		1200	F	2	S	3	0	F	S	S								
F	200	200	800	X		1600	F	2	S	3	0	G	S	S								
F	200	200	800	X		2000	F	2	S	3	0	H	S	S								
F	200	200	800	X		2500	F	2	S	3	0	J	S	S								
F	200	200	800	X		3000	F	2	S	3	0	K	S	S								
F	200	200	1600	X		1000	F	2	S	3	1	E	S	S								
F	200	200	1600	X		1200	F	2	S	3	1	F	S	S								
F	200	200	1600	X		1600	F	2	S	3	1	G	S	S								
F	200	200	1600	X		2000	F	2	S	3	1	H	S	S								
F	200	200	1600	X		2500	F	2	S	3	1	J	S	S								
F	200	200	1600	X		3000	F	2	S	3	1	K	S	S								
F	200	200	2000	X		1000	F	2	S	3	2	E	S	S								
F	200	200	2000	X		1200	F	2	S	3	2	F	S	S								
F	200	200	2000	X		1600	F	2	S	3	2	G	S	S								
F	200	200	2000	X		2000	F	2	S	3	2	H	S	S								
F	200	200	2000	X		2500	F	2	S	3	2	J	S	S								
F	200	200	2000	X		3000	F	2	S	3	2	K	S	S								
F	200	200	3200		X	6000	F	3	S	3	3	2	S	S								
F	200	200	4000		X	6000	F	3	S	3	4	0	S	S								
F	200	200	5000		X	6000	F	3	S	3	5	0	S	S								

Breaking capacity, frame size, switch type and frame rating (4-Pole Non-Automatic Circuit Breakers)

Breaking capacity, frame size, switch type and frame rating (4-Pole Non-Automatic Circuit Breakers)								Switch catalog number															
Class	Breaking capacity (kA)		Frame Max ampere rating (A)	Frame size				1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	
	254VAC 508VAC	635VAC		2	3	Fixed	Drawout	↑	↑	↑	↑	↑	↑	↑	↑	↑	↑	↑	↑	↑	↑	↑	
L	100	85	800	X		X		L	2	J	4	0	8	S	S								
L	100	85	800	X			X	L	2	S	4	0	8	S	S								
L	100	85	1600	X				L	2	J	4	1	6	S	S								
L	100	85	1600	X			X	L	2	S	4	1	6	S	S								
L	100	85	2000	X		X		L	2	J	4	2	0	S	S								
L	100	85	2000	X			X	L	2	S	4	2	0	S	S								
L	100	85	3200	X		X		L	2	J	4	3	2	S	S								
L	100	85	3200	X			X	L	2	S	4	3	2	S	S								
L	100	85	4000		X	X		L	3	J	4	4	0	S	S								
L	100	85	4000		X		X	L	3	S	4	4	0	S	S								
L	100	85	5000		X	X		L	3	J	4	5	0	S	S								
L	100	85	5000		X		X	L	3	S	4	5	0	S	S								
L	100	85	6000		X		X	L	3	S	4	6	0	S	S								

WL Power Circuit Switch

UL 1066 Listed Non-automatic Catalog Number

Breaker ready-to-close auxiliary contacts			Switch catalog number														
Breaker ready-to-close 1b contact	Breaker open/close auxiliary switches		1	2	3	4	5	6	7	8	9	10	11	12	13	14	15
2a + 2b	4a + 4b																
		None									X						
X											B						
	X										C						
		X									D						
X	X										H						
X		X									I						

Shunt trip

Operation voltage		Status contact		
AC	DC			
			None	X
	24			A
	48			B
120	125			C
240	250			D
	24	X		E
	48	X		F
120	125	X		G
240	250	X		H

Undervoltage release (with or without time delay) or 2nd shunt trip

Operation voltage		UVR without delay	UVR with delay	UVR status contact ¹	2nd shunt trip	
AC	DC					
					None	X
	24	X				A
	48	X				B
120	125	X				C
240	250	X				D
	48		X			E
120	125		X			F
240	250		X			G
	24				X	H
	48				X	J
120	125				X	K
240	250				X	L
	24	X		X		M
	48	X		X		N
120	125	X		X		P
240	250	X		X		Q
	48		X	X		R
	125		X	X		S
120	250		X	X		T

¹ Status contact only available when communication is not installed. Signal is sent via communication in lieu of status contact.

WL Power Circuit Switch

UL 1066 Listed Non-automatic Catalog Number

Charging motor, motor switch, operations counter				Switch catalog number														
Charging motor operation voltage		Motor cut-off switch	Operations counter	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15
AC	DC			None											X			
	24														A			
	48														B			
120	125														C			
240	250														D			
	24	X													E			
	48	X													F			
120	125	X													G			
240	250	X													H			
	24		X												J			
	48		X												K			
120	125		X												L			
240	250		X												M			
	24	X	X												N			
	48	X	X												P			
120	125	X	X												Q			
240	250	X	X												R			

Close coil, communications

Close coil operation voltage		Power metering capable	Modbus ¹	PROFIBUS ¹	Modbus TCP / PROFINET ¹											
AC	DC					1	2	3	4	5	6	7	8	9	10	11
	24					None										X
	48															A
																B
120	125															C
240	250															D
			X													G
				X												H
					X											E
	24		X													N
	24			X												P
	48		X													S
	48			X												T
120	125		X													W
120	125			X												Y
120	125				X											J
240	250		X													2
240	250			X												3

¹ Requires 24VDC power supply. BSS is included.

WL Power Circuit Switch

UL 1066 Listed Non-automatic Catalog Number

				Switch catalog number														
Switch locks				1	2	3	4	5	6	7	8	9	10	11	12	13	14	15
Key lock breaker OPEN position (lock type – KIRK) ¹	Key lock breaker OPEN position (lock type – SUPERIOR) ¹	Padlock provisions for OPEN and CLOSE pushbuttons ²	Padlock provisions for charging handle	None														X
X																		A
		X																C
			X															E
	X																	F
X		X																G
	X	X																J
X			X															S
	X		X															U
		X	X															V
X		X	X															W
	X	X	X															Z

Miscellaneous options ³

Key lock breaker OPEN position (provision only) ²																	
	None																N
X																	B

UL 1066 Fixed Mount Breaker Vertical Connector Kits

Description	Catalog number
FS 2 800A - 1600A Rear Vertical Connectors (8 pieces, includes Neutral Pole)	WL4L2R16CONUL
FS 2 2000A Rear Vertical Connectors (8 pieces, includes Neutral Pole)	WL4L2R20CONUL
FS 2 3200A Rear Vertical Connectors (8 pieces, includes Neutral Pole)	WL4L2R32CONUL ⁴
FS 3 4000A - 5000A Rear Vertical Connectors (8 pieces, includes Neutral Pole)	WL4L2R50CONUL ⁴

¹ Custom key locks are not available and must be supplied by others. Order Key Lock Provisions if custom keys or keyed alike breakers are required.

² Lock provided by others.

³ If a breaker lock is chosen for Digit 14, a provision need not be ordered in Digit 15.

⁴ FS II 3200A, FS III 4000A, 5000A breakers include vertical connectors as a standard.

WL Power Circuit Switch

UL 1066 Listed Cradle Catalog Number

Interrupting rating, frame size and frame rating

Cradle catalog number

G	2	3	4	5	6	7	8	9	10	11	12	13	14	15
---	---	---	---	---	---	---	---	---	----	----	----	----	----	----

Class	Interrupt rating (kA)		Frame	Frame size								
	240VAC 480VAC	600VAC	Max ampere rating (A)	2	3	No. of Poles						
N	50	50	800	X		3		N	2	3	0	8
N	50	50	1600	X		3		N	2	3	1	6
S	65	65	800	X		3		S	2	3	0	8
S	65	65	1600	X		3		S	2	3	1	6
S	65	65	2000	X		3		S	2	3	2	0
S	65	65	3200	X		3		S	2	3	3	2
H	85	65	800	X		3		H	2	3	0	8
H	85	65	1600	X		3		H	2	3	1	6
H	85	65	2000	X		3		H	2	3	2	0
H	85	65	3200	X		3		H	2	3	3	2
H	85	85	4000		X	3		H	3	3	4	0
H	85	85	5000		X	3		H	3	3	5	0
L	100	85	800	X		3		L	2	3	0	8
L	100	85	1600	X		3		L	2	3	1	6
L	100	85	2000	X		3		L	2	3	2	0
L	100	85	3200	X		3		L	2	3	3	2
L	100	85	4000		X	3		L	3	3	4	0
L	100	85	5000		X	3		L	3	3	5	0
L	100	85	6000		X	3		L	3	3	6	0
M	150	85	3200		X	3		M	3	3	3	2
M	150	85	4000		X	3		M	3	3	4	0
M	150	85	5000		X	3		M	3	3	5	0
M	150	85	6000		X	3		M	3	3	6	0
F	200	200	800	X		3		F	2	3	0	8
F	200	200	1600	X		3		F	2	3	1	6
F	200	200	2000	X		3		F	2	3	2	0
F	200	200	3200		X	3		F	2	3	3	2
F	200	200	4000		X	3		F	3	3	4	0
F	200	200	5000		X	3		F	3	3	5	0
S	65	65	800		X	4		S	2	4	0	8
S	65	65	1600		X	4		S	2	4	1	6
S	65	65	2000	X		4		S	2	4	2	0
S	65	65	3200	X		4		S	2	4	3	2
H	85	65	800	X		4		H	2	4	0	8
H	85	65	1600	X		4		H	2	4	1	6
H	85	65	2000	X		4		H	2	4	2	0
H	85	65	3200	X		4		H	2	4	3	2
L	100	85	800	X		4		L	2	4	0	8
L	100	85	1600	X		4		L	2	4	1	6
L	100	85	2000	X		4		L	2	4	2	0
L	100	85	3200	X		4		L	2	4	3	2
L	100	85	4000		X	4		L	3	4	4	0
L	100	85	5000		X	4		L	3	4	5	0
L	100	85	6000		X	4		L	3	4	6	0

Type of secondary terminal connection 1

For Breakers:

Screw clamp terminals	P
Spring clamp terminals	T
Ring terminals	R
Screw clamp terminals (low profile, non-partable design)	K

For Switch (Non-automatic):

Screw clamp terminals	D
Spring clamp terminals	E
Ring terminals	F
Screw clamp terminals, non-partable design)	M

Truck Operated Contacts (TOC)

Breaker position switches in the following configurations:

None	X
(1) Connected, (1) Test, (1) Disconnected - all Form C	1
(3) Connected, (2) Test, (1) Disconnected - all Form C	3
(6) Connected - all Form C	6

¹ Terminal blocks (X5, X6, X8, X9) are installed as standard.

² Fused Frame Size 3 circuit breakers include a two cylinder provision as standard, with the second position pre-populated with a key-interlock to prevent racking (in or out) of the separately-mounted fuse carriage while the associated fused circuit breaker is closed.

UL 1066 Listed Cradle Catalog Number

UL 1066 Listed accessories

55