EQUINIX

IBM maximo

CA1-TS-AC-29-ATS

4398474

Site:	AU01-CA1	**Asset:**	1070 - CA1-TS-AC-29-ATS				
Status:	INPRG	**Serial #:**	20204810181938440010A				
Work Type:	PM	**Location:**	CA1-GF-22 - CA1-GF-Node Room				
Priority:	3	**Job Plan:**	ATS-3 - E1.8 ATS-Automatic Transfer Switches				
CrewID:		**Target Start:**	20-May-2026	**Target Finish:**	20-May-2026	**Failure:**	ELECPWR
		Actual Start:		**Actual Finish:**		**Problem:**	
Classification:	ATS-Auto Transfer Switch			**IR Scan p/f:**		**Cause:**	
						Remedy:	

Tasks

Task	Description	Complete	N/A
	Applies To: ATS-Automatic Transfer Switches	..	..
1	The Personal Protective Equipment (PPE) listed is the minimum required PPE to be worn while executing this Job Plan (JP). Category 2: Arc-rated top, Arc-rated trousers, Flame Retardant Belt, Electrical Safety Boots, Safety glasses, Arc-rated grip gloves. Where electrical isolation is required CAT 4 kit will be required. When Job hazard analysis or dynamic risk assessment identifies additional PPE requirements it shall be acquired and used	..	..
2	Ensure that an approved Change Request (CR) is in place	..	..
3	For sites with Smart View, toggle Maintenance Mode for equipment that is to be worked on within SmartView.	..	..
10	Visual inspection of all control wiring and connections for signs of cracking, overheating and insulation deterioration.	..	..
20	Check all indicating lights, if equipped verify HMI is operating.	..	..
30	Verify engine start signal. (if applicable)	..	..
40	Perform IR Scan on Primary source.	..	..
50	Check all settings and verify with historical settings data.	..	..
60	Check and record the Primary Source Voltages	..	..
70	Verify accuracy of metering.	..	..
80	Record operations and inspect Transient Voltage Surge Suppressors (TVSS) for blown fuses or damaged Metal Oxide Varistors (MOV's). (if applicable)	..	..
90	Perform ATS transfer to Alternate source. (may be accomplished in conjunction with the comprehensive utility failure test)	..	..
100	Check and record the Alternate Source Voltages	..	..
110	Verify accuracy of metering.	..	..
120	Perform IR scan on Alternate source.	..	..
130	If bypass isolation ATS, bypass to both sources and verify the following steps are completed.	..	..
140	Validate the bypass is supporting load	..	..
150	Rack out ATS mechanism to the isolated position. (if applicable)	..	..
160	Inspect main, auxiliary, arcing and relay finger contacts. (clean and burnish where necessary)	..	..
170	Lubricate all necessary mechanical parts as per manufacturer's recommendations.	..	..
180	Rack in ATS mechanism to the connected position. (if applicable)	..	..
190	Take ATS out of bypass and restore to normal operation.	..	..
200	The following inspection can only be done when the ATS has all power removed	..	..
210	Check and tighten all control wiring terminals and plug in connectors.	..	..
220	Check and tighten all common and ground wires.	..	..
230	Lubricate all necessary mechanical parts as per manufacturer's recommendations. (if applicable)	..	..
240	Re-torque all bus and lug connections (Primary, Alternate, Load)	..	..
250	Inspect main, auxiliary, arcing and relay finger contacts. (clean and burnish where necessary)	..	..
260	Check motor mounting hardware. (if applicable)	..	..

EQUINIX

IBM. maximo

CA1-TS-AC-29-ATS

4398474

Tasks

Task	Description	Complete	N/A
270	Check Heim joints/linkages, interlocks and operating handles (if applicable)	"	"
280	Clean the interior of the switch cabinet.	"	"
290	Inspect components for signs of overheating	"	"
300	Inspect insulation materials for signs of visible damage.	"	"
310	Once maintenance is complete and equipment is operational, un-toggle Maintenance Mode within SmartView	"	"
320	If required, use the follow-up WO Process to create a CD or CM for any corrective work found during the PM.	"	"
330	Complete work order in Maximo	"	"

Name: Date: Hours:

Comments:

EQUINIX

IBM maximo

CA1-MECH-POP-A

4406648

Site:	AU01-CA1	Asset:	1135 - CA1-MECH-POP-A				
Status:	INPRG	Serial #:	CAN1-ELE-FR-0076				
Work Type:	PM	Location:	CA1-GF-04 - CA1-GF-Link Corridor				
Priority:	3	Job Plan:	ATS-3 - E1.8 ATS-Automatic Transfer Switches				
CrewID:		Target Start:	20-May-2026	Target Finish:	20-May-2026	Failure:	ELECPWR
		Actual Start:		Actual Finish:		Problem:	
Classification:	ATS-Auto Transfer Switch			IR Scan p/f:		Cause:	
						Remedy:	

Tasks

Task	Description	Complete	N/A
	Applies To: ATS-Automatic Transfer Switches	..	..
1	The Personal Protective Equipment (PPE) listed is the minimum required PPE to be worn while executing this Job Plan (JP). Category 2: Arc-rated top, Arc-rated trousers, Flame Retardant Belt, Electrical Safety Boots, Safety glasses, Arc-rated grip gloves. Where electrical isolation is required CAT 4 kit will be required. When Job hazard analysis or dynamic risk assessment identifies additional PPE requirements it shall be acquired and used	..	..
2	Ensure that an approved Change Request (CR) is in place	..	..
3	For sites with Smart View, toggle Maintenance Mode for equipment that is to be worked on within SmartView.	..	..
10	Visual inspection of all control wiring and connections for signs of cracking, overheating and insulation deterioration.	..	..
20	Check all indicating lights, if equipped verify HMI is operating.	..	..
30	Verify engine start signal. (if applicable)	..	..
40	Perform IR Scan on Primary source.	..	..
50	Check all settings and verify with historical settings data.	..	..
60	Check and record the Primary Source Voltages	..	..
70	Verify accuracy of metering.	..	..
80	Record operations and inspect Transient Voltage Surge Suppressors (TVSS) for blown fuses or damaged Metal Oxide Varistors (MOV's). (if applicable)	..	..
90	Perform ATS transfer to Alternate source. (may be accomplished in conjunction with the comprehensive utility failure test)	..	..
100	Check and record the Alternate Source Voltages	..	..
110	Verify accuracy of metering.	..	..
120	Perform IR scan on Alternate source.	..	..
130	If bypass isolation ATS, bypass to both sources and verify the following steps are completed.	..	..
140	Validate the bypass is supporting load	..	..
150	Rack out ATS mechanism to the isolated position. (if applicable)	..	..
160	Inspect main, auxiliary, arcing and relay finger contacts. (clean and burnish where necessary)	..	..
170	Lubricate all necessary mechanical parts as per manufacturer's recommendations.	..	..
180	Rack in ATS mechanism to the connected position. (if applicable)	..	..
190	Take ATS out of bypass and restore to normal operation.	..	..
200	The following inspection can only be done when the ATS has all power removed	..	..
210	Check and tighten all control wiring terminals and plug in connectors.	..	..
220	Check and tighten all common and ground wires.	..	..
230	Lubricate all necessary mechanical parts as per manufacturer's recommendations. (if applicable)	..	..
240	Re-torque all bus and lug connections (Primary, Alternate, Load)	..	..
250	Inspect main, auxiliary, arcing and relay finger contacts. (clean and burnish where necessary)	..	..
260	Check motor mounting hardware. (if applicable)	..	..

EQUINIX

IBM maximo

CA1-MECH-POP-A

4406648

Tasks

Task	Description	Complete	N/A
270	Check Heim joints/linkages, interlocks and operating handles (if applicable)		
280	Clean the interior of the switch cabinet.		
290	Inspect components for signs of overheating		
300	Inspect insulation materials for signs of visible damage.		
310	Once maintenance is complete and equipment is operational, un-toggle Maintenance Mode within SmartView		
320	If required, use the follow-up WO Process to create a CD or CM for any corrective work found during the PM.		
330	Complete work order in Maximo		

Name: Date: Hours:

Comments:

EQUINIX

IBM maximo

CA1-MECH-POP-B

4406759

Site:	AU01-CA1	**Asset:**	1137 - CA1-MECH-POP-B				
Status:	INPRG	**Serial #:**	CAN1-ELE-FR-008				
Work Type:	PM	**Location:**	CA1-GF-04 - CA1-GF-Link Corridor				
Priority:	3	**Job Plan:**	ATS-3 - E1.8 ATS-Automatic Transfer Switches				
CrewID:		**Target Start:**	20-May-2026	**Target Finish:**	20-May-2026	**Failure:**	ELECPWR
		Actual Start:		**Actual Finish:**		**Problem:**	
Classification:	ATS-Auto Transfer Switch			**IR Scan p/f:**		**Cause:**	
						Remedy:	

Tasks

Task	Description	Complete	N/A
	Applies To: ATS-Automatic Transfer Switches		
1	The Personal Protective Equipment (PPE) listed is the minimum required PPE to be worn while executing this Job Plan (JP). Category 2: Arc-rated top, Arc-rated trousers, Flame Retardant Belt, Electrical Safety Boots, Safety glasses, Arc-rated grip gloves. Where electrical isolation is required CAT 4 kit will be required. When Job hazard analysis or dynamic risk assessment identifies additional PPE requirements it shall be acquired and used		
2	Ensure that an approved Change Request (CR) is in place		
3	For sites with Smart View, toggle Maintenance Mode for equipment that is to be worked on within SmartView.		
10	Visual inspection of all control wiring and connections for signs of cracking, overheating and insulation deterioration.		
20	Check all indicating lights, if equipped verify HMI is operating.		
30	Verify engine start signal. (if applicable)		
40	Perform IR Scan on Primary source.		
50	Check all settings and verify with historical settings data.		
60	Check and record the Primary Source Voltages		
70	Verify accuracy of metering.		
80	Record operations and inspect Transient Voltage Surge Suppressors (TVSS) for blown fuses or damaged Metal Oxide Varistors (MOV's). (if applicable)		
90	Perform ATS transfer to Alternate source. (may be accomplished in conjunction with the comprehensive utility failure test)		
100	Check and record the Alternate Source Voltages		
110	Verify accuracy of metering.		
120	Perform IR scan on Alternate source.		
130	If bypass isolation ATS, bypass to both sources and verify the following steps are completed.		
140	Validate the bypass is supporting load		
150	Rack out ATS mechanism to the isolated position. (if applicable)		
160	Inspect main, auxiliary, arcing and relay finger contacts. (clean and burnish where necessary)		
170	Lubricate all necessary mechanical parts as per manufacturer's recommendations.		
180	Rack in ATS mechanism to the connected position. (if applicable)		
190	Take ATS out of bypass and restore to normal operation.		
200	The following inspection can only be done when the ATS has all power removed		
210	Check and tighten all control wiring terminals and plug in connectors.		
220	Check and tighten all common and ground wires.		
230	Lubricate all necessary mechanical parts as per manufacturer's recommendations. (if applicable)		
240	Re-torque all bus and lug connections (Primary, Alternate, Load)		
250	Inspect main, auxiliary, arcing and relay finger contacts. (clean and burnish where necessary)		
260	Check motor mounting hardware. (if applicable)		

EQUINIX

IBM maximo

CA1-MECH-POP-B

4406759

Tasks

Task	Description	Complete	N/A
270	Check Heim joints/linkages, interlocks and operating handles (if applicable)		
280	Clean the interior of the switch cabinet.		
290	Inspect components for signs of overheating		
300	Inspect insulation materials for signs of visible damage.		
310	Once maintenance is complete and equipment is operational, un-toggle Maintenance Mode within SmartView		
320	If required, use the follow-up WO Process to create a CD or CM for any corrective work found during the PM.		
330	Complete work order in Maximo		

Name: Date: Hours:

Comments:

EQUINIX

IBM. maximo

CA1-SMDB-1-1A-GLP (ATS)

4408095

Site:	AU01-CA1	Asset:	1158 - CA1-SMDB-1-1A-GLP (ATS)				
Status:	INPRG	Serial #:	N/A				
Work Type:	PM	Location:	CA1-GF-26 - CA1-GF-Hall 1-1				
Priority:	3	Job Plan:	ATS-3 - E1.8 ATS-Automatic Transfer Switches				
CrewID:		Target Start:	20-May-2026	Target Finish:	20-May-2026	Failure:	ELECPWR
		Actual Start:		Actual Finish:		Problem:	
Classification:	ATS-Auto Transfer Switch			IR Scan p/f:		Cause:	
						Remedy:	

Tasks

Task	Description	Complete	N/A
	Applies To: ATS-Automatic Transfer Switches	..	..
1	The Personal Protective Equipment (PPE) listed is the minimum required PPE to be worn while executing this Job Plan (JP). Category 2: Arc-rated top, Arc-rated trousers, Flame Retardant Belt, Electrical Safety Boots, Safety glasses, Arc-rated grip gloves. Where electrical isolation is required CAT 4 kit will be required. When Job hazard analysis or dynamic risk assessment identifies additional PPE requirements it shall be acquired and used	..	..
2	Ensure that an approved Change Request (CR) is in place	..	..
3	For sites with Smart View, toggle Maintenance Mode for equipment that is to be worked on within SmartView.	..	..
10	Visual inspection of all control wiring and connections for signs of cracking, overheating and insulation deterioration.	..	..
20	Check all indicating lights, if equipped verify HMI is operating.	..	..
30	Verify engine start signal. (if applicable)	..	..
40	Perform IR Scan on Primary source.	..	..
50	Check all settings and verify with historical settings data.	..	..
60	Check and record the Primary Source Voltages	..	..
70	Verify accuracy of metering.	..	..
80	Record operations and inspect Transient Voltage Surge Suppressors (TVSS) for blown fuses or damaged Metal Oxide Varistors (MOV's). (if applicable)	..	..
90	Perform ATS transfer to Alternate source. (may be accomplished in conjunction with the comprehensive utility failure test)	..	..
100	Check and record the Alternate Source Voltages	..	..
110	Verify accuracy of metering.	..	..
120	Perform IR scan on Alternate source.	..	..
130	If bypass isolation ATS, bypass to both sources and verify the following steps are completed.	..	..
140	Validate the bypass is supporting load	..	..
150	Rack out ATS mechanism to the isolated position. (if applicable)	..	..
160	Inspect main, auxiliary, arcing and relay finger contacts. (clean and burnish where necessary)	..	..
170	Lubricate all necessary mechanical parts as per manufacturer's recommendations.	..	..
180	Rack in ATS mechanism to the connected position. (if applicable)	..	..
190	Take ATS out of bypass and restore to normal operation.	..	..
200	The following inspection can only be done when the ATS has all power removed	..	..
210	Check and tighten all control wiring terminals and plug in connectors.	..	..
220	Check and tighten all common and ground wires.	..	..
230	Lubricate all necessary mechanical parts as per manufacturer's recommendations. (if applicable)	..	..
240	Re-torque all bus and lug connections (Primary, Alternate, Load)	..	..
250	Inspect main, auxiliary, arcing and relay finger contacts. (clean and burnish where necessary)	..	..
260	Check motor mounting hardware. (if applicable)	..	..

EQUINIX

IBM. maximo

CA1-SMDB-1-1A-GLP (ATS)

4408095

Tasks

Task	Description	Complete	N/A
270	Check Heim joints/linkages, interlocks and operating handles (if applicable)	..	..
280	Clean the interior of the switch cabinet.	..	..
290	Inspect components for signs of overheating	..	..
300	Inspect insulation materials for signs of visible damage.	..	..
310	Once maintenance is complete and equipment is operational, un-toggle Maintenance Mode within SmartView	..	..
320	If required, use the follow-up WO Process to create a CD or CM for any corrective work found during the PM.	..	..
330	Complete work order in Maximo	..	..

Name:	Date:	Hours:

Comments:

EQUINIX

IBM. maximo

CA1-LVSB-1-1A-DHATS-1-1B (ATS)

4408213

Site:	AU01-CA1	Asset:	1159 - CA1-LVSB-1-1A-DHATS-1-1B (ATS)				
Status:	INPRG	Serial #:	N/A				
Work Type:	PM	Location:	CA1-GF-26 - CA1-GF-Hall 1-1				
Priority:	3	Job Plan:	ATS-3 - E1.8 ATS-Automatic Transfer Switches				
CrewID:		Target Start:	20-May-2026	Target Finish:	20-May-2026	Failure:	ELECPWR
		Actual Start:		Actual Finish:		Problem:	
Classification:	ATS-Auto Transfer Switch			IR Scan p/f:		Cause:	
						Remedy:	

Tasks

Task	Description	Complete	N/A
	Applies To: ATS-Automatic Transfer Switches	..	..
1	The Personal Protective Equipment (PPE) listed is the minimum required PPE to be worn while executing this Job Plan (JP). Category 2: Arc-rated top, Arc-rated trousers, Flame Retardant Belt, Electrical Safety Boots, Safety glasses, Arc-rated grip gloves. Where electrical isolation is required CAT 4 kit will be required. When Job hazard analysis or dynamic risk assessment identifies additional PPE requirements it shall be acquired and used	..	..
2	Ensure that an approved Change Request (CR) is in place	..	..
3	For sites with Smart View, toggle Maintenance Mode for equipment that is to be worked on within SmartView.	..	..
10	Visual Inspection of all control wiring and connections for signs of cracking, overheating and insulation deterioration.	..	..
20	Check all indicating lights, if equipped verify HMI is operating.	..	..
30	Verify engine start signal. (if applicable)	..	..
40	Perform IR Scan on Primary source.	..	..
50	Check all settings and verify with historical settings data.	..	..
60	Check and record the Primary Source Voltages	..	..
70	Verify accuracy of metering.	..	..
80	Record operations and inspect Transient Voltage Surge Suppressors (TVSS) for blown fuses or damaged Metal Oxide Varistors (MOV's). (if applicable)	..	..
90	Perform ATS transfer to Alternate source. (may be accomplished in conjunction with the comprehensive utility failure test)	..	..
100	Check and record the Alternate Source Voltages	..	..
110	Verify accuracy of metering.	..	..
120	Perform IR scan on Alternate source.	..	..
130	If bypass isolation ATS, bypass to both sources and verify the following steps are completed.	..	..
140	Validate the bypass is supporting load	..	..
150	Rack out ATS mechanism to the isolated position. (if applicable)	..	..
160	Inspect main, auxiliary, arcing and relay finger contacts. (clean and burnish where necessary)	..	..
170	Lubricate all necessary mechanical parts as per manufacturer's recommendations.	..	..
180	Rack in ATS mechanism to the connected position. (if applicable)	..	..
190	Take ATS out of bypass and restore to normal operation.	..	..
200	The following inspection can only be done when the ATS has all power removed	..	..
210	Check and tighten all control wiring terminals and plug in connectors.	..	..
220	Check and tighten all common and ground wires.	..	..
230	Lubricate all necessary mechanical parts as per manufacturer's recommendations. (if applicable)	..	..
240	Re-torque all bus and lug connections (Primary, Alternate, Load)	..	..
250	Inspect main, auxiliary, arcing and relay finger contacts. (clean and burnish where necessary)	..	..
260	Check motor mounting hardware. (if applicable)	..	..

EQUINIX

IBM. maximo

CA1-LVSB-1-1A-DHATS-1-1B (ATS)

4408213

Tasks

Task	Description	Complete	N/A
270	Check Heim joints/linkages, interlocks and operating handles (if applicable)	"	"
280	Clean the interior of the switch cabinet.	"	"
290	Inspect components for signs of overheating	"	"
300	Inspect insulation materials for signs of visible damage.	"	"
310	Once maintenance is complete and equipment is operational, un-toggle Maintenance Mode within SmartView	"	"
320	If required, use the follow-up WO Process to create a CD or CM for any corrective work found during the PM.	"	"
330	Complete work order in Maximo	"	"

Name: Date: Hours:

Comments:

EQUINIX

IBM maximo

CA1-SMDB-1-2A-GLP (ATS)

4409209

Site:	AU01-CA1	**Asset:**	1170 - CA1-SMDB-1-2A-GLP (ATS)				
Status:	INPRG	**Serial #:**	N/A				
Work Type:	PM	**Location:**	CA1-GF-26 - CA1-GF-Hall 1-1				
Priority:	3	**Job Plan:**	ATS-3 - E1.8 ATS-Automatic Transfer Switches				
CrewID:		**Target Start:**	20-May-2026	**Target Finish:**	20-May-2026	**Failure:**	ELECPWR
		Actual Start:		**Actual Finish:**		**Problem:**	
Classification:	ATS-Auto Transfer Switch			**IR Scan p/f:**		**Cause:**	
						Remedy:	

Tasks

Task	Description	Complete	N/A
	Applies To: ATS-Automatic Transfer Switches	..	..
1	The Personal Protective Equipment (PPE) listed is the minimum required PPE to be worn while executing this Job Plan (JP). Category 2: Arc-rated top, Arc-rated trousers, Flame Retardant Belt, Electrical Safety Boots, Safety glasses, Arc-rated grip gloves. Where electrical isolation is required CAT 4 kit will be required. When Job hazard analysis or dynamic risk assessment identifies additional PPE requirements it shall be acquired and used	..	..
2	Ensure that an approved Change Request (CR) is in place	..	..
3	For sites with Smart View, toggle Maintenance Mode for equipment that is to be worked on within SmartView.	..	..
10	Visual inspection of all control wiring and connections for signs of cracking, overheating and insulation deterioration.	..	..
20	Check all indicating lights, if equipped verify HMI is operating.	..	..
30	Verify engine start signal. (if applicable)	..	..
40	Perform IR Scan on Primary source.	..	..
50	Check all settings and verify with historical settings data.	..	..
60	Check and record the Primary Source Voltages	..	..
70	Verify accuracy of metering.	..	..
80	Record operations and inspect Transient Voltage Surge Suppressors (TVSS) for blown fuses or damaged Metal Oxide Varistors (MOV's). (if applicable)	..	..
90	Perform ATS transfer to Alternate source. (may be accomplished in conjunction with the comprehensive utility failure test)	..	..
100	Check and record the Alternate Source Voltages	..	..
110	Verify accuracy of metering.	..	..
120	Perform IR scan on Alternate source.	..	..
130	If bypass isolation ATS, bypass to both sources and verify the following steps are completed.	..	..
140	Validate the bypass is supporting load	..	..
150	Rack out ATS mechanism to the isolated position. (if applicable)	..	..
160	Inspect main, auxiliary, arcing and relay finger contacts. (clean and burnish where necessary)	..	..
170	Lubricate all necessary mechanical parts as per manufacturer's recommendations.	..	..
180	Rack in ATS mechanism to the connected position. (if applicable)	..	..
190	Take ATS out of bypass and restore to normal operation.	..	..
200	The following inspection can only be done when the ATS has all power removed	..	..
210	Check and tighten all control wiring terminals and plug in connectors.	..	..
220	Check and tighten all common and ground wires.	..	..
230	Lubricate all necessary mechanical parts as per manufacturer's recommendations. (if applicable)	..	..
240	Re-torque all bus and lug connections (Primary, Alternate, Load)	..	..
250	Inspect main, auxiliary, arcing and relay finger contacts. (clean and burnish where necessary)	..	..
260	Check motor mounting hardware. (if applicable)	..	..

EQUINIX

IBM. maximo

CA1-SMDB-1-2A-GLP (ATS)

4409209

Tasks

Task	Description	Complete	N/A
270	Check Heim joints/linkages, interlocks and operating handles (if applicable)	..	..
280	Clean the interior of the switch cabinet.	..	..
290	Inspect components for signs of overheating	..	..
300	Inspect insulation materials for signs of visible damage.	..	..
310	Once maintenance is complete and equipment is operational, un-toggle Maintenance Mode within SmartView	..	..
320	If required, use the follow-up WO Process to create a CD or CM for any corrective work found during the PM.	..	..
330	Complete work order in Maximo	..	..

Name: Date: Hours:

Comments: