



TYPE CZ VACUUM ON-LOAD TAP CHANGER FOR DRY TYPE TRANSFORMER

Shanghai Huaming Power Equipment Co.,Ltd.



TYPE CZ VACUUM ON-LOAD TAP CHANGER FOR DRY TYPE TRANSFORMER

Technical data

No	On Load Tap Changer			CZ I 500	3×CZ I 500
1	Number of Phase And Application			1 Single Phase	3 single phase OLTCs for any connection
2	Max. Rated Through-Current (A)			500	
3	Short-circuit current test (kA)	Thermal (3s)		5	
		Dynamic (Peak)		12.5	
4	Max. Rated Step Voltage (V)			900	
5	Rated Switching Capacity (kVA)			250	
6	Max. Operating Positions			13, in linear regulation	
7	Rated Frequency (Hz)			50 or 60	
8	Insulation To Ground	Highest Voltage For Equipment Um (kV)		40.5	
		Rated separate source AC withstand Voltage (kV/50Hz,1min)		85	
		Rated lightning impulse withstand voltage (kV, 1.2/50 μs)		200	
9	Internal Insulation	Between Tap In Service And Pre-Selected Tap	Rated separate source AC withstand Voltage (kV/50Hz,1min)		5
			Rated lightning impulse withstand voltage (kV, 1.2/50 μs)		20
		Across Fine Tap Winding	Rated separate source AC withstand Voltage (kV/50Hz,1min)		20
			Rated lightning impulse withstand voltage (kV, 1.2/50 μs)		80
10	Ambient Temperature of Operation (°C)			-25 ~ +65	
11	Ambient Media of Operation			Air	
12	Adopted Motor Drive Unit			SHM or CMA7	
13	Electric Life			Not Less Than 300,000 Operations	
14	Mechanical Life			Not Less Than 800,000 Operations	
15	OLTC Weight (Excluding Motor Drive Unit, Approx.)			80	240



Characteristics

- Enclosed structure and great capability of protection against pollution.
- Three sections of tap selector, diverter unit and vacuum interrupter with reasonable structure and not interfering each other.
- The diverter unit employs traditional mechanical drive system and fast moving mechanism, housed especially in an enclosed cabinet, therefore it realizes oil lubrication and ensures reliable operation.
- The vacuum interrupter are fixed completely in the insulation frame, it will not be interfered by the moving of contacts.
- The tap selector adopts parallel structure, thus capacity of the tap changer is increased.

Shanghai Huaming Power Equipment Co., Ltd.

Address: No 977 Tong Pu Road, Shanghai 200333, P.R.China
 Tel: +86 21 5270 3965 (direct)
 +86 21 5270 8966 Ext. 8688 / 8123 / 8698 / 8158 / 8110 / 8658
 Fax: +86 21 5270 2715
 Web: www.huaming.com E-mail: export@huaming.com