

I want to explain the RS-232 support for the E series. It is a very limited command list that is based on the P/V series type commands.

Using PD Comms Tool:

1. "Test" button - This will not work because the E series display is not going to send the same response as the P and V series.

2. Supported Commands:

Power On - 01 30 41 30 41 30 43 02 43 32 30 33 44 36 30 30 30 31 03 73 0D  
Power Off - 01 30 41 30 41 30 43 02 43 32 30 33 44 36 30 30 30 34 03 76 0D  
Input VGA - 01 30 41 30 45 30 41 02 30 30 36 30 30 30 30 31 03 73 0D  
Input Composite - 01 30 41 30 45 30 41 02 30 30 36 30 30 30 30 35 03 77 0D  
Input TV - 01 30 41 30 45 30 41 02 30 30 36 30 30 30 30 41 03 03 0D  
Input Component - 01 30 41 30 45 30 41 02 30 30 36 30 30 30 30 43 03 01 0D  
Input HDMI 1 - 01 30 41 30 45 30 41 02 30 30 36 30 30 30 31 31 03 72 0D  
Input HDMI 2 - 01 30 41 30 45 30 41 02 30 30 36 30 30 30 31 32 03 71 0D  
Input HDMI 3 - 01 30 41 30 45 30 41 02 30 30 36 30 30 30 31 33 03 70 0D  
Input USB: 01 30 41 30 45 30 41 02 30 30 36 30 30 30 31 34 03 77 0D  
Audio Mute - 01 30 41 30 45 30 41 02 30 30 38 44 30 30 30 31 03 09 0D  
Audio Un-mute - 01 30 41 30 45 30 41 02 30 30 38 44 30 30 30 32 03 0A 0D  
TV Channel Up - 01 30 41 30 45 30 41 02 30 30 38 42 30 30 30 31 03 0F 0D  
TV Channel Down - 01 30 41 30 45 30 41 02 30 30 38 42 30 30 30 32 03 0C 0D  
Control Button Lock - 01 30 41 30 45 30 41 02 30 30 46 42 30 30 30 31 03 71 0D  
Control Button Unlock - 01 30 41 30 45 30 41 02 30 30 46 42 30 30 30 30 03 70 0D  
VGA Auto Adjust - 01 30 41 30 45 30 41 02 30 30 31 45 30 30 30 31 03 01 0D  
Analog Closed Caption Off - 01 30 41 30 45 30 41 02 31 30 38 34 30 30 30 31 03 78 0D  
Analog Closed Caption CC1 - 01 30 41 30 45 30 41 02 31 30 38 34 30 30 30 32 03 7B 0D  
Analog Closed Caption CC2 - 01 30 41 30 45 30 41 02 31 30 38 34 30 30 30 33 03 7A 0D  
Analog Closed Caption CC3 - 01 30 41 30 45 30 41 02 31 30 38 34 30 30 30 34 03 7D 0D  
Analog Closed Caption CC4 - 01 30 41 30 45 30 41 02 31 30 38 34 30 30 30 35 03 7C 0D  
Analog Closed Caption TT1 - 01 30 41 30 45 30 41 02 31 30 38 34 30 30 30 36 03 7F 0D  
Analog Closed Caption TT2 - 01 30 41 30 45 30 41 02 31 30 38 34 30 30 30 37 03 7E 0D  
Analog Closed Caption TT3 - 01 30 41 30 45 30 41 02 31 30 38 34 30 30 30 38 03 71 0D  
Analog Closed Caption TT4 - 01 30 41 30 45 30 41 02 31 30 38 34 30 30 30 39 03 70 0D  
Digital Closed Caption Off - 01 30 41 30 45 30 41 02 31 30 41 31 30 30 30 31 03 04 0D  
Digital Closed Caption Srv1 - 01 30 41 30 45 30 41 02 31 30 41 31 30 30 30 32 03 07 0D  
Digital Closed Caption Srv2 - 01 30 41 30 45 30 41 02 31 30 41 31 30 30 30 33 03 06 0D  
Digital Closed Caption Srv3 - 01 30 41 30 45 30 41 02 31 30 41 31 30 30 30 34 03 01 0D  
Digital Closed Caption Srv4 - 01 30 41 30 45 30 41 02 31 30 41 31 30 30 30 35 03 00 0D  
Digital Closed Caption Srv5 - 01 30 41 30 45 30 41 02 31 30 41 31 30 30 30 36 03 03 0D  
Digital Closed Caption Srv6 - 01 30 41 30 45 30 41 02 31 30 41 31 30 30 30 37 03 02 0D  
Volume 0 : 01 30 41 30 45 30 41 02 30 30 36 32 30 30 30 30 03 70 0D  
Volume 10 : 01 30 41 30 45 30 41 02 30 30 36 32 30 30 30 41 03 01 0D  
Volume 20 : 01 30 41 30 45 30 41 02 30 30 36 32 30 30 31 34 03 75 0D  
Volume 40 : 01 30 41 30 45 30 41 02 30 30 36 32 30 30 32 38 03 7A 0D  
Volume 60 : 01 30 41 30 45 30 41 02 30 30 36 32 30 30 33 43 03 00 0D  
Volume 80 : 01 30 41 30 45 30 41 02 30 30 36 32 30 30 35 30 03 75 0D  
Volume 100: 01 30 41 30 45 30 41 02 30 30 36 32 30 30 36 34 03 72 0D