

250A Cont, 6000A @ 10 sec, 0.21 Ohms		FREQUENCY 60		PHASE 1		TYPE COIL & AIR CORE	
VOLTAGE 4160V L-L (60kV BIL)							
CENTER LEG N/A		TUBE 5-1/8 OD Circular Tube*				COIL LENGTH 22 3/8	
		Wind 1 Coil					
WINDING		Single Winding					
WIRE SIZE		(5 wide) 0.144 x 0.365 Nomex Cu Wire (340825: .144 x .365 220C, Nomex, Non-Solderable, Copper Wire)					
TURNS		91-1/2					
LEADS		H1		H2			
		0		91-1/2			
KEEPBACK		2-3/4 PO Every Third Layer					
WDG LENGTH		16 7/8					
TURNS/LAYER		8. Last layer short. Pack out rest of layer					
LAYERS		12					
LAYER INSULATION		(2) 0.010 TV + 1/4 Stick AR after layer 4, 8** (2) 0.010 TV all other layers					
WRAPPER		(2) 0.010 TV					
MLT		24.5					
WIRE WEIGHT		188.0					
LEADS:				NOTES:			
H1 Braze to TC-800824 Item 101, out 1/2" to 1st bend. LV Sleeve 1/2" past 2nd bend.				*See Winding Tube Sheet for mold and tube details **Place sticks 2.5" or less apart to ensure at least 3/16 gap between layers.			
H2 Braze to TC-800824 Item 102, out face of coil. See position below.							
PADS: H1: (4) 0.015 TV, 4" out, 5" Wide. Fold and tape to match bends. H2: Pad under (4) 0.015 TV, Flush, 5" Wide.							
Top 5-1/8 H2 2-3/4" H1 Bottom Coil Diagram				Finished Coil			
Size over Layer 6: 7 3/4 x 8 1/16							
Calculated Coil Size: 10 1/2 x 11 1/8				Either dimension off by 3/4 (high or low) check winding and alert engineering			
Max Coil Size: 11							
Measured Coil Size:				x			
Revision Notes		ENGINEERED BY		NF		WINDING SHEET WS-800824	
		REVIEWED BY					
		REVISION DATE		9/9/24			
		REVISION NUMBER					