PCB Specification

Sparrow FE N-Top

E-Sharp AB

Revision History

REVISION	AUTHOR	CHANGES
0	Martin Johansson	First draft

Table of Contents

1 Specification 3

1.1 Requirement 3

1.2 Stackup 3

2 Contact Information 4

1 Specification

1.1 Requirement

Board thickness	1.6mm +/-10%
Number of Layers	6
Impedance controlled layers (Target 50ohm +/-10%)	3, 4

1.2 Stackup

The design trace widths are set to hit the target impedance using the below specified stackup. **The stackup and trace width may be changed by the manufacturer if board thickness and impedance control targets are kept.**

Layer Stackup

Layers: 6 Thickness: 1.6 Outer Copper Weight: 1 Inner Copper Weight: 0.5

No requirement | JLC06161H-3313 | JLC06161H-7628 | JLC06161H-1080
JLC06161H-2116A | JLC06161H-1080A | JLC06161H-1080B | JLC06161H-3313E
JLC06161H-3313A | JLC06161H-2116B | JLC06161H-2116 | JLC06161H-7628B
JLC06161H-3313D | JLC06161H-7628A

Layer	Material Type	Thickness	
Top Layer	Copper	0.035mm	
Prepreg	3313*1	0.107mm	
Prepreg	1080*1	0.07640mm	
Inner Layer L2	Copper	0.0152mm	0.25mm H/HOZ without copper
Core	Core	0.25mm	
Inner Layer L3	Copper	0.0152mm	
Prepreg	7628*1	0.21040mm	
Prepreg	2116*1	0.124mm	
Prepreg	7628*1	0.21040mm	
Inner Layer L4	Copper	0.0152mm	0.25mm H/HOZ without copper
Core	Core	0.25mm	
Inner Layer L5	Copper	0.0152mm	
Prepreg	1080*1	0.07640mm	
Prepreg	3313*1	0.107mm	
Bottom Layer	Copper	0.035mm	

* This is a special stackup, and it doesn't support economic PCB assembly.

2 Contact Information

Email address: martin.johansson@esharp.se