PCB Specification

Sparrow Fixture Electronics

E-Sharp AB

Revision History

REVISION	AUTHOR	CHANGES
0	Martin Johansson	First draft

Table of Contents

1 Specification 3

1.1 Requirement 3

1.2 Stackup 3

2 Contact Information 4

1 Specification

1.1 Requirement

Board thickness	1.6mm +/-10%
Number of Layers	8
Impedance controlled layers (Target 50ohm +/-10%)	1, 3, 6, 8

1.2 Stackup

The design trace widths are set to hit the target impedance using the below specified stackup. **The stackup and trace width may be changed by the manufacturer if board thickness and impedance control targets are kept.**

JLC08161H-1080(Finished thickness1.62mm±10%) | **JLC08161H-1080A(Special/Finished thickness1.62mm±10%)** | JLC08161H-1080B(Special/Finished thickness1.65mm±10%)

Impedance (Ω)	Type	Signal Layer	Top Ref	Bottom Ref	Trace Width	Trace Spacing	Impedance trace to copper
50	Single Ended (Non coplanar)	L1	/	L2	118.3640	/	/
50	Single Ended (Non coplanar)	L3	L2	L4	126.2380	/	/
50	Single Ended (Non coplanar)	L6	L5	L7	126.2380	/	/
50	Single Ended (Non coplanar)	L8	L7	/	118.3640	/	/

Layer	Material	Thickness (mil)	Thickness (mm)
L1	Outer Copper Weight1oz	1.38	0.0350
Prepreg	1080 RC67% 3.3mil	3.01	0.0764
L2	Inner Copper Weight	0.60	0.0152
Core	0.10mm H/HOZ without copper	3.94	0.1000
L3	Inner Copper Weight	0.60	0.0152
Prepreg	7628, RC 49%, 8.6 mil	8.28	0.2104
Prepreg	1080 RC67% 3.3mil	3.31	0.0840
Prepreg	7628, RC 49%, 8.6 mil	8.28	0.2104
L4	Inner Copper Weight	0.60	0.0152
Core	0.10mm H/HOZ without copper	3.94	0.1000
L5	Inner Copper Weight	0.60	0.0152
Prepreg	7628, RC 49%, 8.6 mil	8.28	0.2104
Prepreg	1080 RC67% 3.3mil	3.31	0.0840
Prepreg	7628, RC 49%, 8.6 mil	8.28	0.2104
L6	Inner Copper Weight	0.60	0.0152
Core	0.10mm H/HOZ without copper	3.94	0.1000
L7	Inner Copper Weight	0.60	0.0152
Prepreg	1080 RC67% 3.3mil	3.01	0.0764
L8	Outer Copper Weight1oz	1.38	0.0350

2 Contact Information

Email address: martin.johansson@esharp.se