PCB Specification

Sparrow Fixture Link

E-Sharp AB

Revision History

REVISION	AUTHOR	CHANGES
0	Martin Johansson	First draft

Table of Contents

1 Specification 3

1.1 Requirement 3

1.2 Stackup 3

2 Contact Information 4

1 Specification

1.1 Requirement

Board thickness	1.2mm +/-10%
Number of Layers	6
Impedance controlled layers (Target 50ohm +/-10%)	1, 3, 4, 6

1.2 Stackup

The design trace widths are set to hit the target impedance using the below specified stackup. **The stackup and trace width may be changed by the manufacturer if board thickness and impedance control targets are kept.**

< mm±10%) | JLC06121H-2116B(特殊/成品板厚1.12mm±10%) | JLC06121H-1080(Finished thickness1.19±0.10mm) | JLC06121H-1080A(Special/Finished thickness1.22mm±10%) >

Impedance (Ω)	Type	Signal Layer	Top Ref	Bottom Ref	Trace Width	Trace Spacing	Impedance trace to copper
50	Single Ended (Non coplanar)	L1	/	L2	118.3640	/	/
50	Single Ended (Non coplanar)	L3	L2	L4	130.8100	/	/
50	Single Ended (Non coplanar)	L4	L3	L5	130.8100	/	/
50	Single Ended (Non coplanar)	L6	L5	/	118.3640	/	/

Layer	Material	Thickness (mil)	Thickness (mm)
L1	Outer Copper Weight1oz	1.38	0.0350
Prepreg	1080 RC67% 3.3mil	3.01	0.0764
L2	Inner Copper Weight	0.60	0.0152
Core	0.10mm H/HOZ without copper	3.94	0.1000
L3	Inner Copper Weight	0.60	0.0152
Prepreg	2116 RC54% 4.9mil	4.58	0.1164
Bare board	0.5mm H/HOZ without copper	19.68	0.5000
Prepreg	2116 RC54% 4.9mil	4.58	0.1164
L4	Inner Copper Weight	0.60	0.0152
Core	0.10mm H/HOZ without copper	3.94	0.1000
L5	Inner Copper Weight	0.60	0.0152
Prepreg	1080 RC67% 3.3mil	3.01	0.0764
L6	Outer Copper Weight1oz	1.38	0.0350

2 Contact Information

Email address: martin.johansson@esharp.se