Brightline Electrical Contractors Ltd

RISK ASSESSMENT AND METHOD STATEMENT

Electrical containment and first fix

Project	Riverside Quarter office refurbishment
Location of works	Riverside Quarter, 3 Wharf Road, Northbridge NB3 8AF - floors 2 and 3
Document reference	BLE-RAMS-007
Activity	Installation of cable tray, basket and conduit, and first fix wiring to the small power and lighting circuits
Prepared by	Priya Natt
Date of issue	19/10/2026

Revision history

Rev	Date	Description	Prepared by	Approved by
01	19/10/2026	First issue	P. Natt	G. Holloway

METHOD STATEMENT

Scope of works *Describe the work to be carried out and where.*	Install cable tray and basket in the ceiling void and conduit drops to floor boxes on floors 2 and 3, then pull and terminate first fix cabling to distribution boards DB2A and DB3A.
Sequence of works *Set out the work step by step.*	Mark out routes from the containment drawings E-201 and E-301. Fix tray supports, install tray and basket, earth bond all sections. Install conduit drops, pull cables from drums on stands, label and test continuity.
Supervisor and competence *Who supervises and what are the operatives' qualifications?*	Supervisor: Gary Holloway, Approved Electrician (JIB), SMSTS. Electricians hold ECS gold cards; apprentices work under direct supervision.
Communication *How will the RAMS be briefed?*	Toolbox talk on this RAMS before the start, briefing record signed by all operatives.
PPE *List the PPE required for this task.*	Safety helmet, safety boots, hi-vis vest, gloves to EN 388. Safety glasses when drilling or cutting tray; dust mask FFP3 when drilling.
Plant and equipment *List plant and tools and how they are inspected.*	Podium steps (weekly inspection, tagged) and one scissor lift with LOLER certificate. Cordless drills and tray cutters; cable drum stands and rollers.
COSHH *List hazardous substances and attach COSHH assessments.*	Cable pulling lubricant: COSHH assessment BLE-C-12 and safety data sheet attached.
Housekeeping and waste *How will materials and waste be managed?*	Cable drums stored on the floor laydown area, tray in racks. Offcuts of tray and cable segregated in the metal and cable recycling bins at the end of each day.
Permits *Which permits to work are needed?*	Permit to work for any work on or near the existing live distribution boards, issued by the main contractor's authorised person. Isolation and lock-off before connection.
Emergency *Describe the emergency procedures.*	Fire: raise the alarm, leave by the nearest stair, assemble at Wharf Road gate. Electric shock: isolate, call 999, trained first aider Gary Holloway; defibrillator at reception.
Monitoring *How will the safe system of work be monitored?*	N/A
Occupational health *Which health risks apply and how are they controlled?*	Manual handling of cable drums: drum stands and rollers, two-person lifts.

RISK ASSESSMENT

Task	Containment and first fix wiring	**Assessment no.**	BLE-RA-007
Assessed by	Priya Natt	**Date**	19/10/2026
Review date	19/01/2027	**Location**	Riverside Quarter, floors 2 and 3

Persons at risk (tick all that apply)	[X] Own operatives [ ] Other trades [ ] Client staff [ ] Visitors [ ] Members of the public

Activity / hazard	Risk	L	S	R	Control measures	Residual
Work from podium steps and scissor lift	Fall from height	3	4	12	Podium steps with gates closed; IPAF-trained scissor lift operators; no over-reaching.	Low (4)
Use of power tools and tray cutters	Cuts, entanglement	3	3	9	Guards fitted, cut-resistant gloves, tools inspected before use.	Low (3)
Cable pulling	Manual handling, strain injury	3	3	9	Drum stands and rollers, two-person pulls, rotation of tasks.	Low (3)
Work near live boards	Electric shock, burns	2	5	10	Permit to work, safe isolation procedure, lock-off, proving unit, insulated tools.	Low (5)
~~Asbestos in ceiling void~~	~~Exposure to asbestos fibres~~	~~2~~	~~5~~	~~10~~	~~Refurbishment survey checked before work; stop and report if suspect material is found.~~	~~Low (5)~~
Drilling into concrete	Dust	3	3	9	Cordless drills with dust shrouds, FFP3 masks.	Low (3)

L = likelihood, S = severity (1 to 5), R = L x S. 1-6 low, 8-12 medium, 15-25 high.

Emergency: rescue from the scissor lift by ground controls; electric shock procedure as the method statement.

BRIEFING RECORD

I confirm that the contents of this RAMS have been explained to me and that I understand them.

Name	Company	Card / qualification	Signature	Date
Gary Holloway	Brightline Electrical	ECS gold, SMSTS		02/11/2026
Ana Ribeiro	Brightline Electrical	ECS gold		02/11/2026