


This page is referenced in the other drawings, but its contents are unknown. It was possibly a "bed of nails" flying probe schematic. Recreation of Apple engineering drawing 050-0253-01 Sheet: /Unknown/ File: Unknown.sch Title: Unknown Size: USLedger | Date: 2020-05-18 KiCad E.D.A. kicad (5.1.6-0-10_14)

Macintosh SE/30 MLB Address Line Pin Matrix

Address	ROM	UJ2 RAM Mux	UI2 RAM Mux F	UI3 RAM Mux	UJ3 RAM Mux	UJ4 RAM Mux	UI4 RAM Mux	UI8 GLUE	UK12 VIA1	UK11 VIA2	UK6 Vid ROM	UA8 Video Mux	UB8 Video Mux	UC8 Video Mux	UD8 Video Mux	UJ11 SWIM	UG12 Serial	UE10 Sound	UK8 CPU	UI5 FPU	J13 PDS Slot
A(0)								77			10				4			41	A2		116
A(1)								74			9				12		39	42	C4	25	76
A(2)	4	3,6									8			4			37	43	D13	24	36
A(3)	5	2,5									7			12				44	D12	23	115
A(4)	6	10,13									6		4					1	C13	22	75
A(5)	7	11,14									5		12					2	C12		35
A(6)	8		3,6								4	4						3	D11		114
A(7)	9		2,5								3	12						4	B13		34
A(8)	31		10,13								25				3			7	B12		113
A(9)	32		11,14						42	42	24				13	37		8	C11		73
A(10)	33			3,6					41	41	21			3		40		9	A13		33
A(11)	34			2,5					40	40	23			13		41		10	C10		112
A(12)	35			10,13					39	39	2		3			42			B11		72
A(13)	36			11,14				46					13						A12		32
A(14)	37				3,6			45											B10		111
A(15)	38				2,5			44											A11		31
A(16)	39				10,13			41											B9		110
A(17)	40				11,14			28											A10		70
A(18)	41					3,6													C8		30
A(19)	42					2,5													A9		109
A(20)	43					10,13		61											B8		69
A(21)	44					11,14													A8		29
A(22)	45						3,6	58											B7		108
A(23)							2,5												A7		28
A(24)							10,13	56											A6		107
A(25)							11,14	40											B6		67
A(26)								55											A5		27
A(27)								39											B5		106
A(28)								37											A4		66
A(29)								36											B4		26
A(30)								34											A3		105
A(31)								31											B3		25





Macintosh SE/30 MLB Data Line Pin Matrix

Address				D6 Diode Dio			D10 D11 Diode Diode		D13 D14 D15 Diode Diode Diode	D16 Diode	D17 Diode D	D18 D19 Diode	S1A S1B RAM RAM	S2A S2B RAM RAM	S3A S3B RAM			UK12 VIA1	UK11 VIA2	UK6 VROM	UC6 VRAM	UC7 VRAM	UJ11 SWIM	UI12 SCSI	UG12 U		B UI5	J13 PDS
D(0)	14	1											3		3											K1	3 3	13
D(1)	15			1									6		6											K1	2 2	93
D(2)	16				1								10		10											L1	3 1	14
D(3)	17						1						13		13											M1	3 68	3 54
D(4)	18							1					16		16											L1	2 67	7 94
D(5)	19								1				20		20											K1	1 66	5 15
D(6)	20									1			23		23											M1	2 6	5 55
D(7)	21											1	25		25											L1	1 64	4 95
D(8)	22	2											3		3											N1	3 62	2 16
D(9)	23			2									6		6											M1	1 60	96
D(10)	24				2								10		10											L1	59	9 17
D(11)	25						2						13		13											N1	2 58	3 57
D(12)	26							2					16		16											M1	0 57	7 97
D(13)	27								2				20		20											N1	1 56	5 18
D(14)	28									2			23		23											M		
D(15)	29											2	25		25											N1	0 54	4 98
D(16)	47		1											3		3										NS		
D(17)	48			•	1									6		6										M		
D(18)	49					1								10		10										N		
D(19)	50						1							13		13										N7		
D(20)	51								1					16		16										M		
D(21)	52								1		_			20		20										N6		
D(22)	53										1	_		23		23										Me		
D(23)	54											1		25		25		00	00				4	00		NS		
D(24)	55		2		_									3			3	36	36	11		5	4	28		22 M		
D(25)	56			2	2									6			6	35	35	12		6	5	27		21 N4		
D(26)	57					2								10			10	34	34	13		19	8	26		20 N3		
D(27)	58						2		0					13			13	32	32	15	_	20	9	25		19 M		
D(28)	59								2					16			16	31	31	16	5		13	24		18 N2		
D(29)	60								2		0			20			20	30	30	17	6		14	22		17 M		
D(30)	61										2			23			23	29	29	18	19		15	21		16 L4		
D(31)	62											2		25			25	28	28	19	20		18	20		15 N ⁻		3 104 1 68 61

