



V93000 Specifications

EXA Scale Infrastructure

Version 8.6.0

Published on 2023-02-24

Notices

Legal Notices

All rights reserved. All text and figures included in this publication are the exclusive property of Advantest Corporation. Reproduction of this publication in any manner without the written permission of Advantest Corporation is prohibited. Information in this document is subject to change without notice.

Trademarks and Registered Trademarks

- ADVANTEST is a trademark of Advantest Corporation.
- All other marks referenced herein are trademarks or registered trademarks of their respective owners.

Warranty

The material contained in this document is provided "as is," and is subject to being changed, without notice, in future editions. Further, to the maximum extent permitted by applicable law, Advantest disclaims all warranties, either express or implied, with regard to this material and any information contained herein, including but not limited to the implied warranties of merchantability and fitness for a particular purpose. Advantest shall not be liable for errors or for incidental or consequential damages in connection with the furnishing, use, or performance of this material or of any information contained herein. Should Advantest and the user have a separate written agreement with warranty terms covering the material in this document that conflict with these terms, the warranty terms in the separate agreement shall control.

Technology Licenses

The hardware and/or software described in this document are furnished under a license and may be used or copied only in accordance with the terms of such license.

Restricted Rights Legend

If software is for use in the performance of a U.S. Government prime contract or subcontract, Software is delivered and licensed as "Commercial computer software" as defined in DFAR 252.227-7014 (June 1995), or as a "commercial item" as defined in FAR 2.101(a) or as "Restricted computer software" as defined in FAR 52.227-19 (June 1987) or any equivalent agency regulation or contract clause. Use, duplication or disclosure of Software is subject to Advantest's standard commercial license terms for 93000 systems and non-DOD Departments and Agencies of the U.S. Government will receive no greater than Restricted Rights as defined in FAR 52.227-19(c)(1-2) (June 1987). U.S. Government users will receive no greater than Limited Rights as defined in FAR 52.227-14 (June 1987) or DFAR 252.227-7015 (b)(2) (November 1995), as applicable in any technical data.

Safety Notices

⚠ CAUTION A CAUTION notice denotes a hazard. It calls attention to an operating procedure, practice, or the like that, if not correctly performed or adhered to, could result in damage to the product or loss of important data. Do not proceed beyond a CAUTION notice until the indicated conditions are fully understood and met.

▲ Warning A WARNING notice denotes a hazard. It calls attention to an operating procedure, practice, or the like that, if not correctly performed or adhered to, could result in death or severe injury. Do not proceed beyond a WARNING notice until the indicated conditions are fully understood and met.

Infrastructure specifications - V93000 EXA Scale systems

Scope of specifications

Advantest specifies and verifies the specifications at the DUT interface pogo level. Using an adequate DUT board, valid system calibration and a fixture delay measurement (TDR), these specifications are valid at the device under test as well. Specifications describe warranted product performance. Characteristics are included as typical values to provide additional useful information by describing typical non-warranted performance.

Test programming and debug

The SmartTest production test environment includes manufacturing test interfaces to operators, handling equipment and factory networks. A graphical testflow editor links device tests into a production-ready test program, where the tests are set up via fill-in-the-blank test functions. User-specific tests are programmed with test methods in Java. Links are available for design-to-test conversion. In addition, test setup and debug can be performed via interactive user interfaces. Result analysis tools are available for error locations, timing behavior, analog waveforms, shmoo plots, pin margin tests and memory bit map.

Supported channel cards

The following native V93000 EXA Scale channel cards are supported:

- XPS256
- PS5000
- Link Scale USB3

In addition, the following cards of Smart Scale systems are supported:

- AVI64
- DPS128
- DPS64
- PMUX
- PS9G
- PS1600
- PSSL
- UHC4T
- Wave Scale RF/MX
- Wave Scale Precision Source
- RF Pure Clock

These cards can be mixed within one card cage of the test head if the correct slot configuration is selected.

The following combinations in a single test program are not supported:

- PS1600 and PS5000
- DPS64 or DPS128 together with XPS

EXA Scale - Xtreme Link

The V93000 EXA Scale system employs Xtreme Link technology, a communication network designed specifically for Automatic Test Equipment (ATE). The technology provides high-speed data connections, embedded computing power, and instant card-to-card communication.

- **Specialized ATE network:** Xtreme Link technology enables the highest bandwidth for large test data which leads to the fast data transfer across ATE pins and to workstation, reduction test time and Instant pin to pin networking. Instant communication between all pins enables fast response to device conditions, alarms, Instrument to instrument synchronization and real time site shutdown.
- **Digital upload performance:** EXA Scale Xtreme Link dramatically improves the digital capture result upload performance.
- **Scan diagnosis:** EXA Scale Xtreme Link significantly improves uploads scan results.
- **Xtreme Pooling:** Flexible memory pooling and sharing across entire card without application bandwidth limitation for efficiently using on-board memory independent of pin usage enabled by Xtreme Link.
- **Unlimited ganging:** EXA Scale Xtreme Link enables unlimited ganging of DPS channels across cards without compromising accuracy.

Compatibility

Software is compatible between all test heads.

The same DUT boards fit on all test heads. The docking system is identical for all test heads. The detailed docking pin positions might differ between different test heads. For details check the documentation on docking.

Operating system

Linux Red Hat Enterprise is used in all test head configurations.

Calibration and operation

Warm-up time	60 minutes
Basic maintenance period	6 months
Base calibration period (traceable calibration)	6 months
Calibration period (system auto adjustment)	3 months ^[1]
Period for AVI64 enhanced accuracy adjustment (AVI64 enhanced accuracy calibration)	1 week

Further information

For more information about the Advantest V93000 SOC Series, please visit www.advantest.com.

Contact information

For more information about the Advantest V93000 SOC cards, please contact your local Advantest sales representative.

This information is subject to change without notice.

^[1] Valid at ambient temperature within ± 2.5 K of calibration temperature.

Test heads

Maximum channel count	CX test head	SX test head	LX test head
Number of card cages	1	2	3
Number of slots	9	18	27
PS1600	1152	2304	3456
DPS128	1152	2304	3456
PS5000	2304	4608 ^[2]	6912 ^[2]
XPS256	2304	4096 ^[3]	4096 ^[3]

The use of other digital channel cards, DC cards, analog instruments or RF cards may reduce the maximum channel count.

^[2] With EK601-61604 VHD pogo cable assembly: 4 VHD type pogo blocks, 64 channels per pogo block.

^[3] DUT interface limited (32 channel VHD pogo cable only, DUT interface has 128 pogo blocks available)

System slots

Supported slots

Maximum card count	CX test head	SX test head	LX test head
Number of card cages	1	2	3
Max. number of slots	9 ^[4]	18 ^[4]	27 ^[4]

Note

Mixing of different card types is supported within one test head. DC/DC power for V93000 EXA Scale systems is different than for Smart Scale and Pin Scale systems. This means you need to configure the system with the correct power to operate correctly.

Refer to the corresponding card specification for details.

^[4] No Utility Card installed, using Internal Utility Line option.

Device power supplies

Supported channel slot device power supplies

Maximum channel count	CX test head	SX test head	LX test head
Number of slots	9	18	27
DC Scale AVI64 (E8025AVI)	576	1152	1728
DC Scale DPS128-HC (E8023CS)	1152	2048 ^[5]	2048 ^[5]
DC Scale DPS128-HV (E8023CSW)	1152	2048 ^[5]	2048 ^[5]
DC Scale DPS128-HC/HV (E8023CSV)	1152	2048 ^[5]	2048 ^[5]
DC Scale DPS64-HC (E8023CSH)	576	1152	1728
DC Scale FVI16 (E8026PV)	144	288	432
DC Scale UHC4T (E8024UH)	36	72	108
DC Scale XPS256	2304 ^[6]	4096 ^[7]	4096 ^[7]
DC Scale XPS128	1152	2304 ^[6]	3456 ^[6]
DC Scale XPS128+HV	1152	2304 ^[6]	3456 ^[6]

Note

Mixing different device power supply types within one Test Head is supported.
Refer to DC Scale device power supply specification sheet for more information.

^[5] DUT interface limited (16 channel HD pogo blocks, DUT interface has 128 pogo blocks available)

^[6] Requires 32 channel VHD pogo cable assembly

^[7] DUT interface limited (32 channel VHD pogo cable assembly only, DUT interface has 128 pogo blocks available)

Parametric measurements

Direct DVM Access (at utility pogo block)

A DVM can be routed through the DC rail onto each tester channel.

Supported Digital Multimeter (DMM)

Keysight 3458A with option 002


Absolute voltage measurement accuracy

$\pm 40\mu\text{V}$ + DMM specification

Input voltage range

-5 V to 7.5 V

The diagram of the system control board is shown below.



The system control board diagram

Utility resources

Utility resources are the utility power supplies and the utility lines that you can use to supply and control additional hardware on the DUT board.

Utility lines of V93000 EXA Scale systems allow you to control external devices such as relays, solenoids or indicators, depending on the application. The lines are implemented as FET switch outputs.

The utility power supplies of V93000 EXA Scale systems support DUT boards with additional active components. Typical examples for these active components are relays, switches, operational amplifiers, and buffers.

Internal utility resources

Internal utility resources of a V93000 EXA Scale system in the basic configuration consist of 32 statically controlled utility lines, a +5 V utility power supply and the Internal Utility Power Option. For the SX and LX test heads, the internal utility resources can optionally be extended by 32 more utility lines and one +5 V supply. Internal utility resources can be replaced and extended by an optional Utility Card.

Internal utility lines

In the following table, only the "Basic configuration" columns with "Optional Utility Card (EK051A)" set to "none" apply to the internal utility lines. The other columns require the installation of minimum one optional *Utility Card (EK051 and EK051A)* on page 14 that replaces the internal utility lines.

Configuration: Basic configuration			Utility Card configuration		
TH: CX / SX / LX			CX / SX / LX		
Slots: 9 / 18 / 27			9 / 18 / 27		
CX test head supports only one internal utility module.					
Internal utility modules: 1		2 ^[8]	none	none	
Optional Utility Cards (EK051 and EK051A): none		none	1	2	
Configuration					
Number of utility lines		32	64	256	512

^[8] Option of the SX and LX test heads.

Configuration: Basic configuration			Utility Card configuration	
TH: CX / SX / LX			CX / SX / LX	
Slots: 9 / 18 / 27			9 / 18 / 27	
CX test head supports only one internal utility module.				
Internal utility modules: 1		2 ^[8]	none	none
Optional Utility Cards (EK051 and EK051A):	none	none	1	2
Pogo block	UTIL 1 (165)	UTIL 1 (165) UTIL 3 (167)	UTIL 1 ... 8 (165 ... 172)	UTIL 1 ... 8 (165 ... 172) DPS 1 ... 8 (265 ... 272)
			Note: The 4-row utility pogo blocks of the second Utility Card replace all existing 3-row DPS-slot pogo blocks. The DPS block sequence of the second Utility Card differs from the UTIL block sequence of the first card. For the correct pogo block assignment of the second card, refer to "Utility pogo block mapping" in TDC topic "Utility pogo block - Utility Card (V93000 EXA Scale systems)" (347642).	
Sequencer control	no	no	yes	yes

Output

Type Open drain

Maximum current 100 mA per line

Cut-off line current 130 ±15 mA after 250 µs

Voltage

Output switch open,
no load applied

Each utility line has an internal pull-up resistor of 10 kΩ to the internal supply voltage of 3.3 V.

We recommend using external pull-up resistors for applications with different requirements.

Output switch closed

V_{ds} 0.5 V maximum

R_{on} < 5 Ω

Input

Type TTL

Voltage range 0 V ... 5.0 V

^[8] Option of the SX and LX test heads.

Configuration: Basic configuration		Utility Card configuration	
TH: CX / SX / LX		CX / SX / LX	
Slots: 9 / 18 / 27		9 / 18 / 27	
CX test head supports only one internal utility module.			
Internal utility modules: 1	2 ^[8]	none	none
Optional Utility Cards (EK051 and EK051A): none	none	1	2
Maximum voltage rating		5.5 V, internal clamp diode to 5 V	
Maximum clamp current			
per channel	200 mA	200 mA	200 mA
total	800 mA	800 mA per utility module	800 mA per card
Input impedance		10 kΩ typ.	
Input thresholds			
Maximum V _{IL}	1.3 V typ.		
Minimum V _{IH}	2.1 V typ.		

Internal utility power supplies

Utility power supply - UP5V pins

In the following table, only the "Basic configuration" columns with "Optional Utility Cards (EK051A)" set to "none" apply to the internal UP5V utility power supply. The other columns require the installation of minimum one optional *Utility Card (EK051 and EK051A)* on page 14 that replaces the internal UP5V utility power supply.

Configuration: Basic configuration		Utility Card configuration	
TH: CX / SX / LX		CX / SX / LX	
Slots: 9 / 18 / 27		9 / 18 / 27	
CX test head supports only one internal utility module.			
Internal utility modules: 1	2 ^[9]	none	none
Optional Utility Cards (EK051 and EK051A): none	none	1	2
Configuration			
Total number of supplies	1	2	1
			2

^[8] Option of the SX and LX test heads.

^[9] Option of the SX and LX test heads.

Configuration: Basic configuration			Utility Card configuration	
TH: CX / SX / LX			CX / SX / LX	
Slots: 9 / 18 / 27			9 / 18 / 27	
CX test head supports only one internal utility module.				
Internal utility modules: 1		2 ^[9]	none	none
Optional Utility Cards (EK051 and EK051A): none		none	1	2
Supply routed to pogo block	UTIL 1 (165)	UTIL 1 (165) UTIL 3 (167)	UTIL 1 ... 8 (165 ... 172)	UTIL 1 ... 8 (165 ... 172) DPS 1 ... 8 (265 ... 272)
			Note: The 4#row utility pogo blocks of the second Utility Card replace all existing 3#row DPS#slot pogo blocks. The DPS block sequence of the second Utility Card differs from the UTIL block sequence of the first card. For the correct pogo block assignment of the second card, refer to "Utility pogo block mapping" in TDC topic "Utility pogo block - Utility Card (V93000 EXA Scale systems)" (347642).	

Characteristics per supply

Output voltage		+5.0 V ±2 % sensed to the pogo pin			
Total output current		3.5 A	7.0 A	8.0 A	16.0 A
Maximum load capacitance		10000 µF			
Pogo pins	+5.0 V:	UP5V			
	GND:	UGND			
		Note: UP5V pins of different card cages or Utility Cards must not be connected together on the DUT board.			

Internal Utility Power Option

The Internal Utility Power Options can be routed to a 3#row DPS#slot pogo block if maximum one optional Utility card (EK051 or EK051A) is installed. The supply provides compatibility with the legacy SE-UDPS and requires the EK051UP pogo cable assembly.

^[9] Option of the SX and LX test heads.

Configuration

TH: CX		SX / LX
Slots: 9		18 / 27
Optional Utility Cards (EK051 Max 1 and EK051A):		Max 1 ^[10]
Maximum number of supplies	1	1 (SmarTest 8) / 2 (SmarTest 7.10)
First supply routed to pogo block	DPS 8 (268) ^[11]	DPS 8 (268) ^[11]
Second supply routed to pogo block	n.a.	DPS 1 (266) ^[12]
		lot The second supply is currently only supported for SmarTest 7.10.

Characteristics

Voltage	Accuracy	Maximum current	Pogo pins
			The "Internal Utility Power Option" is routed to a 3#row DPS#slot pogo block.
+5.0 V, sensed	±2 %	3 A	P1, PS1, G1 (two pins)
+12.0 V, sensed	±2 %	1 A	P2, PS2, G2 (two pins)
+15.0 V, sensed	±2 %	1 A	P3, PS3, G3 (two pins)
-15.0 V, sensed	±2 %	1 A	P4, PS4, G4 (two pins)

Utility Card (EK051 and EK051A)

The Utility Card provides 256 utility lines and several utility power supplies on eight 4-row pogo blocks. The cards can reside in any slot of a V93000 EXA Scale system. There are two variants available, EK051 and EK051A. The EK051 Utility card is used in SmarTest 8 only. The EK051A Utility card is used in both SmarTest 7 (SmarTest version 7.10 and higher) and SmarTest 8.

Utility lines

In the following table, only the "Utility Card configuration" columns with "Internal utility module" set to "none" apply to the Utility Card. The other columns show the capabilities of the *Internal utility resources* on page 10 with no Utility Card installed.

^[10] Maximum one Utility card (EK051 or EK051A) can be installed for accessing the Internal Utility Power Option. The second Utility card occupies the pogo block position that is required for the Internal Utility Power Option.

^[11] Pogo block DPS 8 (268) is the recommended position as defined in the V93000 Standard Configuration Guidelines.

^[12] Pogo block DPS 1 (266) is the recommended position as defined in the V93000 Standard Configuration Guidelines.

Configuration: Basic configuration		Utility Card configuration	
TH: CX / SX / LX		CX / SX / LX	
Slots: 9 / 18 / 27		9 / 18 / 27	
CX test head supports only one internal utility module.			
Internal utility modules: 1	2 ^[13]	none	none
Optional Utility Cards (EK051 and EK051A):	none	1	2

Configuration

Number of utility lines	32	64	256	512
Pogo block	UTIL 1 (165)	UTIL 1 (165) UTIL 3 (167)	UTIL 1 ... 8 (165 ... 172)	UTIL 1 ... 8 (165 ... 172) DPS 1 ... 8 (265 ... 272)
		Note: The 4-row utility pogo blocks of the second Utility Card replace all existing 3-row DPS-slot pogo blocks. The DPS block sequence of the second Utility Card differs from the UTIL block sequence of the first card. For the correct pogo block assignment of the second card, refer to "Utility pogo block mapping" in TDC topic "Utility pogo block - Utility Card (V93000 EXA Scale systems)" (347642).		
Sequencer control	no	no	yes	yes

Output

Type	Open drain
Maximum current	100 mA per line
Cut-off line current	130 ±15 mA after 250 µs
Voltage	
Output switch open, no load applied	Each utility line has an internal pull-up resistor of 10 kΩ to the internal supply voltage of 3.3 V. We recommend using external pull-up resistors for applications with different requirements.
Output switch closed	
V _{ds}	0.5 V maximum
R _{on}	< 5 Ω

^[13] Option of the SX and LX test heads.

Configuration: Basic configuration		Utility Card configuration	
TH: CX / SX / LX		CX / SX / LX	
Slots: 9 / 18 / 27		9 / 18 / 27	
CX test head supports only one internal utility module.			
Internal utility modules: 1	2 ^[13]	none	none
Optional Utility Cards (EK051 and EK051A):	none	1	2

Input

Type	TTL			
Voltage range	0 V ... 5.0 V			
Maximum voltage rating	5.5 V, internal clamp diode to 5 V			
Maximum clamp current				
per channel	200 mA	200 mA	200 mA	200 mA
total	800 mA	800 mA per utility module	800 mA	800 mA per card
Input impedance	10 kΩ typ.			
Input thresholds				
Maximum V _{IL}	1.3 V typ.			
Minimum V _{IH}	2.1 V typ.			

Utility power supplies**Utility power supply - UP5V pins**

In the following table, only the "Utility Card configuration" columns with "Internal utility module" set to "none" apply to the Utility Card. The other columns show the capabilities of the *Internal utility resources* on page 10 with no Utility Card installed.

Configuration: Basic configuration		Utility Card configuration	
TH: CX / SX / LX		CX / SX / LX	
Slots: 9 / 18 / 27		9 / 18 / 27	
CX test head supports only one internal utility module.			
Internal utility modules: 1	2 ^[14]	none	none
Optional Utility Cards (EK051 and EK051A):	none	1	2

Configuration

Total number of supplies	1	2	1	2
--------------------------	---	---	---	---

^[13] Option of the SX and LX test heads.

^[14] Option of the SX and LX test heads.

Configuration: Basic configuration			Utility Card configuration	
TH: CX / SX / LX			CX / SX / LX	
Slots: 9 / 18 / 27			9 / 18 / 27	
CX test head supports only one internal utility module.				
Internal utility modules: 1		2 ^[14]	none	none
Optional Utility Cards (EK051 and EK051A): none		none	1	2
Supply routed to pogo block	UTIL 1 (165)	UTIL 1 (165)	UTIL 1 ... 8 (165 ... 172)	UTIL 1 ... 8 (165 ... 172)
		UTIL 3 (167)		DPS 1 ... 8 (265 ... 272)
			Note: The 4#row utility pogo blocks of the second Utility Card replace all existing 3#row DPS#slot pogo blocks. The DPS block sequence of the second Utility Card differs from the UTIL block sequence of the first card. For the correct pogo block assignment of the second card, refer to "Utility pogo block mapping" in TDC topic "Utility pogo block - Utility Card (V93000 EXA Scale systems)" (347642).	

Characteristics per supply

Output voltage		+5.0 V ±2 % sensed to the pogo pin			
Total output current		3.5 A	7.0 A	8.0 A	16.0 A
Maximum load capacitance		10000 µF			
Pogo pins	+5.0 V:	UP5V			
	GND:	UGND			
		Note: UP5V pins of different card cages or Utility Cards must not be connected together on the DUT board.			

Utility power supply - XP pins

^[14] Option of the SX and LX test heads.

Configuration

TH: CX / SX / LX		
Slots: 9 / 18 / 27		
Utility Cards (EK051 and EK051A):	1 ^[15]	2
Total number of supplies	1	2
Supply routed to pogo block	UTIL 1 ... 8 (165 ... 172)	UTIL 1 ... 8 (165 ... 172) DPS 1 ... 8 (265 ... 272)
Note: The 4-row utility pogo blocks of the second Utility Card replace all existing 3-row DPS-slot pogo blocks. The DPS block sequence of the second Utility Card differs from the UTIL block sequence of the first card. For the correct pogo block assignment of the second card, refer to "Utility pogo block mapping" in TDC topic "Utility pogo block - Utility Card (V93000 EXA Scale systems)" (347642).		

Characteristics per power supply

Voltage	Accuracy	Maximum current	Max. load capacitance	Label
+5.0 V, sensed	±2 %	12.8 A	10000 µF	XPP5V
-5.0 V, sensed	±2 %	6 A	7000 µF	XPM5V
+3.3 V, sensed	±2 %	6 A	10000 µF	XPP3V3

Utility power supply - UPP15V / UPM15V / F24V pins

Configuration

TH: CX / SX / LX		
Slots: 9 / 18 / 27		
Utility Cards (EK051 and EK051A):	1 ^[16]	2
Total number of supplies	1	2
Supply routed to pogo block		
Voltage	Label	
+15 V	UPP15V	UTIL 2 + 8 (166 + 172) DPS 1 + 7 (266 + 272)

^[15] At least one Utility card (EK051 or EK051A) must be installed if the utility power supply on XP pins is to be used.

^[16] At least one Utility card (EK051 or EK051A) must be installed if the utility power supplies on UPP15V / UPM15V / F24V pins are to be used.

TH: CX / SX / LX			
Slots: 9 / 18 / 27			
Utility Cards (EK051 and EK051A):		1 ^[16]	2
-15 V	UPM15V	UTIL 3 + 5 (167 + 168) DPS 2 + 4 (267 + 269)	UTIL 3 + 5 (167 + 169) DPS 2 + 4 (267 + 269)
24 V floating ^[17]	F24VA	UTIL 4 (168)	UTIL 4 (168) DPS 8 (268)
	F24VB	UTIL 6 (170)	UTIL 6 (170) DPS 5 (270)
Note: The 4-row utility pogo blocks of the second Utility Card replace all existing 3-row DPS-slot pogo blocks. The DPS block sequence of the second Utility Card differs from the UTIL block sequence of the first card. For the correct pogo block assignment of the second card, refer to "Utility pogo block mapping" in TDC topic "Utility pogo block - Utility Card (V93000 EXA Scale systems)" (347642).			

Characteristics per power supply

Voltage	Accuracy	Maximum current	Max. load capacitance	Label
+15.0 V, sensed	±2 %	3 A	1000 µF	UPP15V
-15.0 V, sensed	±2 %	3 A	1000 µF	UPM15V
+24.0 V, sensed, floating ^[17]	±4 %	2 * 1 A	200 µF	F24VA and F24VB

Note

Connect all pogo pins (of all blocks) of a supply domain to a separate power plane on the DUT board. Connect all sense pins (of all blocks) of a supply domain to the power plane.

Maximum offset of utility ground to system ground: ±0.5 V

⚠ CAUTION Incorrect galvanic connection

Fault currents can damage electronic equipment.

➔ Do not connect utility power supply pogo pins of utility blocks together, if these utility blocks have been assigned to different internal utility modules or utility cards.

^[16] At least one Utility card (EK051 or EK051A) must be installed if the utility power supplies on UPP15V / UPM15V / F24V pins are to be used.

^[17] Floating range: ±24 V max.

Miscellaneous characteristics

Side panel port

Characteristics	CX test head	SX test head	LX test head
Number of card cages	1	2	3
DC rails	1	1	1

Reference 10MHz

Frequency	10 MHz
Impedance	50 Ω
Level	6 dBm (1.26Vpp) ^[18]
	1.26 Vpp
	AC-coupled
Accuracy	1 ppm ^[19]

DUT interface types

All test heads support the enhanced DUT Scale interface and feature the "infinite plane" concept, which means any DUT board size fits on any DUT interface.

^[18] Into 50 Ω

^[19] Without external adjustment

Environmental

Operating	15 °C to 30 °C (59 °F to 86 °F)
Maximum rate of change	± 2 #/h (3.6 #/h)
Specification warranted temperature	20 °C to 30 °C (68 °F to 86 °F)
Maximum humidity at 30°C	< 70 % relative humidity, non-condensing
Storage (without water)	-40 °C to +70 °C

Power requirements

Maximum power consumption

Test head type	CX test head	SX test head	LX test head
Number of card cages	1	2	3
Number of slots	9	18	27
Maximum power	20 kW	40 kW	56 kW

Cooling requirements

For use with one CX (9 slot) test head

Cooling unit E2760FAE Small liquid-liquid cooling unit

Cooling capability	18 kW @ 30 °C regulated secondary water temperature
Cooling medium	De-ionized water
Primary chilled water temperature range	5 °C to 20 °C (41 °F to 68 °F)

For use with one SX (18 slot) test head

Cooling unit E2760FAT Liquid-liquid cooling unit

Cooling capability	36 kW @ 30°C regulated secondary water temperature
Cooling medium	De-ionized water
Primary chilled water temperature range	5 °C to 20 °C (41 °F to 68 °F)

For use with one LX (27 slot) test head

Cooling unit E2760FAX and E2760FAXV Liquid-liquid cooling unit

Cooling capability	54 kW @ 30°C regulated secondary water temperature
Cooling medium	De-ionized water
Primary chilled water temperature range	5 °C to 20 °C (41 °F to 68 °F)

Weights and dimensions

Test system weight with manipulator and support rack (fully loaded)

CX test head - 1 CC (attached to the EK101 manipulator)	< 1300 kg [2870 lb]
CX test head - 1 CC (attached to the EK104 manipulator)	< 1400 kg [3086 lb]
SX test head - 2 CC (attached to the EK102 manipulator)	< 1500 kg [3300 lb]
SX test head - 2 CC (attached to the EK104 manipulator)	< 2000 kg [4409 lb]
LX test head - 3 CC (attached to the EK103 manipulator)	< 2300 kg [5070 lb]

Test head dimensions (height x width x depth, incl. docking)

CX test head - 1 CC	0.65 m x 0.73 m x 0.78 m [2.13 ft, 2.40 ft, 2.56 ft]
SX test head - 2 CC	0.67 m x 0.73 m x 0.89 m [2.19 ft, 2.40 ft, 2.92 ft]
LX test head - 3 CC	0.65 m x 1.02 m x 0.98 m [2.13 ft, 3.35 ft, 3.21 ft]

Maximum dimensions of the test cell (TH installed to the manipulator) (height x width x depth, incl. docking)

CX test head - 1 CC (EK101 manipulator)	1.92 m x 2.49 m x 2.53 m [6.30 ft, 8.16 ft, 8.30 ft]
CX test head - 1 CC (EK104 manipulator)	1.88 m x 2.49 m x 2.53 m [6.16 ft, 8.16 ft, 8.30 ft]
SX test head - 2 CC (EK102 manipulator)	2.23 m x 2.71 m x 2.67 m [7.32 ft, 8.89 ft, 8.75 ft]
SX test head - 2 CC (EK104 manipulator)	2 m x 2.63 m x 2.83 m [6.5 ft, 8.62 ft, 9.28 ft]
LX test head - 3 CC (EK103 manipulator)	2 m x 2.79 m x 2.85 m [6.6 ft, 9.15 ft, 9.35 ft]

Cooling unit E2760FAE

Dimensions (height x width x depth)	0.832 m x 0.363 m x 0.815 m [2.73 ft x 1.19 ft x 2.67 ft]
Net weight	81 kg [178.5 lb]

Cooling unit E2760FAT

Dimensions (height x width x depth)	0.852 m x 0.443 m x 0.815 m [2.79 ft x 1.45 ft x 2.67 ft]
Net weight	92 kg [202.8 lb]

Cooling unit E2760FAX

Dimensions (height x width x depth)	1.095 m x 0.504 m x 1.078 m [3.59 ft x 1.65 ft x 3.54 ft]
Net weight	173 kg [381.4 lb]

Cooling unit E2760FAXV	
Dimensions (height x width x depth)	1.095 m x 0.504 m x 1.078 m [3.59 ft x 1.65 ft x 3.54 ft]
Net weight	180 kg [396.8 lb]