机器关机断电，然后打开机箱找到PWRD_EN跳线，如下图所示。

将跳线冒接到4-6针，然后通过启动机器，等待BIOS自检通过后再关机断电，恢复跳线冒位置，通电重启即可。

System Board Jumper Settings		
Jumper	Setting	Description
PWRD_EN	2 4 6 (default)	The password reset feature is enabled (pins 2–4). BIOS local access is unlocked at the next AC power cycle.
	2 4 6	The password reset feature is disabled (pins 4–6).
NVRAM_CLR	1 3 5 (default)	The configuration settings are retained at the next system boot (pins 3–5).
	1 3 5	The configuration settings are cleared at system boot (pins 1–3).