




(BLACK AND WHITE, DOUBLE SIDED-PRINTING)

105(H) x 297(W) mm

<div data-bbox="183 190 252 260"></div> <div data-bbox="284 260 599 349"><h2>ZODIAC</h2><h3>WIRELESS EARBUDS</h3></div> <div data-bbox="259 362 622 393"><h4>INSTRUCTION MANUAL</h4></div> <div data-bbox="199 399 680 456"><p>Thank you for purchasing the Zodiac Wireless Earbuds. This manual provides more information about the wireless earbuds, please read the instructions before using.</p></div> <div data-bbox="206 474 352 495"><h5>Earbuds Overview</h5></div> <div data-bbox="340 541 536 962"></div>	<div data-bbox="750 216 897 236"><h5>Earbuds Overview</h5></div> <div data-bbox="864 269 1113 550"></div> <div data-bbox="733 578 1270 835"><div><div>Front:</div><div>Back:</div><div>Side:</div></div><div><div>LED</div><div>Vol+/Next Song</div><div>On/Off Button</div><div>Play / Pause Music</div><div>Answer / End Call</div><div>Vol-/Previous Song</div></div><div><div>Microphone</div></div><div><div>Micro USB Charging Port</div></div></div> <div data-bbox="740 846 970 949"><div>Micro USB Charging Cable:</div><div><div>USB Plug</div><div>Micro USB Plug</div></div></div>	<div data-bbox="1310 216 1418 236"><h5>Power On/Off</h5></div> <div data-bbox="1310 251 1791 362"><ul style="list-style-type: none">◆ Power on Press and hold down the On/Off Button for 3 seconds and the LED will flash.◆ Power off Press and hold down the On/Off Button for 4 seconds and the LED will turn off.</div> <div data-bbox="1310 389 1726 410"><h5>Pair Zodiac Wireless Earbuds with your mobile device</h5></div> <div data-bbox="1310 436 1764 595"><ol style="list-style-type: none">1. Keep the distance between your wireless earbuds and mobile phone (or other devices) within 32.8 Feet.2. Power on the Zodiac Wireless Earbuds3. Activate the Bluetooth function on your phone within range and select "BT ZODIAC BUD" from the list shown.4. The LED blinks in blue when paired successfully.<ul style="list-style-type: none">◆ Attention: If the pairing is not successful within 5 minutes, the earbuds will power off, please repeat the pairing procedures to try again.</div> <div data-bbox="1310 659 1761 680"><h5>Reconnect Zodiac Wireless Earbuds to your mobile device</h5></div> <div data-bbox="1310 705 1743 741"><ul style="list-style-type: none">◆ When powered on, the earbuds will automatically connect with the last successfully paired device.</div> <div data-bbox="1310 807 1685 827"><h5>Disconnect the earbuds from your mobile device</h5></div> <div data-bbox="1310 855 1706 907"><ul style="list-style-type: none">◆ Power off the earbuds; or◆ Switch off the Bluetooth on your mobile phone; or◆ Leave the earbuds 60ft away from your mobile phone or further.</div>
--	--	--

<div data-bbox="191 1042 360 1062"><h5>Answer / Reject a call</h5></div> <div data-bbox="191 1090 637 1149"><ul style="list-style-type: none">◆ When you receive a call, press the On/Off Button once to accept the call, or answer the call normally via your mobile phone.◆ Long press On/Off Button to reject a call</div> <div data-bbox="191 1182 272 1201"><h5>End a call</h5></div> <div data-bbox="191 1230 655 1249"><ul style="list-style-type: none">◆ Press the On/Off Button once to end the call or hang up your mobile phone.</div> <div data-bbox="191 1282 274 1302"><h5>Functions</h5></div> <div data-bbox="191 1332 493 1410"><ul style="list-style-type: none">◆ Short press + Button to turn up volume◆ Short press - Button to turn down volume◆ Long press + Button to advance to next song◆ Long press - Button to go back to previous song</div> <div data-bbox="191 1443 375 1463"><h5>Charging your Earbuds</h5></div> <div data-bbox="191 1491 589 1533"><ul style="list-style-type: none">◆ LED indicator light turns red when charging your earbuds◆ LED indicator light turns off when your earbuds are fully charged</div> <div data-bbox="191 1580 375 1600"><h5>Technical specification</h5></div> <div data-bbox="204 1624 693 1737"><p>Bluetooth Version: - - - - - 4.2 Bluetooth Operating Range: - - - - - 32.8 Feet Frequency Response:- - - - - 20Hz - 20KHz Playing Time:- - - - - 2 - 2.5hrs Charging Time:- - - - - 2hrs Battery Capacity:- - - - - 55mAh Rechargeable Li-Ion Battery - - - - - 3.7V</p></div>	<div data-bbox="750 1042 791 1062"><h5>FAQ</h5></div> <div data-bbox="750 1090 1237 1374"><ul style="list-style-type: none">◆ If the Zodiac Wireless Earbuds cannot be paired with your device, please try the following: Ensure that your earbuds are in pairing mode or reconnection mode. Ensure that Bluetooth search function of your mobile device is activated.◆ If the Zodiac Wireless Earbuds will not turn on: Make sure the earbuds are fully charged.◆ Can I change the battery for the earbuds? Zodiac Wireless Earbuds use a built-in non-detachable battery which cannot be removed.◆ If the Zodiac Wireless Earbuds cannot be recharged: If you use a power outlet, ensure that the power supply is connected securely and the outlet works. If you use a computer, ensure that it is connected and the USB port is powered.</div> <div data-bbox="750 1426 1244 1446"><p>⚠ Safety instructions for the lithium battery and charging the product</p></div> <div data-bbox="750 1458 1270 1705"><ul style="list-style-type: none">-The input voltage to the product is 5V 1A.-In order to charge the product in safe manner and reliable conditions, please only adopt certified appropriate charger/ adapter for charging the product.-Only charge the product at ambient temperatures between 10 deg °C/ 50 deg °F and 40 deg °C/104 deg °F.-Do not heat above 70 deg °C/158 deg °F, eg. Do not expose to sunlight or throw into fire.-Switch off the product after use.-Please note that we won't take any responsibility for any wrong operation (eg. Voltage higher than 5V) as this may result in severe injury or loss of property, and we cannot control the operating process during the time the user using this product.-In extreme cases, abuse or misuse of Lithium battery pack can lead to explosion, heat generation, fire development or smoke development.</div>	<div data-bbox="1297 1029 1418 1047"><h5>FCC STATEMENT</h5></div> <div data-bbox="1297 1047 1816 1171"><p>1. This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference. (2) This device must accept any interference received, including interference that may cause undesired operation.</p><p>2. Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.</p></div> <div data-bbox="1297 1188 1824 1452"><p>NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:</p><ul style="list-style-type: none">- Reorient or relocate the receiving antenna.- Increase the separation between the equipment and receiver.- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.- Consult the dealer or an experienced radio/TV technician for help.</div> <div data-bbox="1297 1469 1801 1522"><p>RF warning statement: The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.</p></div> <div data-bbox="1297 1622 1512 1644"><h5>FCC ID: 2ADM5-EP-0511</h5></div> <div data-bbox="1297 1657 1605 1766"><p>Distributed by Five Below Merchandising, Inc. 1818 Market Street, Suite 2000 Philadelphia, PA 19103 Made in China Visit us at: www.fivebelow.com Keep All Relevant Information for Future Reference</p></div>
---	--	---