





CHANNEL

Open your LED INNOV App and choose to connect to the "INT HUB" 4 channel system. Mobile phone must be within Bluetooth range. (Approximately 30 feet of the control box)

lighting system and are ready to customize it using the LED INNOV App. Please see the "Info" tab on your LED INNOV App for important tips and You have now successfully installed your new instructions.

OPTIONAL HARDWIRE KIT INSTALLATION INSTRUCTIONS:

 Open the package and find the direct wire harness. (included)




Run the wires toward a 12V power source

- (+) positive power source that is switched (like an instrument panel light or running light) so the light strips will light only when the vehicle The circuit chosen must be able to supply 3 Amps. Connect the (+) black wire with white stripe to a (For example, a fuse box or light switch)
- Or you can connect the black and white (+) positive wire to a circuit with constant power and use the push button on/off switch on the control box or add your own switch to turn it on and off.

ignition is turned on.

- Connect the black (-) negative wire to any clean, metal ground. 5
 - Tuck and conceal all wires.

Kit includes: 2 x Screws



4 x 12' (30.5cm) LED Light Strips 2 x 5' (152.4cm) Wire


WARNING

- Never use the LED Innovation App while driving & obey all traffic laws.
- regulations in your state, county and/or municipality regarding installation and use of this product. This product is not DOT Approved. This product is intended solely for the purpose of decorative or off-road use. Check laws and/or
- Do not install any accessory near or on airbags and
 - never obstruct the driver's view.
 12 Volt use only. Product designed to draw up to 2.8 Amps.
- Do not exceed 12 light strips on each control box.
- Do not exceed 3 light strips on each output wire. Only LED INNOVATION light strips may be used with
 - this product.
- This product is designed and engineered for INTERIOR USE ONLY.

ADDING ON TO YOUR LED LIGHTING KIT:

Your LED INNOVATION Lighting System is modular, so you can easily add more lights to your vehicle! To adď an additionáľ 12" light strip or 4' éxtension cord, (3 light strips on each side) Look for the following simply follow the diagram below. Your system will allow you to connect up to 12 light strips in total item numbers at your favorite retailer

23912: LED INNOVATION 12" Interior RGB Light Strip 23914: LED INNOVATION 4' Extension Cord 2 Pack



ONE YEAR WARRANTY

We guarantee this product to be free of defects in material and workmanship for a period of no year from the date of purchase. If a defect in material or workmanship occurs, call Custom Accessories customer service at (800) 962-6676 for instructions on how to have it replaced for repaired free of charge.

This guarantee does not cover normal damage to the product that is not the result of a defect in materials or workmanship such as for example, normal wear and tear or damage resulting from an accident. Shipment of any product back to Custom Accessories is at the consumer's expense. Custom Accessories, inc. limits its liability consequential damages to other property. Some states do not allow the exclusion or limitation of incidental or consequential damages. This guarantee gives you specific legal rights and you may also have other rights which vary from state to state. only to the replacement of its products, not incidental or

BEFORE INSTALLATION

It is recommended that you download the App, connect and test your LED lighting kit before nstallation

INSTALLATION

vehicle's 12V socke't. Next, choose a mounting location for the control box while making sure you leave enough wire to reach both the 12V socket and your light strips. Install your control box using the included Begin by laying out your new lighting system inside the vehicle. Place your light strips where you'd like to install them and plug the 12V plug into your two-sided tape and screws (if desired)

Note: If planning to use the 12V hardwire kit
instead of the 12V plug, make sure you
have enough cord length to your desired

To install your light strips, clean your installation surface installation. It is recommended that the temperature for thoroughly with alcohol and allow to dry before control box mounting location.

Align arrows to connect LED strips to wire harness. nstallation is 65-90° F (18-32° C).



Peel off the 3M™ tape backer on your light strips Tuck and conceal all wires wires with cable ties. Note: We DO NOT recommend cutting the and carefully apply to the desired area - Let adhesive set for at least 1 hour.

ON/OFF button on your controller. The red light on your controller and your light strips should illuminate. Insert the 12V plug into the 12V socket. Push the wires in order to shorten them.


FCC ID: 2ADMQ-23911



plug, remove fuse and replace with like amperage. Para cambiar el fusible, obturador, saque el fusible v desatornille el extremo del reemplácelo con uno de

To replace fuse, unscrew tip of





equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

• Recrient or relocate the receiving antenna.

• Increase the separation between the equipment and

Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.

Consult the dealer or an experienced radio/TV technician

for help.

CAUTION: Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the product. This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment. This transmitter must not be co-located or operated in conjunction with any other antenna or transmitter.

Color Channels 4 Customizable



Smart Lighting and download the App scan the QR code with your

smartphone!

To learn more about

App





A registered trademark of Bluetooth SIG, Inc Bluetooth

Model: 23911

amperaje similar.

Fuse: 3A, 250V

requirement. The device can be used in portable exposure condition

without restriction

The device has been evaluated to meet general RF exposure

FCC RF Radiation Exposure Statement

Custom Accessories Inc., 5900 Ami Drive, Richmond, IL 60071

For FCC matters please contact:

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation. NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This