Product Parameters:
Bluetooth Version: V2.1
Support Profile: AVRCP1.3, A2DP1.0, HFP1.5, HSP1.0
Working Distance Range: 10m
Frequency Range: 2.402GHz-2.480GHz
Battery Specifications: 3.7V, 300mAh, Built-in rechargeable lithium battery
Charging Voltage: DC4.2 - 5.5V
Charging Time: about 1.5 hours
Talking/Music time: about 4 hours
Standby Time: about 30 hours

Button Description:
ON/OFF: ON/OFF Switch
M: three kinds of playback modes switch(TF Mode，Radio Mode，Bluetooth Mode) & LED flashing lights control
►||: Play/ Pause/ Answer Calls/ Play Music
►►|/V+: long press for Next song or radio station/ short press increase volume
|◄◄/V-: long press for Previous song or radio station/ short press reduce volume

Function Description:
1. Startup:
Toggle switch to "ON", the device starts up and enter "Bluetooth Mode" automatically.

2. Shutdown:
Toggle switch to "OFF", LED indicator light turns off.

3. Bluetooth Mode:
1) Pairing Operation:
a. For the first time pairing: boot into "Bluetooth Mode" automatically, voice prompts "Bluetooth Mode", LED indicator light turns to blue. If can't search and pair with the last connected smart device within 3 seconds, it will automatically enters pairing mode. LED indicator light rapidly alternating flashes with blue and green colors. Please open the smart device's Bluetooth searching function, and select the device "BTL006", no password required, after successful pairing, voice prompts "Connected", LED indicator light turns to blue color.
b. Re-pairing: turn off the attached smart device's Bluetooth function, voice prompts "Disconnected", LED indicator light turns to blue. If can't search and pair with the last connected smart device within 3 seconds, the headset will automatic re-enter the pairing mode. Open another smart device's Bluetooth searching function, and select the device "BTL006", no password required, after successful pairing, voice prompts "Connected", LED indicator light turns to blue color.
c. Follow-up pairing: automatically pair the last connected device in 3 seconds after boot.
2) Answer Calls:
Short press►|| when calls' coming.
3) Hang up phone calls:
Short press►|| after calling.
4) Reject Calls:
Long press►||.
5) Redial the last outgoing number:
Double-click►||.
6) Music Play:
Short press►|| after connected with the smart device.
7) Reset Function:
Long press►|| for over 2 seconds.

4. Micro SD Card playback mode:
1) When the slot is empty, inserted the Micro SD Card, voice prompts "TF Mode". Then it plays media automatically.
2) When the Micro SD Card is inside, switch to TF Mode through M.

5. FM Radio Mode:
1) When the headset is on, switch to FM mode through "M" Button, voice prompts "Radio Mode".
2) Usage Tips: short press "►||" Button to search and save stations automatically(it can be abort with another short press while searching). Once enter FM mode again, it will play the first saved radio station automatically. If you want to re-scan, short press"►||" Button again in the Radio mode.

6. Line-in Mode:
When the headset is on, insert the Line-in cable, voice prompts "Line-in Mode". Then it plays smart device's media automatically.

7. Red, Blue, Green three colors LED flashing lights control
Long press "M" Button can Open/Close the LED flashing lights.

8. Red, Blue, Green three colors LED flashing lights status:
1) LED flashing lights' flash is based on the high, medium and low frequency of the vocal music, which corresponding to the red, blue and green color lights. Only works below the Bluetooth Mode playing smart device music, Radio Mode playing broadcasting of radio and TF Mode playing multimedia.
2) LED flashing lights will stop working while phone calls answering.

9. Maximum volume warning voice prompts "du du".

10. Report incoming call function.

11. Supports MP3, WAV, WNA, APE, FLAC format playback.

12. Battery indication on IOS.

13. Micro USB as common use charging port.

LED indicator light Status:

| Charge Status | Steady red LED. When fully charged, the LED indicator light turns off. |
|---|---|
| Power on Status | Blue LED indicator light turns on. |
| Power off Status | LED indicator light turns off. |
| Pairing Status | Green and Blue LED indicator lights rapidly alternating flash. |
| Standby Status | Blue LED indicator light turns on. |
| Connected Status | Blue LED indicator light turns on. |
| Using Status | Bluetooth Mode, Blue LED indicator light flashes every two seconds. |
| | Radio Mode, Green LED indicator light turns on. |
| | TF Mode, Green LED indicator light flashes every three seconds. |
| | AUX-in Mode, the headset automatically turns off, LED light goes out. |

Note:
If no pairing connection after the Bluetooth headset enters the pairing mode, please turn off the headset as for power saving.
Do not perform other operations when searching Bluetooth to prevent the program error.
Please select the appropriate volume in use to prevent damage to your ears.

# FCC Caution.

§ 15.19 Labelling requirements.
This device complies with part 15 of the FCC Rules.
Operation is subject to the following two conditions:
(1) This device may not cause harmful interference, and
(2) this device must accept any interference received,
including interference that may cause undesired operation.
§ 15.21 Information to user.
Any Changes or modifications not expressly approved by
the party responsible for compliance could void the user's
authority to operate the equipment.
§ 15.105 Information to the user.
Note: This equipment has been tested and found to
comply with the limits for a Class B digital device,
pursuant to part 15 of the FCC Rules. These limits are
designed to provide reasonable protection against harmful
interference in a residential installation. This equipment
generates uses and can radiate radio frequency energy and,
if not installed and used in accordance with the instructions,
may cause harmful interference to radio communications. However,
there is no guarantee that interference will not occur in a particular
installation. If this equipment does cause harmful interference to radio
or television reception, which can be determined by turning the equipment
off and on, the user is encouraged to try to correct the interference
by one or more of the following measures:
-Reorient or relocate the receiving antenna.
-Increase the separation between the equipment and receiver.

-Connect the equipment into an outlet on a circuit different
from that to which the receiver is connected.
-Consult the dealer or an experienced radio/TV technician for help.
RF warning for Portable device:
The device has been evaluated to meet general RF exposure
requirement. The device can be used in portable exposure condition
without restriction.