

Tune up procedure

Tune up procedure shall be over the power range or at specific operating power levels.

1. It must provide an operational voltage (3.3 ~ 4.3V DC) to turn on the device and on one certain channel in service mode by means of company proprietary software.
2. Base station simulator (CMW 500) measures Mobile phone, Model: Infineum Z5 device specific RF characteristics.
3. The maximum gains of each individual device are adjusted until the target value met.

Tune-up Power		
Mode	Frequency Bands	Tune-up Power
GSM	GSM850	31.5dBm \pm 1dB
	GSM1900	28.0dBm \pm 1dB
GPRS	GPRS850(1 slots)	31.5dBm \pm 1dB
	GPRS850(2 slots)	30.5dBm \pm 1dB
	GPRS850(3 slots)	29.0dBm \pm 1dB
	GPRS850(4 slots)	28.0dBm \pm 1dB
	GPRS1900(1 slots)	27.0dBm \pm 1dB
	GPRS1900(2 slots)	27.0dBm \pm 1dB
	GPRS1900(3 slots)	25.5dBm \pm 1dB
	GPRS1900(4 slots)	24.5dBm \pm 1dB
EDGE	EDGE850(1 slots)	25.5dBm \pm 1dB
	EDGE850(2 slots)	24.0dBm \pm 1dB
	EDGE850(3 slots)	22.0dBm \pm 1dB
	EDGE850(4 slots)	21.0dBm \pm 1dB
	EDGE1900(1 slots)	24.0dBm \pm 1dB
	EDGE1900(2 slots)	23.0dBm \pm 1dB
	EDGE1900(3 slots)	20.5dBm \pm 1dB
	EDGE1900(4 slots)	19.5dBm \pm 1dB
WCDMA850	WCDMA	21.5dBm \pm 1dB
	HSDPA	21.0dBm \pm 1dB
	HSUPA	21.0dBm \pm 1dB
WCDMA1900	WCDMA	21.0dBm \pm 1dB
	HSDPA	21.0dBm \pm 1dB
	HSUPA	20.5dBm \pm 1dB

FDD-LTE	Band 2	23.5dBm \pm 1dB
FDD-LTE	Band 4	22.5dBm \pm 1dB
FDD-LTE	Band 7	23.5dBm \pm 1dB
WIFI 802.11	2.4GHz	13.0dBm \pm 1dB
BT	2.4GHz	4.5dBm \pm 1dB

Then these appropriate gain settings are stored in each device individually.

The user has no possibility to change these settings later on, and during manufacturing each device will be individual calibrated. The measurement is done in fully calibrated setup, which is based on a **CMW 500** base station simulator. Furthermore, the highest power level is verified afterwards in a call measurement on three channels (low, middle and high).