


Q65


TWS 蓝牙耳机
说明书



中/英语音提示音切换:

左右耳机互连状态，任意快速5击其中一个耳机的触摸键，听到“滴”的提示音后，将耳机放入充电仓，待红灯长亮，再同时取出左/右耳机，即可。

产品概述



1: 多功能触摸键 2: 耳机指示灯 3: 麦克风
4: 耳帽 5: 充电仓指示灯 6: 充电顶针
7: Micro USB 充电口 8: 挂绳孔

开机/关机

自动开机：当您打开充电仓取出耳机时，耳机会自动开机。

自动关机：① 将耳机放入充电仓充电时，耳机自动关机。

② 耳机处于配对状态，两分钟内未与任何设备连接，自动关机。
注：耳机不能通过多功能触摸键手动开关机。

蓝牙配对

① 打开充电仓，取出耳机自动开机。



② 开机后，将左右耳机贴近（小于3cm），组队成功后伴有提示音“咚”。
组队成功后指示灯：一个耳机为红蓝灯交替闪烁，另一个为蓝灯慢闪。




1

③ 打开手机蓝牙界面，搜索“Q65 Pro”，点击配对，连接成功并伴有提示音。




备注：连接成功后，蓝灯呼吸灯4秒循环1次。

音乐



▶ 音乐暂停/播放：播放时，短按多功能触摸键。
▶ 上一曲：双击左耳多功能触摸键。
▶ 下一曲：双击右耳多功能触摸键。



2

▶ 唤醒语音助手功能（需手机支持）

① 在音乐播放或暂停状态，3击多功能触摸键，启动语音助手功能（SIRI）。
② 再次3击多功能触摸键，关闭语音助手功能（SIRI）。

3

通话



▶ 接听：来电时，短按多功能触摸键，并伴有提示音。
▶ 拒接：来电时，长按多功能触摸键2秒，并伴有提示音。
▶ 挂断：通话时，短按多功能触摸键，并伴有提示音。
▶ 接电第二方来电，双击左耳或副耳，接听第二方来电，保留当前通话，恢复上一个通话，单击时挂断当前通话，恢复另一个通话。

耳机恢复出厂设置

耳机在配对状态下（红蓝灯交替闪烁），三击触摸键，伴有提示音“嘀”，即可。

充电

① 通过充电线给充电仓充电，充满后电仓指示灯4个灯常亮。
② 耳机放入充电仓，自动充电，充满后耳机指示灯熄灭。

耳机充电	红灯亮
耳机充满电	红灯灭
充电仓充电	依次亮灯
充电仓充满电	灯长亮

4

参数规格


- 型号：Q65
- 蓝牙版本：5.0
- 单个耳机重量：4.5g
- 耳机尺寸：20*20*24MM
- 耳机电池容量：3.7V*2*50mAh
- 耳机充电时间：约1小时
- 播放音乐时间：约6小时(中等音量)
- 支持协议：SPP / HFP / A2DP / AVCTP / HID
- 频率：2.4GHz-2.48GHz
- 蓝牙距离：10M
- 电源输入：DC 5V/500mA
- 充电盒给耳机充电次数：2次
- 充电盒尺寸：66*30*30mm
- 充电盒重量：37g

5


45x70mm

Q65

TWS Bluetooth Earbuds
Instruction manual



Product Description



1: Multi-function touch button
2: Earbud indicator
3: microphone
4: Earbud cap
5: charging compartment indicator
6: charging thimble
7: Micro USB charging port
8: lanyard hole

Power on/off

Auto power on: When you open the charging compartment to remove the earbud, the earbud will automatically turn on.

Auto power off:


① When the earbud is placed in the charging compartment to charge, the earbud automatically shuts down.

② The earbud is paired and does not connect to any device for two minutes, it will automatically shutting down (power off).

Note: The earphone cannot be turned on/off manually by touch key.

Bluetooth pairing

① Open the charging compartment and take out the earbud to turn it on automatically.



② After booting up, put the left earphone and the right earphone together (<3cm). After the pairing is successful, there will be a prompt tone "DONG".
the indicator light: one earphone flashes alternately with red and blue lights, and the other light flashes with blue light.




1

③ Open the phone's Bluetooth connection interface, search for "Q65 Pro", click pair, then the connection is successful and accompanied by a tone.



Note: After the connection is successful, the blue light breathing light is cycled once for 4 seconds.

Music




▶ Music pause/play: During playback, short press the multi-touch button.
▶ Previous song: Double-click the left ear multi-function touch button.
▶ Next song: Double-click the right ear multi-function touch button.

Wake up voice assistant function (requires mobile phone support)

① In the music play or pause state, click the multi-function touch button 3 times to activate the voice assistant function (SIRI).
② Touch the button three times again to turn off the voice assistant function (SIRI).

2



▶ Answer: When calling, short press the multi-function touch button with a prompt tone.

▶ Reject: When calling, press and hold the multi-function button for 2 seconds, accompanied by a tone.

▶ Hang up: During a call, press the multi-function touch button with a beep.

▶ Answering a third-party call: Double-click the host or additional earbud to answer a third-party call, keep the current call. Double click again to keep the current call and resume the previous one, when you click one time, hang up the current call and resume another call.

Headset restore factory settings

When the headset is in the pairing state (the red and blue lights flash alternately), the quick three-stroke button is accompanied by the prompt tone "DING".

Charging

① The charging compartment is charged by the charging line, and after the full charging, the 4 indicator lights of the battery compartment should be on.

② The earbud is placed in the charging compartment, automatically charged, and the earbud indicator is off after being fully charged.

Earbuds charging	Red light is on
Earbuds is fully charged	Red light is off
Charging compartment is charging	Red light is light up in sequence
Charging compartment is fully charged	The light is always on

Specifications

- Model: Q65
- Bluetooth version: 5.0
- Single earbud weight: 4.5g
- Earbud size: 20*20*24MM
- Earbud battery capacity: 3.7V*2*50mAh
- Earbud charging time: about 1 hour
- Play music time: about 6 hours(Medium volume)
- Support Agreement: SPP / HFP / A2DP / AVCTP / HID
- Frequency: 2.4GHz-2.48GHz
- Bluetooth distance: 10M
- Power input: DC 5V/500mA
- Charging bin to charge the earbud: 2 times
- Charging bin size: 66*30*30mm
- Charging bin weight: 37g

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment. This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

- (1) this device may not cause harmful interference, and
- (2) this device must accept any interference received, including interference that may cause undesired operation.

FCC ID:2AGHA-Q65

Chinese/English prompt tone switching:
While Left/right earphones interconnection status, any fast 5 hits the touch key of one of the earphones, after hearing the "di" prompt tone, put the earphone into the charging compartment and wait for the red light constantly bright, and then pick up both of the left and right earphone at the same time. Now it works.

5

6