

**** MPE Calculations for Bluetooth (2.4GHz) ****

The EUT will only be used with a separation of 20 centimeters or greater between the antenna and the body of the user. The MPE calculation for this exposure is shown below.

The peak radiated output power (EIRP) is calculated as follows:

EIRP = P + G EIRP = 9.22 – 0.53 EIRP = 8.69 dBm	Where, P = Power input to the antenna (mW) G = Power gain of the antenna (dBi)
---	--

Power density at the specific separation:

S = $PG / (4R^2 \pi)$ S = $(8.36 * 0.89) / (4 * 20^2 * \pi)$ S = 0.0015 mW/cm ²	Where, S = Maximum power density (mW/cm ²) P = Power input to the antenna (mW) G = Numeric power gain of the antenna R = Distance to the center of the radiation of the antenna (0.5cm = limit for MPE)
--	--

The Maximum permissible exposure (MPE) for the general population is 1 mW/cm² .

The power density at 0.5cm does not exceed the 1 mW/cm² limit.

Therefore, the exposure condition is compliant with FCC rules.

Estimated safe separation:

R = $\sqrt{PG / 4 \pi}$ R = $\sqrt{(8.36 * 0.89 / 4 \pi)}$ R = 0.77 Cm	Where, P = Power input to the antenna (mW) G = Numeric power gain of the antenna R = Distance to the center of the radiation of the antenna (0.5cm = limit for MPE)
--	---

The numeric gain(G) of the antenna with a gain specified in dB is determined by:

$$G = \text{Log}^{-1} (\text{dB antenna gain} / 10)$$

$$G = \text{Log-1} (-0.53 / 10)$$

$$G = 0.89$$