RF Exposure evaluation

Product Description: K20 Multimedia Backlit Bluetooth Keyboard
Model Number: K20, AFA-K20
FCC ID: 2AH35K20

According to 447498 D01 General RF Exposure Guidance v05 The 1-g and 10-g SAR test exclusion thresholds for 100 MHz to 6 GHz at test separation distances ≤ 50 mm are determined by: [(max. power of channel, including tune-up tolerance, mW)/(min. test separation distance, mm)] ·[√f(GHz)] ≤ 3.0 for 1-g SAR and ≤ 7.5 for 10-g extremity SAR,   where
    f(GHz) is the RF channel transmit frequency in GHz
    Power and distance are rounded to the nearest mW and mm before calculation

According to the follow transmitter output power（P_t）formula：
P_t=（E x d）^{2}/（30 x g_t）
P_t=transmitter output power in watts
g_t=numeric gain of the transmitting antenna (unitess)
E=electric field strength in V/m
d=measurement distance in meters (m)

According to the above test data,
Emax=93.32dBuv/m=0.046V/m,d=3m,g_t=1
P_t=（E x d）^{2}/（30 x g_t）=(0.046x3)^2/(30x1)=0.0006348W=0.63mW

The result is rounded to one decimal place for comparison
Worse case is as below: [2480MHz -0.63mW output power]
(0.63mW /5mm) .[√2.480(GHz)]= 0.19<3.0 for 1-g SAR
Then SAR evaluation is not required

NOTE: For the maximum power, you can refer FCC test report.