RF EXPOSURE EVALUATION METHOD

SAR Test Exclusion Thresholds for 100 MHz -6 GHz and ≤ 50 mm

Approximate SAR Test Exclusion Power Thresholds at Selected Frequencies and Test Separation Distances are illustrated in the following Table.

| MHz | 5 | 10 | 15 | 20 | 25 | mm |
|------|----|----|-----|-----|-----|-----------------------|
| 150 | 39 | 77 | 116 | 155 | 194 | |
| 300 | 27 | 55 | 82 | 110 | 137 | |
| 450 | 22 | 45 | 67 | 89 | 112 | |
| 835 | 16 | 33 | 49 | 66 | 82 | |
| 900 | 16 | 32 | 47 | 63 | 79 | |
| 1500 | 12 | 24 | 37 | 49 | 61 | SAR Test Exclusion |
| 1900 | 11 | 22 | 33 | 44 | 54 | Threshold (mW) |
| 2450 | 10 | 19 | 29 | 38 | 48 | 11110311010 (11111) |
| 3600 | 8 | 16 | 24 | 32 | 40 | |
| 5200 | 7 | 13 | 20 | 26 | 33 | |
| 5400 | 6 | 13 | 19 | 26 | 32 | |
| 5800 | 6 | 12 | 19 | 25 | 31 | |

The 1-g and 10-g SAR test exclusion thresholds for 100 MHz to 6 GHz at test separation distances ≤ 50 mm are determined by:

[(max. power of channel, including tune-up tolerance, mW)/(min. test separation distance, mm)] • [$\sqrt{f(GHz)}$] \leq 3.0 for 1-g SAR and \leq 7.5 for 10-g extremity SAR,where f(GHz) is the RF channel transmit frequency in GHz

Power and distance are rounded to the nearest mW and mm before calculation. The result is rounded to one decimal place for comparison

The test exclusions are applicable only when the minimum test separation distance is ≤ 50 mm and for transmission frequencies between 100 MHz and 6 GHz. When the minimum test separation distance is < 5 mm, a distance of 5 mm is applied to determine SAR test exclusion.

Maximum measured transmitter power.

WIFI The Worst Case

Antenna number: 2 Antenna A gain : 0dBi Antenna B gain : 0dBi

MIMO technology Directional gain= 3.01dBi

Remark: The worst case gain of the antenna is 3.01dBi.

3.01dBi logarithmic terms convert to numeric result is nearly 2.00

| frequency (GHz) | Maximum Peak Conducted Output Power (dBm) | Tune up tolerance (dBm) | Tune up Power (mW) | Result | Limit |
|--------------------|---|-------------------------------|--------------------------|---------|-------|
| 2.412 | 9.62 | 9.2±0.5 | 9. 332543008 | 2.8988 | 3 |
| 2.437 | 9.46 | 9.2±0.5 | 9. 332543008 | 2. 9138 | 3 |
| 2.462 | 9.33 | 9.2±0.5 | 9. 332543008 | 2. 9287 | 3 |

| frequency (GHz) | Maximum Peak Conducted Output Power (dBm) | Tune up tolerance (dBm) | Tune up Power (mW) | Result | Limit |
|--------------------|---|-------------------------------|--------------------------|---------|-------|
| 2.412 | 9.16 | 9.0±0.5 | 8. 912509381 | 2.7683 | 3 |
| 2.437 | 8.74 | 9.0±0.5 | 8. 912509381 | 2. 7826 | 3 |
| 2.462 | 8.71 | 9.0±0.5 | 8. 912509381 | 2. 7969 | 3 |

| frequency (GHz) | Maximum Peak Conducted Output Power (dBm) | Tune up tolerance (dBm) | Tune up Power (mW) | Result | Limit |
|--------------------|---|-------------------------------|--------------------------|---------|-------|
| 2.412 | 9.57 | 9.2±0.5 | 9. 332543008 | 2.8988 | 3 |
| 2.437 | 9.45 | 9.2±0.5 | 9. 332543008 | 2.9138 | 3 |
| 2.462 | 9.43 | 9.2±0.5 | 9. 332543008 | 2. 9287 | 3 |

| frequency (GHz) | Maximum Peak Conducted Output Power (dBm) | Tune up tolerance (dBm) | Tune up Power (mW) | Result | Limit |
|--------------------|---|-------------------------------|--------------------------|---------|-------|
| 2.422 | 9.1 | 9.0±0.5 | 8. 912509381 | 2.7741 | 3 |
| 2.437 | 8.84 | 9.0±0.5 | 8. 912509381 | 2. 7826 | 3 |
| 2.452 | 8.12 | 9.0±0.5 | 8. 912509381 | 2. 7912 | 3 |

Threshold at which no SAR required is $2.9287 \leqslant 3.0$ for 1-g SAR, Separation distance is 5mm.