

#### \* RF Exposure

#### 1. Regulation

According to §15.247(i), systems operating under the provisions of this section shall be operated in a manner that ensures that the public is not exposed to radio frequency energy levels in excess of the Commission's guidelines. See § 1.1307(b)(1) of this Chapter.

Limits for Maximum Permissive Exposure: RF exposure is calculated.

Emilio for Maximum I offinosity Emposore. The emposore is careafaced.								
Eraguanay Danga	Electric Field	Magnetic Field	Power Density	Averaging Time				
Frequency Range	Strength [V/m]	Strength [A/m]	$[mW/cm^2]$	[minute]				
Limits for General Population / Uncontrolled Exposure								
0.3 ~ 1.34	614	1.63	*(100)	30				
1.34 ~ 30	824/f	2.19/f	$*(180/f^2)$	30				
30 ~ 300	27.5	0.073	0.2	30				
300 ~ 1 500	/	/	f/1 500	30				
1 500 ~ 15 000	/	/	1.0	30				

f=frequency in Mz, \*= plane-wave equivalent power density

#### MPE (Maximum Permissive Exposure) Prediction

Predication of MPE limit at a given distance: Equation from page 18 of OET Bulletin 65, Edition 97-01

$$S = PG/4\pi R^2$$
  $(\Rightarrow R = \sqrt{PG/4\pi S})$ 

 $S = power density [mW/cm^2]$ 

P = Power input to antenna [mW]

G = Power gain of the antenna in the direction of interest relative to an isotropic radiator

R = distance to the center of radiation of the antenna [cm]

KCTL-TIR001-002/0

Page: (1) /(2) Pages



# 2. RF Exposure Compliance Issue

The information should be included in the user's manual:

This appliance and its antenna must not be co-located or operation in conjunction with any other antenna or transmitter. A minimum separation distance of 20 cm must be maintained between the antenna and the person for this appliance to satisfy the RF exposure requirements.

# 3. Calculation Result of RF Exposure

Mode	Target power [dBm]	Tune up tolerance	Max tune up power [dBm]	Max tune up power	Ant Gain	Ant Gain	Power Density at 20 cm	Limit
Bluetooth LE_GFSK	-1.0	±2.0	1.0	1.26	1.99	1.58	0.000 40	1.000 00
Total							0.000 40	1.000 00

# 4. Target power and tolerance, Max tuneup power

Mode	Target power [dBm]	Tolerance [dB]	Max tuneup power [dBm]	Average Power [dBm]
Bluetooth LE_GFSK Lowest	-1.0	±2.0	1.0	-0.51
Bluetooth LE_GFSK Middle	-1.0	±2.0	1.0	-0.04
Bluetooth LE_GFSK Highest	-1.0	±2.0	1.0	0.55

KCTL-TIR001-002/0 Page: (2) /(2) Pages