RF EXPOSURE EVALUATION

According to FCC 1.1310: The criteria listed in the following table shall be used to evaluate the environment impact of human exposure to radio frequency(RF) Radiation as specified in §1.1307(b)

FCC ID：2AIPK-PERE

EUT Specification

EUT	Peek Relay
Frequency band (Operating)	☒ WLAN: 2.412GHz ~ 2.462GHz ☐ WLAN: 5.18GHz ~ 5.32GHz / 5.50GHz ~ 5.70GHz ☐ WLAN: 5.745GHz ~ 5825GHz ☐ Others
Device category	☐ Portable (<20cm separation) ☒ Mobile (>20cm separation) ☐ Others ___
Exposure classification	☐ Occupational/Controlled exposure (S = 5mW/cm2) ☒ General Population/Uncontrolled exposure (S=1mW/cm2)
Antenna diversity	☐ Single antenna ☒ Multiple antennas ☐ Tx diversity ☐ Rx diversity ☐ Tx/Rx diversity
Max. output power	17.57dBm (0.0571W)
Antenna gain (Max)	2 dBi
Evaluation applied	☒ MPE Evaluation ☐ SAR Evaluation

Limits for Maximum Permissible Exposure(MPE)

Frequency Range(MHz)	Electric Field Strength(V/m)	Magnetic Field Strength(A/m)	Power Density(mW/cm²)	Average Time
(A) Limits for Occupational/Control Exposures				
300-1500	--	--	F/300	6
1500-100000	--	--	5	6
(B) Limits for General Population/Uncontrol Exposures				
300-1500	--	--	F/1500	6
1500-100000	--	--	1	30

Friis transmission formula: Pd=(Pout*G)\(4*pi*R2)

Where

Pd= Power density in mW/cm^2

Pout=output power to antenna in Mw

G= gain of antenna in linear scale

Pi=3.1416

R= distance between observation point and center of the radiator in cm

Pd the limit of MPE, 1mW/cm2. If we know the maximum gain of the antenna and total power input to the antenna, through the calculation, we will know the distance where the MPE limit is reached.

Measurement Result

ANT A:

Operating Mode	Channel Frequency (MHz)	Measured Power (dBm)	Tune up tolerance (dBm)	Max. Tune up Power (dBm)	Antenna Gain (dBi)	Power density at 20cm (mW/ cm^2)	Power density Limits (mW/cm^2)
802.11b	2412	16.45	16.45±1	17.45	2	0.0175	1
	2437	16.33	16.33±1	17.33	2	0.0171	1
	2462	16.60	16.60±1	17.60	2	0.0181	1
802.11g	2412	14.31	14.31±1	15.31	2	0.0107	1
	2437	16.38	16.38±1	17.38	2	0.0172	1
	2462	14.97	14.97±1	15.97	2	0.0125	1
802.11n (HT20)	2412	14.52	14.52±1	15.52	2	0.0112	1
	2437	14.54	14.54±1	15.54	2	0.0113	1
	2462	13.34	13.34±1	14.34	2	0.0086	1
802.11n (HT40)	2422	9.61	9.61±1	10.61	2	0.0036	1
	2437	11.96	11.96±1	12.96	2	0.0062	1
	2452	10.22	10.22±1	11.22	2	0.0042	1

ANT B:

Operating Mode	Channel Frequency (MHz)	Measured Power (dBm)	Tune up tolerance (dBm)	Max. Tune up Power (dBm)	Antenna Gain (dBi)	Power density at 20cm (mW/ cm^2)	Power density Limits (mW/cm^2)
802.11b	2412	14.86	14.86±1	15.86	2	0.0122	1
	2437	14.49	14.49±1	15.49	2	0.0112	1
	2462	15.80	15.80±1	16.8	2	0.0151	1
802.11g	2412	12.89	12.89±1	13.89	2	0.0077	1
	2437	14.51	14.51±1	15.51	2	0.0112	1
	2462	13.89	13.89±1	14.89	2	0.0097	1
802.11n (HT20)	2412	12.65	12.65±1	13.65	2	0.0073	1
	2437	14.57	14.57±1	15.57	2	0.0114	1
	2462	13.77	13.77±1	14.77	2	0.0095	1
802.11n (HT40)	2422	10.21	10.21±1	11.21	2	0.0042	1
	2437	12.31	12.31±1	13.31	2	0.0068	1
	2452	10.96	10.96±1	11.96	2	0.0050	1

Antenna A Gain= 2 dBi

Antenna B Gain= 2 dBi

Array Gain= 5.01 dBi= GANT+10*log(NANT)dBi

Operating Mode	Channel Frequency (MHz)	ANT A Power density at 20cm (mW/ cm^2)	ANT B Power density at 20cm (mW/ cm^2)	Power density at 20cm (mW/ cm^2)	Power density Limits (mW/cm^2)
802.11n (HT20)	2412	0.0112	0.0073	0.0185	1
	2437	0.0113	0.0114	0.0227	1
	2462	0.0086	0.0095	0.0181	1
802.11n (HT40)	2422	0.0036	0.0042	0.0078	1
	2437	0.0062	0.0068	0.0130	1
	2452	0.0042	0.0050	0.0092	1