FCC ID: 2AK3TINSIGHTRX

MPE calculation

According to FCC 1.1310: The criteria listed in the following table shall be used to evaluate the environment impact of human exposure to radio frequency(RF) Radiation as specified in §1.1307(b)

Limits for Maximum Permissible Exposure (MPE)

Frequency Range(MHz)	Electric Field Strength(V/m)	Magnetic Field Strength(A/m)	Power Density(mW/cm^2)	Average Time
(A) Limits for Occupational/Control Exposures				
300-1500	--	--	F/300	6
1500-100000	--	--	5	6
(B) Limits for General Population/Uncontrol Exposures				
300-1500	--	--	F/1500	6
1500-100000	--	--	1	30

11.1 Friis transmission formula: Pd= (Pout*G)\ (4*pi*R^2)

Where
Pd= Power density in mW/cm^2
Pout=output power to antenna in mW
G= Numeric gain of the antenna relative to isotropic antenna
Pi=3.1416
R= distance between observation point and center of the radiator in cm(20cm)
Pd the limit of MPE, 1mW/cm^2. If we know the maximum gain of the antenna and total power input to the antenna, through the calculation, we will know the distance where the MPE limit is reached.
mW=10^(dBm/10)

11.2 Measurement Result

Operation Frequency: WIFI 5180-5240, 5745-5825MHz(802.11a/n(HT20))
WIFI Antenna 1 Gain =5dBi, Antenna 2 Gain =5dBi ,MIMO mode: Directional gain
= 10log(antenna 1 + antenna 2) dbi =8dbi in 802.11n(20)

	Frequency	Antenna port	Maximum Conducted Output Power(PK)	Maximum Conducted Output Power(PK)	Total Conducted Output Power(PK)	Total Conducted Output Power(PK)	LIMIT
	(MHz)		(dBm)	(mW)	(mW)	(dBm)	dBm
802.11a	5180	Ant.1	14.75	31.33	N/A	N/A	30
		Ant.2	14.27	28.05			
	5220	Ant.1	14.69	30.90	N/A	N/A	30
		Ant.2	14.12	27.10			
	5240	Ant.1	14.35	28.58	N/A	N/A	30
		Ant.2	14.18	27.48			
	5745	Ant.1	15.15	34.36	N/A	N/A	30
		Ant.2	15.36	36.06			
	5785	Ant.1	15.29	35.48	N/A	N/A	30
		Ant.2	15.11	34.04			
	5825	Ant.1	15.38	36.22	N/A	N/A	30
		Ant.2	15.37	36.14			
802.11n20	5180	Ant.1	13.57	22.75	44.03	16.44	28
		Ant.2	13.28	21.28			
	5220	Ant.1	13.76	23.77	44.53	16.49	28
		Ant.2	13.17	20.75			
	5240	Ant.1	13.08	20.32	40.60	16.09	28
		Ant.2	13.07	20.28			
	5745	Ant.1	14.31	26.98	52.86	17.22	28
		Ant.2	14.13	25.88			
	5785	Ant.1	14.37	27.35	53.84	17.31	28
		Ant.2	14.23	26.49			
	5825	Ant.1	14.22	26.42	54.22	17.34	28
		Ant.2	14.44	27.80			

5G WIFI:

5GWIFI max possible output power (PK,conducted)：17±1dbm

Pout=18dBm=63.10mW

5G WIFI Antenna 1 Gain =5dBi, Antenna 2 Gain =5dBi ,MIMO mode: Directional gain = 10log(antenna 1 + antenna 2) dbi =8dBi 802.11n(20) ,numeric gain result =6.31=G R=20cm

Pd=(Pout*G)\ (4*pi*R2)=0.079211（mW/cm2）

Conclusion:

For the max result : 0.079211≤ 3.0 for 1g SAR, No SAR is required.