

## RF EXPOSURE EVALUATION

According to FCC 1.1310: The criteria listed in the following table shall be used to evaluate the environment impact of human exposure to radio frequency(RF) Radiation as specified in §1.1307(b)

FCC ID: **2ALPD-GT08**

### EUT Specification

EUT	GPS Vehicle Tracker
Frequency band (Operating)	<input checked="" type="checkbox"/> GSM: 850/1900 <input checked="" type="checkbox"/> WCDMA: UMTS FDD Band II, UMTS FDD Band V <input type="checkbox"/> Others
Device category	<input type="checkbox"/> Portable (<20cm separation) <input checked="" type="checkbox"/> Mobile (>20cm separation) <input type="checkbox"/> Others ____
Exposure classification	<input type="checkbox"/> Occupational/Controlled exposure (S = 5mW/cm <sup>2</sup> ) <input checked="" type="checkbox"/> General Population/Uncontrolled exposure (S=1mW/cm <sup>2</sup> )
Antenna diversity	<input checked="" type="checkbox"/> Single antenna <input type="checkbox"/> Multiple antennas <input type="checkbox"/> Tx diversity <input type="checkbox"/> Rx diversity <input type="checkbox"/> Tx/Rx diversity
Max. output power	32.92dBm (1.959W)
Antenna gain (Max)	1.0 dBi
Evaluation applied	<input checked="" type="checkbox"/> MPE Evaluation <input type="checkbox"/> SAR Evaluation

Limits for Maximum Permissible Exposure(MPE)

Frequency Range(MHz)	Electric Field Strength(V/m)	Magnetic Field Strength(A/m)	Power Density(mW/cm <sup>2</sup> )	Average Time
<b>(A) Limits for Occupational/Control Exposures</b>				
<b>300-1500</b>	--	--	<b>F/300</b>	<b>6</b>
<b>1500-100000</b>	--	--	<b>5</b>	<b>6</b>
<b>(B) Limits for General Population/Uncontrol Exposures</b>				
<b>300-1500</b>	--	--	<b>F/1500</b>	<b>6</b>
<b>1500-100000</b>	--	--	<b>1</b>	<b>30</b>

## Friis transmission formula: $P_d = (P_{out} * G) / (4 * \pi * R^2)$

Where

$P_d$  = Power density in mW/cm<sup>2</sup>

$P_{out}$  = output power to antenna in Mw

$G$  = gain of antenna in linear scale

$\pi$  = 3.1416

$R$  = distance between observation point and center of the radiator in cm

$P_d$  the limit of MPE, 1mW/cm<sup>2</sup>. If we know the maximum gain of the antenna and total power input to the antenna, through the calculation, we will know the distance where the MPE limit is reached.

## Measurement Result

Operating Mode	Channel Frequency (MHz)	Measured Power (dBm)	Tune up tolerance (dBm)	Max. Tune up Power (dBm)	Antenna Gain	Power density at 20cm (mW/ cm <sup>2</sup> )	Power density Limits (mW/cm <sup>2</sup> )
GSM850	824.2	32.85	32.0±1	33	1	0.4997	0.55
	836.6	32.92	32.0±1	33	1	0.4997	0.56
	848.8	32.89	32.0±1	33	1	0.4997	0.57
GPRS850	824.2	32.91	32.0±1	33	1	0.4997	0.55
	836.6	32.69	32.0±1	33	1	0.4997	0.56
	848.8	32.65	32.0±1	33	1	0.4997	0.57
EGPRS	824.2	32.28	32.0±1	33	1	0.4997	0.55
	836.6	32.83	32.0±1	33	1	0.4997	0.56
	848.8	32.48	32.0±1	33	1	0.4997	0.57
PCS1900	1850.2	28.97	29±1	30	1	0.2505	1
	1880.0	28.26	29±1	30	1	0.2505	1
	1909.8	29.43	29±1	30	1	0.2505	1
GPRS 1900	1850.2	28.31	28±1	29	1	0.1989	1
	1880.0	28.1	28±1	29	1	0.1989	1
	1909.8	28.33	28±1	29	1	0.1989	1
EGPRS 1900	1850.2	29.24	29±1	30	1	0.2505	1
	1880.0	29.17	29±1	30	1	0.2505	1
	1909.8	29.36	29±1	30	1	0.2505	1
WCDMA 850	826.4	21.95	22±1	23	1	0.0500	0.55
	835.0	22.16	22±1	23	1	0.0500	0.56
	846.6	21.87	22±1	23	1	0.0500	0.56
WCDMA	1852.4	21.33	22±1	23	1	0.0500	1

1900	1880.0	21.42	22±1	23	1	0.0500	1
	1907.6	21.51	22±1	23	1	0.0500	1

Conclusion: No SAR is required.