Calibration Laboratory of

Schmid & Partner **Engineering AG** Zeughausstrasse 43, 8004 Zurich, Switzerland

Client

EMC Australia

CALIBRATION CERTIFICATE

Object(s)

D1640V2 - SN:314

Calibration procedure(s)

QA CAL-05.v2

Calibration procedure for dipole validation kits

Calibration date:

May 25, 2004

Condition of the calibrated item

In Tolerance (according to the specific calibration document)

This calibration statement documents traceability of M&TE used in the calibration procedures and conformity of the procedures with the ISO/IEC 17025 international standard.

All calibrations have been conducted in the closed laboratory facility: environment temperature 22 +/ 2 degrees Celsius and humidity < 75%.

Calibration Equipment used (M&TE critical for calibration)

Model Type	ID#	Cal Date (Calibrated by, Certificate No.)	Scheduled Calibration
Power meter EPM E442	GB37480704	6-Nov-03 (METAS, No. 252-0254)	Nav-04
Power sensor HP 8481A	US37292783	6-Nov-03 (METAS, No. 252-0254)	Nov-04
	MY41092317	18-Oct-02 (Agilent, No. 20021018)	Oct-04
	100698	27-Mar-2002 (R&S, No. 20-92389)	In house check: Mar-05
Network Analyzer HP 8753E	US37390585	18-Oct-01 (SPEAG, in house check Nov-03)	In house check: Oct 05
Power sensor HP 8481A RF generator R&S SML-03	MY41092317 100698	18-Oct-02 (Agilent, No. 20021018) 27-Mar-2002 (R&S, No. 20-92389)	Oct-04 In house check: Mar-0

Calibrated by:

Function Judith Mueller

Technician

Approved by:

Katja Pokovic

Name

Laboratory Director

Date issued: May 26, 2004

This calibration certificate is issued as an intermediatesolution until the accreditation process (based on ISO/IEC 17025 International Standard) for Calibration Laboratory of Schmid & Partner Engineering AG is completed.

880-KP0301061-A

Page 1 (1)

s p e <u>a g</u>

Zoughauss rasse 43, 9004 Zurich, Switzerland Phone +41 1 245 9700, Fax -41 1 245 9779 info@speeg.com, http://www.speeg.com

DASY

Dipole Validation Kit

Type: D1640V2

Serial: 314

Manufactured: March Calibrated: May 2

March 19, 2004 May 25, 2004

1. Measurement Conditions

The measurements were performed in the flat section of the SAM twin phantom filled with **head** simulating solution of the following electrical parameters at 1640 MHz:

Relative Dielectricity 41.3 $\pm 5\%$ Conductivity 1.20 mho/m $\pm 5\%$

The DASY4 System with a dosimetric E-field probe ET3DV6 (SN:1507, Conversion factor 5.08 at 1800 MHz) was used for the measurements.

The dipole was mounted on the small tripod so that the dipole feedpoint was positioned below the center marking of the flat phantom section and the dipole was oriented parallel to the body axis (the long side of the phantom). The standard measuring distance was 10mm from dipole center to the solution surface. The included distance spacer was used during measurements for accurate distance positioning.

The coarse grid with a grid spacing of 15mm was aligned with the dipole. The 7x7x7 fine cube was chosen for cube integration.

The dipole input power (forward power) was $250 \text{mW} \pm 3 \%$. The results are normalized to 1W input power.

2. SAR Measurement with DASY4 System

Standard SAR-measurements were performed according to the measurement conditions described in section 1. The results (see figure supplied) have been normalized to a dipole input power of 1W (forward power). The resulting averaged SAR-values measured with the dosimetric probe ET3DV6 SN:1507 and applying the advanced extrapolation are:

averaged over 1 cm³ (1 g) of tissue: 33.0 mW/g \pm 16.8 % (k=2)¹

averaged over 10 cm³ (10 g) of tissue: 18.6 mW/g \pm 16.2 % (k=2)¹

¹ validation uncertainty

3. Dipole Impedance and Return Loss

The impedance was measured at the SMA-connector with a network analyzer and numerically transformed to the dipole feedpoint. The transformation parameters from the SMA-connector to the dipole feedpoint are:

Electrical delay: 1.230 ns (one direction)

Transmission factor: 0.986 (voltage transmission, one direction)

The dipole was positioned at the flat phantom sections according to section 1 and the distance spacer was in place during impedance measurements.

Feedpoint impedance at 1640 MHz: $Re\{Z\} = 52.0 \Omega$

Im $\{Z\} = 1.0 \Omega$

Return Loss at 1640 MHz -33.7 dB

4. Handling

Do not apply excessive force to the dipole arms, because they might bend. Bending of the dipole arms stresses the soldered connections near the feedpoint leading to a damage of the dipole.

5. Design

The dipole is made of standard semirigid coaxial cable. The center conductor of the feeding line is directly connected to the second arm of the dipole. The antenna is therefore short-circuited for DC-signals.

6. Power Test

After long term use with 40W radiated power, only a slight warming of the dipole near the feedpoint can be measured.

Date/Time: 05/25/04 09:47:23

Test Laboratory: SPEAG, Zurich, Switzerland

DUT: Dipole 1640 MHz; Type: D1640V2; Serial: D1640V2 - SN314

Communication System: CW-1640; Frequency: 1640 MHz; Duty Cycle: 1:1

Medium: HSL 1640 MHz;

Medium parameters used: f = 1640 MHz; $\sigma = 1.2$ mho/m; $\varepsilon_r = 41.3$; $\rho = 1000$ kg/m³

Phantom section: Flat Section

Measurement Standard: DASY4 (High Precision Assessment)

DASY4 Configuration:

- Probe: ET3DV6 SN1507; ConvF(5.08, 5.08, 5.08); Calibrated: 1/23/2004
- Sensor-Surface: 4mm (Mechanical Surface Detection)
- Electronics: DAE3 Sn411; Calibrated: 11/6/2003
- Phantom: SAM with CRP TP1006; Type: SAM 4.0; Serial: TP:1006;
- Measurement SW: DASY4, V4.2 Build 44; Postprocessing SW: SEMCAD, V1.8 Build 112

Pin = 250 mW; d = 10 mm/Area Scan (81x81x1): Measurement grid: dx=15mm, dy=15mm

Reference Value = 90.6 V/m; Power Drift = 0.0 dB

Maximum value of SAR (interpolated) = 9.43 mW/g

Pin = 250 mW; d = 10 mm/Zoom Scan (7x7x7)/Cube 0: Measurement grid: dx=5mm, dy=5mm, dz=5mm

Reference Value = 90.6 V/m; Power Drift = 0.0 dB

Maximum value of SAR (measured) = 9.26 mW/g

Peak SAR (extrapolated) = 13.3 W/kg

SAR(1 g) = 8.25 mW/g; SAR(10 g) = 4.66 mW/g



