

Verint Systems Canada Inc. S4100, S4200 and S4300 Wireless Devices Family

Electromagnetic Compatibility Criteria for Intentional Radiators

§ 15.247(b) Peak Power Output and RF Exposure

RF Exposure Requirements: §1.1307(b)(1) and §1.1307(b)(2): Systems operating under the provisions of this

section shall be operated in a manner that ensures that the public is not exposed to

radio frequency energy levels in excess of the Commission's guidelines.

RF Radiation Exposure Limit: §1.1310: As specified in this section, the Maximum Permissible Exposure (MPE)

Limit shall be used to evaluate the environmental impact of human exposure to radiofrequency (RF) radiation as specified in Sec. 1.1307(b), except in the case of portable devices which shall be evaluated according to the provisions of Sec. 2.1093 of

this chapter.

MPE Limit Calculation: EUT's operating frequencies @ 2412-2462 MHz; highest conducted power = 18.8dBm (peak) therefore, **Limit for Uncontrolled exposure:** 1 mW/cm² or 10 W/m²

EUT maximum antenna gain = 15.5 dBi – Panel Antenna

Equation from page 18 of OET 65, Edition 97-01

 $S = PG / 4\pi R^2$ or $R = \int PG / 4\pi S$

where, $S = Power Density (1 mW/cm^2)$

P = Power Input to antenna (75.8 mW)

G = Antenna Gain (35.5 numeric)

 $S = (75.8*35.5/4*3.14*20^2) = (2690.9 / 5024) = 0.54 \text{mW/cm}^2$ @ 20cm

EUT maximum antenna gain = **8.5dBi** – **Integrated Antenna**

Equation from page 18 of OET 65, Edition 97-01

 $S = PG / 4\pi R^2$ or $R = \int PG / 4\pi S$

where, $S = Power Density (1 mW/cm^2)$

P = Power Input to antenna (75.8mW)

G = Antenna Gain (7.1 numeric)

 $S = (75.8*7.1/4*3.14*20^2) = (536.62 / 5024) = 0.10 \text{mW/cm}^2 @ 20 \text{cm}$



Verint Systems Canada Inc. S4100, S4200 and S4300 Wireless Devices Family

MPE Limit Calculation: EUT's operating frequencies @ <u>5725 - 5850 MHz</u>; highest conducted power = 25.6dBm (peak) therefore, **Limit for Uncontrolled exposure: 1 mW/cm² or 10 W/m²**

EUT maximum antenna gain = 24 dBi - Panel Antenna

Equation from page 18 of OET 65, Edition 97-01

$$S = PG / 4\pi R^2$$
 or $R = \int PG / 4\pi S$

where, $S = Power Density (1 mW/cm^2)$

P = Power Input to antenna (363.0 mW)

G = Antenna Gain (251.1 numeric)

 $R = (363.9*251.1/4*3.14*1.0)^{1/2} = (91149.3/12.56)^{1/2} = 85.1cm$ separation required in order to meet 1 mW/cm2 exposure limit.

EUT maximum antenna gain = 16 dBi - Sector Antenna

Equation from page 18 of OET 65, Edition 97-01

$$S = PG / 4\pi R^2$$
 or $R = \int PG / 4\pi S$

where, $S = Power Density (1 mW/cm^2)$

P = Power Input to antenna (363.0 mW)

G = Antenna Gain (39.8 numeric)

$$S = (363.9*39.8/4*3.14*20^2) = (2543.22/5024) = 0.50 \text{mW/cm}^2 @ 20 \text{cm}$$

EUT maximum antenna gain = 12 dBi – Integrated Antenna

Equation from page 18 of OET 65, Edition 97-01

$$S = PG / 4\pi R^2$$
 or $R = \int PG / 4\pi S$

where, $S = Power Density (1 mW/cm^2)$

MET Report: EMCS22622-FCC247

P = Power Input to antenna (363.0 mW)

G = Antenna Gain (15.8numeric)

 $R = (363.9*15.8/4*3.14*1.0)^{1/2} = (5749.62/12.56)^{1/2} =$ **21.4cm separation required in order to meet 1 mW/cm2 exposure limit.**