

RF Exposure / MPE Calculation

No. : 30KE0072-HO-02

Applicant : Murata Manufacturing Co., Ltd.

Type of Equipmen : Wireless LAN Module

(11a(5180-5320, 5500-5700MHz), 11n-20(5180-5320, 5500-5700MHz), 11n-40(5190-5310, 5510-5670MHz))

Model No. : LBWA1ZZSJ1

FCC ID : VPY-LBSJ

Murata Manufacturing Co., Ltd. declares that Model : LBWA1ZZSJ1

complies with FCC radiation exposure requirement specified in the FCC Rules 2.1093(for portable)/2.1091 (for mobile).

RF Exposure Calculations:

The following information provides the minimum separation distance for the highest gain antenna provided with the “LBWA1ZZSJ1” as calculated from FCC OET Bulletin 65 Appendix A, Table (B) Limits for General Population / Uncontrolled Exposure. This calculation is based on the highest EIRP possible from the system, considering maximum power and antenna gain, and considering a 1.0mW/cm² uncontrolled exposure limit. The Friis formula used was:

5180-5240MHz	Chip antenna (ANT 0)	12.68dBm + (-1.0) dBi = 11.68 dBm EIRP
	PWB Pattern antenna (ANT 1)	13.25dBm + 1.3dBi = 14.55 dBm EIRP
5260-5320MHz	Chip antenna (ANT 0)	12.78dBm + (-0.8) dBi = 11.98 dBm EIRP
	PWB Pattern antenna (ANT 1)	13.34dBm + 2.3dBi = 15.64 dBm EIRP
5500-5700MHz	Chip antenna (ANT 0)	13.73dBm + (-0.6) dBi = 13.13 dBm EIRP
	PWB Pattern antenna (ANT 1)	14.42dBm + 1.6dBi = 16.02 dBm EIRP

$$S = (P * G) / (4 * \pi * r^2)$$

Where

P = 27.67 mW (Maximum peak output power)

G = 1.45 Numerical Antenna gain; equal to 1.60 dBi

r = 20.0 cm

For: LBWA1ZZSJ1

$$S = 0.00796 \text{ mW/cm}^2$$

UL Japan, Inc.

Head Office EMC Lab.

4383-326 Asama-cho, Ise-shi, Mie-ken 516-0021 JAPAN

Telephone : +81 596 24 8116

Facsimile : +81 596 24 8124