

LED T8 Tube Light Introduction

Item No. : SL-A-2012P-011

一 . FEATURES:

- Low power consumption, high intensity.
- It can be directly placed in conventional T8 fluorescent brackets, remove ballast and starter before replacement.
- Solid-state, high-shock/vibration resistant.
- Contains no mercury, safer to use, simpler to dispose.
- Long life span up to 30,000 hrs(5 years), major reduction in maintenance costs and tube replacement costs, easy installation.
- The directional beam means light can goes where you need it.

二 . SPECIFICATION

Lamp Size: 1196mm(L) X Φ 30mm

Cover Material : PC

三 . ELECTRO-OPTICAL CHARACTERISTIC

Lamp source: High efficiency LED

Colour Temperature: 6500K

Luminous Flux : 1550Lm

Color Rendering Index (CRI) : 60 Ra<80

Power: 25W

Input Voltage : AC110V/240V

Frequency: 50/60 Hz

Output Voltage: 38.5V

Output Current: 320mA

四 . INSTALLATION

Directly place in conventional T8 fluorescent brackets without use ballast and starter.

五 . APPLICATION

Widely apply to Hospital、 Shopping mall、 Supermarket、 Museum、 School、 Computer room、 Bank、 Subway、 Exhibition hall、 Hotel etc.

六 . FCC STATEMENT

Manufacturers of RF lighting devices must provide an advisory statement, either on the product packaging or with other user documentation, similar to following: This product may cause interference to radio equipment and should not be installed near maritime safety communications equipment operating between 0.45-30MHz. Variations of this language are permitted provided all the points of the statement are addressed and may be presented in any legible font or text style.

SHEN ZHEN SUNLIGHT CORPORATION

TEL: 86-755-61110139 FAX:86-755-61569015

Add: 6th Floor, B Bldg. Yijiayang Industrial Park, Huming Road, Dalang Area, Bao'An District, Shenzhen City, Guangdong Province, China. PostCode:518109

Website: www.xuguangled.com