

RF EXPOSURE EVALUATION METHOD

For RF exposure report, the power limit is $60/f(\text{in GHz})$ mW,

Tx frequency range: 2412~2462MHz

For limit $60/f$ is equal:

$$60/2.412=24.87\text{mW}$$

$$60/2.437=24.62\text{ mW}$$

$$60/2.462=24.37\text{mW}$$

Maximum measured transmitter power.

EIRP=conducted power + antenna Gain

802.11B

frequency range	MAX Conducted Power (dBm)	Max Antenna Gain (dBi)	EIRP (dBm)	EIRP (mW)	limit(mW)
2412	11.20	0.3	11.50	14.13	24.87
2437	10.42	0.3	10.72	11.80	24.62
2462	10.22	0.3	10.52	11.27	24.37

802.11G

frequency range	MAX Conducted Power (dBm)	Max Antenna Gain (dBi)	EIRP (dBm)	EIRP (mW)	limit(mW)
2412	9.57	0.3	9.87	9.70	24.87
2437	8.98	0.3	9.28	8.47	24.62
2462	8.54	0.3	8.84	7.65	24.37

802.11N(20MHz)

frequency range	MAX Conducted Power (dBm)	Max Antenna Gain (dBi)	EIRP (dBm)	EIRP (mW)	limit(mW)
2412	9.18	0.3	9.48	8.87	24.87
2437	8.49	0.3	8.79	7.56	24.62
2462	8.22	0.3	8.52	7.11	24.37

802.11N(40MHz)

frequency range	MAX Conducted Power (dBm)	Max Antenna Gain (dBi)	EIRP (dBm)	EIRP (mW)	limit(mW)
2422	9.47	0.3	9.77	9.48	24.77
2437	8.25	0.3	8.55	7.16	24.62
2452	8.54	0.3	8.84	7.65	24.46

PASS